

SEPT. - 20¢

POPULAR SCIENCE

Fort Busters

BLAST THE PATH FOR INVASION
WITH FLAME AND TNT. Page 49



Your Home

AFTER THE WAR WILL BE A MIRACLE
OF BUILT-IN COMFORTS. Page 76



Iron Horse

GETS NEW POWER AND EFFICIENCY




Guns

BETTER ONES AND MORE OF THEM GIVE OUR
SOLDIERS A DEADLY ADVANTAGE. Page 82

All the Sciences

1500 Pages
1200 Illustrations



SIZE
7 1/4 x 10 1/4 in.
2 1/4 inches thick

THIS great new work presents—for the first time in one volume—a complete coverage of the terms of science and engineering. Principles are clearly explained—methods of calculation are fully described with the formulae and units—chemical structures and reactions, physical laws and instruments, engineering design, construction, and operation are merely suggestive of its tremendous scope—which extends throughout the entire range of technical knowledge up to the most recent advances and inventions. The great number of photographs, diagrams, and charts have been specially prepared and selected to show the salient facts most clearly. Innumerable tables and summaries make all this information easily available for instant reference. This vast fund of information has been prepared and organized by a plan that insures its usefulness, completeness, and accuracy. Each entry is first explained in simple, broad terms that are easy to understand, and that serve as an illuminating introduction to the detailed and more advanced information which follows.

From Fundamentals to Latest Advanced Discoveries—

Principles, Methods, Formulas—Clear Charts, Diagrams

FOR the student, the hobbyist, the manual worker, this great volume supplies, for the first time, a single, convenient source of reference covering all the sciences. The ample cross-references make it easy to follow a complete course of study on any chosen subject. By this flexible plan of arrangement, the professional scientist, who wants specific information instantly, either in his own field or *any related field*, can find it in a few seconds in its alphabetical place—comprehensively treated in the language he works with—the language of science.

The Instant Question-Answerer for Laboratory and Shop Workers, Mechanics, Home Scientists, Students

Answers tens of thousands of questions such as: The value of radial, rotary gas engines—How the Diesel Engine operates—How air conditioning functions—What is the coming television system—How storage batteries work—How to find your position at sea—How to do dead reckoning—How your nervous system works—How to recognize every star, planet, constellation—How optical instruments are constructed—How to work arithmetic, algebra, geometry problems—How bridges are constructed—How an airplane beacon system works—How petroleum is cracked to make gasoline—How rayon is made—How to survey a piece of land—and thousands more.

in One Great Book

10,000 Separate Subjects Twelve Big Volumes in One

The vast wealth of useful information in the Scientific Encyclopedia, if published in the ordinary way, would fill more than 12 average-size volumes. Here is just a brief outline of some of the subjects covered:

CHEMISTRY: Chemical elements—symbols, atomic number, atomic weight, density, hardness, melting point, etc.—common reactions, occurrence in nature, method of production from ores, uses in industry. Compounds—full information, including manufacture and use. Organic compounds; industrial products. Agricultural chemistry, food chemistry.

PHYSICS: Mechanics, heat, light, sound, electricity, magnetism, X-rays, fully covered; principles and application profusely illustrated.

MATHEMATICS: From fundamentals of arithmetic to algebra, geometry, trigonometry, calculus, differential equations, etc.; with special emphasis on their application to science.

ASTRONOMY: Articles cover the entire subject. Each important constellation is shown on a star map so that it can be easily located in the sky. Complete information on planets, use of telescope, spectrometer, etc.

ZOOLOGY: The whole story of life from the tiniest single-celled organisms up to man himself, including vast numbers of common insects, mollusks, worms; birds, fish, reptiles, mammals.

MEDICINE: Thorough coverage of anatomy, circulatory system, nervous system, muscular system, skeletal system, excretory systems, etc. Vitamins, hormones. Bacteriology. Diseases—symptoms, diagnosis, treatment. Drugs. Latest researches and findings.

MECHANICAL ENGINEERING: Principles of mechanics, machine design, engineering parts and instruments. Types and functions of bolts, cams, gears, and other fundamentals up to automobiles, aeroplanes, locomotives, etc. Steam, gas, gasoline, diesel engines.

CIVIL ENGINEERING: Surveying. Bridges, highways, railways—every subject thoroughly explained.

ELECTRICAL ENGINEERING: Motors, generators, lighting, radio and television—every branch fully covered and clearly illustrated.

The foregoing is only a partial list of the countless special subjects covered. You will find hundreds of articles on GEOLOGY, BOTANY, NAVIGATION, CHEMICAL ENGINEERING, and, in fact, any special branch of science in which you want information.

EXAMINE A COPY FREE

It is difficult in this limited space to give you a complete adequate idea of the immense amount of material contained in the Scientific Encyclopedia. See this volume for yourself, without expense or obligation. We will send it to you for free examination.

Prepared by Outstanding Authorities
In Each Field of Science

The high technical standing of the editors is your assurance of the authoritativeness and accuracy of every statement. Although the responsibility for each subject was in the hands of a single noted scientist, the authors and publishers have had the co-operation and advice of a large group of well-known authorities.

CONTRIBUTING EDITORS

GEOLOGY	
RICHARD M. FIELD, Ph.D.	Princeton University
ASTRONOMY AND NAVIGATION	
WARREN K. GREEN, Ph.D.	Ankner College
ZOOLOGY	
ARTHUR W. LINDSEY, Ph.D.	Drexel University
FREDERICK T. MOUSE, M.E., E.E.	University of Virginia
MEDICINE	
R. S. MUELLER, M.D.	Columbia University
MATHEMATICS	
LOYD L. SMAIL, Ph.D.	Lehigh University
MINERALOGY	
EDWARD S. C. SMITH, S.B., A.M.	Union College
CHEMISTRY	
RALPH S. STRONG, Ph.D.	Rose Polytechnic Institute
PHYSICS	
LEROY D. WELD, Ph.D.	Coe College
BOTANY	
R. M. WHELDEN, Ph.D.	Massachusetts Institute of Technology

Among the many

CONSULTING EDITORS

ROBERT H. BAKER, Ph.D., D.Sc.	University of Illinois
HEMPSTEAD CASTLE, Ph.D.	Yale University
C. W. CUNNINGHAM, B.S.	College of the City of New York
HERBERT O. ELFTMAN, Ph.D.	Columbia University
ERICH HAUSMAN, E.E., Sc.D.	Polytechnic Inst. of Brooklyn
ADOLF KNOPP, Ph.D.	Yale University
JOHN C. RATHBUN, Ph.D.	College of the City of New York
EDGAR P. SLACK, S.B.	Polytechnic Institute of Brooklyn
HUGH S. TAYLOR, D.Sc., F.R.S.	Princeton University
JOHN TURKOVICH, Ph.D.	Princeton University
VOLNEY H. WELLS, Ph.D.	Williams College

MAIL THIS COUPON

Send No Money Now Unless You Wish To

D. VAN NOSTRAND CO., Inc.
250 Fourth Avenue 10, N. Y.
Send me Van Nostrand's SCIENTIFIC ENCYCLOPEDIA, complete in one volume, 1500 pages, bound in Sturdy Fabrikoid. Within 10 days I will either return it or send you \$2.00 as first payment, and \$2.00 monthly for four months thereafter. (P.S.M. 9-43)

Name
Address
City and State
Reference
Address




The EVINRUDE you're doing without helped put this "big 'un" into the fight

It takes a whole flock of pleasure motors to build a single mighty outboard for service on a battle front. And in this picture of a great fighting Evinrude, there's a heap of satisfaction for the thousands who are gladly "doing without" a new motor this year.

Their motors are *here* . . . built into this greatest outboard of them all! Here is power enough to drive a fleet of average boats... stamina to take a terrific beating and come right back for more... flashing speed that means *everything* when water boils white with deadly bursts of lead and shrapnel.

Day and night they are coming off the production lines... motors like this one, and motors of many other types required in amphibian operations on every front. In the peacetime Evinrude you'll some day enjoy, you'll find ample and satisfying evidence of how good these fighting Evinrudes were!

EVINRUDE MOTORS, Milwaukee, Wisconsin
Evinrude Motors of Canada,
Peterboro, Canada



EVINRUDE
OUTBOARD MOTORS

★ EVERY DOLLAR HELPS SPEED VICTORY . . . BUY MORE BONDS!

Popular Science Monthly for September, 1943, Volume 143, Number 3. Published monthly at 353 Fourth Avenue, New York 10, N. Y., by Popular Science Publishing Co., Inc. Entered as second-class matter Dec. 28, 1918, at the Post Office at New York under the act of March 3, 1879; additional entry as second-class matter at Dayton, Ohio. Yearly subscriptions to the United States, \$3.00.

YOUR FUTURE IS PLASTIC—



ANYTHING capable of being molded is plastic. So it's a word that applies to your future as well as to the materials of the plastics industry. There are giant possibilities in this field. Their realization depends upon the planning of *trained* men.

Within **YOU**, too, are great possibilities. Their realization depends upon your being a *trained* man. The world-famous International Correspondence Schools offer you

the opportunity to obtain that *training* in your spare time, at low cost.

With *training*, you can mold your place in the coming Victory-world to your heart's desire. A more responsible job, higher pay—whichever you want is attainable if you qualify as an *expert*.

The time to qualify—in plastics or any other industry—is **NOW**. Mail the coupon today and let I. C. S. tell you how!

INTERNATIONAL CORRESPONDENCE SCHOOLS

HELPING TO TRAIN AMERICANS FOR VICTORY

BOX 7659-K, SCRANTON, PENNA.

Without cost or obligation, please send me booklet and full particulars about the course *before* which I have marked X:

- ☐ **PLASTICS**
- ☐ Air Brake
- ☐ Air Conditioning
- ☐ Airplane Drafting
- ☐ Architectural Drafting
- ☐ Architecture
- ☐ Auto Engine Tune-up
- ☐ Auto Technician
- ☐ Aviation ☐ Aviation Mechanic
- ☐ Blueprint Reading
- ☐ Boilermaking
- ☐ Bridge Engineering
- ☐ Chemistry ☐ Coal Mining
- ☐ Civil Engineering

- ☐ Accounting ☐ Advertising
- ☐ Bookkeeping
- ☐ Business Correspondence
- ☐ Business Management
- ☐ Cartooning ☐ Civil Service

- ☐ Advanced Dressmaking
- ☐ Foods and Cookery

- ☐ **TECHNICAL AND INDUSTRIAL COURSES**
- ☐ Concrete Engineering
- ☐ Contracting and Building
- ☐ Cotton Manufacturing
- ☐ Diesel Engines
- ☐ Electrical Drafting
- ☐ Electrical Engineering
- ☐ Electrician
- ☐ Electrical Maintenance
- ☐ Foundryman ☐ Heating
- ☐ Heat Treatment of Metals
- ☐ Highway Engineering
- ☐ House Planning
- ☐ Industrial Metallurgy
- ☐ Locomotive Engineer
- ☐ Machinist ☐ Inspector
- ☐ Management of Inventions
- ☐ Marine Engines
- ☐ Mechanical Drafting
- ☐ Mechanical Engineering
- ☐ Mine Foreman
- ☐ Patternmaking ☐ Plumbing
- ☐ Public Works Engineering
- ☐ Pulp and Paper Making
- ☐ Radio, General
- ☐ Radio Operating
- ☐ Radio Servicing
- ☐ R. R. Section Foreman
- ☐ R. R. Signalman ☐ Refrigeration

- ☐ **BUSINESS COURSES**
- ☐ First Year College
- ☐ Foremanship ☐ French
- ☐ Good English
- ☐ High School
- ☐ Managing Men at Work

- ☐ **HOME ECONOMICS COURSES**
- ☐ Home Dressmaking
- ☐ Professional Dressmaking and Designing

- ☐ Sanitary Engineering
- ☐ Sheet Metal Work
- ☐ Ship Drafting
- ☐ Shipfitting ☐ Shop Practice
- ☐ Steam Electric ☐ Steam Engines
- ☐ Steam Fitting
- ☐ Structural Drafting
- ☐ Structural Engineering
- ☐ Surveying and Mapping
- ☐ Telegraphy ☐ Telephony
- ☐ Textile Designing
- ☐ Toolmaking ☐ Tool Design
- ☐ Welding, Gas and Electric
- ☐ Woolen Manufacturing

- ☐ Railway Postal Clerk
- ☐ Salesmanship
- ☐ Secretarial ☐ Spanish
- ☐ Showcard and Sign Lettering
- ☐ Traffic Management

- ☐ Tea Room and Cafeteria Management, Catering

Name..... Age..... Address.....

City..... State..... Staff..... Present Position.....

Canadian residents send coupon to International Correspondence Schools Canadian, Limited, Montreal, Canada
British residents send coupon to I. C. S., 71 Kingsway, London, W. C. 2, England

POPULAR SCIENCE

FOUNDED 1872

MONTHLY

VOL. 143 NO. 3

Mechanics & Handicraft

A TECHNICAL JOURNAL OF SCIENCE AND INDUSTRY

CONTENTS /for SEPTEMBER, 1943

News

How Fort Busters Lead Invasion.....	49
Guns for Guerrillas.....	54
Postwar Styles in Locomotives.....	58
Can We Grow Hemp Without Dope?	62
Movies Train Air Gunners.....	65
Strip Germany of Machine Tools.....	73
Your Home . . . Tomorrow.....	76
Flying Gun Carriers.....	82
Making Lightning Behave.....	89
Why "DE" Boats Are Death to Subs	94
The Fork-Tailed Devil.....	96
How a Violin Is Made.....	106
Saving Lives with Blood.....	110
Captured Guns Reveal Secrets.....	118
War Hooks the Shark.....	120
No Truce in the War on Fire.....	124

Automobiles

Taking Kinks Out of Steering Systems	128
Handy Ideas for Motorists.....	131
Gus Wilson's Model Garage.....	132

Home and Workshop

Twin Models of Converted Ship.....	HW 385
How to Camp Out in Comfort.....	HW 390
Whittle Your Own Fishing Plugs.....	HW 396
Three-in-One Nesting Tables.....	HW 400
Using Small Carving Motors.....	HW 410
Laughs for Your Home Movies.....	HW 424
Oxygen—Mainstay of Life.....	HW 432
Picture Post-Card Projector.....	HW 438
Harnessing Electrons in Glass.....	HW 440

(Continued on page 6)



AIRCRAFT MACHINE GUN. This French mitrailleuse, mounted behind a shield on a plane in World War I, was a forerunner of the powerful weapons that arm our new warplanes. "Flying Gun Carriers," on page 82, tells the story of aircraft armament from the days when pilots wore pistols to the duels between cannon-bearing fighters over Europe today.

EDITOR Charles McLendon
ASSISTANT EDITOR Arthur Wakeling
HOME & WORKSHOP EDITOR Harry Walton
ART EDITOR Carsten Grande

EDITORIAL ASSOCIATES: Fred O. Newman, news editor; Alden P. Armagnac, B. T. Richards, Harry Samuels, Michele de Santis, Don Romero, Bernard Wolfe, Jack O'Brine, J. Harold Hawkins, Jean Ackermann.

ART ASSOCIATES: Stewart Rouse, Wayne Smith, William Patrick, Samuel Dukler, Evelyn Cooper.

PHOTOGRAPHY: W. W. Morris, Robert F. Smith.

Published monthly at 353 Fourth Avenue, New York 10, N. Y., by Popular Science Publishing Co., Inc. Godfrey Hammond, President and Treasurer; R. C. Wilson, Raymond J. Brown, Charles McLendon, Stephen P. Glennon, Vice-Presidents; F. W. Briggs, Secretary. Entered as second-class matter Dec. 28, 1918, at the Post Office at New York under the act of March 3, 1879; additional entry as second-class matter at Dayton, Ohio. Entered as second-class matter at the Post Office Department, Canada. Printed in U.S.A. Copyright, 1943, by Popular Science Publishing Co., Inc. All rights reserved in the United States, Great Britain, and in all countries participating in the International Copyright Convention and the Pan American Copyright Convention. Yearly subscriptions to United States and its possessions, \$2.00; Canada, \$2.50; foreign countries, excepting Canada, \$3.00. Subscribers must notify us of change of address four weeks in advance of the next publication date. Be sure to give both old and new address.

GIVE HIM A BREAK !



Evening is about his only chance to telephone home. He can get through easier if the wires aren't crowded — and his calls mean so much to him and the home folks. So please don't call Long Distance between 7 P. M. and 10 P. M. unless your calls are really necessary. Many thanks.

BELL
TELEPHONE
SYSTEM





Contents [CONTINUED]

Automobiles

Army Uses Amphibian Trucks.....	60
Adding a Tool Compartment.....	131
Shoe Bag Carries Odds and Ends..	131
Improving Radio Reception.....	131
Emergency Battery Connections....	131
Bodies for Ambulances.....	135
Speeding Up Tire Inspection.....	135

Aviation

Portable Pressure Chamber.....	56
Plastic Tools Replace Metal.....	60
Three-in-One Combat Gloves.....	64
An Air-Age Globe.....	64
Adjustable Inspection Mirrors.....	80
Atlantic Seadromes After War?....	81
Gliders Aid Take-Offs.....	104
Emergency Control Rights Plane..	105

Facts and Ideas

New Gun for Paratroops.....	56
"Scenic Trip" Through Torpedo Hole	57
Scale Models Train Army Cooks....	64
Sun Controls Big Cooling System..	88
Tricks with Figures.....	93
"Sinking" a Floating Island.....	101
Army Gets New Snake-Bite Kit....	102
Inside Three Allied Tanks.....	114
How to Beat a Mugger.....	115
Women's War Bonnets.....	122
Horse Meat for Circus "Cats".....	123

Inventions

Device Finds Land Mines.....	56
Secret Block-Buster Explosive....	61
Jungle Boots Resist Dampness....	102
Electric Bomb-Nose Shaper.....	104
Sling Hurls Grenades Farther.....	104
Amphibian Combat Vehicle.....	105

Craftwork

Twin Models of Converted Ship..	HW 384
Turned Shakers Resemble Dolls..	HW 387
Photo Frame Built of Cardboard..	HW 395

(Continued on page 8)

IMPORTANT NOTICE: The contents of this magazine must not be reprinted without permission. The editors are not responsible for unsolicited contributions, and cannot guarantee the return of such material or insure against its loss. Contributions not accompanied by sufficient postage will not be returned. In presenting numerous stories of new products of applied science, Popular Science Monthly does not underwrite the business methods of the individuals or concerns producing them. To avoid liability for patent infringement, readers should investigate before making, using, or offering for sale any of the devices, machines, or processes described; Popular Science Monthly takes no responsibility. The use of Popular Science Monthly articles for stock-selling schemes is never authorized.

**You'll Find the Help You Need in
These Up-to-Date, Authoritative**

BOOKS

FOR THE TECHNICAL man

THESE BOOKS, on subjects important in war industries and in the U. S. Armed Services, will help you qualify for a better job, more pay, higher rank. And they will prepare you for the peace-time opportunities to come. Make your choice, then mail coupon at once! (Order by number.)

1. SWOOPE'S LESSONS IN PRACTICAL ELECTRICITY

By **Erich Hausmann, Prof. Physics, Brooklyn Polytech. Inst.**
More men have learned electricity from this book than any other. Clear, plain, practical. Starts from simplest principles and takes you through entire subject—A.C. and D.C. instruments and machinery, lighting, heating, telegraphy, radio. 707 pages, illustrated. **\$2.50**

2. INDUSTRIAL ELECTRICITY

By **John M. Naden, Supervisor Electrical & Auto Eng., Ford Apprentice School; and Bert J. Gelmine, Instructor Indus. Elect., Ford Apprentice School**

Used in Apprentice School of Ford Motor Co. Gives all training you need in practical electrical work of every kind, installation and repair. Starts from fundamentals, builds up thorough knowledge of every type equipment used today. 607 pages, illustrated. **\$3.00**

3. BASIC RADIO

By **J. Barton Hoag, Professor with rank Commander, U.S.C.G.; Head Science Dept., U.S.C.G. Acad.**

An entire training in radio circuits. Explains each type tube and circuits, with actual applications, clear self-teaching diagrams. Includes present-day radio uses in war and peace—oscillograph, ultra-high frequency, superheterodyne circuits and alignment, etc. 380 pages, illustrated. **\$3.25**

4. ULTRA-HIGH-FREQUENCY TECHNIQUES

Edited by **J. G. Brainerd, Prof. Moore School Elect. Eng. of U. of Penn.**

Organized so you can master and apply contents rapidly. Learn this subject—vital in war, destined for great role in peacetime industry. Explains principles, experiments, tests, diagrams—including all pertinent facts from other branches radio and electricity. 334 pages, illustrated. **\$4.50**

5. MACHINE SHOP: THEORY AND PRACTICE

By **Albert M. Wagener, Instructor, Ford Trade School; and Harlan R. Arthur, Principal, Ford Apprentice and Eng. School**

Every topic and method in this book has proved its value in teaching practical men quickly. Vivid, "self-teaching" drawings and photographs that show you just how the work is done. Complete explanations—of everything from simplest hand tools to most complex machines used today. 306 pages, illus. **\$2.28**

6. ENGINEERING TOOLS AND PROCESSES:

A STUDY OF PRODUCTION TECHNIQUE

By **Herman C. Hesse, Assoc. Prof. Eng. Drawing and Machine Design, U. of Va.**

Teaches actual methods and techniques of mass production. Takes you through entire manufacturing sequence—from "how to select engineering materials" to testing of finished products. Numerous line drawings show essential operating principles of every machine. 627 pages, illustrated. **\$4.50**

7. THE MATHEMATICS OF THE SHOPS

By **Frank J. McMackin, Principal, Wm. L. Dickinson H. S., Jersey City, N. J.; and John H. Shaver, Asst. Supervisor H. S. Methods and Director National Defense Program, Jersey City A.** multitude of practical problems, fully worked, cover the electrical shop, machine shop and all building trades, giving every step in solving every problem you are ever likely to meet. Profit to the utmost by applying mathematics in all your work. 444 pages, illustrated. **\$2.50**

8. DRAFTING FOR ENGINEERS

By **Carl L. Svensen, Chairman, Texas State Board of Registration for Professional Engineers**

Thorough training in engineering drafting; 31 chapters explain fully and simply every branch of the subject. Answers every question about dimensioning, shading, developments, drawing of threads, bolts, screws, piping, etc., in short, every question likely to arise in practical work. 606 pages, illustrated. **\$3.00**

9. A PILOT'S METEOROLOGY

By **Chas. Graham Halpine, Commander, U. S. Navy (Ret.)**

You can gain from this book a comprehensive, working knowledge of meteorology, without knowing mathematics or physics. Trains you to interpret weather reports and maps, and to read the "signs of the sky." All this knowledge is applied directly to flying, by a veteran pilot. 220 pages, illustrated. **\$2.00**

10. AIRCRAFT INSTRUMENTS

By **D. E. Patton, Aeronautical Engineer**

More than 200 clear-cut photos and diagrams—accompanied by the most direct explanations—show you how all the latest airplane instruments look and operate. This manual tells you how to read these instruments, how to use them in flying. 220 pages, illustrated. **\$2.75**

11. SIMPLIFIED THEORY OF FLIGHT

By **Thomas C. Gillmer, Lieut., U. S. N.; and H. Erich Nietsch, Aeronautical Engineer and Instructor in Aeronautics, C.A.A.**

This book gives pilots and students a clear, complete understanding of why and how a plane flies—without using mathematical formulas or engineering terms. The essential physical laws are explained in plain English; with simple, vivid diagrams. 162 pages, illustrated. **\$1.75**

12. MAP READING AND AVIGATION

By **Richard M. Field, Assoc. Prof. Geology, Princeton Univ.; and Harlan T. Stetson, Cosmic Terrestrial Research, Mass. Inst. Tech.**

All the knowledge needed to determine position in the air, over land and sea. Gives maps, models and airplane photographs of each area; you learn to visualize the surface of the earth as seen from aloft. Teaches avigation by H. O. 214, the simplest method, widely used in U. S. Services. 129 pages, illustrated. **\$2.50**

D. Van Nostrand Co., Inc., 250 4th Ave., New York 10, N. Y.

D. VAN NOSTRAND CO., INC.

250 Fourth Avenue, New York 10, N. Y.

Please send me postpaid the books whose numbers I have circled below. I enclose \$..... in payment. 10-day return privilege; full refund.

1 2 3 4 5 6
7 8 9 10 11 12

Name.....

Address.....

City and State.....

P.S.M. 9-43

**MAIL THIS COUPON TODAY OR
ORDER FROM YOUR BOOKSTORE**



THE great air age of the future will help every one of us. Then you will fly your own Piper Cub to your favorite vacation spots and take business trips with unbelievable ease. You may even make aviation your vocation.

Be ready for this bright future in the sky. Take aviation subjects at night school, study aeronautics at home. Then, when peacetime comes, see your Piper Dealer and learn to fly. He can solo you with as little as 8 hours of dual instruction in a Piper Cub.

Send Today for Your "HOW TO FLY" Booklet!

Prepared by a certificated flight instructor. Clearly explains basic flight principles. Send 10c for booklet and Piper catalog to cover postage-handling. Piper Aircraft Corporation, Dept. PS 93, Lock Haven, Penna.



PIPER *Cub*
POINTS THE WAY TO WINGS FOR ALL AMERICANS

Contents [CONTINUED]

Novel Marble Bombing Game.....	hw 398
Muffin Server from Salad Bowl.....	hw 399
Ship Model for Weather Vane.....	hw 414
Decorating Painted Furniture.....	hw 416
Three Craftwork Projects.....	hw 420

Electrical

Post-Card and Photo Projector.....	hw 438
Harnessing Electrons in Glass.....	hw 440
Servicing Your Own Radio.....	hw 443
New Radio Ideas.....	hw 444

Miscellaneous

Keeping the Home Shipshape.....	hw 388
Amusing Button Place Cards.....	hw 395
Aids to Wartime Housekeeping.....	hw 402
Home Experiments with Gases.....	hw 430
Oxygen—Mainstay of Life.....	hw 432

New Shop Ideas

Rig for Extra Drill Speeds.....	hw 405
Micrometer as Centering Gauge.....	hw 405
How to True Grinding Wheels.....	hw 406
The ABC's of Blowtorch Use.....	hw 408
Guard on Gauge Prevents Error.....	hw 409
Flaring Tool for Copper Tubes.....	hw 409
Reamer Works in Tight Corners.....	hw 409

Outdoors

How to Camp Out in Comfort.....	hw 390
Camper's Pack for Bicycle.....	hw 394
How to Whittle Fishing Plugs.....	hw 396
Hints for Boat Owners.....	hw 404

Photography

Putting Laughs in Home Movies.....	hw 424
Darkroom Scale Made of Scrap.....	hw 428
Double Jar Useful in Darkroom.....	hw 429

The Handy Man

Closet Shelf for Umbrellas.....	hw 389
Brush Holder from Clothespins.....	hw 389
Products for Home Owners.....	hw 422
Restoring Old Paintbrushes.....	hw 436
Repairing Mowing Machines.....	hw 446
Sealed-Beam Floodlight Unit.....	hw 448

Woodworking

Nesting Tables in Modern Mode.....	hw 400
Jig Built for Carving Motor.....	hw 410
Wood Shopping Cart Folds Away.....	hw 418



EVERY drafting board is a battlefield across which move tanks, guns, planes and ships. Every new weapon must pass through this design stage before it reaches production and moves on to the literal fighting fronts.

Learn now to fight as a *trained* draftsman and help your country while you help yourself.

Freedom to pick your own battlefield in fighting for success in life is one of your great heritages

as an American. And in choosing the drafting board, you know that big, well-paid jobs are to be won there. Thousands of successful men made their start in just that way.

Many of today's draftsmen will be among tomorrow's leaders. *You* can learn drafting—at low cost—by studying an I. C. S. Course in your spare time! Mail this coupon *today* and you're getting into communication with a real future.

INTERNATIONAL CORRESPONDENCE SCHOOLS

HELPING TO TRAIN AMERICANS FOR VICTORY

BOX 7640-K, SCRANTON, PENNA.

Without cost or obligation, please send me booklet and full particulars about the course *before* which I have marked X:

- ☐ Airplane Drafting
- ☐ Architectural Drafting
- ☐ Electrical Drafting
- ☐ Mechanical Drafting
- ☐ Ship Drafting
- ☐ Structural Drafting
- ☐ Blueprint Reading
- ☐ Air Brake
- ☐ Air Conditioning
- ☐ Architecture
- ☐ Auto Engine Tune-up
- ☐ Auto Technician
- ☐ Aviation ☐ Aviation Mechanic
- ☐ Boilermaking

- ☐ Accounting ☐ Advertising
- ☐ Bookkeeping
- ☐ Business Correspondence
- ☐ Business Management
- ☐ Cartography ☐ Civil Service

- ☐ Advanced Dressmaking
- ☐ Foods and Cookery

- TECHNICAL AND INDUSTRIAL COURSES**
- ☐ Bridge Engineering
 - ☐ Chemistry ☐ Coal Mining
 - ☐ Civil Engineering
 - ☐ Concrete Engineering
 - ☐ Contracting and Building
 - ☐ Cotton Manufacturing
 - ☐ Diesel Engines
 - ☐ Electrical Engineering
 - ☐ Electrician
 - ☐ Electrical Maintenance
 - ☐ Foundryman ☐ Heating
 - ☐ Heat Treatment of Metals
 - ☐ Highway Engineering
 - ☐ House Planning
 - ☐ Industrial Metallurgy
 - ☐ Locomotive Engineer
 - ☐ Machinist ☐ Inspector
 - ☐ Management of Inventions
 - ☐ Marine Engines
 - ☐ Mechanical Engineering
 - ☐ Mine Foreman
 - ☐ Navigation ☐ Patternmaking
 - ☐ Plastics ☐ Plumbing
 - ☐ Public Works Engineering
 - ☐ Pulp and Paper Making
 - ☐ Radio, General
 - ☐ Radio Operating
 - ☐ Radio Servicing

- BUSINESS COURSES**
- ☐ College Preparatory
 - ☐ Commercial
 - ☐ Commercial Illustrating
 - ☐ Cost Accounting
 - ☐ C. P. Accounting
 - ☐ First Year College
 - ☐ Foremanship ☐ French
 - ☐ Good English
 - ☐ High School
 - ☐ Managing Men at Work

- HOME ECONOMICS COURSES**
- ☐ Home Dressmaking
 - ☐ Professional Dressmaking and Designing

- ☐ R. R. Section Foreman
- ☐ R. R. Signalman ☐ Refrigeration
- ☐ Sanitary Engineering
- ☐ Sheet Metal Work
- ☐ Shipfitting ☐ Shop Practice
- ☐ Steam Electric ☐ Steam Engines
- ☐ Steam Fitting
- ☐ Structural Engineering
- ☐ Surveying and Mapping
- ☐ Telegraphy ☐ Telephony
- ☐ Textile Designing
- ☐ Toolmaking ☐ Tool Design
- ☐ Welding, Gas and Electric
- ☐ Woolen Manufacturing

- ☐ Railway Postal Clerk
- ☐ Salesmanship
- ☐ Secretarial ☐ Spanish
- ☐ Showcard and Sign Lettering
- ☐ Traffic Management

- ☐ Tea Room and Cafeteria Management, Catering

Name.....Age.....Address.....

City.....State.....Present Position.....

Canadian residents send coupon to International Correspondence Schools Canadian, Limited, Montreal, Canada
British residents send coupon to I. C. S., 71 Kingsway, London, W. C. 2, England

SPECIAL
TUITION RATES
FOR MEMBERS
OF THE
ARMED FORCES
★

FREE LESSON

See For Yourself How BE A RADIO



J. C. Smith
President

National Radio
Institute
Established 28 years

**Jump Your
Pay!**
**Vital Jobs Go To
Men I Train**



Communication
Station Operator
"Am with the
Civil Aeronautics
Administration as
Aircraft communication
operator at the Shreve-
port Airways Com-
munication station. Have a life-
time position, with pension
after retirement."—JESSE N.
ROBERTS



\$200 a Month in
own Business
"For several years
I have been in
business for myself
making around
\$200 a month. Busi-
ness has steadily
increased. I have
N.R.I. to thank
for my start in this field."—
ARLIE J. FROEHNER



\$10 per Week
in Spare Time
"I am doing spare
time Radio Work.
Am averaging
around \$500 a year.
Those extra dollars
mean so much—
the difference be-
tween just barely
getting by and living comfort-
ably."—JOHN WASHKO



Chief Operator
Broadcasting
Station
"Before I complet-
ed your lessons, I
obtained my Ra-
dio Broadcast Op-
erator's license and
immediately joined
Station WMPC
where I am now
HAYES



Lieutenant in
Signal Corps
"I cannot divulge
any information as
to my type of work,
but I can say that
N.R.I. training is
certainly coming
in mighty handy
these days."—
LIEUTENANT RICHARD W.
ANDERSON.



Radio Service
Manager of
4 Stores
"I was working in a
garage when I en-
rolled with N.R.I.
I am now Radio
Service Manager
for M— Furniture
Co. for their 4 stores."—
JAMES E. RYAN

Mail the Coupon for a FREE Lesson from
my Radio Course. It shows you how practical
and easy to understand my lessons are—and
why N. R. I. training offers a *quick way to more
pay*. And with this free Lesson I'll send my
64-page, illustrated book, "Win Rich Rewards
in Radio." It describes many fascinating types
of Radio jobs; tells how you can train for them
at home in spare time!

Jobs Like These Go to Many Men I Train
There's a big shortage of capable Radio
Technicians and Operators. Fixing Radios pays
better now than for years. With new Radios



out of production, fixing old sets, which were
formerly traded in, adds greatly to the normal
number of servicing jobs.

Broadcasting Stations, Aviation and Police
Radio, Ship Radio and other communications
branches are scrambling for Operators and
Technicians to replace men who are leaving.
You may never see a time again when it will be
so easy to get started in this fascinating field.
The Government, too, needs hundreds of compe-
tent civilian and enlisted Radio men and women.
Radio factories now working on Government or-
ders for war equipment, employ trained men.
And think of the NEW jobs Television, Fre-
quency Modulation, Electronics and other Radio
developments will open after the war! This is
the sort of opportunity you shouldn't pass up.

**Many Beginners Soon Make \$5, \$10
a Week Extra in Spare Time**

There's probably an opportunity right in your
neighborhood to make money in spare time fixing



EXTRA PAY IN ARMY, NAVY, TOO

Men likely to go into military
service, soldiers, sailors, ma-
rines, should mail the Coupon
now! Learning Radio helps Service men get extra
rank, extra prestige, more interesting duties, much
higher pay. Also prepares for good Radio jobs after
service ends. Over 1,700 Service men now enrolled.



Get Sample Lesson and

IN RADIO

I Train You at Home to TECHNICIAN

Radios. I'll give you the training that has started hundreds of N.R.I. students making \$5, \$10 a week extra within a few months after enrolling. The N.R.I. Course isn't something just prepared to take advantage of the present market for technical books and courses. It has been tried, tested, developed, perfected during the 28 years we have been teaching Radio.

A Great School Helps You Toward the Rich Rewards in Radio

Throughout your training, the staff and resources of the world's largest private home study institution devoted entirely to training men for Radio will be squarely behind you. N.R.I. has stuck to the one job of teaching Radio for 28 years. Our combined efforts have made the Course so interesting, with hundreds of pictures, charts, and diagrams, and with special teaching methods designed especially for home study—that we believe you will be "old friends" with Radio almost before you know it.




Broadcasting Stations employ N.R.I. trained Radio Technicians as operators, installation, maintenance men and in other capacities and pay well.

Find Out What N.R.I. Can Do for You

MAIL THE COUPON NOW for my FREE Lesson and 64-page book. You'll see how N.R.I. trains you at home; read letters from men I trained; learn about many fascinating jobs Radio offers. No obligation—no salesman will call. Just MAIL THE COUPON AT ONCE, in an envelope or paste on a penny postal: J. E. SMITH, President, Dept. 3JP3, National Radio Institute, Washington—9, D. C.

TRAINING MEN FOR VITAL RADIO JOBS

64 page Book FREE



Here Are Just a Few of The Subjects This Lesson Covers 31 PHOTOS, CHARTS, DRAWINGS

- How superheterodyne receivers work
- How to remove tubes, tube shields
- Three reasons why radio tubes fail
- Electrodynamic loudspeaker:
 - How it works
- Replacing damaged cone
- Recentering voice coil
- Remedies for open field coil
- Output transformer construction, repair
- Gang tuning condenser:
 - Construction of rotor, stator
 - How capacity varies
- Restringing dial cord
- Straightening bent rotor plates
- I. F. transformers—What they do, repair hints
- How to locate defective soldered joints
- Inside story of carbon resistors
- Paper, electrolytic, mica, trimmer condensers
- How condensers become shorted, leaky
- Antenna, oscillator coil facts
- Power transformer: construction, possible troubles
 - Installing Power cord
- Troubles of combination volume control, on-off switch
- Tone controls
- Dial lamp connections
- Receiver servicing technique:
 - Checking performance
 - Testing Tubes
- Circuit disturbance test
- Isolating defective stage
- Locating defective part

MAIL COUPON NOW.

J. E. SMITH, President, Dept. 3JP3
National Radio Institute,
Washington—9, D. C.

Mail me FREE without obligation.
your Sample Lesson and 64-page
book, "Win Rich Rewards in Radio."
(No salesman will call. Write
plainly.)

NAME..... AGE.....
ADDRESS.....
CITY..... STATE..... 4FR



"THIS WISDOM MUST DIE!"



Truths That Have Been Denied Struggling Humanity

FOR every word that has left the lips of bishops or statesmen to enlighten man, a thousand have been withheld. For every book publicly exposed to the inquiring mind, one hundred more have been suppressed—*damned to oblivion*. Each year of progress has been wilfully delayed centuries. Wisdom has had to filter through biased, secret sessions or ecclesiastical council meetings, where high dignitaries of state and church alone proclaimed what man should know.

Are you prepared to demand the hidden facts of life? Will you continue to believe that you are not capable of weighing the worth of knowledge that concerns your personal freedom and happiness? Realize that much that can make your life more *understandable* and *livable* has been left unexplained or intentionally destroyed. At first by word of mouth only, and now by private discourses, are *revealed* those truths which secret brotherhoods preserved in ancient temples and hidden sanctuaries, from those who sought to selfishly deprive humanity of them.

THIS free BOOK OF EXPLANATION

Let the Rosicrucians, one of these ancient brotherhoods of learning, tell you about these amazing truths, and explain how you, too, like thousands of others, may now use them to enjoy the fullness of life. The Rosicrucians, (not a religious organization) invite you to use the coupon opposite and receive the FREE copy of the fascinating, Sealed Book, with its startling tale of *self help*.

The ROSICRUCIANS (AMORC)
SAN JOSE, CALIFORNIA, U. S. A.



Scribe X. F. A.
THE ROSICRUCIANS (AMORC)
Rosicrucian Park, San Jose, California, U.S.A.

Please send me your FREE Sealed Book. I am sincerely interested in learning how I may receive these long-concealed facts of life.

Name.....

Address.....

BILL, YOU SURE HAVE A SWELL BUILD! DID YOU TRAIN FOR A LONG TIME ?

ABSOLUTELY NOT! THE ATLAS DYNAMIC TENSION SYSTEM MAKES MUSCLES GROW FAST!

Here's the Kind of MEN I Build!

Charles Atlas

An actual untouched photo of Charles Atlas, holder of the title, "The World's Most Perfectly Developed Man."



J. G. O'BRIEN
Atlas Champion
Cue Winner
This is an ordinary snapshot of one of Charles Atlas' California pupils.

Will You Let Me PROVE I Can Make YOU a New Man?

Only 15 Minutes a Day

My method—"Dynamic Tension"—will turn the trick for you. No theory—every exercise is practical. And, man, so easy! Spend only 15 minutes a day in your own home. From the very start you'll be using my method of "Dynamic Tension" almost unconsciously every minute of the day—walking, bending over, etc.—to BUILD MUSCLE and VITALITY.

FREE BOOK "Everlasting Health and Strength"

In it I talk to you in straight-from-the-shoulder language. Packed with inspirational pictures of myself and pupils—fellows who became NEW MEN in strength, my way. Let me show you what I helped THEM do. See what I can do for YOU! For a real thrill, send for this book today. AT ONCE, CHARLES ATLAS, Dept. 19, 115 East 23rd Street, New York 10, N. Y.



**CHARLES ATLAS, Dept. 19,
115 East 23rd Street, New York 10, N. Y.**

I want the proof that your system of "Dynamic Tension" will help make a New Man of me—give me a healthy, husky body and big muscular development. Send me your free book, "Everlasting Health and Strength."

Name.....
(Please print or write plainly.)

Address.....

City..... State.....

☐ Check here if under 16, for Booklet A.

I DON'T care how old or young you are, or how ashamed of your present physical condition you may be. If you can simply raise your arm and flex it I can add SOLID MUSCLE to your biceps—yes, on each arm—in double-quick time! Only 15 minutes a day—right in your own home—is all the time I ask of you! And there's no cost if I fail.

I can broaden your shoulders, strengthen your back, develop your whole muscular system INSIDE and OUTSIDE! I can add inches to your chest, give you a vise-like grip, make those legs of yours lithe and powerful. I can shoot new strength into your old backbone, exercise those inner organs, help you cram your body so full of pep, vigor and red-blooded vitality that you won't feel there's even "standing room" left for weakness and that lazy feeling! Before I get through with you I'll have your whole frame "measured" to a nice, new, beautiful suit of muscle!

What's My Secret?

"Dynamic Tension!" That's the ticket! The identical natural method that I myself developed to change my body from the scrawny, skinny-chested weakling I was at 17 to my present super-man physique! Thousands of other fellows are becoming marvelous physical specimens—my way. I give you no gadgets or contraptions to fool with. When you have learned to develop your strength through "Dynamic Tension" you can laugh at artificial muscle-makers. You simply utilize the DORMANT muscle-power in your own God-given body—watch it increase and multiply double-quick into real, solid LIVE MUSCLE.



*If he could only see me
Now!*

There's one guy back in Florida who would get just as big a bang out of this as I do—my first instructor. And in a way, he got the Zero, not me. I wouldn't have been up there in the sun when they came over this morning if he hadn't had the confidence and patience during those first hours. Sometimes I think the primary instructors are the guys that are really winning the War.

**SPECIALIST TRAINING COURSES
FOR WOMEN
(Age 18-40)**

Radio code, radio maintenance, instrument technician, aircraft drafting and design, Link trainer instructors.

Send for our free beautifully illustrated 24 page booklet giving details of our aviation specialist courses. Address Dept. 9.

Buy More War Bonds

"Keep 'em Flying"



SCHOOL OF AVIATION

3240 N. W. 27th AVENUE • MIAMI, FLORIDA

Name _____ 9
Address _____
City _____ State _____

Contractors to
**UNITED STATES ARMY AIR FORCES
CIVIL AERONAUTICS ADMINISTRATION
ROYAL AIR FORCE**

Coming Next Month

SPIES are at work in our midst, trying to help our enemies with reports on our arms production, convoys, and troop movements. Against them are pitted the best brains of the FBI. Arthur Grahame brings you the thrilling story of this deadly battle of wits, in which modern scientific methods are mingled with the time-honored tricks of the secret agent.

GOING UP! Ceilings for aircraft operation have been pushed upward by the war. Now, aviation men are looking ahead toward commercial flying at the 50,000-foot level when peace comes. William S. Friedman discusses the problems of high-altitude flying and tells how experimenters are blazing the trail for the sky liners that will navigate the stratosphere tomorrow.


INSECTS offer fascinating subjects for your camera. All about you in summer are fantastic faces and figures, waiting to be recorded on film. Your guide to this inviting field of photography is Edwin Way Teale, whose insect pictures in newspapers, magazines, and books have won him top rank in his field. He tells you how to do it with ordinary equipment, and illustrates his advice with his own inimitable work.

DON'T SNEER AT THE FILE. This humble tool, sometimes treated as the stepchild of the machine shop, is playing a big part in war production. You will find a lot of things you didn't know about files—how they are made, what kinds there are, and how to take care of them—in an article by Jean Ackermann. Since there are over 3,000 specialized types of files in use, the subject is no small one.

PLANET OF MYSTERY. Mars, Earth's closest kinsman in the solar system, has always fascinated men. Because its climatic conditions approach those of our own planet, we suspect that it may be peopled by creatures like ourselves; strange markings on its face suggest canals or other artificial works. What are the latest views of science on this perennially attractive theme? A distinguished astronomer brings you up to date on the mystery of Mars.

IT WILL SOON BE TIME to lay up your boat for the winter. And right there is a place where the proverbial stitch in time saves plenty. Let J. A. Emmett show you how to make the small repairs and take the precautions that will lengthen the life of your boat and save you expensive jobs later on.

MEN! **ELECTRICITY** *whether you are* **16** OR UP TO **50** GET THE TRAINING YOU NEED IN 12 WEEKS AT COYNE



DON'T BE HELD BACK BY:

- **AGE!**
See the "oldster" in this picture! Men like him can have a real fut re in Electricity. It isn't how young or old you are, it's what you KNOW, that counts!
- **LACK OF EXPERIENCE!**
You get actual shop experience on real equipment at Coyne, to qualify you for a good job quickly.
- **LACK OF CASH!**
My "Pay-tuition-after-graduation" plan has helped hundreds of fellows who had very little money. I even help you get part-time work to help pay living expenses while training.
- **LACK OF SCHOOLING!**
It is not necessary that you be a high school graduate, to take my training. Coyne instructors know how to explain each step in an easy, understandable way.

Do VITAL WAR WORK...with a VICTORY FUTURE!



I'LL FINANCE YOUR TRAINING!

Don't wait to be assigned to some dull, low-pay, no-future job! Get your training at Coyne NOW — and be ready soon to take your pick of many well-paid electrical positions.

Learn to do more vital work for America's war program. In 12 short, busy weeks in the Coyne Shops you can get the "know-how" you need for a real opportunity now — and at the same time you'll be in a field with a peace-time future.

Learn-by-Doing on Real Equipment

Coyne has a vast amount of floor space in shops where you learn on motors, switchboards, electronic devices, air conditioning and refrigeration apparatus, auto and aircraft engines. You also learn house wiring, motor wiring, armature winding, etc., etc.

You don't need previous experience or advanced education. You train by actual work. In 90 days at Coyne you can master this training and be ready for a good job—a COYNE-TRAINED ELECTRICIAN!

START NOW—PAY LATER!

Lots of fellows who come to Coyne have very little cash. So don't delay for that reason. I'll finance your training. I'll help you get part-time work to help pay living expenses while in school. You can pay tuition in easy monthly payments AFTER YOU GRADUATE.

JOB SERVICE FOR LIFE

As soon as you're trained, my Graduate Employment Service will assist you in getting located. This service is FREE to graduates. We have placed men in fine jobs all over America. You'll find this service a big help now and throughout your lifetime.

GET MY BIG FREE BOOK!

See what Coyne offers. My big book of pictures, facts and PROOF is yours on request. Clip and mail coupon at once. Learn how quickly and easily you can become a COYNE-TRAINED ELECTRICIAN. Your opportunity is waiting. Send for my big book TODAY.



H. C. LEWIS
President
COYNE ELECTRICAL SCHOOL
500 So. Paulina St. Dept. 63-73 Chicago, Ill.

SEND COUPON NOW—for My Big Free Book!

New Opportunity Offer!

EXTRA COURSE IN

RADIO AND ELECTRONICS INCLUDED!



Electricity is the foundation of all Radio, Television and Electronics. When you combine your Coyne electrical training with my new special Radio and Electronics course, you have the basis for a great future in this sensational, fast-growing field.



44 YEARS OF SUCCESS — AMERICA'S PIONEER "LEARN-BY-DOING" SCHOOL

H. C. LEWIS, President
COYNE ELECTRICAL SCHOOL
500 S. Paulina Street, Dept. 63-73, Chicago, Ill.
Send me your Free Book. Tell me about your Special Radio-Electronics Training at no extra cost, and Pay-Tuition-after-Graduation offer.

NAME.....
ADDRESS.....
CITY..... STATE.....

Readers Say:

Here's the Wright Dope on Early Airplane Engines

IN A recent issue you make the statement that the engine made by the Wright brothers was the first engine powerful enough and light enough to permit sustained flight. I

DA VINCI DESIGNED
A FLYING MACHINE TOO,
A FEW HUNDRED YEARS
AGO, BUT!!



would therefore like to call your attention to the fact that when the Wrights designed and built their engine, there already existed a better engine, designed and built in 1901 by Charles M. Manley, who at the time was also working on the problem of flight. Let me hasten to explain that I have no intention of belittling the work of the Wright brothers. Despite that they were not engine designers, they were successful in building their engine even after automotive engineers had told them that such an engine was impossible.

Manley's engine was a five-cylinder, water-cooled, radial type of five-inch bore, with a $5\frac{1}{2}$ -inch stroke, and 539.96-cubic-inch displacement. It developed 52.4 hp. at 950 r.p.m., and its total weight, including radiator, gasoline tanks, and water, was 192 pounds—or 3.66 pounds per horsepower.

The Wrights' engine, built in 1903, was a four-cylinder in-line type of four-inch bore and stroke. It developed 12 hp. at 1020 r.p.m., and, complete with radiator, tanks, water, and fuel, it weighed 200 pounds—or 16.66 pounds per horsepower. For the first few moments of its life it developed 16 horsepower, but when finally installed in the plane, it gave only 12.—C. E. St. J., Honolulu, T. H.

Two Good Puffs for the Chest-Inflation Dept.

IN TODAY'S paper there is a news item that our Army Air Forces have accepted a new type of portable radio which sends sustained distress signals. The aerial is held aloft by a kite. In the April issue of your magazine, which I received a couple of months ago, this same radio is described in full on pages 94-95. A few weeks ago, the newspapers published the "startling" news that one of Great Britain's secret weapons consists of a shell which, after it has been fired, floats down on a parachute, entangling enemy planes in its dangling wires and forcing them down. On page 111 of your May, 1940, issue, this "new" weapon is described in full. These are but two of many instances in which I find that P.S.M. has "scooped" the newspapers. Keep up the good work.—D. M., Brooklyn, N. Y.

How To Give a Sucker a Break

IN ONE of your recent articles there arose the question of how to pour water into an aquarium without disturbing the contents. A good way is to lower the bottom of a net slightly below the surface of the water and then pour the fresh water into the net. I find this is a lot easier on the poor fish.—D. B., Webster Groves, Mo.

He Puts a Ceiling on Ciphers

IN CONNECTION with your recently published article, "Pellets of Power," there appears the statement—"that the number of vagrant electrons in a cubic inch of copper wire is

15 x 10²³—ten followed by 23 ciphers." This is incorrect. Ten to the 23rd power is 10 followed by 22 ciphers, or one followed by 23 ciphers.—D. R., Lansing, Mich.

AW, THAT'S ONLY
ONE LESS!



You're quite right, D. R. Thank you for calling it to our attention, and for giving us an opportunity to make this belated acknowledgment for the

benefit of those readers who might have found themselves burdened down with one too many ciphers.—Ed.

THE TOUCH OF TOMORROW IN THE PLANES OF TODAY



A New Industry Comes Out of the Woods

Plywood, the structural material of the future, takes to the skies today. Planes of many types are now being made of plywood, superior in certain characteristics even to fine steel or aluminum.

With war-time expansion of plane production, Fairchild foresaw shortages in the light metals. Research and engineering development of plywood at Fairchild were given a great stimulus. New data and new techniques were developed, made possible by recently perfected adhesives. Plywood craftsmanship jumped ahead many years in a few short months.

By a patented Fairchild process, known as DURAMOLD, layer-on-layer of wood, laid cross-grain and permanently joined with special resins under heat and pressure, may now be molded into single and multi-curved structural surfaces of consistently high quality.

DURAMOLD possesses some distinct advantages over metal aircraft surfaces. It is more fire-resistant. It makes lighter, stronger planes; the rigid

DURAMOLD shell is its own support, eliminating the need for a great clutter of internal stiffeners, bulkheads, and other reinforcing members necessary in thin metal construction. It does not wrinkle nor buckle in the airstream, as does a metal surface. There are no non-flush rivets, as no rivets are required. Thus, it is *smoother* in the air . . . horsepower is not handicapped by increased "drag." The plane can fly faster, is more maneuverable and has greater lift and range in the field of high-speed performance.

Production of DURAMOLD structures in spars, flat pieces, and complex curved surfaces is now concentrated within the aviation industry. Its purposes are 100% the purposes of war. But, when victory is won, the techniques, facilities and craftsmanship of a new industry can and will be applied to a multitude of peace-time products.

DURAMOLD, another example of those Fairchild achievements which put the "touch of tomorrow in the planes of today," is available to all "priority" manufacturers. Write for free illustrated booklet.

BUY U. S. WAR BONDS AND STAMPS



ENGINE AND AIRPLANE CORPORATION
30 ROCKEFELLER PLAZA, NEW YORK

Ranger Aircraft Engines Division
Farmingdale, L. I.

Fairchild Aircraft Division
Hagerstown, Md. . . . Burlington, N. C.

Duramold Division
New York, N. Y.

SEPTEMBER, 1943

Please mention POPULAR SCIENCE MONTHLY when writing to advertisers.

17

FREE DICTIONARY of names



- ★ 29 informative pages
- ★ Over 900 given names
- ★ Both men's and women's
- ★ 36 color illustrations

Look up the origin and meaning of your own name and the names of your friends. We want you to have a free copy of this fascinating dictionary so you'll remember what our name means:

"ETHYL is a trade mark name. It stands for an antiknock fluid made only by the Ethyl Corporation. Ethyl fluid is put into gasoline by oil companies to prevent knocking."



**SEND TODAY FOR YOUR
FREE COPY**

"WHAT'S IN A NAME?"

Dept. H-11, Box 18, Madison Sq. P. O., N. Y. C.
Please send me a free copy of "What's in a Name?"

Name.....
(PLEASE PRINT)

Address.....

City & State.....

Know the Technical Art of Tomorrow

PLASTICS

FOR INDUSTRIAL USE

By John Sasso
229pp., illustrated, only \$2.50

Packed with clear explanations and data on plastic materials, properties, working factors—molding methods—pointers on good mold design—causes and remedies of faults in molded parts—how to machine and finish plastic parts—kinds of plastics, advantages for different uses—etc.—practical treatment of essentials of plastic design and production.

10 DAYS' FREE TRIAL. Read and examine book before purchase. Write name, address, and business reference in margin of this ad, and receive book on approval—pay for or return it in 10 days. For this offer, write Frank B. Dickman, McGraw-Hill Book Co., 330 W. 42nd St., New York 18, N. Y.

for
**DESIGNERS
INVENTORS
DRAFTSMEN**

Readers Say:

He'll Drive His Bathtub Water Crazy

To P. W. M. whose letter appeared in the July issue, and who states that the water that leaves the bathtub on Saturday night usually has a tendency to whirl counterclockwise, I say **BA-LONEY!** Many's the time I've reversed the direction of the whirl—whether it was clockwise or counterclockwise—merely by spinning my hand in it the opposite way. In fact, I changed the direction of one whirl so often, and got the water so dizzy, that it tried to escape by climbing up over the edge of the bathtub.

I also want to say that the reason a dog makes several turns before lying down is that, having spent the day going around in circles chasing cats, birds, and postmen, he naturally wants to unwind before he goes to bed. So he takes a few turns in the opposite direction.—M. L. H., Levering, Mich.

**NOT WHEN I TOOK
SATURDAY NIGHT
BATHS!**



Anyone Got a Better Recipe for Pi?

HERE is something that has been puzzling me for quite a while—and I'm wondering if you know the answer. When, where, and how was Pi (3.1416159) first brought into use, and to how many places may it be carried out? I believe that a lot of readers would be glad to know the answers to these questions.—J. M., St. Louis, Mo.

According to our best information, Pi (3.14159265359) has been carried out to 707 decimal places by a W. Shanks, whose work recently appeared in a French scientific journal. It can, however, be carried out indefinitely. In the computing of Pi, two polygonal figures have been used; one inscribing a circle, the other circumscribing it—the mean length of the two then being taken as the perimeter of the circle. The first use of Pi probably dates back to the days when Archimedes took to running naked through the streets of Syracuse shouting "Eureka!" over his now famous law of displacement.—Ed.

AUTO-LITE SPARK PLUGS

IN SERVICE ON EVERY FRONT



"Gran'maw—thar's someone a-knockin' at the door!"

"PLUG-CHEK" WAKES UP SPARK-WEARY ENGINES

Today, opportunity is knocking at the garage doors of America's car owners. Here's the good news! If your car is "spark-weary" Auto-Lite Spark Plug dealers can help you make your gas coupons go further with "Plug-Check" inspection service.

Actual tests by the American Automobile Association show "Plug-Check" can increase gas mileage as much as 12%.

Get more essential miles of transportation. Ask your nearest Auto-Lite Spark Plug Dealer for "Plug-Check" Inspection Service today.

THE ELECTRIC AUTO-LITE COMPANY
Toledo, Ohio • Merchandising Division • Sarnia, Ontario



Color and condition tell if plugs are operating properly. Matching your plugs with those illustrated on the "Plug-Check" is the first step in getting new life for "spark-weary" engines.

50 ELECTRICAL WAYS TO Make Money.



**Build These Newly Designed
Electrical Items for Pleasure
or Profit**

**No Experience or Special
Tools Necessary
LEJAY MANUAL Newly
Enlarged and Revised**

No other book of its
type on the market.
Never before has so
much information been
jammed between two
covers as in the 1943 Le-
Jay Manual—for only
ONE DOL-
LAR BILL
and Fifty
Cents.

**Over 100
Electrical
"Build Your
Own" Items
Under One Cover**

200 Amp. Generator Welders
Large Transformer Welders
Workshop Spot Welder
Gensmith's Carbon Welder
8, 12, 22, 110-Volt Motors
Electric Outdoor Water
Wind-driven Light Plant

Electric Fanucers
Electric Drills
Electric Saws
Bench Grinders
Electric Bicycle Pusher
Inset Electrocutters
Armature Rewinding, etc.

Welding fits you for a defense
job, and the LeJay Manual is
chock full of other money-mak-
ing projects for the home work-
shop. Shows how to build and
install electrical equipment for
farms, camps, cottages, garages,
homes and workshops. Also how
to provide your own light
and power where no electric
service is available. Most
of these items can be made
from old generators avail-
able at car wreckers and
others.

**\$ 1⁵⁰
ONLY**

**LeJAY MANUFACTURING COMPANY,
23 LeJay Building, Minneapolis 8, Minn.**

Gentlemen: Please send me (Postpaid) your big 1943 LeJay
Manual, for which I enclose a DOLLAR BILL and Fifty Cents:

☐ Check ☐ Money Order ☐ Cash or Stamps ☐ COD Plus Postage

NAME.....

ADDRESS.....

CITY..... STATE.....

Readers Say:

*He Finds the Coffee Good,
and Our Timeliness Amazing*

I WANT to say that I heartily agree with
the coffee-making method described by C.
J., of Elgin, Ill. I have never drunk any cof-
fee that tastes as well as that made by the
old-fashioned pot-boiling method. You use
less coffee and still get the full flavor. I also
want to say that I am amazed by the timeli-
ness with which you print precisely the in-
formation that I happen to be looking for
at the moment. Whenever I run into a prob-
lem, I simply pick up P. S. M. and there is
the answer—handed up to me on a silver
platter.—C. G., San Francisco, Calif.

*In Washington, Even the
Weather Is Uncertain*

IT OCCURS to me that a company that could
make some new kind of an overcoat that
would be waterproof, warm, and yet not too
heavy, and that could be worn in the busses
and street cars of Washington, D. C., without
having it torn off your back, would stand
to make a lot of money. When I leave the
house in the morning, the day might be a
rainy one. On my way to work, the sun will
come out strongly, and the day will sud-
denly become very warm. When I leave my
work at night the weather is likely to have
become cold and windy. And then to top
it all, I get a thorough pushing around rid-
ing home in the bus. I have lived all my life
in Washington, but I still haven't found a
coat that answers all these problems. Do
you think that some of your readers in other
cities might be able to give me the solution?
—W. P. C., Washington, D. C.

*Wanted: An Attractive Girl
to Be Fictional Character*

A TERRIBLE thought has just occurred to me,
and I'm rushing to let you know about it
so that you can take the proper precautions.
The Gus and Joe stories in your automobile
department are a favorite feature of mine.
So will you please have Gus get a lady
mechanic so that she won't be drafted. I'd
hate to have anything really go wrong with
those stories.—W. R. K., Elmwood Park, Ill.

AUDELS AIRCRAFT WORKER . . . \$1

Answers Your Questions on 1—Aircraft Materials, Terms, Parts. 2—Blueprints, Working Drawings. 3—Mathematics, How to Figure. 4—Layout & Bending. 5—Tools & Machines. 6—Riveting, Spot Welding & Hints. 7—Fabrication, Angles, etc. 8—Assembly, Fuselage, Wing & Final—How to Use Tools. 9—Tables & Data. Symbols, Army & Navy Specifications, etc. 240 Pages illus.

AUDELS SHEETMETAL PATTERN LAYOUTS . . . \$4

Developed by Experts for Sheet Metal Workers, Layout Men & Mechanics. A Practical Encyclopedia in 10 Sections, size 7 x 10 2-1125 Pages—240 Layouts—1600 Illustrations. 1901 Key Facts. Fully Indexed for ready reference in answering your layout problems. Covers all phases of sheet metal work including Pattern Cutting, Pattern Development & Shop Procedure.

AUDELS SHEETMETAL WORKERS HANDY BOOK . . . \$1

Practical inside information. Fundamentals of Sheet Metal Work. 388 pages. Illustrated. 11 sections. Clearly written. Essential & important facts, figures, pointers in everyday language. Ref. Index.

AUDELS WELDERS GUIDE . . . \$1

A concise, practical text on operation & maintenance of all welding machines for all mechanics. Over 450 pages. Illustrated. Covers all methods of electric and acetylene welding including airplane work.

AUDELS ANSWERS ON BLUE PRINT READING . . . \$2

For Mechanics & Builders. Covers all types of blue print reading including ship & airplane. 376 pages, fully illustrated.

AUDELS NEW MACHINIST & TOOLMAKERS HANDY BOOK . . . \$4

Covers modern machine shop practice in all its branches. 5 practical books in 1. New from cover to cover. Tells how to set up & operate lathes, screw and milling machines, shapers, drill presses and all other machine tools. 1600 pages, fully illustrated. 5 x 6 1/2 x 2. Indexed. 1540 questions, 1540 answers. 55 chapters. Indexed. 2—Blue Print Reading & How to Draw. 3—Calculations & Mathematics for Machinists. 4—Shop Physics. 5—How to Use the Slide Rule. 60 chapters. Easy to read and understand. A shop companion that answers your questions.

AUDELS MATHEMATICS & CALCULATIONS FOR MECHANICS \$2

Mathematics for home study or reference. 700 pages, 550 illus. Practical material for mechanics. How to figure correctly. Easy, correct methods covering a complete review of all the mathematics.

AUDELS AUTOMOBILE GUIDE . . . \$4

A practical quick ready reference book for auto mechanics, service men, operators & owners. Explains theory, construction & servicing of modern motors cars, trucks, buses & auto type Diesel engines. 1540 pages, fully illustrated. 55 chapters. Indexed. A standard book for mechanics. New build drive cover.

AUDELS DIESEL ENGINE MANUAL . \$2

A practical, concise treatise with questions and answers on the theory, operation and maintenance of modern diesel engines including General Motors 2 cycle Diesel. 384 pages, fully illus., flexible binding, pocket size. All details plainly brought out, this book is of extreme value to engineers, operators & students.

AUDELS RADIOMANS GUIDE . . . \$4

A key to the practical understanding of radio include Frequency Modulation, Television, etc., Aircraft & Marine Radio. For radio engineers, servicemen, amateurs. 772 pages. 400 Illustrations & Diagrams. Photos. Review Questions & Answers, Reference Index. Authentic, clear, concise.

AUDELS HANDY BOOK OF PRACTICAL ELECTRICITY . . . \$4

For maintenance engineers, electricians & all electrical workers. 1440 Pages, 2600 Illus. Covers important electrical information in handy form—including Marine Wiring, Radio Principles, Welding. Indexed. A Key to a practical understanding of electricity.

AUDELS CARPENTERS & BUILDERS GUIDES—4 Vols. . . . \$6

A practical illustrated trade assistant on modern construction for carpenters, joiners, builders, mechanics and all woodworkers. 4 vols., 1600 pages, 3700 Illustrations, flexible covers. Each volume pocket size. Sold separately \$1.50 a Vol.

AUDELS PLUMBERS & STEAMFITTERS GUIDES—4 Vols. . . . \$6

A Practical Trade Assistant & Ready Reference. Explains in plain language & by clear illustrations diagrams the principles of modern plumbing practice including Marine Pipe Fitting and Air Conditioning. 4 Vols.—1670 Pages—3410 Diagrams. Each Vol. Pocket Size. Sold Separately \$1.50 a Vol.

AUDELS WIRING DIAGRAMS . . . \$1

210 Pages. Illustrated. Gives practical facts on wiring of electrical apparatus. It explains clearly in simple language how to wire apparatus for practically all fields of electricity. Each diagram is complete & self-explanatory. Highly Endorsed Pocket Companion.

AUDELS ELECTRONIC DEVICES . . . \$2

Tells What You Want to Know About Electric Eye. Easily Understood. Covers photo-electric cells & their applications. Amplifiers, illumination, frequencies, voltage, photocell, tubes, Ohm's Law, wiring diagrams, etc.

AUDEL, PUBLISHERS, 49 W. 23 St., N. Y.

AN AUDEL GUIDE IS A GOOD FRIEND!

Use the brains and experience of others in these Guides of the Trades. Save time and money with right methods, short cuts, labor saving ideas. CHECK NOW! You can look over any Audel Guide in your home. Start the Easy Payments if satisfied.

----- CUT HERE ----- MAIL ORDER

THEO. AUDEL & CO., 49 West 23rd St., New York

Please mail me for 7 days' free examination the books marked (X) below. I agree to mail \$1 in 7 days on each book or set ordered, and to further mail \$1 a month on each book or set ordered until I have paid purchase price.

If I am not satisfied with Guides I will return them.

- | | |
|--|------|
| ☐ Audels AIRCRAFT WORKER . . . | \$1 |
| ☐ Audels SHEET METAL PATTERN LAYOUTS . . . | 4 |
| ☐ Audels SHEET METAL WORKERS Handy Book . . . | 1 |
| ☐ Audels WELDERS GUIDE . . . | 1 |
| ☐ Audels ANSWERS ON BLUEPRINT READING . . . | 2 |
| ☐ Audels MACHINISTS & TOOLMAKERS Handy Book 4 . . . | 2 |
| ☐ Audels MATHEMATICS AND CALCULATIONS . . . | 2 |
| ☐ Audels AUTO GUIDE . . . | 4 |
| ☐ Audels DIESEL ENGINE MANUAL . . . | 2 |
| ☐ Audels SHIPFITTERS Handy Book . . . | 2 |
| ☐ Audels RADIOMANS GUIDE . . . | 4 |
| ☐ Audels MECHANICAL Dictionary . . . | 4 |
| ☐ Audels Handy Book of PRACTICAL ELECTRICITY 4 . . . | 4 |
| ☐ Audels CARPENTERS and Builders Guides (4 vols.) 6 . . . | 6 |
| ☐ Audels PLUMBERS and Steamfitters Guides (4 vols.) 6 . . . | 6 |
| ☐ Audels WIRING DIAGRAMS . . . | 1 |
| ☐ Audels ELECTRIC Dictionary . . . | 2 |
| ☐ Audels MILLWRIGHTS and Mechanics Guide . . . | 2 |
| ☐ Gueths Mechanical DRAWING Course . . . | 1 |
| ☐ Audels ELECTRONIC DEVICES . . . | 2 |
| ☐ Audels MARINE Engineers Guide . . . | 3 |
| ☐ Rogers MECHANICAL DRAWING and Design . . . | 2 |
| ☐ Rogers MACHINIST Guide . . . | 2 |
| ☐ Audels MASONS and Builders Guides (4 vols.) . . . | 6 |
| ☐ Audels ENGINEERS and Mechanical Guides . . . | 12 |
| Nos. 1, 2, 3, 4, 5, 6, 7 and 8 complete . . . | 12 |
| ☐ Audels Answers on PRACTICAL ENGINEERING . . . | 1 |
| ☐ Audels ELECTRICAL POWER CALCULATIONS . . . | 2 |
| ☐ Hawkins ELECTRICAL Guides at \$1 each . . . | 1 |
| Nos. 1, 2, 3, 4, 5, 6, 7, 8, 9 and 10 . . . | 10 |
| ☐ Audels ANSWERS TO REGENERATION . . . | 2 |
| ☐ Hawkins Aids to ENGINEERS EXAMINATION . . . | 2 |
| ☐ Master PAINTER and DECORATOR . . . | 2 |
| ☐ Audels GARDENERS & GROWERS GUIDES \$1.50 a Vol. . . . | 1.50 |
| ☐ Audels NEW ELECTRICAL LIBRARY at \$1.50 a Volume . . . | 1.50 |
| Vols. I, II, III, IV, V, VI, VII, VIII, IX, X, XI, XII. | |

Name _____

Address _____

Occupation _____

Employed by _____ P.S.M.



High School Course at Home

MANY FINISH IN TWO YEARS

You may finish this simplified yet complete course as rapidly as your time permits. Individual instruction for each student. Equivalent to resident school work—prepares for college entrance exams. Standard texts furnished—Diploma. Credit for subjects completed elsewhere. Single subjects if desired.

BUSINESS—INDUSTRY—MILITARY

Perhaps in no other time has such great emphasis been placed upon the importance of a High School education. Military authorities, management of essential industry, and executives of civilian business all join in emphasizing the need for High School training.

Promotions, to higher rank and to better jobs, go to those who can think clearly, speak correctly, write intelligently, and figure accurately as a result of their High School training.

Our High School course prepares you to meet preparatory educational requirements in all fields—quickly.

COLLEGE ENTRANCE

During the past 19 of our 46 years, our High School graduates have been admitted to 531 different Universities, Colleges, Junior Colleges, and Normal Schools—80% of them without entrance examinations. Course also prepares you for passing pre-professional examinations.

TO HELP WIN TODAY— TO HELP BUILD TOMORROW— COMPLETE YOUR TRAINING NOW

No matter what work you do today, you can do it better—improve it—if you're a High School graduate. No matter what you earn now, you'll meet keen competition "when the lights go on again," and you'll need a High School education to hold your own.

No matter what you plan to do—to enter College, Business, Industry, the Professions, or to be more successful socially—the increased ability and self-confidence you get from our High School training will be invaluable to you. Moderate fees, payable monthly, cover all instruction, textbooks and Diploma. Start your training NOW.

MANY OTHER COURSES

Over 150 noted Educators, Engineers, and Business Men helped prepare our special instruction material, which is used by many resident schools, colleges, war training classes, apprenticeship programs, U. S. Navy and Province of Manitoba, Canada. We offer you quality training at home for the best paying lines as listed in the coupon. No obligation. Write TODAY.

Turn
Spare Time
into \$\$\$ by
Home Study

Mail coupon for information about line that interests you
American School, Drexel at 58th, Chicago 37

American School, Dept. H646, Drexel at 58th, Chicago 37, Ill.
Tell me how to train for line checked. No obligation.

☐ HIGH SCHOOL COURSE

- | | |
|---|---|
| ☐ Accounting (C.P.A.) | ☐ Drafting & Design |
| ☐ Air Conditioning | ☐ Electrical Engineering |
| ☐ Architecture & Bldg. | ☐ Mechanical Engineering |
| ☐ Automotive Engineering | ☐ Plastics Engineering |
| ☐ Aviation | ☐ Radio |
| ☐ Business Management | ☐ Refrigeration |
| ☐ Commercial Courses | ☐ Shipbuilding |
| ☐ Diesel Engineering | ☐ Shop Management |

Name

Address

AVIATION FOR YOUR CAREER PLUS WAR SERVICE



Both

AT THE SAME TIME

Before you are 18, MAKE YOURSELF THE KIND OF MAN THE AVIATION INDUSTRY OR THE AIR SERVICES WANT... THE KIND THEY CANNOT DO WITHOUT... so you can ADVANCE RAPIDLY. Since 1929, Curtiss-Wright Tech has been specializing in modern and progressive training for Aeronautical Engineers and Master Aviation Mechanics. (No flying involved.) Write for full information. Include name, address and date of birth. Dept. P5-9



CURTISS TECHNICAL **WRIGHT INSTITUTE**

GRAND CENTRAL AIR TERMINAL
Glendale (Los Angeles Co.) California

THIS TOWER OVERLOOKS AVIATION'S MOST DISTINGUISHED SCHOOL OF AERONAUTICS

Keep car radiators cleaned out for
greatest motor efficiency. Use

Sani-Flush 10c and 25c sizes
Directions on can

JIU JITSU 3 LESSONS 10¢

Investigate the course experts buy. Authentic, complete. Send 10c today for 3 trial lessons, full details. Modern School of JIU JITSU, Dept-K, S W. 52 St., N. Y. 19

Get the BIG book, "WONDERS OF SCIENCE SIMPLIFIED" and FREE "33 Power Telescope Kit"—all for \$1.98 prepaid. Order from

METRO PUBLICATIONS, Dept. 34-K, 50 West 17th St., N. Y. 11, N. Y.



GENUINE U. S. BARGAINS
O. D. Wool Blankets (used)...\$2.95
U. S. Army Ratton Bags (New)...49
U. S. Army Pup Vests (used)... 3.50
Slightly Used Army Caution Wheel with
Axles, 56" high, Wt. 322 lbs. \$37.50
Thousands of other bargains in military,
outdoor & sport goods for hunter, farmer,
scout. Send 10c for 32 page catalog re-
turned with first order.

A and N SUPPLY CO.
4784 LESTER ST. RICHMOND, VA. EST. 1892



HIGH BLOOD PRESSURE A DANGER SIGNAL

Often associated with Hardening of the Arteries, a Stroke, Paralysis, Heart Trouble, Kidney Disease, and other grave complications. Resultful treating methods of the Ball Clinic have proven dependable for nearly a quarter of a century. Send for FREE Blood Pressure Book today. No obligation.

BALL CLINIC, Dept. 5160, Excelsior Springs, Mo.

"NOW Show me the AUTO REPAIR JOB I can't DO!"

Here's proof you **CAN** do it:
FREE 7-DAY OFFER

How MoToR's New AUTO REPAIR MANUAL Serves as Your Complete Repair, Tune-Up & Service Guide for Every Car Built Since 1935!

ANY expert mechanic can tell you that this is the ONE and ONLY book needed to know everything necessary to keep America's cars rolling today! Easy, step-by-step instructions anyone who can read can follow. Hundreds of photos, diagrams and drawings show exact how-to-do-it.

Packed full of short cuts, it saves time and money—even for experts. Try it at our risk, and see for yourself!

It's a BIG BOOK, 8½ x 11 inches. More than 1000 illustrations, 603 pages. Special fabrikoid binding. Lies open at any page for work-while-

you-read. The only up-to-date book of its kind in all America!

Just Like 150 Official Shop Manuals—But All in One Book!

MoToR's AUTO REPAIR MANUAL contains all essential information from each manufacturer's own official shop procedure manual. Just look up the job, the model, the make, and go to work! Quick index gives you page and job instantly. Clear instructions, detailed pictures give you the "how" you want at once. PARTIAL Contents here can only give you an idea of the jobs it covers!

Thousands Now in Use!

Used by the U. S. Armed Forces, trade, technical schools all over the country, auto servicemen in nearly every town.

Right now—to see how this book can help you get at each job easier, do it better, and finish it faster—send coupon below for a FREE 7-DAY TRIAL.

SEND NO MONEY

When the postman brings you the AUTO REPAIR MANUAL, try it out on a few extra-tough jobs. See how the book can pay for itself! The first few days you use it! And unless thoroughly satisfied, return book in 7 days and pay nothing. Send coupon without money, TODAY! Address: MoToR Book Dept., Desk X29, 572 Madison Ave., New York 22, N. Y.

Published by MoToR, The Leading Automotive Business Magazine. Where MoToR's manuals are used you are assured of high standards of service and repair work.



Clear, Pictured, Job Facts on Every Car Built Since 1935!

Nearly 200,000 service and repair facts on all these makes:

American	Ford	Oldsmobile
Bentley	Graham	Overland
Auburn	Hudson	Packard
Austin	Hupmobile	Pierce
Buick	Lafayette	Arrow
Cadillac	La Salle	Plymouth
Chevrolet	Lincoln	Pontiac
Chrysler	Lincoln	Reo
Cord	Zephyr	Studebaker
De Soto	Mercury	Terreplane
Dodge	Nash	Willys

603 pages; 60 pages of text, charts, illustrations, covering carburetors and automatic chokes on all models.

Over 450 charts, tables covering important specifications, clearances, measurements, arranged in handy form, including: Tune-up Chart; Valve Measurements; Compression Pressure; Torque Wrench Reading; Starting Motor; Engine Clearances; Main & Rod Bearing Journal Dimensions; Generator; Clutch & Brake Specifications; Front End Measurements, etc.

Detailed, pictured instructions on Engines; Electric, Fuel, Cooling, Lubricating Systems; Transmissions; Wheels; Front Ends; Universals; Rear Ends, etc., etc.

Same FREE 7-Day Offer
Applies on MoToR's New

TRUCK REPAIR MANUAL!

Just published, for truck specialists, service stations, fleet owners—the first complete TRUCK REPAIR MANUAL covering EVERY job on EVERY truck made since 1936! 1400 pictures, 905 pages, 300,000 facts based on truck manufacturers' own official manuals. Used by U. S. Armed Forces. Every essential fact you need to know to do ANY job. Strong, fabrikoid binding, size 8½ x 11.

Covers all models, 1936-1942. All Gasoline Engines; ALL DIESELS, Hesselmans, Diesel Fuel Injection Systems. All basic adjustment and repair procedures described in easily-understood text and pictures: Fuel Systems, Governors, Lubrication Systems, Ignition Systems, Starters, Generators, Clutches, Transmissions, Front and Rear Axles, Torque Dividers, Transfer Cases, Brakes, etc.

Offered to you on the same FREE 7-Day Trial offer. Just check box in coupon at right—and mail us coupon.

MAIL COUPON NOW FOR 7-DAY FREE TRIAL

MoToR BOOK DEPT., Desk X29, 572 Madison Avenue, New York 22, N. Y. Rush to me at once: (check box opposite book you want).

☐ MoToR's AUTO REPAIR MANUAL (formerly MoToR's Factory Shop Manual). If O.K., I'll remit \$1 in 7 days, \$1 monthly for 4 months, plus 35c postage with final payment (\$5.35 in all). Or I'll return book in 7 days. (Foreign, remit \$7 with order.)

☐ MoToR's TRUCK REPAIR MANUAL. If O.K., I will remit \$2 in 7 days, \$2 monthly for 3 months, plus 35c postage with final payment (\$8.35 in all). Or I'll return book in 7 days. (Foreign, remit \$11 with order.)

Name _____ Address _____
City _____ State _____ Age _____
Employer _____ Occupation _____

☐ **SAVE 35¢!** Check here if enclosing full payment (check or money-order) WITH coupon. WE will then pay 35c postage. Same 7-day return privilege.

ELECTRICIANS

—and those who want to know Electricity!

Here at last is a 3-Volume Set of practical electrical books for the "beginner" or "old timer"

MAIL COUPON FOR 7 DAY FREE TRIAL

THE BOOKS YOU'VE BEEN WAITING FOR!

FREE With This Training!

150 COYNE SHOP PRINTS

Big 8½x11 in. book of 150 Coyne Shop Prints. Actual wiring diagrams, motor windings, radio hook-ups, etc. For daily use on job. Limited quantity, so ACT NOW. 1 yr. Personal Technical Service by mail from the Coyne Staff on any Electrical or Radio problem, FREE with set.

HUNDREDS OF PICTURES AND DIAGRAMS. HUNDREDS OF SUBJECTS, INCLUDING:

Radio—Television Electronics
Air Conditioning
Auto Electricity
Talking Pictures
Generators
Refrigeration
Power Plants
Diesel Engines
Motors—Armatures A.C. and D.C.

Now! What every Electrician, service man, radio man, maintenance man — in fact, any man interested in Electricity—has long needed!

It's an amazing 3-volume set of Electrical books to help you solve your every day problems in an easy, practical way, and to increase your knowledge of the electrical field.

WRITTEN SO YOU CAN UNDERSTAND IT!

The material is written so you don't have to wade through a lot of useless theory. It comes to the point and tells you in simple, understandable language about any electrical subject. Every subject is indexed so you can quickly locate it.

It is a course of Electricity in itself. Used by hundreds of Electricians on the job.

DON'T SEND A PENNY!

I'm so sure you'll never part with this set that I want to send it to you on 7 days FREE TRIAL. Mail coupon today. If satisfied with the books, send \$1.95 in 7 days and then \$3 a month until the total price of \$13.95 is paid. If not satisfied, send them back in 7 days and you won't owe me a cent.

H. C. LEWIS, Pres., Dept. 43-84, COYNE ELECTRICAL SCHOOL, 500 S. Paulina St., Chicago, Ill.

Send me, postpaid, the big 3-volume NEW EDITION Coyne Electrical and Radio Reference Encyclopedia and 150 Shop Prints FREE. Within 7 days after receiving books, I'll either return them or send you \$1.95 and then \$3 a month until the total price of \$13.95 is paid.

NAME.....
ADDRESS.....
CITY.....STATE.....
OCCUPATION.....AGE.....

SAVE 10%. Send cash price, \$12.55, with order if preferred — you save \$1.40. Same 7-day free trial and return privilege.

FREE TRIAL COUPON

Do You Make Mistakes in English?

EVERY time you speak or write you show just what you are. Mistakes in English reveal you as a person who lacks education and refinement. Lack of language power prevents you from presenting your thoughts in the strongest possible way. No matter what you do, real command of English will help you to your goal. Stop making mistakes in spelling, punctuation, pronunciation. Increase your vocabulary.

WONDERFUL INVENTION

Only 15 minutes a day with Sherwin Cody's new invention—and you can actually SEE your English improve. It teaches by HABIT—makes it easier to do the RIGHT way. Wonderful self-correcting lessons include spelling, punctuation, grammar and expression.



FREE BOOK ON ENGLISH Lack of language power may easily be costing you thousands of dollars every year. See what Mr. Cody can do for you; it costs nothing to find out. Mail a postal card or letter this very minute for free book. "How You Can Master Good English in 15 Minutes a Day." It will prove a revelation to you. **WRITE NOW.** Address: Sherwin Cody School of English, 189 Seaside Bldg., Rochester, N. Y.

Learn Profitable Profession in 90 days at Home



Earnings of Men and Women in the fascinating profession of Swedish Massage run as high as \$40 to \$70 per week but many prefer to open their own offices. Large incomes from Doctors, hospitals, sanitariums and private patients come to those who qualify through our training. The Army and Navy need hundreds trained in massage. Write for Anatomy Charts and booklet—They're FREE.

THE COLLEGE OF SWEDISH MASSAGE
100 E. Ohio St., Dept. 670, Chicago 11

Learn PHOTOGRAPHY at Home

Splendid opportunities. Prepare in spare time. Easy plan. No previous experience needed, common school education sufficient. Send for free booklet "Opportunities in Photography", particulars and requirements.

American School of Photography
1315 Michigan Ave., Dept. 1366, Chicago, Ill.

ARTISTS MAKE MONEY

Find out your ability. Send name, age, occupation and address for Free Vocational Art Test.

ART INSTRUCTION, INC., 9143 Art Instruction Bldg., Minneapolis, Minn.
(Formerly Federal Schools, Inc.)

KILLS FLEAS, LICE AND TICKS

PULVEX
FLEA POWDER

25¢ AND 50¢



SAVE RUBBER

Easy to fix cuts, bruises, worn spots in tires. SO-LO also mends shoes, raincoats, boots—any animal rubber, leather, cloth.


MEND the HOLE for 1¢
SPREADS ON like butter. Dries overnight. Flexible. Won't crack. Waterproof. Won't come off—guaranteed.
So-Lo AT HARDWARE & 10¢ STORES

SUPER JI JITSU

NOW GET TOUGH DOUBLE-QUICK!



Learn how YOU can be dangerous. Lick brutes twice your size with *only your bare hands*, even when they are armed. This powerful fighting system is unbelievably efficient. You don't need ox-like muscles — it's brains that count! New, easy self-study course at amazing low price. Free-trial offer and money-back guarantee. Hurry! Write today for FREE DETAILS. Nelson Co., 321 S. Wabash, Dept. J-505, Chicago.



RADIONICS- 3 Big Fields in 1

RADIO
ELECTRONICS
TELEVISION

Sales and services in this miracle industry have boomed in a few short years to billions of dollars. That requires more and more experts, trained men, to fill the ever-increasing number of technical positions constantly opening up. Everywhere you go you hear about Radar as a war weapon and how in peacetime it will have many applications in seeing thru fog, clouds and darkness. Ambitious men enrolled with National Schools today are preparing themselves for perhaps the most far-reaching technical-industrial expansion the world has ever known. They are looking ahead to personal prosperity. You can, too. Mail the coupon today.

MASTER ALL BRANCHES OF RADIO

NOW, as never before, the urgent need for Trained Radio Men has created a tremendous shortage. Manpower is being mobilized for duty on the TECHNICAL FRONT. Radio Engineers, Service men and operators, Experts in shops, in laboratories and countless unimagined of other applications are on the "MUST HAVE" list. The war has stimulated demand in both civilian and military fields. Regardless of whether you remain a civilian or enter Military Service, National Radio Training will qualify you for a real future, a good pay job, responsibility and marvelous opportunity for advancement.

LEARN AT HOME

NOW, you can learn AT HOME in your spare time. National's VICTORY training plan speeds up your progress right from the start, yet omits absolutely nothing vital to your preparation.

FASCINATING WAY TO LEARN RADIO

Eliminating dry text books, National's plan of rapid Home Training actually brings you the proved Shop-Studio-Lab service methods that are followed by National's resident training shops. This training is simplified so that you can easily grasp Radio step by step in a way that grows in its fascination every day. No previous experience needed. When you complete this Course you are prepared for a good Radio job at excellent pay or may establish your own radio business. Bear in mind that with the war-time curtailment of radio sets there is a huge increase in service work in homes. Radio manufacturing plants also need trained technicians to help produce over two billion dollars worth of military radio equipment. Factories are installing elaborate sound systems. Electronics is growing by leaps and bounds.

NATIONAL GRADUATES WIN GOOD POSITIONS

Thousands of graduates of National Schools are employed throughout America and in many parts of the World—strong testimonials of successful training.

"National Schools has done wonderful work for the man who wants to get ahead in life. Your trained men can get a job at a much higher salary."

G. K. Ivey, Washington, D. C.



"Your schooling helped me obtain a swell job. Now, in the Navy, I am finding the profession I learned at National. It will help my chances for rapid advancement."

E. Schroeder, U. S. Navy

SHOP PLAN
HO
TRAI

MEN WANTED

Ages 16-50

In Radio, age is not a factor. Training is the main requirement.

More than 37,000 National Graduates

2 FREE BOOKS

RADIO OPPORTUNITIES

— TRIAL LESSON —

REQUEST FULL DETAILS

GET INTO RADIO NOW!

PREPARE FOR CIVILIAN OR U.S. GOV'T. SERVICE



TESTED HOME TRAINING BY PROVED SHOP-FIELD METHOD

For 38 years National Schools has trained ambitious men for Top Pay trades. Squared behind your Home Training are the modern, completely-equipped Training Shops of National Schools where we develop and prove every Shop Method Assignment sent to you. Every phase of your training is personally supervised by an established Faculty of practical, experienced instructors and engineers.

They have developed progressive methods of training you in your own home, based on actual shop practice. Unique training facilities give you Home Training based on Resident School Shop principles—methods not available from any other source, to our knowledge. You'll be amazed when you receive our Complimentary Lesson and full details.

KEEP PRESENT JOB WHILE LEARNING

Regardless of previous education or age, you can Train for Radio. Continue your present job. Earn while you learn. If subject to Military Service, all the more important that you get pre-training.

MILITARY SERVICE

Prepare for Radio opportunities in U. S. Gov't. Service, in Army, Navy, Marine, Air Corps, Coast Guard and other branches. Pre-induction preparation gives many National graduates promotion and increased pay from the start. In addition, the time you spend in military service further develops your Radio technical ability so after the war you will be well qualified to handle the most expert, high-paying jobs in the booming Radio Industry. Many men now in military service are today taking National's shop-field training.

SPECIAL OFFER

So that you can demonstrate to yourself the ease and rapidity of learning Radio at home, National Schools will present to you one Complimentary Lesson free, accompanied by Opportunity Book of Facts and Details about all branches of Radio. Use the Coupon. Mail it today.

Quality for These Jobs
Radio Expert,
Broadcasting,
Aircraft-Marine-Indust.
Electronics,
Studio Techni-
cian, Gov't.
Service, Re-
manufacture.

NATIONAL SCHOOLS

Los Angeles
California

ESTABLISHED 1905

MAIL OPPORTUNITY COUPON FOR QUICK ACTION

National Schools, Dept. PS-9

4000 So. Figueroa, Los Angeles 37, Calif. (paste on penny postal)

Mail me FREE, without obligation, one Lesson and Opportunity Book, with full details about how I CAN become a RADIO Technician.

NAME AGE

ADDRESS

CITY STATE



THIS SIGN HAS BEEN SCRAPPED!

If you are over 40, you know that this unwritten policy formerly faced you in many cases. Youth was preferred.

But not now.

War has created a premium on you. You have advantages to offer an employer. You can get jobs—you can win promotion with your present employer. Today is your day to build yourself into greater responsibility and larger pay—for both war and post-war times.

You need, perhaps, only a little more specialized ability—a little more knowledge for the better job. And we can help you—that has been our business for 34 years.

Ask about our training in the field of your choice. The information is free and it may help insure your success and happiness now and when peace comes.

LASALLE EXTENSION UNIVERSITY

A Correspondence Institution

Dept. 983-R Chicago

I want to know whether—and how—you can help me to more ability and success. Please send me—without obligation—your free 48-page booklet on the business field checked below.

- | | |
|--|--|
| ☐ Bookkeeping | ☐ Accounting |
| ☐ Foremanship | ☐ Industrial Management |
| ☐ Business Law | ☐ Traffic Management |
| ☐ Business Management | ☐ Law: LL.B. Degree |
| ☐ Salesmanship | ☐ Business Correspondence |

Name.....Age.....

Address.....

Present Position.....

HEAR a world of sound through a MAICO



MAICO
Vacuum Tube
Hearing Aid

Small, light and easy to wear, yet enables hard of hearing person to carry on normal conversation at 20 feet—ta hear even a whisper with loud noises cushioned.

Send name of relative, friend or your own name for a new experience in hearing. No obligation. Address Maico Co., Inc., Dept. 50-K, 2632 Nicollet Avenue, Minneapolis.

A product of the Maico Company which provides 90% of America's precision hearing test equipment. Choice of ear physicians, hospitals, universities, clinics, airlines, U. S. Army and Navy.

Learn To MOUNT BIRDS

Tan SKINS, Make Up FURS

Be a Taxidermist. Double your hunting fun. We teach you at Home. Mount Birds, Animals, Pets, Heads and Fish. Save your hunting trophies; decorate home and den. **MAKE MONEY.** Mount and Knead for others. Big sparetime profits. **INVESTIGATE TODAY.**

FREE BOOK with 100 game pictures, 48 pages.

Hunters, get yours! It's Now Free! Send postal card **TODAY**—This Minute! State your Age. **NORTHWESTERN SCHOOL OF TAXIDERMISTRY**, Dept. 3186, Omaha, Nebr.



STAMMER?

This new 128-page book, "Stammering, Its Cause and Correction," describes the Bogue Unit Method for scientific correction of stammering and stuttering—successful for 42 years. **Free—no obligation.** Benjamin N. Bogue, Dept. 1853, Circle Tower, Indianapolis, Ind.

GET THIS
FREE
BOOK!

AMERICA'S BEST KNOWN SHOES

W. L.

Douglas Shoes

W. L. DOUGLAS SHOE CO., BROOKTON, MASS.

DO YOU

run as high as \$50-\$100, weekly after a few weeks home training—not medical or chiropody—easy terms, no further capital needed, no goods to buy. 47th year. Write for free booklet. **Stephenson System of Foot Correction, 62 Back Bay, Boston, Mass.**

WINDOW SIGN LETTERS

For Store Fronts and Office Windows. Anyone can put them on. Free Samples. Liberal Offer to general agents.

METALLIC LETTER CO., 441 N. Clark St., Chicago

Correspondence Courses in
RADIO and ELECTRICAL ENGINEERING













LOW AS \$25

FREE Write for free copies of school catalogs, student magazines, etc. **LINCOLN ENGINEERING SCHOOL**, Frankfort, Ky. Box 61-587 (Formerly at Lincoln, Nebr.), WASHINGTON, D. C.

MONEY for MEN ALL FREE

THE PLASTEX Industry needs manufacturers on small scale and for big production of Lamp and Clock Stands, Art Goods and Novelties in Plastex and Marble imitation. Experience unnecessary. 1/2c material makes regular 10c store sellers. Rubber moulds furnished for speed production. Small investment brings good returns. Big chain store orders now being placed. Ambitious men have chance for real prosperity. Our Free booklet will interest and benefit you.

PLASTEX INDUSTRIES, Dept. 2, 1085 Washington Ave., New York, N.Y.



What Can You Read In This



FINGER PRINT?

Study it carefully. There is a secret hidden in it, just as there is in every finger print. For 27 years we have been training men to become Finger Print experts. Over 53% of all American Identification Bureaus employ I.A.S. trained men. Get into this steady-employment, good pay profession. Learn at home. Small cost. Fine opportunities.

"THE BLUE BOOK OF CRIME"

FREE This thrilling book tells all about many famous crime cases and how you can qualify for one of the fine positions in the Identification field. Write for it, stating your age.

INSTITUTE OF APPLIED SCIENCE

Dept. 1366, 1920 Sunnyside Ave., Chicago 40, Ill.

STUDY ENGINEERING AT HOME

With A Chartered Educational Institution

Courses in **ENGINEERING**: Electrical, Civil, Mechanical, Drafting, Architectural, Steam, Aeronautical, Radio, Structural, Mining, Industrial, Highway, Petroleum, Marine, Chemical.
Courses in ARTS AND SCIENCES: Philosophy; Education; Letters; Public Health; Medical Jurisprudence; Psychology; Sociology; Physics; Chemistry; Geology; Pol. Science; Theology; Law; Business and Commerce; Accounting; Mathematics; Statistics; Agriculture.
 McKinley-Roosevelt Incorporated, 4610-BC, Sheridan Road, Chicago

Short-Cut Mathematics

COMBINED WITH
Practical Mechanics Simplified

NEW 2-in-1 reading course! Now you can learn the speedy, simplified system of calculation used by draftsmen, engineers, accountants, "master minds" on the stage. Learn easy way to multiply 4 figures by 4 figures without using old-fashioned multiplication; add long columns of figures this lightning short-cut method. Learn horsepower, slide rule, micrometer, logarithms, wood measure, puzzles, etc., etc. Large illustrated volume complete with answers, only \$1 postpaid. Satisfaction or refund. Amaze friends with your magic-like mental powers.

FREE Complete details... mail coupon TODAY!

NELSON CO., 321 S. Wabash Dept. J-304 Chicago
 Please send free details about "Short-Cut Mathematics and Practical Mechanics Simplified." No obligation.

Name _____
 Address _____
 City _____ State _____
 (Please write or print plainly)



INVENTORS

Now

IS THE TIME TO PATENT & SELL YOUR INVENTION

Now, more than ever before, is the right time to patent your invention. Why? Because manufacturers presently engaged in war production are looking ahead to the future by buying up patent rights now, so they will have new and attractive items to make and sell for civilian consumption as soon as the war is over. This is what happened during and after the last war. Hence, the smart thing for you to do is to look ahead to the future too. Protect your invention by applying for a patent now, so you will be in position to cash in on an outright sale, or on the royalties your invention will bring.

"PATENT GUIDE" SHOWS WHAT TO DO

Our Free "Patent Guide" contains complete information about patent procedure and how to sell inventions. It tells you how to find out whether your invention is probably patentable; what steps to take in order to obtain patent protection for your invention; how to arrange for the profitable sale of your invention; and how to secure financial backing if necessary. Our "Patent Guide" also gives many illustrations of successful inventions; how many simple improvements on already existing inventions proved to be large commercial successes; contains countless other items of vital interest to all inventors including the illustration of over 150 basic mechanical movements. With our "Patent Guide" you also will receive free a "Record of Invention" form with instructions for making disclosure and establishing date of your invention.



TAKE FIRST STEP NOW

Send for your free "Patent Guide" today. Remember—action is important—delay may be costly. Mail the coupon in an envelope or paste it on a penny postcard NOW.

CLARENCE A. O'BRIEN & HARVEY B. JACOBSON
 Registered Patent Attorneys
 32-J Adams Building, Washington, D. C.

CLARENCE A. O'BRIEN & HARVEY B. JACOBSON

Registered Patent Attorney before the United States Patent Office
 32-J Adams Building, Washington, D. C.

Please send me your 48-Page "Patent Guide for the Inventor" and specially prepared "Record of Invention" FREE. This request does not obligate me.

Name _____
 Address _____
 City _____ State _____
 (Please write or print plainly)



Know Electricity as Experts Know it—and Get an Expert's Pay!

What about your future? Who is safe today? Surely not the man who is contented to stand still! Know your job thoroughly—prepare yourself for jobs ahead. To do just this thousands of men have used

The Croft Library of Practical Electricity

The Croft Library is a complete electrical educator. It is founded on practice—on 20 years of shirt-sleeve experience—on work as it is actually done. It is learned from cover to cover with the kind of hard-headed facts you want. Written so that the beginner can easily understand it, yet so sound, so thorough, that it is the daily guide of 50,000 highly paid electrical workers and engineers. Croft tells you the things you need to know about motors, generators, armatures, commutators, transformers, circuits, switchboards, distribution systems—electrical machinery of every type—wiring for light and power—wiring of finished buildings—under-voltage and music requirements—illumination in its every phase—the most improved methods of lighting lamps—and lamp effects, etc.—how to do a complete job, from planning it, to completion.

No money down—easy payments

Fill in and mail the coupon attached and we will send you the entire set of seven volumes for ten days' examination on approval. We take all the risk—you assume no obligation. If you decide to keep the books, send \$3.00 in ten days and the balance at the rate of \$3.00 a month. Send the coupon NOW and see the books for yourself.

EXAMINATION COUPON

McGraw-Hill Book Co., 330 W. 42nd St., New York 18, N. Y.

Send me for ten days' examination on approval the Croft Library of Practical Electricity, 7 vols. If satisfactory I will enclose \$3.00 in 10 days and \$3.00 monthly until the price of \$18.00 is paid. If not wanted, I will return the books paid. (To insure prompt shipment write plainly and fill in all lines.)

Name.....

Home Address.....

City and State.....

Position.....

Company..... PSM-9-43

DRAFTSMEN NEEDED

Industry is clamoring for more draftsmen for the job can't start until plans are drawn. Buildings, airplanes, guns, tanks, bridges, all start on the drafting board, so it's no wonder that every good draftsman has a fine job. Yes, more draftsmen are needed NOW. The day is good and the opportunities for advancement great.

Learn at Home in Spare Time

Begin now to turn spare hours into money. Be a draftsman, the connecting link between a mechanic and an engineer. Enjoy the wonderful opportunities for promotion that exist now. No experience or artistic talent is needed NOW. You don't have to leave your present job while learning. Use spare time.

American School, Dept. DD646, Drexel Ave. at 58th Street, Chicago 37, Ill.

Gentlemen: Send me FREE information covering special training in subjects checked below. No obligation on my part.

- ☐ Drafting and Design for men and women
- ☐ Cost Accounting for Manufacturing
- ☐ Architecture and Building
- ☐ Automotive Engineering
- ☐ Business Management

- ☐ Electrical Engineering
- ☐ Diesel Engineering
- ☐ High School Course
- ☐ Mechanical Engineering
- ☐ Aviation
- ☐ Shipbuilding
- ☐ Radio

Name.....

Address.....

GET TOUGH! How to Win in Hand-to-Hand Fighting



By Major W. E. FAIRBAIN formerly head of the famous Shanghai Riot Squad and originator of the "close combat" system known as the "Fairbairn System." Major Fairbairn taught his methods to the British Commandos and then was loaned to us to teach instructors of the U. S. Armed Forces. Much more than just a book on judo, this is the most famous of all books on self protection and tough fighting. Hundreds of thousands of copies now being used by civilians and soldiers. You don't need brute strength when you follow Fairbairn's instructions. With your bare hands you can put a thug out of action so fast he won't know what hit him. Women can use it too! All the different methods are clearly explained and illustrated with graphic drawings showing each of the easy-to-learn steps of the Fairbairn system. Price \$1.00.

D. APPLETON-CENTURY CO., 34 W. 33rd St., NEW YORK

730 SHAVES FROM BLADE

AMAZING NEW BLADE SHARPENER



New sharpener for all makes of double-edge razor blades—performing miracles! "No need necessary to change blades," writes one user. Another says, "Have used the RAZOROLL for 10 years. It plus few cents postage. Use RAZOROLL for 5 days and if you're not delighted with smooth, velvet shaves you get return RAZOROLL and we'll return your dollar. Hurry—order today!" RAZOROLL COMPANY
620 North Michigan Avenue, Dept. 299, Chicago, Illinois

POWERFUL VISION—6 MILE RANGE



6-POWER TELESCOPE \$2.49

Perfect for spotting ships, planes; watching sporting events, people, birds, etc. Genuine black life-time plastic eyepieces with scientifically-ground 3 mm. lens. Objects 600 yards away appear as 100 yds. distant. Simple to focus on both moving and stationary objects. 15 DAYS FREE RETURN. If not fully satisfied, return for refund. SEND NO MONEY. Just pay postage \$2.49 plus few cents postage on delivery. Don't wait—production of telescopes may be curtailed as it has been on binoculars. Vogue Telescope Co., 7759 S. Halsted, Dept. B-208, Chicago.

REFRIGERATION

Repair and improve all refrigerators. New manual tells how. Charts and pictures to help you. Price only \$1.00. postpaid. Money back guarantee. Supreme Publications, 328 S. Jefferson St., Chicago, Illinois.



Begin today. Write now for our Free Book, "How to Become a Good Penman." It contains exercises and tells how others learned to write in spare time. Enclose 10c for your name beautifully written and a ten point outline of cursive writing. Write for THE TAMBLYN SCHOOL OF PENMANSHIP, 4339 Ridge Building, Kansas City, Mo.

OTTAWA LOG SAW Write for FREE BOOK



PUT THIS OTTAWA to work for you. MONEY! Wood is valuable. Does more than 10 men. Easily operated. Falls trees—and saws limbs. Use 6-hp. engine for other work. OTTAWA MFG. CO.
901 Wood St., Ottawa, Kans.

Burn Your Name On Tools Electro Name Etcher

PROTECT valuable tools from thieves and tool borrowers! Electro Etcher BURNS your name, any design, permanently on tools, instruments, dog collars, any metal. Easy! Simple as writing with pen or pencil. Rush order—supply limited—no more when these are gone! Write NOW! Pay \$1.00. Postage \$1.00 plus few cents postage on delivery. Use day money back if not delighted. Electro Etcher, Dept. S-603, Strader Ave., Cincinnati, O.

Now It Can Be Told ...

MIDWEST *makes* RADAR!



NOW that the veil of military secrecy has been lifted we can tell you that since shortly after Pearl Harbor, MIDWEST RADIO CORPORATION has been making RADAR sets and other Electronic devices for the U. S. Armed Forces.

What Is RADAR?

A detecting or locating device that sweeps sea or sky with a searchlight beam of ultra high frequency radio waves. If these encounter an enemy ship, plane or surfaced sub, they bounce back to a radio receiver which instantly reports the exact position, speed and direction of travel of the object, enabling naval or aircraft guns to fire accurately at the invisible enemy.

What RADAR Has Done

In the battle of Britain, when the RAF whipped the Luftwaffe, RADAR is credited with picking up with unerring fingers the range, speed and direction of Hitler's bombers, far out over the water (even over Europe itself) and

thus enabled the RAF to wreak unprecedented destruction upon them.

At Guadalcanal, November 14, 1942, RADAR on a U. S. naval ship probed the darkness and detected a Jap ship more than 8 miles away. U. S. guns thundered, their second salvo sinking the Jap vessel. American ships then went on to turn the battle for Guadalcanal into one of the most costly routs in naval history.

The Future of RADAR

So infinite and far reaching are its potentialities that no man can accurately predict its future uses. But of one thing aircraft authorities are certain . . . it will make flying enormously safer in enabling pilots to avoid mountains and other obstacles regardless of fog, smoke or darkness.



When Peace comes, MIDWEST will be ready to incorporate every new scientific development into its production of Radio, Television and Electronic instruments.

MIDWEST RADIO CORPORATION
CINCINNATI, OHIO

Quick, easy way to get MACHINIST TRAINING

7-DAY FREE TRIAL



New Amazing 3-Volume MACHINE SHOP TRAINING COURSE

FOR BEGINNERS & EXPERTS



WAR WORKERS & TRAINEES

PARTIAL CONTENTS

Machine Tools Completely Described and Fully Demonstrated
Measurements and Gages.
Drill Press Operations.
Lathe Operations.
Milling Machines—All Types.
Shaper and Planer Set-ups.
Plain and Universal Grinders.
Blueprint Reading & Drafting.
Expert Mechanic—What He Must Know.
How to Lay Out Holes for Drilling.
Shop Projects—Layout Fabrication.
Lathe Cutting Tools and Grinding.
Drill Jigs, Speeds and Feeds.
Standard and Open-Side Planers.
Vernier Caliper and Depth Gages.
American Standard Machine Tapers.

Now, for the first time, the world of machinery is concentrated into a complete, 3-Volume Course. It is vitally necessary for all Machinists. It is also a Training Course for beginners who are employed or seek good pay jobs in Machine Shop Work.

HUNDREDS OF DRAWINGS—DIAGRAMS

- Written in easy-to-understand language by practical shop instructor.
- Proluse with illustrations, diagrams, charts and valuable tables.
- Easy-to-follow and understand, regardless of your previous work.
- All phases of modern machine shop work.

FROM RIGHT OUT OF NATIONAL'S SHOPS

This training at home is comparable to fundamentals learned by residential students at National Schools. Out of the experience in teaching thousands of students has come this simplified easy-to-understand Machinists' Course.

10 FREE GIFTS

If you mail Coupon immediately, we'll give you absolutely Free, seven marvelous Drafting Lessons, and a complete Machinist's Dictionary of terms, etc., and two Practical Shop Mathematics Texts which you will find essential in your daily work.

NATIONAL SCHOOLS
Los Angeles, California



FREE 7-DAY TRIAL EXAMINATION

J. A. ROSENKRANZ, President
National Schools, Dept. L-9
4000 So. Figueroa St., Los Angeles 31, Calif.

Yes, without obligating myself in any way, ship me at once, your big 3-VOLUME MACHINIST TRAINING COURSE. Within 7 days after receiving the Course (and marvelous Bonus Gift for promptness), I'll either return the shipment, and owe you nothing; or if satisfied, I'll send you \$9.00 and \$9.00 a month until a total of \$12.50 is paid (final payment, \$3.50).

NAME

ADDRESS

CITY STATE

OCCUPATION AGE

SAVE 10% You may deduct \$1.25 if you enclose cash (\$11.25) with this Coupon. Same return privilege and refund guaranteed.



LEARN RADIO Faster, Easier With the Aid of MOVIES

You get the loan of a genuine DeVry projector and dramatic motion pictures in your home. ACTION pictures are easier to understand and remember. Learning is fun... more effective! You also get lessons prepared under the supervision of Dr. Lee DeForest, often called the "Father of Radio." Write for BIG FREE BOOK.



DeFOREST'S TRAINING, INC.

2535-41 N. Ashland, Dept. B, Chicago, U. S. A.

BOSKO

Cartoon Home Movies
PACKED With Thrills

This mischievous colored fellow is sometimes a hero of fantasy, or the victim of his own witty pranks. One of the most delightful characters seen in Cartoon HOME MOVIES.

GET THESE FEATURES

50 ft. 8MM—\$1.50
100 ft. 16MM—\$3.00

Hen Pecked Bosko.....1866-A Bosko's Magic Carpet...1868-A
Bosko's Bad Dream.....1867-A Bosko's Cannibal Capers 1869-A
Show thrilling AVIATION features, also Mickey Mouse, Donald Duck, Three Monkeys and Oswald Rabbit Cartoons.

AT YOUR DEALERS. WRITE FOR CATALOG & PRICES TO

HOLLYWOOD FILM ENTERPRISES INC.

6060 Sunset Blvd. Dept. 116 Hollywood 28, Calif.



MAKE MONEY!

Sell Warm LEATHER Jackets

Hundreds of prospects near you: sportsmen, workers in lumber yards, warehouses, stock rooms, war plants, etc. Men of action demand their snug warmth, free-action comfort, sturdy construction.

COMPLETE LINE

Leather and wool jackets, work shirts, 250 shoe styles for men and women. Liberal Commissions! Write today for FREE SALES OUTFIT.

VICTOR THOMAS SHOE CO.
Dept. V-124 610 W. Van Buren St. Chicago, Ill.

Tired Kidneys Often Bring Sleepless Nights

Doctors say your kidneys contain 15 miles of tiny tubes or filters which help to purify the blood and keep you healthy. When they get tired and don't work right in the daytime, many people have to get up nights. Don't neglect this condition and lose valuable, restful sleep. When disorder of kidney function permits poisonous matter to remain in your blood, it may also cause nagging backache, rheumatic pains, leg pains, loss of pep and energy, swelling, puffiness under the eyes, headaches and dizziness.

Don't wait! Ask your druggist for Doan's Pills, used successfully by millions for over 40 years. They give happy relief and will help the 15 miles of kidney tubes flush out poisonous waste from your blood. Get Doan's Pills.

Hot Meals . . . EVEN in a "FOX HOLE" with HEATABS and VEST POCKET "STOVE"



Food calls for HEAT, wherever you are! HEATABS (Tablets of Concentrated Heat) will light instantly, and will burn long, with intense heat . . . outdoors or indoors, Campers, picnic-ers, hunters, fishermen can cook, fry, boil food, start fires under any circumstances with HEATABS. Many uses for Boy Scouts, Girl Scouts, housewives, doctors, nurses, Red Cross and Civilian Defense workers, dentists, chemists, industrial workers, etc. Important in First Aid and Emergency Kits. Carried by armed forces to heat combat rations. Solid, compact, non-poisonous . . . NO SMOKE, SOOT, FUMES or ASH! SPECIAL OFFER (limited): COLLAPSIBLE "STOVE" (Vest pocket size) with TWO LARGE CARTONS of HEATABS, only \$1.00. Postpaid. ORDER BY MAIL TODAY! J. W. SPEAKER CORP., 1675 N. Water St., Milwaukee, Wis.

HEATABS TABLETS OF concentrated HEAT

POST-WAR PRODUCTS WANTED

One of our clients, a large Eastern plastic products manufacturer, is looking for good saleable products or ideas for post-war manufacture. This firm has ample capital, facilities, and sales connections. If you have a product or idea, patented or otherwise, write us fully. Please do not telephone or call in person; do not send models until requested. HAROLD MARSHALL ADVERTISING CO. 9 East 46th St. NEW YORK 17

QUICK WAY TO LEARN MUSIC —play any instrument

GET A REAL thrill out of music! Play the musical instrument you like best. Start right in with simple tunes. No tedious, old-fashioned drills and exercises.

It's easy! Everything is in print and picture. You see every position and move. Thousands have been amazed at their progress in just a few short weeks. Now they're sought-after guests for every party! Don't miss out on the popularity that is rightfully yours!

Mail coupon today for free illustrated Booklet and Print and Picture sample that show how easily and quickly you can learn music at home. Just check instrument in coupon below that interests you. U. S. School of Music, 89 Brunswick Bldg., New York 10, N. Y.

FREE PRINT AND PICTURE SAMPLE

U. S. School of Music, 89 Brunswick Bldg., New York 10, N. Y. Please send me Free Booklet and Print and Picture Sample. I would like to play instrument checked below. (Do you have instrument.....)

Piano Accordion Trumpet Ukulele
Guitar Saxophone Tenor Banjo Krumpholtz & Traps
Violin Mandolin Cornet Other Instrument

Name..... (Please Print)

Street.....

City..... State.....



INVENTORS

and INVENTION RECORD (Cost You Nothing) FREE BOOK



HOW TO PROTECT, FINANCE and SELL YOUR INVENTION

Our FREE BOOK and other literature available to our clients—gives you complete details on how to "ready" your invention for money-making. It tells you how others did it—who they went to for finances—how they arranged partnerships—how they made contacts with manufacturers—how they dictated royalty arrangements—how much money they made—how you can find a market. Our new FREE BOOK discloses sources of quick revenue if your invention is patentable and saleable with profit possibilities.

THE FIRST STEP

The first step in getting your invention ready for market is to make a dated record of it on our "Invention Record" Form. This Form properly filled out and witnessed will be invaluable to you later in establishing the date of your invention should need for such evidence arise. We will be glad to send you our "Invention Record" and have it witnessed in this office when you return it with disclosure of your device. This service costs you nothing—and it immediately puts you on record as the originator of your device.

Protect Your Invention NOW!

We have many letters in our files from manufacturers requesting inventions. Today's demand for new devices is tremendous—added to by emergency needs. Protect your invention now with a U. S. Patent. By acting promptly you may prevent another inventor getting in ahead of you at the Patent Office here in Washington. The first step is to make a sketch and description of your invention on our "Invention Record", have it witnessed and mail it to us. We will then make a Search of the U. S. Patent Office files to ascertain whether we can get patent protection for you. This is a step you should make NOW—before another steps in ahead of you and walks away with a patent.

COUPON
TODAY!

McMORROW & BERMAN

REGISTERED PATENT ATTORNEYS BEFORE U. S. PATENT OFFICE

142-M Albee Building
Washington 5, D. C.

Send me your NEW FREE Book "How to Protect, Finance and Sell Your Invention" and specially prepared "Invention Record" form at once. I understand that this request does not obligate me.

NAME.....

ADDRESS.....

CITY..... STATE.....

Write or Print Name Clearly

DIESEL MEN WANTED!

THOUSANDS OF NEW WAR JOBS!

BIG PEACETIME FUTURE!

War-time demands for Diesel-powered tanks, artillery tractors, Army trucks and many types of Navy craft are creating enormous strides of Diesel progress—opening immediate opportunity for thousands of Diesel-trained men! Now more than ever, you need to be authoritatively up-to-date on all engineering details! Send at once for your **FREE** inspection copy of Chief Engineer Rosbloom's famous **DIESEL HANDBOOK**—now yours at a saving of 40¢! Here's just the book you need to get started toward a big pay job in the booming, prosperous Diesel business.



719 PAGES—HUNDREDS OF ILLUSTRATIONS

All types of Diesel engines are explained and comprehensively illustrated in this book—land, marine, locomotive, aero, automotive, power and portable units. Numerous tables, charts, diagrams, formulas. All arranged in simple, clear, readable type—for easy study by beginners or quick reference by professional Diesel men. **SPECIAL SECTION:** Questions and Answers for License Examinations for Diesel Engineers.

SEND NO MONEY

A copy of **DIESEL HANDBOOK** will be sent to you for 10 days **FREE** inspection. Send no money now. Just mail coupon. Deposit \$2.98 with postman (plus postage). Money refunded promptly if not more than satisfied.

PIONEER PUBLICATIONS, INC., Dept. 129
1790 Broadway, New York 19, N. Y.

Send me for 10 days **FREE** inspection, **DIESEL HANDBOOK**. I will pay postman \$2.98 (plus postage) when the book arrives. If not completely satisfied, I may return it and you will refund my money promptly.

Name

Address

☐ I will pay Postage if you enclose \$2.98 now. Mark box. (Same Free Inspection and Refund Privilege.)

HOW SPRAYBERRY RADIO TRAINING PAYS OFF 3 WAYS



TRAIN IN SPARE TIME
AT HOME OR AT CAMP . . .

The greatest OPPORTUNITY that ever existed in Radio is open to you **RIGHT NOW!** Don't miss it! No practical Home Training will fit you quickly for a profitable Radio Repair business of your own . . . OR for a good-paying Radio job in one of the Nation's Radio and repair shops on equipment for planes, tanks, ships, etc. . . OR for higher rating and better pay if you enter the Army, Navy or Marines.

NO PREVIOUS EXPERIENCE NEEDED

Sprayberry Training starts right at the beginning of Radio. You can't get lost. My proved methods will get each subject across to you in simple, understandable style. You learn Aviation Radio, Radio Set Repair and Installation Work, Mobile Radio (Auto-Tank), Television, Frequency Modulation, Signal Tracing. You will be prepared to cash in on the coming great era of Electronics.

EARN WHILE YOU LEARN

Along with your Training, you will receive my famous Business Builders, which can bring you in a nice profit shortly after you begin my Course.

Get the facts about my training

—NOW! Take the first important step toward the money-making future of your dreams. All features are fully explained in my big, illustrated free book. Write for it at once.



RUSH COUPON for FREE BOOK

SPRAYBERRY ACADEMY OF RADIO, F. L. Sprayberry, President
655-S University Place, N. W., Washington 9, D. C.
Please rush my **FREE** copy of "HOW TO MAKE MONEY IN RADIO."

Name Age

Address

City State

(Mail in envelope or paste on penny postcard)

INVENTORS

Don't file your patent application until you have read these three invaluable guides. **THEY'RE FREE** and they tell you how to protect and commercialize your invention. Act today . . . write to:



VICTOR J. EVANS & CO.
REGISTERED PATENT ATTORNEYS FOR NEARLY 50 YEARS
740-K MERLIN BUILDING — WASHINGTON, D. C.

LAW

STUDY AT HOME

Legally trained men win higher positions and bigger success in business and public life. Greater opportunities now than ever before. Big corporations are headed by men with legal training.

More Ability: More Prestige: More Money

We guide you step by step. You can train at home during spare time. We furnish you with legal training graduates in every section of the U.S. We furnish all text material, including 14-volume **Law Library**. Low cost, easy terms. Get our valuable 30-page "Law Training for Leadership" and "Evidence" books **FREE**. Send for them **NOW**.

LaSalle Extension University, Dept. 933-L, Chicago

A Correspondence Institution

Learn TOOL DESIGN

Qualify quickly as Machine or Tool Designer through spare-time home study. Many making \$100 to \$125 a week. Expanding industry calling for more machine and tool designers than available. Good pay jobs waiting. Rush name and kind of job wanted today for full free facts.

OHIO INSTITUTE OF TECHNOLOGY, Box 114, Greenville, Ohio

REFRIGERATION MECHANICS SPARE TIME COURSE

Learn at home how to start your own repair shop on little capital. No previous experience needed. Common school education sufficient. Splendid opportunity for older men. Prepare now for after the war. **FREE** illustrated booklet, **MECHANICS TRAINING SCHOOL**, Dept. 11, 4701 W. Pico, Los Angeles 6, Calif.

Learn CARTOONING



FREE TRIAL LESSON! Cash in on your sense of humor—**AT HOME—BY MAIL**. Have fun! Make money! No experience necessary to start. Write today for **FREE LESSON**, mailed postpaid. No obligation.

MOON Gag-Cartoon School, Dept. 5, Argyle, Wis.



LAME PEOPLE

Need my Nature form Extension Shoe. Makes both feet look alike. Ready-made shoes worn. Possess style, comfort and security. Distance no barrier. Write for Booklet.

A.P.S. Sinn, 748 Bergen St., Newark, N.J.



MONEY IN RABBITS-CAVIES

WE BUY and put you in touch with other markets. Catalog and copy of magazine 10c. Or send 25c for Book Catalog and Price List and 50c for Subscription to the **AMERICAN SMALL STOCK FARMER**.

OUTDOOR ENTERPRISE CO., BYSS, PEARL RIVER, N. Y.

CHRONIC AILMENTS

Explained in—**FREE BOOK**

Neglected piles, fistula and colon troubles often spread infection. Read about rheumatism and other chronic conditions. Write today for 122-page **FREE BOOK**. Learn facts. McCleary Clinic, 971 Elms Blvd., Excelsior Springs, Mo.



EARN MONEY PAINTING PORTRAITS

• No previous training or talent necessary. Unique Stuart System teaches you, by mail, in 10 simple, easy-to-follow lessons, to make excellent charcoal and oil likenesses. Detailed guidance for your every step. Send for free book today.

STUART STUDIOS,

121 Monument Circle, Room 289, Indianapolis, Ind.

Please send me free book and outline of lessons.

Name

Street

City State

PREPARE NOW for POST-WAR OPPORTUNITIES with LINGUAPHONE

In your own home you can now prepare for peace-time opportunities in many fields by learning to speak in an amazingly short time any of 29 languages by the world-famous

LINGUAPHONE Ear-Eye METHOD

It's quick, easy, correct

SPANISH JAPANESE RUSSIAN
PORTUGUESE FRENCH GERMAN
ITALIAN CHINESE NORWEGIAN
and 20 others.

Successfully used by Army, Navy, Flying and Signal Corps and other services; in thousands of schools and colleges; endorsed by leading educators.

Send for FREE Book—

Call for FREE Demonstration

LINGUAPHONE INSTITUTE

58 RCA Bldg., Rockefeller Plaza, N. Y. (20)

ENGINEERING DEGREE IN 27 MONTHS

INDIANA
TECHNICAL
COLLEGE

Courses in Aeronautical, Chemical, Civil, Electrical, Mechanical, and Radio Engineering. One-year courses in Radio and Drafting. Approved by C.A.A. Prep courses without added cost. Low tuition. Large industrial center. Opportunity to earn part living expenses. Enter September 1, December, March, and June. Catalog.

693 E. Washington Blvd., Ft. Wayne, Ind.



TRAILER BUILDERS' PARTS CATALOG

We'll save you money on everything. Largest and most complete trailer builders' supply house in the United States. Member TRAILER COACH MPRS' ASSOC. Send 10c for parts catalog.

NATIONAL TRAILER EQUIPMENT CO., Milwaukee, Wis.

Complete Plans and Building Instructions 25¢ 719 N. Seventh St.

ANYONE CAN
DO THIS IF
THEY HAVE
OUR CHART



SPECIAL
OFFER
FOR
AGENTS

Blue Print 27" x 36" shows how to find length of any rafter, find any angle in degrees, frame any polygon to 16 sides, read board foot and brace tables, octagon scale, rafter tables and many other uses. Can be scaled down for model work as well as full scale framing. Also chart changing pitches to degrees for use with Radial saws. Send 50c in coin or money order. No stamps or checks.

MASON & PALMER, ENGINEERS

2105-S. N. Burdick St. Dept. B Kalamazoo, Michigan



MECHANICAL DENTISTRY AT HOME!

To make Crowns, Plates, Bridgework, etc., for Dentists. Easy practical way to learn mechanical dentistry at home in spare time. FULL EQUIPMENT OF TOOLS AND MATERIALS INCLUDED WITH COURSE Low tuition. Easy terms. Write for FREE BOOK about this money making profession that is not affected by machine age.

McCARRIE SCHOOL OF MECHANICAL DENTISTRY Philadelphia, Pa.

207 N. Broad St.

Dept. 818

Philadelphia, Pa.

The Dennison Handy Helper says:
"WRAP IT TIGHT—MARK IT RIGHT"

Dennison
MAILING LABELS

Transparent Mending Tape • Crepe Paper
Gummed Reinforcements • PRES-a-ply Labels
Index Tabs • Shipping Tags • Gummed Labels

DENNISON MFG. CO., Framingham, Mass.





WANTED 1000 HIGH SCHOOL SENIORS

To Combine

AVIATION TRAINING

with 4th YEAR HIGH SCHOOL

The War Manpower Commission recommends deferment for students in technical training...so you now have the opportunity to finish your high school at Aero Tech and at the same time gain a full year of aviation training. Make the most of your next twelve months—by enrolling now in the Aero Tech combination High School and Aviation Mechanics, or Engineering Course.

APPROVED HIGH SCHOOL AND AVIATION COURSES

State certified instructors teach the high school subjects...the aviation subjects and instructors are approved by the CAA and the Army Air Forces Technical Training Command. When successfully completed, you receive your High School Diploma...also your Certificate of Award for completing the Master Mechanics Course which makes you eligible to qualify for a CAA Airplane & Engine License.

ONE AND TWO-YEAR ENGINEERING

You can also secure advanced training in Aeronautical Engineering, as well as post-graduate and research work...during or after your 4th year of High School at Aero Tech.

SUPERVISED LIVING AND RECREATION IN CALIFORNIA

You may live right on the campus, in new dormitories, where you will enjoy comfortable lodgings, wholesome food and real companionship. You will take part in campus activities—the band, basketball, baseball—and enjoy privileges in nearby YMCA—all under the supervision of the Students Welfare Council.



SEND COUPON TODAY for Fall Semester Application

AERO INDUSTRIES TECHNICAL INSTITUTE

5247 W. San Fernando Road, Los Angeles 28, California

Gentlemen: Please send details and enrollment application on the course checked below, without obligation:

☐ 4th year high school and Master Aircraft Mechanics ☐ 4th year high school and Aeronautical Engineering

Name _____ Age _____

Street _____

City _____ State _____ A-2-1



Every Ambitious Man In Industry Should Read this Free Booklet!

"FORGING AHEAD IN BUSINESS" contains FACTS for all thoughtful, forward-looking men; it has a message of particular interest to technical men.

This 64-page booklet, of which more than 3,000,000 copies have been circulated, outlines a definite plan of training for your future progress in industry.

Said one man who had sent for it:

"In thirty minutes this booklet gave me a clearer picture of my business future than I have ever had before."

Fill in the coupon below and this helpful manual will be sent to you by mail and without cost.

ALEXANDER HAMILTON INSTITUTE

Dept. 47, 73 West 23rd Street, New York 10, N.Y.
In Canada, 54 Wellington St., West, Toronto, Ont.
Please mail me a copy of the 64-page book—"FORGING AHEAD IN BUSINESS."

Name.....

Address.....

PATENT YOUR IDEAS SEND FOR FREE BOOK


HOW
TO OBTAIN A
PATENT

Written by Former Member Examining Corps (1922-24) U.S. Patent Office.

CARL MILLER, Registered Patent Attorney
Former Member Examining Corps U.S. Patent Office
Woolworth Bldg., Dept. 83-C, New York—Good Bldg., Dept. 83-C, Washington, D. C.

Please mention POPULAR SCIENCE when writing to advertisers.

MASTER DRAFTING MACHINE



● Biggest time saver for dimensioned sketches, lettering and layouts ever sold at—This Low Price—While they last. Limited Supply. Only

\$3.95

ORDER TODAY

RANDOLPH RADIO 611 West Randolph St.
CHICAGO, ILLINOIS

LEARN AT HOME TO MOUNT BIRDS



Animals, Heads, Fishes, Pets; to TAN. Be a Taxidermist. Profit and FUN. Hunters, save your valuable TROPHIES.

Mount ducks, squirrels, everything. Learn to TAN for leather and fur. Wonderful HOBBY. Have a HOME MUSEUM—BIG PROFITS mounting for others. INVESTIGATE NOW.

FREE BOOK With 100 fine game pictures. NOW absolutely FREE. Write TODAY.

Send Postal TODAY for FREE BOOK. State AGE. N.W. SCHOOL OF TAXIDERM, Dept. 3396, Omaha, Neb.



LAW STUDY AT HOME for PERSONAL SUCCESS and LARGER EARNINGS. 31 years expert instruction—over 100,000 students enrolled. LL.B. Degree awarded. All texts furnished. Easy payments. Send for FREE BOOK—"Law and Executive Guidance."

AMERICAN EXTENSION SCHOOL OF LAW
Dept. 33-5 8 East Huron St., Chicago, Ill.



RADIO OPERATORS WANTED

Be a "key" man. Learn how to send and receive messages in code by telegraph and radio. Army, Navy and Commerce needs thousands of men. Good pay, adventure, interesting work. Learn at home quickly through famous Candler System. Write for FREE BOOK.

CANDLER SYSTEM CO.
Dept. 6-K, Box 928 Denver 1, Colo., U.S.A.



THERE'S MONEY IN CARTOONS!

RAYE BURNS will teach you HOW TO CREATE ORIGINAL CARTOONS at home that you may SELL! Course contains 26 lessons and over 600 illustrations. All for Only..

\$2.85

Send name and address for free details.
RAYE BURNS SCHOOL, Dept. S, Box 1298, CLEVELAND, OHIO

Alloy Metals
Finding List and List of Sources

Free! ...if you subscribe at once to HOBART'S

Alloy Metals Data Service

First you get the condensed Finding List and List of Sources. Determine characteristics you want in a metal, apply code listed, locate metal by the corresponding code in list. Another column gives instant reference to manufacturer. Saves hours of searching for special metals.

SEPARATE ALLOY METAL SUGGESTIONS
These loose-leaf sheets come free periodically. Complete with specifications, drawings. Send name and address to ...
HOBART BROS., Box P-93, TROY, OHIO

HOBART
ARC WELDERS

"One of the World's Largest Builders of Arc Welders"

Practical Arc Welding Manual and Text book every man connected with arc welding should own. **\$2.00**

WILCOX & FOLLETT THIS 10" SLIDE RULE



Has genuine Lucite, Non-shattering Magnifying indicator
... A B C D and K scales.

If you are doing figure work without a slide rule you are wasting from 60% to 87% of your time. Every mechanic, machinist, draftsman, accountant, electrician, aircraft worker and business man should have a slide rule and know how to use this greatest time-saving mathematical instrument.

PROMOTIONS ARE WAITING

For Men Who Know

HOW TO USE THE SLIDE RULE

Here is a brand new text complete with work sheets and an answer book and 5 place logarithm tables that will teach you how to use the slide-rule in a series of simple, easy to understand lessons, authoritatively written by Hobart H. Sommers, M.A., Dean, Austin Evening Junior College; Harry Dreil, B.S., Lockheed Aircraft Corporation; T. W. Wallschlaeger, M.S., Illinois Institute of Technology. It will show you how to do all kinds of figure-work in seconds and without pencil or paper—multiplying, dividing, extracting roots, ratios, percentages, squares, areas

of circles, radius of circles, volumes of prisms, cylinders, cones, pyramids, spheres and innumerable other problems important in business and industry. Beginners or experts will find this valuable book complete in every detail—the novice will learn to do rapid slide-rule calculations in a couple of hours—the engineer can review methods and problems with the work sheets and answer book. Get this text and a free Mannheim Type 10" slide rule bound right with the book itself ... complete for only \$2.98.

Money back if not doubly satisfied. Return in 10 days for Full Refund.

Regular
\$5.00 Value

Slide rule alone worth \$1.00. Logarithm Table Books cost from 75c to \$1.00. Slide Rule Course worth \$3.50. All complete with Answer Book for only \$2.98.

\$5.00 VALUE
ONLY
\$2.98

FREE SLIDE RULE

WILCOX & FOLLETT CO.,

1255 So. Wabash Ave., Dept. 39, Chicago, Illinois.

Please send me the new "The Slide Rule and How To Use It" with a free 10" Slide Rule with Magnifying Indicator.

☐ An enclosing check or money order for \$2.98. ☐ Ship C.O.D. I will pay postman \$2.98 plus charges.

Name.....

Address.....

City..... State.....

WILCOX & FOLLETT Co., Dept 39, 1255 S. Wabash, CHICAGO, ILL.

ELECTRICAL BOOKS

shipped
FREE

10
BIG BOOKS

FOR EXAMINATION
MODERN
ELECTRICITY
INCLUDING RADIO
AND REFRIGERATION

Here's great news for anybody interested in Electricity. NEW 18th edition of Applied Electricity brought right down to date with NEW Electrical subjects fully covered, including Electrical Blue Print Reading. 10 big Volumes and all shipped FREE for examination.

New Edition

FOR BEGINNERS
AND EXPERTS
over 3,000 pages
—hundreds of
illustrations—the
most complete
work of its kind
ever published.
Dynamotors,
motors, power
stations, wiring,
radios, everything
electrical explained
so anyone can
understand it.

BIG FIELD! Big Demand!

Big Pay! Men who understand electricity are urgently needed in thousands of war production industries. Airplanes, shipbuilding, arms plants, machine shops—practically every industry depends on electricity and men who know this subject make big money. Pleasant, fascinating work, easy to learn and do; learn with these books. Send coupon for a set for FREE examination and see for yourself.

SEND
NOW

A year's consulting privileges
with our engineers now given
to all buyers of this famous
Cyclopedia of Electricity.

AMERICAN TECHNICAL SOCIETY
Vocational Publishers since 1898

.....
American Technical Society, Dept. E620, Drexel at 58th St., Chicago 37
Send for 10 days' free use, 10 volume set of New 18th Edition Applied
Electricity, including a certificate entitling me to consulting privileges
for one year. I will pay the delivery charges only on the books. If I
within 10 days return them in 10 days and order you to keep them, but I
keep them, I will send \$2.00 after 10 days, then \$3.00 a month
please give home address.

NAME.....

ADDRESS.....

CITY..... STATE.....

Please attach letter stating age, occupation and name and address of employer and give at least one business man as reference. Men in service, also please give home address.

EVERY Musician SHOULD GET THIS BOOK!

ADD YEARS
TO THE LIFE OF
YOUR BAND
INSTRUMENT



40 PAGES
46
ILLUSTRATIONS
COVERS ALL
MAKES OF
INSTRUMENTS

Your band instrument must last for the duration. That's why you need this new and helpful book, "How To Care For Your Instrument." In no other book can you find such valuable and helpful information. Covers all makes and types of wind and percussion instruments. 40 pages of instructions, 46 illustrations, to help make your instrument last longer. Worth many times its 10c cost. Get yours at your Conn dealer's or send 10c today.

ONLY
10¢
WORTH FAR
MORE

C. G. CONN, Ltd., 932 CONN BLDG., ELKHART, IND.

Send me.....copies of "How To Care For Your Instrument." Enclosed find 10c in coin or stamps for each copy.

NAME.....

ADDRESS.....

CITY..... STATE.....

Be Popular—Learn
the Newest DANCES
in 5 DAYS—or NO COST!

NEW REVISED EDITION
includes the Rhumba, Congo,
Samba, Jitterbug . . . Fox
Trot, Waltz and Tap Dancing.

All the newest Swing steps—
the Rhumba, Congo, Samba,
Jitterbug, as well as the
Fox Trot, Waltz and basic
tap steps—explained with
simple, graphic diagrams.
**GET MORE FUN OUT OF
LIFE!** Swing your way to
popularity! Start now and
fill your future with
romance! **MAKE THIS FREE
TEST!** The new REVISED
edition of Betty Lee's book
dancing, helps you learn
correctly and quickly. Be convinced—if not satisfied with results,
you will get your money back! And remember, we include two other
books—“Tip Top Tapping” and “Swing Steps”—FREE of extra charge.
SEND NO MONEY! Pay the postman \$1.00 plus a few cents postage.
Follow instructions in ALL THREE BOOKS—practice simple dance
steps each day and in 5 days if you haven't learned to dance,
we will refund your money!



PIONEER PUBLICATIONS, INC.
1790 Broadway, Dept. 879H
New York 19, N. Y.

Send me “Dancing,” by Betty Lee, and
include 2 free books.
☐ Ship C.O.D. I will pay on arrival,
plus postage.
☐ I enclose \$1.00. Ship postage prepaid.
If in 5 days I do not learn to dance, I may
return book and you will refund purchase price.

Name.....
Address.....
City.....State.....

AN INFANT INDUSTRY ... SUDDENLY MATURED PLASTICS

Get In at the Start—and Grow

Plastics is a new industry which the nation's war
needs is forcing to quick maturity. Already Plastics
are indispensable in practically every branch
of the Service—Aircraft, Ordnance, Chemical,
Marine, Signal Corps, etc. Opportunities? Nearly
everything, from homes to clothing, from gadgets
to tools, will be affected by Plastics.

Spare Time Training Now Ready

The time to get started is now. You can prepare
at home, in your spare time, to take your place in
an infant industry that even now is leaping
into prominence. A new, practical training plan
is now ready to help you realize your ambitions
and build your future security. Act now. Don't
delay. Mail this coupon today.

AMERICAN SCHOOL, Dept. P648
Brexal Ave. at 58th St., Chicago 37, Ill.

Send me FREE information covering special training in
subjects checked below. No obligation on my part.

- | | |
|---|--|
| ☐ Plastics | ☐ Cost Accounting |
| ☐ Electrical Engineering | ☐ for Manufacturing |
| ☐ Drafting and Design | ☐ Automotive Engineering |
| ☐ for Men and Women | ☐ Architecture & Building |
| ☐ Diesel Engineering | ☐ Shipbuilding |
| ☐ Mechanical Engineering | ☐ Business Management |
| ☐ Aviation | ☐ High School Course |

Name.....
Address.....



No More Damage from Condensation or Sweating Pipes,
Water Softeners, Tanks, Walls, Ceilings and Air Ducts



A SURE CURE—Sensational plastic
cork coating prevents condensation drip
from metal, concrete, brick, wood, plaster or
composition surfaces. Protects metal against
rust and corrosion, prolonging life of pipes, tanks, etc.
Forms a moisture-proof, insulation type coating. Apply
with brush, trowel or spray.

Requires no maintenance. A gallon covers 30 feet
of 1/2" pipe. Comes in 1, 5 and 55 gallon drums. Get at
Hardware, Plumbing, Mill Supply Dealers or send \$1.90
for 1 gal. prepaid (\$2.10 west of Rockies). **FREE—NoDrip
Handbook**, all about Condensation drip and its Prevention.
J. W. MORTELL CO., 534 Burch St., Kankakee, Ill.

Inventions Wanted Patented or Unpatented

Inventions can now be safely sold without patenting
expense. If you have a practical, useful idea for sale,
either unpatented or patented, write today!

Chartered Institute of American Inventors
Dept. 3, 631 Pa. Ave. N. W., Washington, D. C.

PATENTS PERSONAL SERVICE

My Personal
service assures
strictest confi-
dence on all
your patent
problems. Send
me a model or
drawing, or

sketch and description of your invention, and \$5.00. I will make a
search and report promptly as to its patentability and send you a
copy of my 72-page booklet. Or, if you prefer to read my booklet
first, write today for **FREE** copy. Registered Patent Attorney.

L. F. Randolph, 340-D Columbian Bldg., Washington, D.C.

Now \$15
Only



REAL ENGINE VALUE

The G. H. Q. is a miniature gasoline engine
that really operates! Over 15,000 sold in the
last year. 1/5 H.P. Complete with flywheel
(or propeller), fuel, accessories and full in-
structions. Fully bench tested and ready to
run. For boats, planes, midget cars, etc. Send
only \$1.00—Shipped Collect C.O.D. same day.
Send 25c for Catalog of hundreds of hobby
items. Rough Castings set, including blue-
prints, only \$6.95.

GHQ MOTORS, Dept. ST, 40 East 21 St., New York 10, N. Y.



OTTAWA TRACTOR SAW

Falls Tree—Cuts Log
Uses Power Take-off any tractor.
tor. Direct drive. Long stroke. Saws fast.
Easy on fuel. Thousands of satisfied users.
Big labor saver. Low in Price.

**Write for FREE
Book and Prices**

OTTAWA MFG. CO., 8901 Forest Ave., OTTAWA, KANSAS



PATENTS

AND TRADE MARKS

C. A. SNOW & CO.

Registered Patent Attorneys Since 1875
Write for Free Book and "Certification of Invention" form
427 SNOW BUILDING, WASHINGTON, D. C.



INTRODUCING-New Victory Model HANDIWELD ELECTRIC

ARC WELDER

RETAILS ONLY
FULLY GUARANTEED \$1.95



PLUGS INTO LIGHT SOCKET

Victory Model Handiweld Arc Welder operates from 110 volts, A.C. or D.C. current same as other arc welders higher priced; generates tremendous heat to weld all metals. Not a toy welder that uses carbons, but actually uses standard coated rods—sizes 1/16" and 3/32". However, due to Priorities a generous supply of 1/16" rods only are supplied with the welder. Guaranteed not to burn out. Repairs fenders, auto bodies, radiators, machinery parts, etc. Take Victory Model Handiweld anywhere to job, operate right from light socket. You'll find a thousand uses for this welder around your home, garage, workshop. Also in garages, factories, repair shops, tin shops; mechanics, inventors, plumbers, farmers, etc. Order a "Victory Model" Handiweld now. SEND NO MONEY. We'll rush one to you with rods, goggles, electrode holder and a small piece of extension cord; these most everyone has. Pay postman only \$1.95 plus a few cents postage. If not delighted return Victory Model Handiweld in 5 days from receipt and money paid for it will be refunded promptly. Rush your order now.

KUMFY PRODUCTS INC., Dept. T-205, Cincinnati, Ohio.

Marlin

RIFLES & SHOTGUNS
Famous for accuracy
and long life since 1870
NOW ENGAGED SOLELY IN WAR PRODUCTION



The CONTENTS Include:

Just A Freudy-Cat:
Dr. "Memoirs of a Freudian Nightmarer". The author is addicted to dreams. Sometimes he is confused as to where the dream ends and reality begins. **Mr. Preble Gets Rio of His Wife:** How Mr. Preble, who accomplished his objective without benefit of Reno, vermouth or money!
Limericks On Parade: Here is a selection of new and old limericks, lightly edited in gay prints, to charm and beguile a droll and care-worn world.
The 99 44/100's, Puritans: Colonial History not found in our school textbooks. Tarrying and bundling kept the pilgrims warm and happy.
The Playboy At Fifty: Advice to keep you alive and kicking until your friends get tired of looking at you.
Wit and Wisdom: A miscellany of witticisms, comprising the wisdom of Solomon, the art of Casanova, the cynicism of Shaw and the philosophy of Socrates!
The Greeks Had A Yen For It: They lived and loved in a happy Steg Lines:
A repertoire of anecdotes, jokes, banter, quips and epigrams to make your conversation sparkle. A sure-fire laugh and chuckle getter when you tell them to your friends and associates.
The Art of Persuasion: The Feminine Point of View.
Advice to a Young Man on the Choice of a Maiden: Benjamin Franklin's classic masterpiece, considered the wittiest piece of old American wisdom.
ALSO A GALAXY OF GAY, CLEVER CARTOONS

THE PLAYBOY'S HANDBOOK is a Gay, Whimsical Reader—fresh... frivolous... flip... and funny. It's a man's book, just like hunting is a man's sport. There's something for every man and a bookful for the "bon vivant". But the whole of it, is the gayest, most human, most hilarious pattern of frivolity put together in recent years.

Send for your copy of The Playboy's Handbook now. The price is only \$1.00—the enjoyment is a thousand-fold. Money Back Guarantee. Mail the coupon Now!

Knickerbocker Pub. Co. Dept. D-82
120 Greenwich St., New York 6, N. Y.

Send me a copy of THE PLAYBOY'S HANDBOOK. If I don't like it, I can return it and get my money back at once.

() I enclose \$1.00 () Send C.O.D. plus postage.

Name.....
Address.....
City..... State.....

MEN

whether you are 16 OR UP TO 50

Come to
COYNE
for a great
future in



RADIO OPERATING and ELECTRONICS

"Learn-by-Doing" on Real Radio Apparatus!

Airports, radio stations, film studios, police short-wave, television, industrial electronics—all need TRAINED RADIO SPECIALISTS. Learn the quick practical way on actual equipment in the great Coyne Shops. Not by correspondence, but personal training based on 44 years of "know-how"!

I'LL FINANCE YOUR TRAINING!

Don't let lack of money hold you back. My plan lets you start now, pay tuition in easy monthly payments when you're trained and on the job. I help you get part-time work to help pay living expenses while training, give you Lifetime Employment Service as a Coyne graduate.

Prepares for Govt. License

Many of the better Radio jobs require government license. Coyne has enabled hundreds to pass this test successfully. You learn to send Code rapidly—no trouble-shooting—handle real transmitting equipment, etc., etc.

Dozens of Branches to Choose From

Why be satisfied with a narrow, future line when by putting in a short time in my Shops, you can qualify for unlimited opportunities in RADIO AND ELECTRONICS, today's fast-growing field! These pictures show only a few of countless well-paid jobs for trained Radio Operators.

SEND FOR FREE BOOK

Fully illustrated with big pictures of my Shops—facts about your future. Mail coupon now. No obligation. No salesman will call. Act today!

**H. C. LEWIS, Pres., RADIO DIV.
COYNE ELECTRICAL SCHOOL
500 S. Paulina St. Dept. 63-4S
Chicago, Illinois**

**H. C. LEWIS, Pres.,
RADIO DIV. COYNE ELECTRICAL SCHOOL
500 S. Paulina St., Dept. 63-4S, Chicago, Illinois**
Send FREE BOOK, "Your Future in Radio", and details of easy "Pay-After-Graduation" plan.

NAME.....
ADDRESS.....
CITY..... STATE.....

Please mention POPULAR SCIENCE when writing to advertisers.

LEARN CODE

THIS EASY WAY!

MODEL 100
\$9.85

COMPLETE

Plus
Postage

OFFICIAL
U. S.
SIGNAL
CORPS
FIELD
TELEPHONE-
TELEGRAPH

SELF-
CONTAINED
BATTERY PORTABLE

JUST RELEASED FOR CIVILIAN USE!

MODEL 100—FOR CODE AND PHONE. Practice code with this convenient, portable telegraph set or operate it as an outdoor, field telephone over hundreds of feet on a line without external batteries. Includes constant frequency buzzer, adjustable key, microphone, headphone, 4 batteries, genuine leather carrying case, diagram, operating instructions. Complete. **\$9.85**

MODEL 101—FOR CODE PRACTICE ONLY. Similar to Model 100 except it does not include microphone or headphone. Price. **\$6.85**

—MAIL ORDERS FILLED—

Please add 75c to all postal money orders to cover cost of special handling, packing, insurance and postage.

SUN RADIO CO., Dept. 5-9
212 Fulton St., New York City
Enclosed find \$..... Rush at once

☐ Model 100 Signal Corps Buzzer Outfit complete at \$9.85 (plus 75c postage).

☐ Model 101 (less microphone and headphone) at \$6.85 (plus 75c postage).

NAME.....

ADDRESS.....

CITY..... STATE.....

**RUSH COUPON
TODAY!**
New York's Oldest
Radio Supply House
**SUN
RADIO
COMPANY**
212 FULTON ST.
NEW YORK CITY

LAW STUDY AT HOME FOR PERSONAL SUCCESS AND LARGER EARNINGS. 31 years expert instruction—over 100,000 students enrolled. LL.B. Degrees awarded. All texts furnished. Easy payments. Send for FREE BOOK—“Law and Executive Guidance”.

AMERICAN EXTENSION SCHOOL OF LAW
Dept. 33-5 8 East Huron St., Chicago, Ill.

MATHEMATICS FOR RADIO

TWO VOLUMES covering the algebra, radio arithmetic, geometry; advanced algebra, trigonometry, complex numbers needed to read technical books on radio.

MAEDEL PUBLISHING HOUSE, Room 112
593 East 38 Street, Brooklyn, N. Y.

Send me MATHEMATICS FOR RADIO AND COMMUNICATION as checked below. I enclose payment therefor with the understanding that I may return the book(s) within 5 days in good condition and my money will be refunded.

Name.....

Address.....

☐ Book I at \$3.75 plus 6c postage ☐ Book II at \$4.00 plus 6c postage

Foreign and Canadian prices 25c per volume higher

BUILD THE BIGGEST \$1.00 PLANE IN U. S.

Huge 7-Ft. Super CONDOR Glider Soars for Hours

Stronger, longer flights, more graceful lines, construction simplified. Easier than ever to build. Kit E-5019, only **\$1.00**

Big 3-Ft. Famous War Models

Kit T74—Messerschmitt ME-109; Kit T76—Bell Airacobra P-39; Kit T77—Curtiss P-40 “Warhawk”; Kit T85—P-38 “Lightning”; Kit T78—Hawker “Hurricane”; Kit T79—P-51 “Mustang”.

Each Only **\$1.50** If your dealer can't supply you, order direct. **Cleveland Model & Supply Co., 4508C86 Lorain Ave., Cleveland 2, Ohio**

Rich Rewards in PLASTICS



Majestic New

Industry Unfolded

The whole story now revealed by noted authority describes many fascinating and amazing experiments in Plastics—tells of great opportunities “Now & Future.” Defense workers, farmers, executives, and men with their eyes to the future will want this wealth of new money-making inspiration and information.

SEND NO MONEY

Simply mail name and address and pay postman \$2.00 plus mail c.o.d. and postage charge upon delivery. (25c extra in Canada) Return in ten days for refund if not fully satisfied. Simply write “Send Louge's book on trial,” giving your name and address. Mail it today! You'll be glad you did it!

PLASTICS INSTITUTE

221 NO. LA SALLE ST., DEPT. 5-9 • CHICAGO, ILLINOIS

THRILLING!
25 Actual Photographs 25¢
of U. S. ARMY and NAVY
Planes, Tanks, Warships, Camps

Send for amazing miniature packets containing 25 genuine photographs, only 25¢ per set. All photos approved by the Government. Check below packets you want. Mail this ad with your name and address or write letter. Send remittance in stamps, currency, money order. Satisfaction or money back.

- ☐ U. S. Army Airplanes
- ☐ U. S. Navy Airplanes
- ☐ U. S. Army Tanks
- ☐ U. S. Navy Warships
- ☐ U. S. Navy Activities
- ☐ U. S. Marines in Action
- ☐ U. S. Army Camp Scenes



SEE NEW AIRPLANES, GIANT TANKS, DREADNAUGHTS IN REAL ACTION

Start collecting these sharp, clear, genuine photographs which will be valuable from the historical standpoint in the years to come. Order now!

THE GROGAN PHOTO CO., DEPT. 11 DANVILLE, ILLINOIS

AIRCRAFT Designing & Engineering



You can learn to design airplanes. A Ryan Home Study Course in Aeronautical Engineering will prepare you quicker for a job with good pay and a future. Easy to understand. No experience necessary.

FREE 24 Page Valuable Illustrated Booklet

RYAN AERONAUTICAL INSTITUTE
419 Lindbergh Field, San Diego, California



“POPULAR SCIENCE”

A Paramount one-reel feature in Magnacolor. Produced by Fairbanks & Carlisle—in cooperation with the editors of Popular Science Monthly.



Send 5c for new No. 40 Catalog (none free)

When Worming for
Tape, Round (ascarid)
and Hook Worms



You Cannot Worm Your Dog WRONG

—you're sure to worm right if you follow the easy picturized directions with Pulvex (the combination treatment) Worm Capsules. Here's why: Your dog can have Tape, Round (ascarid) and Hook Worms, any or all, at the same time! To worm for all three AS YOU ALWAYS SHOULD, especially tapeworms, YOU MUST USE 2 TYPES OF CAPSULES. No single-type capsule can expel those three worms. You definitely expel them (including tapeworms) when you use the 2 types of capsules, to be given a few days apart, in the Pulvex Combination Treatment Worm Capsule package.

Worm right; avoid worming wrong for those worms; use Pulvex Capsules. Packaged two ways: for puppies, for dogs. Either 50c. Double size package, 75c. Quantity discounts to kennels; write direct to—

WILLIAM COOPER & NEPHEWS, Inc.
1921 Clifton Ave., Chicago

PULVEX

Combination Treatment

WORM CAPSULES



LEARN MONEY-MAKING CARTOONING

Some simplified method that has helped train creators of "Terry & Pirates," "Wash Tubbs," "Out Our Way," "Winnie Winkle," "Reggie Pellers," "Strange As It Seems," "Secret Agent X-9," and many others. Earn while learning. Rush life for Picture Chart (test your ability), and full details, (State age). THE LARON SCHOOL, 4325 National Building, Cleveland 14, Ohio



MOTORISTS Wanted!



TO MAKE THIS UNIQUE GAS SAVING TEST

Will you permit us to send you at our risk the Vacu-matic, a device which auto-owners everywhere are praising? Install it on your car. Test it at our risk. Unless it trims dollars off your gas bills by saving up to 50% on gasoline consumption, gives more power, quicker pickup and faster acceleration, the test will cost you nothing.

Automatic Supercharge Principle
Vacu-matic is entirely different! It operates on the supercharge principle by automatically adding a charged extra oxygen drawn free from the outer air into the heart of the gas mixture. It is entirely automatic and allows the motor to "breathe" at the correct time, opening and closing as required. Saves up to 50% on gas costs, with better motor performance.

AGENTS Get Yours FREE

FOR INTRODUCING. Here's a splendid opportunity for unusual sales and profits. Every car, truck, tractor owner a prospect. Send name and address now for big money making offer and how you can get yours Free. The Vacu-matic Co., 7617-835 W. State Street, Wauwatosa, Wis.

"Jim's Last Letter is Really TERRIFIC!"

(Pst! He read the book!)



NOW—It's Easy To Write Thrilling Love Letters!

This amazing book shows you how the most common things can sound interesting—helps you express your personality in your letters! Contains dozens of actual sample letters that tell just how to write letters from beginning to end. Scores of love letters by world-famous people—lists of useful synonyms—common errors, and how to avoid them—correct spelling of many catchy words—many other important letter-writing hints. **MONEY-BACK OFFER!**—Examine for 10 days—if not delighted with results, return book and your money will be refunded! And remember, with each book you receive ONE YEAR'S SUPPLY of Gold Monograms for your writing paper, FREE! Stravon Publishers, 342 Madison Ave., N. Y. C.



One Year's Supply of
Gold Monograms
for Your Stationery
INCLUDED FREE

PARTIAL CONTENTS

How to express your love,
How to make him or her miss you,
How to assure him or her of your
affection,
How to "break the ice,"
How to tell your husband (or wife)
those "little things" of love,
And Many Other Chapters!

MAIL COUPON TODAY

STRAVON PUBLISHERS, Dept. L-589
342 Madison Ave., New York 17, N. Y.

Send book, "How to Write Love Letters," in plain wrapper, and one year's supply of Gold Monograms free. If not delighted, I may return purchase in 10 days and my money will be refunded.

() Send C.O.D. I will pay postman 98c plus few cents postage.

() I enclose 98c—send postpaid.

NAME.....

ADDRESS.....

THOUSANDS of MEN NOW

Appear Feel Look
SLIMMER BETTER YOUNGER
with Commander



Now you can get sensational results—at once—with the new Commander Supporter, slenderized with this amazing free-action, ever comfortable, elastic woven garment! Once you try it, you'll never be without the Commander!

"THE INTERLOCKING HANDS" The Sensational NEW PRINCIPLE Of Abdominal Support

Clasp your hands over the abdomen, as in the picture—then raise and press gently against it—and notice how much better you feel! Sturdy non-stretch fabric is BUILT IN with the two-way stretch weave of the Commander for EXTRA DOUBLE SUPPORT across the abdomen. Instantly the Commander flattens your "corporation" BRACES YOUR BACK—improves your posture—Your clothes fit smartly—You look better, too. No binding, no riding, no sagging! Send for this famous all-purpose supporter today!



TRY IT TEN DAYS
At Our Expense
Do this today! Send the coupon—wear a Commander for TEN DAYS AT OUR EXPENSE—and if you do not get all the results you expect, return it and YOUR MONEY WILL BE REFUNDED promptly.

\$2.95



10 Day Free Trial Coupon—Mail Today

Ward Green Company, Dept. A-919
342 Madison Ave., New York 17, N. Y.

Send me The "Commander" for Free Trial. I will pay postman \$2.98 plus postage. (Sizes 28 to 47.) If not satisfied after wearing 10 days I may return it for a prompt refund. (Sizes 48 to 60 \$3.98.)

My waist Measure..... My Height.....

NAME.....

Does a busy day make an OLD MAN out of you?



● Maybe you're *missing* something, mister . . . maybe you *could* end that "old man" feeling *this* simple, scientific way . . . with a Bauer & Black self-adjusting Suspensory. Men everywhere in all walks of life, active or quiet, heavy or light . . . say the firm, comfortable, flexible support of a Suspensory makes them *feel* years *younger* . . . less tired . . . *all* the time.

Mail Coupon for FREE BOOK



This free illustrated book tells you how men claim to have found new vigor . . . helped to banish quitting-time fatigue . . . how they *stay* fit and energetic all day long . . . every day. Send for your free copy today.

BAUER & BLACK

Suspensories

Division of The Kendall Company

Dept. S-482

2500 S. Dearborn St., Chicago, Ill.

Please send me your booklet about Suspensories.

Name.....

Address.....

City.....State.....

My Occupation is ☐ Active ☐ Not Active

STUDY AT HOME

With A Chartered Educational Institution

Courses in **ENGINEERING**: Electrical, Civil, Mechanical, Drafting, Architectural, Steam, Aeronautical, Radio, Structural, Mining, Industrial, Highway, Petroleum, Marine Chemical.
Courses in **ARTS AND SCIENCES**: Philosophy; Education; Letters; Public Health; Medical Jurisprudence; Psychology; Sociology; Physics; Chemistry; Geology; Pol. Science; Theology; Law; Business and Commerce; Accounting; Mathematics; Statistics; Agriculture.
McKinley-Roosevelt Incorporated, 4610-A.C. Sheridan Road, Chicago

Get this Handy OHMITE Ohm's Law Calculator!



Figures Ohms, Watts, Volts, Amperes—Quickly, Easily!

Solves any Ohm's Law Problem with one setting of the slide. Requires no slide rule knowledge. All values are direct

reading. Scales on two sides cover the range of currents, resistances, wattages and voltages commonly used in Radio and Electrical Work. Size 4 1/2" x 9".

Send only 10c in coin to cover cost of handling.
OHMITE MFG. CO., 4944 Flournoy St., Chicago, Ill.



Why It Pays To LEARN PHOTOGRAPHY NOW

Never before so many job and career opportunities! Photographers needed in business, industry, science, N.Y.I. graduates winning promotion, higher pay in Armed Forces. Quality at America's largest, oldest school. Resident or home study. FREE catalog describes commercial, portrait, motion picture and color courses. Write today!

N. Y. INSTITUTE of PHOTOGRAPHY, Dept. 5, 10 W. 33 St., New York 1, N. Y.



America's Fastest Selling Novelty Sensation!

Flippy

Military Strip Tease CIGARETTE CASE

You ain't seen nuthin' 'til you "flip the cover"

Flippy is Daring . . . yet so clever it never offends. Everyone wants one on sight! Friends will clamor to learn where you got it. **SEND NO MONEY:** Simply send your name and address on 1c postcard for your Flippy today, and pay postman \$1.50 plus postage. Or send \$1.50 with order and we pay postage.

FLIPPY, Dept. P.S. Box 3620
Mdse. Mart, Chicago



Unrequited Gift Item for Every Smoker
Any smoker will get a bang out of Flippy. There's a floor show with every smoke. Fits comfortably in the vest pocket or any ladies' purse. Each case is moulded in smart colorful plastic, sparkles like a jewel.

EYEGLASSES BY MAIL

ALWAYS 16 DAYS TRIAL

\$1.95 WRITE TODAY FOR

FREE CATALOG SEND NO MONEY

ADVANCE SPECTACLE COMPANY

537 South Dearborn Street

CHICAGO ILLINOIS DEPT. SP-9



LEARN ARC WELDING IN 5 WEEKS



EXCELLENT PAY—Here's a trade which has always demanded good pay. Once you have it, you never lose it, and there's always room for advancement as you increase your skill.

POST WAR SECURITY—Welding has grown to be one of the top trades in the country, and with plants swinging over, you'll have no trouble sticking to this profitable work after the war.


NON-PROFIT INSTITUTION—Learn welding from A to Z in 5 weeks where materials are your only cost. Ask for details today.

HOBERT SCHOOL OF
ARC WELDING
Box P-931, TROY, OHIO

There's a
**GROWING
DEMAND**

for trained
welders in factories,
shipyards, contract-
ors, railroads etc.

**HOBERT SCHOOL
of ARC WELDING**



HOBERT "One of the World's Largest Builders of Arc Welders and Equipment"

Mechanically Inclined Men HOME APPLIANCE REPAIRING

Offers Big Money-Independence

America's War Made Industry

Restriction of manufacturing has meant that the men who know Home Appliance Repairing—fixing refrigerators, vacuum cleaners, washing machines, motors, welding, nickle plating, etc. etc. are reaping a steady, daily stream of dollars and building for themselves a permanent profitable business.

No Previous Experience Needed

The ability to hold and use a tool plus an ambition to make money is all that you need to become a successful Repair Shop Owner.

Full Time or Spare Time

Work as many hours as you want. \$5.00—\$6.00 an hour often made.

New Course Tells All

Our new course on Home Appliance Repairing . . . profusely illustrated shows you in simple, easy to understand language how to make all repairs, build tools you need and how to get business to come to you. Price of course is so low that your savings on your own household repairs will quickly pay for it. Send today for complete FREE literature on how you too can get started.

CHRISTY SUPPLY CO.,

2835 N. Central Ave., Dept. D-801, Chicago

HOW YOU CAN BUILD A MIGHTY ARM



**THIS BOOK Shows You
HOW TO BUILD A MIGHTY
ARM AND 16-in. BICEPS
ONLY 25c TO YOU**

A COMPLETE PICTURE COURSE ON ARM BUILDING

Why not get an arm of might with the power and grip to obey your physical desires? Weaklings whose arms were scrawny pieces of skin and bone have taken this course and in a short time developed themselves into strong men of powerful proportions with bulging biceps and brawny forearms . . . strong, solid arms of power that are respected by men and admired by women.

Learn THE WORLD'S GREAT SECRETS OF ARM STRENGTH

This course is especially planned to build every muscle in your arm. Many pupils have developed a pair of triceps shaped like a horseshoe, and just as strong, and a pair of biceps that show their double head formation. The sinewy cables between the biceps and elbow are deep and thick with wire cable-like ligaments. The forearm bellies with bulk, the great supinator lifting muscles become a column of power, and their wrists are alive and writhing with cordy sinew. Wouldn't you like to have a magnificent arm like the figure pictured above?

You can't make a mistake. The strongest armed man in the world wrote this course for you. His great experience stands as proof that you too can succeed. You get his secret methods of strength development illustrated and explained as you like them. Rush only 25c. You are not limited to the arm. Also try: Moulding a Mighty Back, Moulding a Mighty Chest, Moulding a Mighty Grip, Moulding Mighty Legs.

**SEND FOR THESE FIVE FAMOUS COURSES
FORMERLY \$5.00 EACH. NOW IN BOOK FORM
ONLY 25c EACH OR ALL 5 FOR \$1.00.**

Mail your order now and "NERVES OF STEEL, MUSCLES LIKE IRON" will be included FREE! It is a priceless book to the strength fan and muscle builder. Full of pictures of marvelous bodied men who will show you what The Jowett Progressive Power Course has done for them and how it can build you into a man of marvelous muscular symmetry and dynamic strength. Reach out . . . Grasp this last chance—limited time offer.



Book With Photos of Famous Strong Men FREE
...and how you can become one of them!

If You Mail Coupon NOW!

JOWETT INSTITUTE OF PHYSICAL CULTURE
230 Fifth Ave., New York, I. N. Y. Dept. 369

George F. Jowett. Your proposition looks good to me. Send by return mail, prepaid, the courses checked below for which I am enclosing:

- | | |
|---|---|
| ☐ All 5 courses for | ☐ Moulding a Mighty Grip, 25c |
| ☐ Moulding a Mighty Arm, 25c | ☐ Moulding a Mighty Chest, 25c |
| ☐ Moulding a Mighty Back, 25c | ☐ Moulding Mighty Legs, 25c |
| Send all 5 courses C. O. D. (\$1 plus postage). No orders less than \$1 sent C. O. D. | |

GEORGE F. JOWETT
"Champion of Champions"

Holds more strength than any other teacher or athlete.

Name _____ Age _____

Address _____

INVENTIONS wanted!!

New ideas for the farm, factory, business, home. We are looking for all kinds of useful inventions to develop, manufacture and sell. Write: Kinner Motors—635 West Colorado, Glendale, California.

FREE TRIAL LESSON IN DRAFTING

FREE TRIAL LESSON

More good jobs now in Drafting. Learn AT HOME in spare time (or at our Chicago School). Send postcard for **FREE TRIAL LESSON** and see how easy to learn and get a good job.

CHICAGO TECHNICAL COLLEGE

M-219 Tech Bldg., 2000 S. Mich Ave., Chicago, Ill.

RADIO

ENGINEERING, Broadcasting, Servicing, Electronics, Aviation, Marine & Police Radio taught thoroughly. 48 weeks' Engineering course equivalent to 3 years' college radio work. School established 1874; all expenses low. Co-educational. Catalog free.

Dodge Institute. Dept. 503 Valparaiso, Ind.

MAKE BIG MONEY at HOME! NEW INVENTION Electroplates by Brush



New, patented invention makes possible big earnings AT HOME. Replate auto parts—worn articles in homes, stores, hotels, restaurants, etc.—with durable, sparkling, new coat of metal—with stroke of brush. Easy, simple, quick. Genuine Gold, Silver, Nickel, Cadmium, etc. Everything furnished. Outfit complete, ready for use. No shop required. Clear from \$2 to \$5 an hour in lifetime business. Small investment gets you in business. Steady repeat. Machine can pay for itself in time. Send TODAY for FREE SAMPLE and illustrated BOOKLET how you can have a life income from a business of YOUR OWN built upon satisfied customers. Act at once!

WARNER ELECTRIC COMPANY

663 N. Wells St., Chicago, Ill., Dept. 405

ADVERTISING

ADVERTISING placed—any publication—lowest rates. Personal service. Skilled advertising-merchandising counsel. Rate list and booklet, entitled "Advertising Results For Sale" free. Baker Agency, 3302 West Dodge, Omaha, Nebraska.

MAIL—Order or agent at reaching 1,000,000 families throughout United States \$15.40 monthly. Newspaper, magazine, radio, TV, ratebook, free. Chicago Advertising Agency, 40-2P West Jackson, Chicago.

ADVERTISING—newspapers, magazines, Publishers' rates, Martin Agency, 1717 Madison Avenue, New York.

ADVERTISING—24 words, 149 newspapers, \$6.50. Lists Free. Advertising Bureau, 4515-P Cottage Grove, Chicago.

AGENTS WANTED

100 SENSATIONAL Money Makers. Sell friends outstanding Christmas, Religious Scripture Text, Etching, Humorous, Birthday, Secret Free Patriotic greeting cards and Gift Wrappings by the box and in cabinets—30c up. Individual Sweetheart, Valentine, Serenades, name retailing \$1.00 and \$1.00 each. Request famous \$1 Christmas 21 card assortment on approval. 50c for \$1 name imprinted Christmas Cards. Special Get Started Offer, 50c. Baker & Co., 343 Broadway, Dept. PS-9, New York.

START Your Own Business on our capital. Always your own boss. Hundreds average \$3,000 to \$5,000 annual sales year after year. We supply stocks, equipment on credit. 200 home necessities. Selling experience unnecessary to start. Wonderful opportunity to own pleasant, profitable business backed by world wide industry. Write Rawleigh Co., Dept. I-U-PCS, Free-press III.

MAKE extra money easily. Sell 50 assorted Personal Christmas Cards for only \$1.00. Twenty-two Box Assortments for 33c up. Odd Cards 2c each. Cards for Boys Service, Sentimental Free Samples exclusive \$1 line Personal Cards and Imprinted Stationery. Request \$1 assortment on approval. New England Card Publishers, North Abington, F-382, Mass.

SELL Christmas Cards. Outstanding selection smart designs with Name Imprinted—low as 50c for \$1. Amazing values for \$1.00. Send for Free Samples exclusive \$1 line Personal Cards and Imprinted Stationery. Request \$1 assortment on approval. HerteilArt, 305 Adams, Dept. 830, Chicago.

EXTRA money for you. Sell 50 for \$1.00 Christmas Cards and Personal Stationery. Miracle value \$1.00 Christmas assortment. Other money making boxes 25c up. Up to 100% profit. Friends, neighbors buy readily. Samples on approval. Special offer. Elмира Greeting Card Co., M-46, Elмира, N.Y.

CALL On Friends with sensational Personal Christmas Cards—50 for \$1.00 up. Personal Stationery. Also magnificent 21 Card 50 Assortment. Profit 50c. Experience unnecessary. Samples on approval. Wallace Brown, 225 Fifth Ave., Dept. Z-35, New York.

CHRISTMAS Cards—Sell 50 for \$1 with Sender's Name Imprinted. Amazing values get quick easy orders. Also fast-selling Box Assortments. Generous cash profits. Sell experience money making boxes 25c up. approval. Cardinal Craftsmen, Dept. 573, Cincinnati, Ohio.

SELL Christmas Card sensation! New "Prize" 21-card assortment leads in value, appeal. Sell \$1.00 pays out 10c. Other fast-selling assortments. Christmas Cards with name 50c for \$1.00. Samples on approval. Chilton Greetings, 147 Essex, Dept. 41-C, Boston, Mass.

GOOD Paying Business Silvering mirrors, plating autotops, reflectors, bicycles, bathroom fixtures, etc., by late method. No tools or shop required. Write for Free Sample. Gummetal Co., Ave. G, Decatur, Illinois.

SELL Christmas Cards—Make extra money. 20 gorgeous color pictures with sensational selling 21-card box. Many other big value Assortments. Up to 100% profit. Experience unnecessary. Free Samples. South-east Greeting, Dept. 810, Memphis, Tenn.

EXCELLENT Sideline for Printing Salesmen. Decalomania Name Plates in small quantities. Also, make money applying Initials on Automobiles. Free Samples. "Redco", 1463 Washington, Boston (18), Mass.

BIG Bargains for Big Profits. Men's undershirts 25c, suits \$1.50, overcoats 50c, shoes 12 1/2c. Over 100 sensational items. Experience unnecessary. Free Wholesale Catalog. Superior, 1250-JA Jefferson, Chicago.

TAKE orders for new, sensational Plastic Lifetime Reproductions of any photo, negative. Amazingly beautiful. Big earning opportunity. Part or full time. Get details quickly. Sell for \$1.00. Service Co., 914 Walnut St., Philadelphia, Pa.

SELL Art Calendars featuring gorgeous artists' models photographed in nude colors. Biggest commissions. 8 assorted salesmen, \$1.00 to \$15 assortment. Money Back Guarantee. Ray Rogers, 604 Arbutus Building, Brooklyn, N.Y.

WE Pay You \$5 for selling ten \$1 boxes. 60 beautiful assorted name imprinted Christmas Cards. Sell for \$1.00. You make 50c. Free samples. Cheerful Card Co., 42 White Plains, N.Y.

AGENTS—Coin Money—It's New—It's Hot! Everyone wants radiant plastic plaques of loved ones. Commissions advanced. We deliver. Collect. Kondon, Box 157, Upper Darby, Pa.

INCREASE Income. Sell native handicrafts and novelties. Details free. Barlington Smith, Half-Way-Ten—100, Jamaica, B. W. I.

HANDY Hair Trimmer. Sells like wild. Claims 100% profit. Free details. Order. Samples sent on trial. Kristie 127, Akron, Ohio.

AGENTS—300% Profit selling Gold Leaf Window Letters; stores and offices. Free samples. Metallic Letter Co., 437 N. Clark, Chicago.

LICK After-war layoffs! Start own business; home office. Booklet describing "Outlets of 17 Test Plans" free. Elite Co., 2144 Grand St., New York.

FREE Water and our concentrates, make flavors, lotions, shampoos, 72 products, labels, bottles furnished. Qualco, F-20030 Rm. 100, Detroit.

NUSILVER—Silver Plating and Polishing Liquid. Apply with cloth. \$1.00 bottle postpaid. Nusilver, Aurora, Ill.

REAL Live Mexican Jumping Beans—20—25c, 100—85c, 500—\$2.00, 1000—\$3.00. J. J. Frank, 3255 Palm, Rockford, Illinois.

QUICK sellers. Big Profits. Stamp appreciated. Dissell, 4667 Rockwood Road, Cleveland, Ohio.

DANDELION Death Make—Sell 1,500%. Simple, simplified, manufacturing processes. Thermofab, Peoria, Ill.

PLAYING card game. 250% profit. Sample game 25c. Box 842, Denver 1, Colorado.

ANTIQUES, RELICS

INDIAN GOODS

INDIAN Relics, coins, minerals, glass buttons, catalogue 6c. Vernon Lemley, Osborn, Kansas.

276 ANTIQUE Firearms, Swords, Cartridges, Rifles, Indian Relics. Catalog, 10c. (Photographs of Most) Heike, Wenona, Ill.

SWORDS, rapiers, daggers, pistols, armor; illustrated catalog. 25c. Robert Abels, 866 E. 1st Ave., N. Miami Beach, Fla.

100 BRINGS you a beautiful agate bird arrow. L. B. Noel, Box 282, Kingsport, Tenn.

AUTHORS SERVICE

NEW Writers Wanted to re-write ideas in papers, magazines, books. Splendid opportunity to "break into" profitable writing. Learn, postcard for Free Details. Comfort Writer's Service, 210-R, South Semventh, (2), St. Louis, Mo.

AUTOMOBILES

WHIRLGAS Turbulator, 3c, gives cyclonic, vaporizing whirl to carburetor mixture engine, makes thereby perfect. Results require readjustment for economic motor operation. Wrench installs 15 minutes. Any car; give make, year. If not surprisingly pleased with motor performance, return for immediate refund. John Hanley, 5719 Loraine, Detroit 8, Michigan.

SAVE Gas—With "Moto-Purr,"—new revolutionary laboratory-tested, tablet, new report saving gas up to 40% Results guaranteed. \$1.00 package treats 140 gallons. Liberal supply 25c. Free literature. Moto-Purr Distributors, Ames Station, Omaha, Nebraska.

AUTOMOBILE Racing Book, Fifth Edition—Revised. Tells how to build dirt track bodies, frames, engines. Records, superchargers, rules, formula, plans, stock vehicle road racing record for Free. Postpaid; \$1.15 C.O.D. Ray Kuns, Department 274, Madisonville, Cincinnati, Ohio.

1943 IGNITION Supercharger, \$3.50. Fast Starting, More Power, Fewer Sales Mfg. Co., 60 John St., New York.

RENEW car batteries inexpensively. Instructions \$1.00. Popular Service, Racine, Wisconsin.

AUTO SUPPLIES & EQUIPMENT

SPECIAL: 15 Picked formulas \$1.00. Renew old tires. Carbide removed. Retread your tires. Puncture-proof your tires. Auto-top dressing. Mechanic's hand soap. Increase gasoline mileage. Renew car batteries. Ignition supercharger. Anti-freeze. Iron-cement. Plastic-wood. Iceless-ice. Illuminous paint. Invisible-ink. Mounting materials. Box 4766, San Francisco, Calif.

DIESEL conversions for auto, tractor, and Marine engines. Cheap installation. Wonderful performance. Proven factory method. Differentiated. Write for free circular No. 3. Harrington Company, 201-204 Manchester Bridge, Portland, Oregon.

OPERATE your car on wood or coal gas, extensively used in Europe. Complete detailed instructions \$1.00. Frank Harris, Barracks 8-4, Naval Construction Training Center, Norfolk, Va.

GASLESS Gas Quickly, easily compounded. Formula, 25c. Duffey, 247, Covington, Ky.

GASOLINE Substitute: 4c per gallon. Details 10c. R. Plumb, Herkimer, N.Y.

AVIATION

SOLVE, Wind-Speed Triangles Mentally. Easy when you know how. Ten cents in stamps for Particulars. M., Box 92, Little, Pa.

BUILD and fly your own motorcycle powered monoplane. Home. Easy, cheap. Tested and guaranteed, \$1.00. Aerochek, Dearborn, Mich.

BATTERIES, GENERATORS, ETC.

EDISON Batteries: Power, Light, Five year guarantees. Fifteen year life. Complete lighting equipment. Free literature. See-Jay Battery Corp., 321 Yonkers Avenue, Yonkers, New York.

BOATS, OUTBOARD MOTORS, ETC.

FULL size, cut to shape boat patterns, blueprints, 7 1/2—38 feet. Illustrated "Build a Boat" catalogue, 10c (coin). "How to Build Boats" book, \$1.00. Cleveland Boat Builders' Co., Station A-77, Cleveland, Ohio.

MARINE Power—Easily convert any Ford motor (domestic and foreign) with Oeco parts and kits. Complete catalogue, 25c (coin). Oeco Motors Corp., 3627-29 N. Lawrence St., Philadelphia, Pa.

OUTBOARD Motors. Used and Rebuilt. Save money. Used parts. Bargain list free. Randall-Ricks, 955 Commonwealth, Boston, Mass.

14' SAILING Rowboat, Wood Duck. Easily built. Blueprints, \$4.00. Marine Productions, Box 1492-J, Milwaukee 1, Wis.

BOY-BUILDING COURSES

SUPER Ju-Jitsu—lightning defense and attack system. Sensational new home study course. Now only 10c. It teaches twice your size with only your bare hands. Free details. Nelson Co., 321 South Wabash, Dept. Z-509, Chicago.

HEIGHT, Beauty, Sight, etc., particulars 10c. Hystreth, 186 Rutledge Street, Brooklyn, New York.

BE strong, muscular, full of pep. Amazing new body-building course. Write Olympic System, 1000 Broadway, New York.

SUPER system of Natural Physical Training. Free booklet. Harry Good, 3261-PS Wason Road, St. Louis 9, Mo.

LEARN Acrobatic Tumbling. Complete course. 50c. Power, 923 W. Vine, Kalamazoo 44, Mich.

BOOK MATCHES

NOVELTY Matches. Strike on Hitler's crimes or Jax Solid. Match. Strike 'Em Dead—Specify—10 matchbooks, 280 postpaid. Shepherd Service, 3085 Rincon, San Francisco, Calif.

MONOGRAM or name gold stamped on 50 matchbooks. \$1.00 Postpaid. Shepherd Service, 3085 Rincon, San Francisco, Calif.

BOOKS, PERIODICALS

BUSINESS—Vocational— Diversion Magazines. Current single copies. Covering Advertising, Aviation, Building, Clothing, Hobbies, Journalism, Life, Stock, Mail Order, Medical, Metal-Working, Music, Patents, Photography, Printing, Poultry, Radio, Refrigeration, Signs, Sports and outdoor sports fields. List with prices free. Commercial Publications, Inc., Box 34S North Ritter, Indianapolis 1, Indiana.

LOVE Diary—(Ruthbella-Sanacchi). Deluxe, illustrated volume (private), published—\$5.00. Sample, prospectus—25c. Paul Ferrante Press, Fallides Park, N.J.

WHAT every Mason wants. We have Masonic books for Blue Lodge, Chapter, Commandery, Scottish Rite, Shrine. Our rituals are used the world over. Send for free catalog of books and rituals for Masters, Odd Fellows, Knights of Pythias, Knights of Columbus, Elks, etc. Ezra A. Cook, Publisher, Inc., P. O. Box 796, Dept. Z, Chicago, Ill.

ART Students—Artists! "Learn to draw from nature!" Professional artist study photo-poses. Complete instructions, \$1.00. Money-back guarantee. Charles D. Allen, P. O. Box 71, Times Square Station, New York.

EDUCATIONAL Books sold cheaply or rented for small fee. Books bought. Money back guarantee. 4,000 Bargains. Catalog (Free Bought). Lee Mountain, Pisgah, Ala.

CHINESE Physicians, Secrets, 165 pages, rare illustrations, unpublished truth, secret healing arts, peculiar custom. \$1. Write Garding Lui, Box 622, Metropolitan Station, Los Angeles, California.

ANY Book (New, Used, Out-of-print, Rare) promptly supplied! Lowest prices! Send for free bargain catalog. Write: Book Shop, 516 Arcadia Court, Pontiac, Michigan.

"HOW To Draw From Nude Models" Gorgeous art photo-tone poses. Complete instructions, \$2.00. Money Back Guarantee. Ray Rogers, 905 Boro Hall Building, Brooklyn, New York.

BOOKS (out-of-print, new, used) quickly supplied. Many titles in new catalog. T. Mamkowsky, 13870 Mark Ave., Detroit, Michigan.

SEVEN Keys to Power \$1.00; Catalog of strange, occult books, merchandise sent free. Dixie, P. O. Box 932-S, Birmingham, Ala.

FASCINATING Girls—Art Pictures—Books—Male Athletes—Post Cards—Large assortment \$1.00. Particulars free. Novak, 203 East 21st, Oakland 6, Calif.

EXCELLENT Sparetime profits taking subscriptions—2500 magazines. Complete starting supplies Free! Plans, 144-34 70th Avenue, Flushing, New York.

ARTISTIC girl pictures, Real Models. 40 Photos \$1.00, 8 for 35c postpaid. All different, postcard size, Scott's, Box 342, Covington, Ky.

GLAMOUR Girls, Artcards: Hilarious Comics, 50 \$1.00. Books, Novelties. Samples, lists 25c. Western Sales Agency, 815 Sg Hill, Los Angeles.

ADULT books, Sample and catalog, 10c. Alstone, 260, Lunenburg, Mass.

BOOK lovers, Would you pay \$2.98 for 101 best sellers, value \$295.05? Information free. Jenkins 292B2, New York.

PRETTY Girls photos, cartoons, novelties, books. Jumbo assortment with list \$1. Edward Gross, P. Carnegie, Pa.

5c BUYS back-dated magazines, Foreign, domestic, arts. Catalogs 10c. American Magazines, 853 4th Ave., New York, N.Y.

ADULT Books—Catalog, lists, sample books 25c. Lefavor, Box 571, San Bernardino, Calif.

5 MOST read mail order magazines, 20c. Armand Cartier, 695-B North, Pittsfield, Mass.

TECHNICAL Books, Free List, Edwards, 324 North 18th, Quincy, Illinois.

BUILD IT YOURSELF

BUILD your tractor from second-hand automobiles! Convert your horse drawn farm equipment into tractor driven equipment. Nolan's Garage, East Machan, Mass.

BUSINESS OPPORTUNITIES

PLASTEX Industries offer industrious men an opportunity to start a business of their own, manufacturing art goods, novelties and utility products in rubber and marble imitation. 75c material makes regular 10c store seller. Rubber molds furnished for speed production. Small investment brings big return. Write now. How placing big chain store orders with manufacturers. Ambitious men have chance for prosperity. Plastex Industries, Dept. S, 1085 Washington Ave., New York, N.Y.

START Home Business making statues, plaques, art goods, novelties, souvenirs, concrete pottery, garden furniture, artificial marble floors, liquid marble. Make your own flexible molds. Amazing profits. Valuable folder free. Creative Publishers, P89, Glencoe, Illinois.

LEARN Refrigeration Service. Open your own shop. No independent after the war. Little capital necessary. Opportunity for older men. Completely illustrated course, reasonable. Write: Refrigeration School, Dept. S24, 417 West Pico, Los Angeles.

GUARANTEED industrial and technical formulas. Stamped envelope. Box 177, Cambridge, Illinois.

LIQUID Marble: snow-white, multi-colored, Glazed, Unglazed. Composition Floor, Liquid Marble, Liquid Shrink, Liquid Priorities, Flexible molds, Plaster casting. Get into the big money. Write—Compo-Text, Box 786-F, St. Louis, Mo.

MECHANICALLY Inclined Men—Own and operate general Appliance Repair shop. Complete, illustrated course shows you how to repair refrigerators, motors, motor repair, How to get business, etc., all phases covered. Free literature. Christy Supply, Dept. 132, 2835 N. Central Ave., Chicago.

Plating, Paying Business Silvering mirrors, plating auto parts, reducing bathroom fixtures, etc., by late method. No tanks or shop required, outfit furnished. Write: Plating, Gunmetal Co. Ave. E., Decatur, Illinois.

MAIL Order Business Course shows you how to make money, spare or fulltime. Teaches professional mail order technique —not penny-catching schemes. Free details. Nelson Company, 321 South Wabash, Dept. 2-403, Chicago.

OPPORTUNITY—Mail Order business is today's biggest profit-making field. Mail order business is booming. Learn about your opportunities in this business today. Write for free information to Al Siddall.

Easy Way to Paint Signs, Use Letter Pat- terns. Avoid sloppy work and wasted time. No experience needed for expert work. Write for descriptive Folder. John Ray, Box 259, Central Ave., Chicago, Ill.

127 WAYS to make money, in home or office, business of your own. Full particulars free. Elite Co., 214-A, Grand St., New York.

PERFUMERS make big money. I furnish complete detailed instructions. Don't delay—write Dr. Abell, Parkway Bldg., Pasadena, Calif.

"HOW To Make Simple Molds and Plaster Plaques." Profit in popular novelties! Booklet 25c. Plastacraft, 1406 E. 43rd St., Cleveland, Ohio.

AFTER Victory What? Prepare now. Be- come financially independent. Particulars free. Bay State Service, 10 Bulfinch, Boston 14, Mass.

PAYING Mail Business—Start on "shoe- string". General Publications, Ossining, N.Y.

MAIL Order business for sale. Established ten years. M. Walke, 304 84th Street, Brooklyn, N.Y.

SWISS Music Box Works—\$1.85 to \$2.25. Suitable for many novelties. Mermoid Manufacturers, 147 West 46th Street, N.Y.

10c BRINGS You magazine filled with op- portunities. Colco Service, 210 Fifth, New York City 10.

MAKE Money at home in spare time by mail. Write Gordon Publishers, Box 23, Pawtucket, R.I.

WEBER Typewriter Mechanic School. Simplified homestudy. Repairing in- creased earnings. Write now.

COLLECT Bad accounts, send 50c for col- lection letters. P. Vinick, 1468 Montpelier, Baltimore 18, Md.

INTERESTED in mailorder? Send 10c for huge opportunity mail. Alvin Thomas, 1622 W. 53rd St., Erie, Pa.

FINANCIAL backer wanted by successful John Boulton, 2119 Scott, San Francisco, Calif.

SUCCESS, happiness assured regardless race, creed. Write—Nirvana, Norfolk, N.Y.

BUSINESS SERVICE

JACKSONVILLE, Fla. Mail address \$2.00 monthly. Your mail received and forwarded. Empire Mail Service, Box 85, Jacksonville, Fla.

CAMERAS, PHOTO SUPPLIES

WRITE Bass First—Largest stocks of fine cameras, (still and movie) in the U.S.A. Latest Argus C-3 with coupled range finder, synchro flash, 50mm., F3.5 lens; also 75mm. Bach & Lomb. 35mm. f/2.8 lens; also coupled to range finder, \$82.55 value—\$60.50, unconditionally guaranteed. Cowhide Eveready case, \$4.75, P. Thage, F-43 Anagrams, Front Street, New York. Whatever you want in photography, write Bass first. Liberal trades. For over thirty years, money back if not satisfied. Bass Camera Company, Dept. S.F., 179 W. Madison Street, Chicago, Ill.

WE Pay Top Prices for used cameras and photographic equipment. Turn your idle camera, enlarger, printer, lenses, development equipment, etc., into cash. Just send us a list of what you have. State make, model, age, condition. We will write you a check on the spot. What we'll pay. Prepare your list today. Send to Central Camera Co. (Photographic Headquarters since 1899), 230 W. Wabash Ave., Dept. H-182, Chicago, Illinois.

AMATEUR Photographers attention! Improve your hobby of picture taking and learn to make professional business. Write now for our 40-page book catalog and a sample copy of American Photography, enclosing 10 cents. Write: Southern States articles and pictures of the world's foremost writers and pictorialists. Camera House 141, 353 Newbury St., Boston, Mass.

OIL coloring photographs a fascinating hobby. Profitable business. Learn at home. Easy simplified method. Previous experience unnecessary. Send for free information and requirements. National Art School, 1315 Michigan, Dept. 174C, Chicago.

CASH! Spot cash for cameras, lenses, binoculars, movie or still, sound projectors. No trade-in. Profitable business. Write for prompt cash offer. Over 30 years of dependability insures honorable dealings. Business Camera Company, 179 West Madison Street, Chicago, Illinois.

MAKE money in photography. Learn quick- ly at home. Easy plan. Previous experience unnecessary. Common school education sufficient. Booklet, business plan free. American School of Photography, 1315 Michigan, Dept. 174C, Chicago.

GORGEOUS Girls! Nude photographs for Art Study! Post card size. Glossy finish, no two alike. \$2.00. Write for details. Paid. Cinema Artists Studios, Box 328-G, Hollywood, Calif.

CAMERA Repairing, Bellows made to order, sh-rs repaired. Bellows made to fit. \$2.00. Write for details. Universal Camera Co., Inc., B-1515 Belmont, Chicago.

CARTOONING, SIGN PAINTING, DRAWING AIDS

QUICK Landscape Painting Course \$3.00. List free. Sign Publishing Company, Farmington, Conn.

SENSATIONAL Cartoon Business, Markets, Hartman Studios, 2438 W. Lincoln, Neb.

CHALK TALK STUNTS

LAUGH producing program, \$1.00. Illustrated catalog. 10c. Cartoonist Balda, Oshkosh, Wis.

CHEMICALS & APPARATUS

CHEMISTRY Laboratory apparatus and chemicals for industrial, analytical, and experimental laboratories. Complete supply service for students taking correspondence school chemistry courses. Send 3c postage for free 44 page catalog. Dept. M59, Chemical Supply Co., 1176 Mt. Hope Ave., Rochester, N.Y.

WINN's new idea Home Laboratory Chem- ical Kits and apparatus outfits for home experimenting. Write for literature and retail supply catalogue. J. H. Winn Co., Dept. 611, 124 W. 23rd St., N.Y.

HANDBOOK for Chemical Experimenters. Hundreds of experiments; illustrated; 50c. Write for booklet. Reading Scientific Company, Reading, Pa.

FREE Catalog: Chemistry, Mineralogy, Biology, Optics, Tracey Laboratories, Evanston, Illinois. Special: Laboratory Manual, 275 pages, illustrated. Send 50c.

LABORATORY Spectroscope for chemical analysis \$2.50. McCutting Sons, Campbell, California.

LUMINOUS Paints will glow in dark. Six colors. Fairchild Chemical Co., 126 Liberty St., New York City 6.

FREE chemical catalogue. Enclose 3c Postage. Greenwood, 398 Broadway, New York.

288 PAGE Apparatus Catalog sent for 50c. 153 Page Chemical Catalog 25c. Laboratory Materials, 7317 Vincennes, Chicago.

DETECTIVES

DETECTIVE training—Secret Investigations —Easy method—Fingerprints. Booklet Free. International Detective System, Box 756-P, Jacksonville, Fla.

DETECTIVE Training Phillips Secret Service, 1917-C North Kenneth, Chicago, Ill.

DETECTIVES—Work home—Travel. Experience unnecessary. Write, Wagoner, P-125 West 82nd, New York.

DOGS, BIRDS, PETS

ST. BERNARD puppies, Champion sired beauties. Franklin Young, R3, Riverhead, Long Island, New York.

DRAFTING INSTRUMENTS

FREE catalog of drafting instruments and supplies. Gordon's, 162-PSB Madison, Chicago.

EDUCATIONAL & INSTRUCTION

PREPARE yourself now for a well paying radio position. Independent after the war. Obtain your FCC commercial radiotelephone and telegraph licenses through our home study courses, written for the man who has forgotten higher mathematics. An easily understood course. Moderate tuition fee. Write for particulars, American Radio Institute, 44 East 23rd Street, New York, N.Y.

MODERN machine tools such as Mills and Shapers easily and quickly built from Lewis plain or semi-chemical castings. Furnished complete with materials and detailed blueprints at a fraction of the cost of comparable finished tools. Widely used in war production. Send 10c to cover cost of mailing catalog describing 23 items. Lewis Machine Tool Co., Box 15, Station A, Dept. S-32, Los Angeles 31, California.

BED Turrets, Hex, Head Self Indexing, Cross Slides, Two Post; Lever Collet Chucks. For large A-1, California and South Bend Lathes. Quick deliveries. Thomas, 4153 West Ave. 40, Los Angeles 41, Calif.

STEEL beam trammels for draftsmen, engravers, mechanics. Circular Free. Clay Company, Box 92, Blythebourne Station, Brooklyn, N. Y.

FOR sale new and used reamer and milling cutters not catalogued. Furnish your list requirements for prices. Write P. O. Box 493, Flint, Michigan.

NEW calliper, direct reading, speeds up dimension work, cheap. Free illustrated circular catalogue, 811-H East 31st, Kansas City, Mo.

GRIND Drills Like Factory: Attachment for Bench Grinder. Cheap, Factory, 811 East 31st, Kansas City, Mo.

ATTACHMENT grinds, drills, factory accuracy, \$5.85 postpaid. Write, Clay Co., 327 N. California, Burbank, California.

BUILD Your own lathe grinder, castings, building instructions, \$2.50. Particulars, 100 Star Machine Co., Springfield, Ohio.

USED Lathes, Millers, Grinders, Shapers, Planer, Machine Service, Newfane, Vermont.

RECLAIM dull and broken grinds with Nut-All Drill Grinder. Circular free. Tractor-ite-Mfg. Co., Spirit Lake, Iowa.

TELESCOPE Gauges made to order, guaranteed. Morocco, 19148 Marx, Detroit.

MAGIC TRICKS, PUZZLES, JOKER NOVELTIES

1943 EDITION Douglas famous Catalog of 500 Tricks you can do! All the latest with cards, coins, thumbles, ball, and apparatus, books, illusions, 128 pages, only 10c. Douglas' Magicland, Dallas, Texas.

SURPRISE your pals. Your name (or theirs) in screaming headlines, front page Hollywood newspaper, 4 for 10c postpaid. Lefavor, Printer, Arrowhead Springs, San Bernardino, Calif.

HOLLYWOOD Special! Magicians button, catalog, ghost illusion and free trick for 25c. Magic Isle of Charles, Box 8685, Hollywood, Calif.

FREE, Magicians send for Catalogue. Bargain Lists latest Magic Tricks, Jokes, Puzzles, Novelties, Books, Magazines, Dean Smith, Box No. 18-PS, Monroe, Louisiana.

WORLD'S largest professional magic keeps you in touch with latest tricks. To receive mailings send 3c for 1943 catalog. Holdens, P.O. 42, New York.

MAGICIANS' Gambler's secrets exposed. Cards Dice, Punchboards, Slot Machine. Catalog 10c. Book Co., Box 671, St. Louis, Mo.

JOIN Magicians' Fraternity! Monthly magazine of tricks, magic, 10c. International Magicians, Mount Morris, Ill.

BOOKS, Cards; Novelties, Samples, Catalogue 10c. Eastern City, 330-SE Wells, Chicago.

LEARN Ventriiloquism, 3c stamp brings particulars. Maher, 1707 Cassgrain, Detroit 9, Michigan.

DOLLAR Magic Set Free with Professional Illustrated Catalog. 25c. 4482-PS Germania, Philadelphia.

HYPNOTIZE Anyone, Easily, Speedily! Simplified Course, \$5.00. Guaranteed! 2404N15, Philadelphia.

BE a Magician. Large professional magic catalog of latest tricks, 25c. Ireland, P.O. 109 North Dearborn, Chicago.

MANUFACTURING

MODELS, small lot manufacturing, metals, plastics, etc. Milburn, Burlington, Kentucky.

MILITARY INSIGNIA

EMBROIDERED Emblems for service men. Send 10c for sample worth 25c, price list; 10c for Insignia Guide. Hobbygild, 35A West 32nd Street, New York.

MILK GOATS

DAIRY Goat Journal, Dept. 366, Columbia, Mo. Monthly magazine crammed with latest information, 1 year, introductory 5-month subscription 25c.

MISCELLANEOUS

MEDICAL Laboratory Technicians in great demand. We train you in your spare time, in your own home. You can practice while studying. Write for catalogue. Hospital Technicians Institute, Box 973-S, Austin, Texas.

A THOUSAND Laughs—Uncle, Jackass Cigarette Dispenser. Hold 10 cigar slots. Simply press down—head down, tail rises—presto—out slips cigarette. Satisfaction guaranteed. Ship to C. O. D. for 98c plus small money order or \$1.00 with order. Sanimo Industries, Dept. PS-4, Spencer, Ind.

DEAFNESS, Why? Good hearing without mechanical aids. No drugs. Relieving deafness. Johnston, Sta. C, Vancouver, Canada.

WE buy, sell and trade anything of value, old or new—free lists. Can use agents to represent us. Estes, Box 158, St. Matthews Branch, Louisville, Ky.

DESCRIPTIVE Photos; 100 Addresses 25c. Hobby Humor 10c. Morrelle, 130 Nob St., Chicago.

RECEIVE mails, magazines, samples. Your name in numerous mailing lists 10c. Howard, 396 Broadway, New York.

MEXICAN Jumping beans—dozen 25c. American Products, 126 North Main, Tulsa, Oklahoma.

SNAPPY cartoon booklets, 7 for 50c. Torian's, 247 Chapel Street, Hampton, Va.

COIN changers \$3.50 postpaid. D. Seizman, 875 Thornhill, Cleveland 8, Ohio.

MODELS & MODEL SUPPLIES

SHIP model kits and fittings. Complete line Fisher model yacht equipment. All boats, ferries, Marine Motor, etc. Kits, fittings and blueprints at standard prices. Most complete stock in New England. S. J. Bliss & Co., Inc., 220 State St., Boston, Mass.

MOST complete illustrated Catalog—"O R O O" Model Railroad Parts ever published. Send 3c for mailing. Selly, 1377 Gates Ave., Dept. 608, Brooklyn, N. Y.

RAILWAY models, complete line informative catalogs. O Gauge 104 pages, 25c. HO 48 pages, 15c. Waitheers, 269 Erie, Milwaukee, Wisconsin.

SHIP Model and yacht supplies, complete large 64 page Catalogue, 1c. Wm. Wild, 150 E. 11th St., New York City.

MONEY MAKING OPPORTUNITIES

LEARN Metacscience. Remarkable drugless healing. No manipulation. No apparatus. Unbelievable simplicity and results. Inexpensive correspondence course. Write Metacscience, De Land, Florida.

STRENGTH alone is not enough to get you what you want! Read "If It's Wealth You Desire". Only \$1 postpaid. C. E. Seafast, 1000 Seafast Building, Educational Books, Dept. B, Homer, N. Y.

WORK for yourself. Operate special mail-order service selling money-making plans, formulas, courses, books. Sample stamp. Supreme, 858 East Sixth, South Boston, Mass.

OPERATE your own refrigeration repair business. Little capital required. 1120 Madison Avenue, New York. Free booklet. Mechanics School, Dept. S23, 4701 West Pico, Los Angeles.

EARN \$3.00 selling 10 boxes sensational new Christmas Deal. Sample prepaid 50c. Chas. Lake, 8930 164th, Jamaica 3, New York.

"EARN Extra Money At Home", Spare or Full Time. Free circular describes 127 Money Making Plans, Ideas, etc. Details stamp. Gofit Service, Alhambra, Calif.

NEED extra money? Let us show you how to make extra money in spare time at home, without personal selling. Plans, 5000 Trenton, Cleveland, Ohio.

NEW low priced lawn mower grinders, hand or power operated. Stamp appreciated. Anton Wellert, 142 Gaylord St., Binghamton 24, New York.

DETECTIVES Earn Big Money. Experience not necessary. Particulars, 1c. Wagner, P-125 West 86th, N. Y., N. Y.

EARN money evenings, copying and duplicating comic cartoons for advertisers. Comic-Ade, Argyle, Wisconsin.

OPPORTUNITIES Galore, giant mails 10c, sample mailing free. Harvey Teeple, (PS), Decatur, Ind.

MONUMENTS

MONUMENTS—Direct Low Prices, Freight paid, Guaranteed. Free Catalog and samples. Write Granite-Marble Factory, A49, Oneco, Florida.

MOTION PICTURE & SOUND EQUIPMENT

COMPLETE 16mm, 35mm sound subjects—perfect—\$5.75; 8—16—35MM. Films home—\$1.00. Complete Catalogue, sample film—10c. International-S, 2120 Strauss, Brooklyn, N. Y.

NEW Movie Films—Wholesale Free Catalogue! "Surprise" Samples, 10c. Superior, 126 Fourth, Paterson, N. J.

ESCAPADE at Dawn, 8mm, 50 ft., \$2.00; 16mm, 100 ft., \$4.00. Glamour films, samples, dime, Jenkins, 392, Elmira, N. Y.

LEARN Movie Projection, Management. Free catalog. Give age. Theatre School, Elmira, N. Y.

HOW I added sound to my 8mm projector. Information will be given for \$1.00. D. SARGENT, 3239 Fenton Avenue, Bronx, N. Y.

35MM SOUND features! Short! Technical color samples! 10c. Demsey, 1518 Stewart, Youngstown, Ohio.

SALE—rent—exchange—8-16mm movies. Send stamp for catalogue. Bailey Films, 1653 Chicago, Hollywood, California.

SEND stamp for 16mm, 8mm catalogue. Sterling's, 679 Northampton, Easton, Pa.

FREE Movie Catalog; sample film 10c. Goodwill Company, Jackson, Tennessee.

MOTORCYCLES, BICYCLES & SUPPLIES

MOTORCYCLE Manual—192 Page American "Questions-Answers" complete servicing information. Harley's, Indians, Hendersons, Servicycles, Villiers including war models, \$1.10. Modern Motorcyclist's Workshop, \$1.50. Modern Motorcyclist's Workshop, \$1.50. Modern Motorcyclist's Workshop, \$1.50. Modern Motorcyclist's Workshop, \$1.50.

Plans, drawings, specifications, instructions for building attractive Motor-Scooter complete. \$2.00. Motor Scooter Catalogs 10c. Clymer, 307 W. Pico, Los Angeles, Calif.

100 Miles Gallon! Motor-Scooters, Motorcycles, Whizzer Bicycle Engines, Midgert Automobiles, Gasoline Engines. No priority Necessary. Full information, prices, illustrations, catalog one dime. Clymer, 307 W. Pico, Los Angeles, Calif.

PLANS, Drawings, specifications, instructions for building attractive Motor-Scooter complete. \$2.00. Motor Scooter Catalogs 10c. Clymer, 307 W. Pico, Los Angeles, Calif.

BEAUTIFUL Recap Motor-Scooter Tire. No Priority Necessary. All sizes. Information catalog 10c. Clymer, 307 W. Pico, Los Angeles, Calif.

BUILD Electric Bicycle. No chains, gears, welding. Plans \$1. Klaus, 1369 Missouri St., Pittsburgh, Pa.

MUSIC, MUSICAL INSTRUMENTS

PIANISTS—Free booklet shows how you can make money. Includes 100 songs, Memorizing, Sightreading and Playing through Mental-Muscular Co-ordination. Quick results. No obligation. Broadwell Studios, New York.

SONGWRITERS! Send your poems for our offer and Free "Rhyming Dictionary". Phonograph Records made. Vanderbilt Music, 1000 Broadway, Box 112, Dept. WS, Coney Island, N. Y.

LEARN Popular Piano! Play hit songs in boogie-woogie style. Pianists, send dime for sample arrangement. Home-study folder free. Christensen Studios, 765 Kimball Hall, Chicago.

ROOT'S Pleasant Hours, Piano Instructor, 88 pages. Sold nearly a million. 75c postpaid. Satisfaction guaranteed. McKinley Publishers, 1900 East 55th St., Dept. 3396, Chicago.

SONGWRITERS! Write for Free Instructive Booklet Outlining Opportunities. Write Musical Corporation, Dept. 31, Salem, Indiana.

ACCORDIONS—60¢—Buy—Sell—Repair all makes. Metro, 43 North Albany, Chicago.

WANTED! Lyrics, melodies for songs. We arrange, publish, sell. Superior Songs Studios, Passaic, N. J.

PATENT ATTORNEYS

INVENTORS: Learn now—without obligation—how to protect and sell your invention. Secure the "Certificate of Invention" form for establishing date of your invention—and Free Book "Patent Guide for the Inventor", containing complete information about patent procedure and selling inventions; illustrating over 150 basic mechanical movements. Delay may be costly. For prompt, confidential service write—Harmon O'Brien—Harvey Jacobson, Registered Patent Attorneys, 32B-J Adams Building, Washington, D. C.

INVENTORS: Before disclosing your invention to anyone send for Free "Evidence of Conception!" "Schedule of Government and Attorney's Fees" and instructions. Sent free. Lancer, Alliance Building, 415 Bowen Building, Washington, D. C.

INVENTORS: Send for free copy my 72-page book on patents. Reasonable terms. Prompt attention. Confidential service. (L. F. Randolph, Dept. 340-A, Washington, D. C.)

"INVENTOR'S Guide" free, containing 100 mechanical movements, instructions about patenting, selling inventions. Frank B. Lederman, 154 Nassau St., New York.

PROTECT your invention through medium of my expert personal service. Preliminary information without obligation. Horace L. Beall, 902 F Street, N. W., Washington, D. C.

PATENTS

INVENTORS: Forethought manufacturers already planning post-war sale of new non-military products. If you have a useful invention, patented or unpatented, write to the Institute of American Inventors, Dept. 3-B, Washington, D. C.

PATENTS FOR SALE

POST-WAR priming will pay us! Investigate. Plastic compounds dispenser delivers uniformly, continuously. T. Pasanen, Franklin Mine, Michigan.

PERSONAL

ATTRACT success, health, companionship, happiness through Ontology. Discover your real self. Learn to pray metaphysically. Solve your problems through scientific mind power. Write today for free 24-page booklet. My change your life. My pattern. Alexander Keene, D-9, Sedalia, Missouri.

LEARN mental telepathy. Get the things you want the telepathic way quickly, easily, with the power of your mind. Write quick for Free Booklet, or send \$1. for 5 weekly lessons plus personal instruction. Allan Teague, 2466 Pacific Guid, Box 5822, Harrisburg, Pa.

PSORIASIS sufferers: Pixacol has brought relief when everything else failed. Caution: use only as directed. Apply externally. Cures quickly and conveniently. Try required \$1. bottle without investing a cent! Write: Pixacol Lab., Box 1298, Cleveland, Ohio.

12 USED Dresses, \$1.00 plus postage. Free family catalogue. If not satisfied, return package prepaid and your money will be refunded. Send \$1.00 to World Mail Order Co., Dept. 8, 372 Thaxford Ave., Brooklyn, N. Y.

WE Don't Die! Facts Speak! Amazing Demonstration. Proofs backed by World Famous Scientists. "Atheism's Death" 16-page pamphlet of facts. Dr. Otto Kaemmerer, 3801 Sulphur, St. Louis, Mo.

GIVE yourself the "breaks". Use Auto-Hypnosis, new, easy way to success. Free information. Victor, 675 Elliot, Denver 4, Colorado.

MEN, why feel old? Amazing Hindu secret keeps you youthful, lusty, vigorous. Free details. Hindu, 675 Elliot, Denver 4, Colorado.

BUY wholesale: sell razor blades; tooth paste; shaving cream; personal care products; etc. Free catalog. Keystone, 72 Fifth Avenue, New York, New York.

EXTERMINATE Axis Rats! No experience necessary: pays well. Put your rat in War Bonds and Stamps to buy the powder to powder these rats!

SENSATIONAL, Thrilling. Mexican-Cuban, art pictures, books, miscellaneous. Samples, lists, etc. Jordan, 135-L Brighton St., Boston.

SONGWRITERS, write for free booklet, Profit Sharing Plan, Allied Music, Dept. 58, 204 East Fifth, Cincinnati, Ohio.

ADVICE, Health, Business, Letters #1. Joseph Erlich, 106 Australas Ave., San Jose, Calif.

HYPNOTISM, Complete 20 Method Course, Western Institute Hypnotism, D-1619, Palestine, Ill.

QUALITY Photostamps from any snapshots \$1.00 per 100. 82-29 60th Road, Elmhurst, N. Y.

LONELY? Read "Love Diary"—deluxe, illustrated, 45.00. Sample—25c. Paul Terjan, Publisher, Palisades Park, N. Y.

HOW To Become Popular, \$1.00 particulars. Laura Saebø, Anchorage, Alaska.

PHOTO FINISHING

IMMEDIATE Service! Pictures returned same day order received. Smashing Low Price! Free! Sixteen guaranteed Deck-Edge Vexol prints from roll, 25c. Or one colored or two plain enlargements Free with 8 Deck-Edge prints. 25c. 16 reprints from negative 25c. Candid Rolle developed, Magic-Eye Timed, Vapored, and enlarged to 3 x 4 on Deck-Edge Vexol Paper—50c. 16 reprints 18 exp. 60c. 16 exp. No 127, 50c; 8 exp. Bantam, 25c. Reprints, 3 x 4, 3c each. We have new, perfect 35mm film! Low prices. Free Mail! Details on request. American Studios, Dept. 607, LaCrosse, Wis.

YOUR choice—16 sparkling prints; or 8 over-size prints (deck-edge if desired); or 3 prints and two extra time enlargements. Only 25c. Dept. 200, May's Photo, LaCrosse, Wisconsin.

BEAUTIFUL 4 x 6 pictures 3½c each, from 116 and 120 negatives, 3¼ x 4½ from all other sizes. All work guaranteed. Overnight service. Roll developed and 8 pictures from 12½ pictures 45c. Roll 16 pictures 60c. Enlargements on double weight portrait paper 5 x 7—30c, 8 x 10—50c. Copies from any pictures 15c. Pacific Photo Service, Box 666, San Francisco, Calif.

BIGGEST \$1.00 value in 35MM finishing today. 36 exposure fine grain 3¼x4½ enlargements; decked, embossed margin. 36 exposure 35mm exposures. Roll 16 pictures exposure splits 55c. Free mailers, 8 exposure rolls in beautiful, decked contact finish with embossed wide margin. 36c. Mailbag Film Service, Box 54404, Chicago.

FINE Finishing Specials 35c. Eight exposure rolls developed with two prints of each or one larger print of each negative. Genuine nationally known Moenone Enamel finish. Superior quality since 1898. Moen Photo Service, 200 Moen Bldg., LaCrosse, Wis.

OIL coloring photographs a fascinating and profitable business. Learn at home. Easy simplified method. Previous experience unnecessary. Send for free information and requirements. National Art School, 1315 Michigan, Dept. 172C, Chicago.

CHERISHED photographs or snapshots enlarged. We will make a life-like 8 x 10 print of any picture. Original may be old and any size. For Free estimate and details, send picture which we return. Grand Photo Studio, Dept. O-1, 2309 Grand Concourse, Bronx, N. Y.

FREE Your favorite star's autographed photo with trial eight exposure roll developed, including 16 prints—25c. Hollywood Photo Service, 107 Dewey St., Newark, N. J.

FILMS Scientifically developed, plus 8 beautiful 4 x 6 enlargements, 30c complete. Photo Service, 107 Dewey St., Newark, N. J.

BEAUTIFUL enlargement from each picture on roll, 25c. Cut Rate Photos, Dept. A-6, Janesville, Wisconsin.

NEWS Photographers—"Press Identification" Catalogues, Press Supplies, 1934-S. E. Washington, D. C.

REPRINTS 16 for 25c; 75 for \$1.00. Eschman Studios, Box 331H, Perth Amboy, N. J.

PRINTING, MULTIGRAPHING, MIMEOGRAPHING, LABELS

DISTINCTIVE Printing—Business Forms, Letterheads, Stationery, Folders, etc. Get our information on your needs, free copy service, counsel, samples. United Enterprises, Dept. PS-2, Box 93, Downingtown, Pa.

5 8½ x 11 Hammermill Letterheads and 75 Whitewave Envelopes, \$1.00 postpaid. Bennette, 907 West Roosevelt, Phila.

CLASSY printing economically produced. Quick deliveries. Samples, Sicoan, 6348 Wilcox, St. Louis.

PRINTING and labels all kinds, samples. Printrite, 39 Banks, Asheville, N. C.

1000 6 x 9 CIRCULARS for \$1. Armand Cartier, 695 North, Pittsfield, Mass.

PRINTING OUTFITS & SUPPLIES

PRINTING Outfits and Supplies. Send stamp for details or dime for complete illustrated supply book. Kelsey, Inc., W-8, Meriden, Conn.

PRINT at home. 10c will bring a complete catalog of presses, type and supplies. P. Peifer Company, 4 Columbia St., Newark, N. J.

INEXPENSIVE 6x9 Printing Press, Details Free. Novelty Shop, Downsview, La.

PRINTING Presses, Type, Supplies. Lists 3c. Turnbaugh Service, Louisville, Pa.

PROFITABLE OCCUPATIONS

MECHANICALLY Inclined Men—Own and operate general Appliance Repair shop. Complete, illustrated course shows you how. Welding, Refrigeration, Motor repair. How to get business, etc., all phases covered. Free literature, Christy Supply Dept. 1032, 2835 N. Central Ave., Chicago.

LOCKSMITHING Course—Practical inexpensive lessons for handy men. Just one hour's pick locks. Free literature, masterkeys. Satisfaction guaranteed. Send for Free Details. Nelson Co., 321 South Wabash, Dept. 709, Chicago.

RAISE Highly-Profitable Angora Rabbits. Wool brings \$6.50 per pound. Plant markets. Send 25c for Literature, Instructions, Prices. Wm. White Angoras, Crawfordville, Va.

"RAISE Earthworms for Profit." Information free. Bureau of Zoological Research, 106-A Broadway, Peoria, Ill.

\$5000 From Half Acre! Growing Ginseng. Fall Planting, Seed, contact supplied. Particulars 10c. Associated Growers, Dept. 12, St. Norbert, Manitoba.

\$40.00 WEEKLY Made growing mushrooms, Fresh, Dried, Dominion Patent 331583, free spawn, North American, 169Y Yonge, Toronto, Canada.

RADIOS, SUPPLIES & INSTRUCTION

RADIO Service men and experimenters send for our giant radio catalogue. Save dollars. United Radio Co., (1000-V), Newark, N. J.

REVISED Plans 18 Crystal Sets (SW record 5300 miles), with "Radiobuilder"—25c. Laboratories, 1406-T 77th Avenue, Oakdale, Cal.

RADIO Servicing hints; diagrams, circuit explanations. Booklet, 10c. Supreme Publications, 328 South Jefferson, Chicago.

CRYSTAL Radio Experimenters. Write Hewlett, 29 E. 39th, New York.

RAKE COINS

FREE! Foreign coin, banknote and Coin Collectors' Illustrated Catalog to approval service applicants. Send 3c postage. Up to \$20 cash paid for Indian head cents. All dates wanted. Buying list 10c. Tatham, Springfield, Mass.

WE buy Indian Cents, Lincoln Cents. Old Rare coins wanted. Highest prices paid. Send 10c today for new 1943 price Catalogue of all U. S. Coins, American Rare Coin Co., Dept. 4, Transportation Bldg., Chicago.

SAN FRANCISCO Mint Lincoln Cents, 10 different 25c, 10 different Indian, 25c. New Silver Dollar \$1.50. Big illustrated coin book 50c. 1943s silver nickel and quarter 50c. Coins, Box 77, Alameda, Calif.

COMMEMORATIVE \$1½. Cleveland, Lord Island, York, Eighth Texas, Kentucky, \$1.50 each. Large Illustrated Catalogue 10c. Norman Shultz, Salt Lake, Utah.

COMPLETE Catalogue of all U. S. coins cost \$1.00. 75 illustrations. 3500 Quotations. Price 10c. James Randall, 341 South Dearborn, Chicago.

WE purchase all Indian head pennies. Complete catalogue 10c. Waltman, 398 Broadway, New York.

10 IND. Head cents, different dates, also cents, 10c. Schultz, 1053½ Richmond, Cincinnati, Ohio.

HOBBY News with large premium 25c a year. Keim, Box 103, Sta. A, Flushing, N. Y.

FIVE Foreign Bins 25c. Twenty-five Different \$1. Beffel, Box 37, Ottawa, Ill.

REFRIGERATION

REPAIR Refrigerators. Complete Manual, \$1.00. Supreme Publications, 328 South Jefferson, Chicago.

RUBBER STAMPS

3 LINES, cushioned, indexed, 35c. 500 Printed statements or Noteheads \$1.50 postpaid. Printrite, Wauwatosa, Wis.

CUSHIONED, 3 lines 45c, signatures \$1.75. Federich Mfg., East Pittsburgh, Pa.

ONE line 15c, 2 lines 25c, 3 lines 35c. Excello, Box 500, Shreveport, Louisiana.

SONGWRITERS

SONGWRITERS! Send your poems for our offer and Free "Rhyming Dictionary". Phonograph Records, 10c. Music Studios, Box 112, Dept. WT, Coney Island, N. Y.

SONGWRITERS: Our complete service includes melodies without charge, song recordings, presentation, radio publishing, Cinema Song Co., Box 670B-1, Beverly Hills, Calif.

SONGWRITERS—Send Poem For Immediate Examination and Free Rhyming Dictionary. Richard Brothers, 46 Woods Building, Chicago.

POEMS Wanted For Musical Setting. Send poem for immediate consideration. Five Star Music Masters, 646 Beacon Building, Boston.

SONG Poems Wanted: Write for Free Instructive Booklet, Outlining Opportunities in Music Corporation, Dept. 26, Salem, Indiana.

SONGWRITERS—Your poem arranged to music, copyrighted, printed, published and distributed. Puritan Publishing Co., 343 S. Dearborn St., Chicago.

SONG Poems Wanted. We offer services noted Hollywood studio writer-arranger. Excellent offer. Hollywood Melodies, Box 2168C, Hollywood, Calif.

GOOD Music composed to good words. Reginald Belcher, Chatham, New Jersey. Established 1910.

SONGWRITERS: Collaborate with writer "Goodnight Sweetheart" and other sm. hits. Songs recorded, exploited. Songland, Box 590C, Beverly Hills, Calif.

SONGWRITERS: We offer complete service. Melody writing, recording, radio broadcast, promotion. Screen Records, Box 1247D, Hollywood, Calif.

SONGWRITERS: Write for free booklet, Front Sharing Plan, Allied Music Company, 204 East Fourth, Cincinnati, Ohio.

SONGWRITERS: Write today. Free booklet, plan. Song Service, 331-J West 46th, N.Y.

SONGWRITERS! Amazing, convincing composition. Hibbler, C15, 2157 N. Avera, Chicago.

SONGWRITERS, Melodies Written to Poems. Send Poems, "Popular Songwriters", Paines Creek, Pa.

SONGWRITERS: Free Book. Send Poems. Variety, Dept. 3, Salem, Indiana.

SPORTING GOODS, GUNS, FISHING TACKLE, ARCHERY

SWAP Guns and Ammunition with Klein's—or get Cash. We pay More—you pay Less because we're always known, biggest traders. Thousands upon thousands of new and used Guns from \$5—up to the finest. All models, gauges, calibers, makes: Winchester, Remington, Colt, Savage, Smith & Wesson, etc. We also buy, sell or trade Ammunition, Fishing Tackle, Outboards, Golf Equipment, Cinctels, Cameras, Watches. Describe fully what you have to trade or sell for cash. Special! Ferrine "Magic Circle" sight for shotguns. (State model, gauge, plain or ribbed barrel.) Postpaid \$1. "Money Back Guarantee" backed by 58 years' fair dealing. Free Catalogue guaranteed. Roger Catledge, thousands of "Hard-to-get" items; send time (refunded with first order) to cover handling costs. Klein's, 508 South Halsted, Chicago.

BOWS—Arrows for Recreation—Hunting—Fishing. Beautiful Archery instruction book, 80 pages, 80 illus. for camp and lake. Illustrated catalogue Free. Archery, 617 South State, Chicago.

GUNSMITHING Readily learned at home. Earn extra money repairing neighbors' firearms. Free catalog 22 firearms and gunsmithing textbooks. Samworth, Plantersville, South Carolina.

USED Guns, Binoculars, bought, traded, sold. Ammunition bought. Highest Cash Prices Paid. Stoeger Arms Corp., 507 Fifth Ave., New York, N.Y.

SEND for free illustrated catalog of Lawrence leather belts, holsters, gun cases and other sporting equipment. George Lawrence Company, Portland, Oregon.

76 ANTIQUE Firearms, Swords, Cartridges, Rifle, 112B West Blodgett St., (Photographs of Most) Heike, Wenona, Ill.

GUN Smithing antique and modern. Joseph Gravitt, 112B West Blodgett St., Marshfield, Wisconsin.

ARCHERY Equipment: Catalogue Free. Mid-West Archery, 2209-D East 75th, Chicago.

USED guns, bought, sold, exchanged. List camp. Howe, Coopers Mills, Maine.

SEND 10c for list 100 used Guns, Frayser's, Willmar, Minn.

STAMP COLLECTING

WOW! \$100 Worth of Fun for only 10c! 500 Foreign Stamps, unsorted and unposted (mostly 1c), sent to you and received from the church missions and other sources. Africa, So. America, Australia, China, Philippines, Dutch Indies, and other countries are represented. Includes a few commemoratives, airmails, and stamps cataloguing up to 25c or more each! The Biggest Package of Fun for Stamp Collectors you might find something really valuable! Price only 10c to serious approval applicants! Money back if not satisfied. Jamestown Stamp Co., Dept. No. 5, Jamestown, New York.

POSITIVELY Greatest Free offer—Latest Scott's International 84-100 Stamp Album—covering entire World, contains 36,000 illustrated, descriptive spaces; Scott's 1943 Standard \$4.00. Catalogues "Philately's Encyclopedia"—also available. Free catalogs for Foreign Approvals becoming customers. Bargain Stamp Service, Palm Springs, California.

VICTORY Catalog Free: Includes stamps from Tanganyika—British Chaguan Islands—Animal—Scarce Babyhead—Continental Early View—New Air Mail—Map Stamps—with Big Catalogue—all free—send 5c for postage. Gray Stamp Company, Dept. PR, Toronto, Canada.

SUPER-WONDER Packet offered containing stamps from Afghanistan, (tobong), Costa Rica (triangle), Saar (collier), Cydon (harbor), Iraq (late king), Manchukuo (scenery), Honduras (seal). This entire packet for only 3c to approval applicants. Kent Stamp Company, G. F. O. Box 87 (214), Brooklyn, N.Y.

MACARTHUR Commemorative Stamp from Australia—Joe-China "Bomber" packet, new Cuba "V-for-Victory" stamps; scarce 1.00 Abyssinia; also packet fine stamps from Far East War zones. Total catalogue price \$1.25. Everything only 10c to serious approval applicants! Methuen Stamp Service, Dept. 18B, Lawrence, Mass.

500 UNITED STATES for 10c! 500 U.S.A.—absolutely unprinted and uncanceled as received from church Missions. Many varieties, including commemoratives, airmails, high values up to \$5.00 approval applicants! Price only 10c to approval applicants! Money back if not delighted. Swan Stamp Co., Dept. 69A, Dunirk, N.Y.

WORLD'S Smallest Airmail—Diamond and Triangle Stamps. Free Stamp Magazine, also magnifier to study your stamps, with large collection of stamps from scarce countries. A. A. Bargain, 12340 Highway 1, Capital Stamp, Dept. 10, Little Rock, Arkansas.

\$1.00 (Cat. Price) for 1c! Two mint U.S.A. 100c. "Queen of countries" packet (Djibouti, Manchuria, etc.); scarce set Russia, cat. 75c. Everything for only one cent! Approval applicants! Universal Stamp Company, Box 418, Calais, Maine.

SMOKY Mountain commemorative sheet, largest U. S. stamp issued, and 33 U. S. including commemoratives, airmail revenue, etc. Catalog 75c. To approval applicants for 5c. Curban Stamp Company, Dept. C. Gloucester, Mass.

FINE Approvals, freshly mounted. Fast, personal service. Tell me what you prefer and I'll send their stamps. Milton Skinner, 345 East Ocean, Long Beach, Calif.

BRITISH Empire Collection! Burma, Cyprus, Gwalior, Sarawak, Tasmania. Also 50 other British. Only 5c with Pictorial and Commemorative Approvals. Lyman, 97 Nassau, New York City.

15TH Century U. S. Commems., Civil War Revenues, Battleships, \$5 & \$10 Stamps Free to U. S. Approval Applicants. Metroplan Stamps, 198-G Broadway, New York.

118 DIFFERENT stamps including Commemorative, Charities, Airmail, sets, etc. for only 10c. Approvals, War Collectors. Bargain Stamp Company, Milwaukee S-3, Wis.

FREE—Canadian Sets, Royal Visit, George VI, George V, Coronation, Jubilee, Others, etc. approval applicants, Ensign, Box 118-P, So. Orange, N.J.

FREE! Complete "United States" stamp catalog with 1,000 illustrations! Send 3c for postage. Harris & Co., 99 Transit Building, Boston, Mass.

SOLOMON Islands, Seychelles, Nejd, Caymans, Manchukuo, Brunei. Everything 3c with approvals, Viking, 130 (P) Clinton St., Brooklyn, N.Y.

FREE—Your choice of any 10 stamps from any first class U. S. Approval selection. Illustrated list included. Cosmopolitan Stamp Company, 1457 Broadway, Dept. 6P, N.Y.C.

205 DIFFERENT stamps including Haiti, Johore, Perak, Selangor, Triangle, only 10c to approval applicants. Free Catalogue, C. 4647 Kenmore, Chicago, Dept. S6.

79 DIFFERENT including Tunisia, Australia, Indo-China, 5c approval applicants, Ransom, 1333 Pontiac, Ann Arbor, Mich.

SPECIAL—Airmails—23 different, including Zeppelin, Triangles, Latin-America, etc., 5c with approvals, Continental Stamp Co., Dept. C, Sandy Hook, Conn.

UNITED STATES approvals complete covering the quality. Free Catalogue, Seminole Stamp, Box 436, Coconut Grove, Florida.

WANTED: 130,000,000 Bondholders to do their share in stamping out the Axis. Remember your pledge and "Keep on buying to keep 'em flying."

MEXICO Census Commemorative Set, Free with approvals. Paddon Stamps, 1717-S Idaho, Toledo, Ohio.

U. S. POSTAGE Due Set. ½ to \$5.00. Philatelic Exchange, 413 Columbia, Irvington 11, New Jersey.

FREE Stamps. Write for approvals and details. Armstrong, 40 Jeanette, Youngstown, Ohio.

55 DIFFERENT United States 5c with Approvals, Bookman, Box 145-P, Maplewood, N.J.

150 DIFFERENT with triangles, airmails, commemoratives, 10c to approval applicants. Knowles, Box 432, Baltimore, Maryland.

200! Afghanistan, Siberia, banana airpost, etc.—3c with approvals! Saxon, Valley Stream, N.Y.

FREE!!! British Empire Packet. Postage 3c. Williams, 601 Archerbridge, Baycity, Mich.

FREE! Western Hemisphere Packet. Postage 3c. Owens, 801 Welshbridge, Baycity, Mich.

FREE! Pony Express set (facsimiles). Postage 3c. Roberts, 401 Shearbridge, Baycity, Mich.

FREE to approval applicants 25 different stamps. Dormers Stamp Co., Lenox, Mass.

JUMBO foreign approvals. Selection of 250 stamps. Beaumont Stamp Exchange, 2667 McCaddin, Beaumont, Texas.

U. S. 50 Different 5c to Approval Applicants. Neumann Co., 6728 W. Finkler Pl., Milwaukee 14, Wisconsin.

A \$2.00 stamp plus 50 different, 3c with approvals. O. Knopp, Box 1381, Bristol, Conn.

FREE! World wide packet; Approvals. Krutner, 14 S. Sedgewick, Wichita, Kansas.

200 DIFFERENT 25c, Cat. \$4.04, approvals. Burtis, Brown A, Lafayette, N. J.

50 FREE, pictorial etc., stamp dictionary, list. Burtis, Brown A, Lafayette, N. J.

PENNY Approvals that satisfy. Neil Gronberg, Box 5415, Philadelphia 43, Penn.

1000 MIXED U. S. Old and New 25c, 2 lbs. \$1.00. Weatherby, Troy, Ohio.

300 STAMPS—10c to approval applicants. Fair, 7800 Bristow, Oklahoma City.

MODERATE Cost Approvals. Reference. Wilson, 2999 East Blvd., Cleveland, Ohio.

UNITED STATES stamps on approval. Large stock. Box 488A, Minneapolis.

400 DIFFERENT stamps \$1.00. No approvals. N. Greenstreet, Port Angeles, Wash.

TOBACCO—PIPES

IMPORTED Briar Pipes. No putty, plugs or clay flimsy. Guaranteed Genuine Imported Virgin Briar. Excellent quality. Only \$1.75. Send for free catalog and trial offer. Sidney Ram, 59 West Montross, 24, Chicago.

FREE To Pipe Smokers—For a new pipe smoking thrill and experience, tell us your brand of tobacco and get Free package MARY MASTY, Green River, Vermont. Write today. Pete Moberly, Box 964, Owensboro, Ky.

TRAPPING

FOXES, Nine in one day. Trap all furbearers. Particulars Free. Guaranteed. White-Estabrook, Sherburne, Vermont.

WANTED—MISCELLANEOUS

WANTED, 1930, V-16 Cadillac. Convertible sedan or cabriolet. Must be in good condition. Dix Griemser, Lakemills, Wis.

ACCORDION—any condition. Give description, price. Chanton, 600 Blue Island, Ill.

OUTBOARD Motors, any condition. Write for cash price. Asa Gallupe, Fort Fairfield, Maine.

CASH for used optical, mechanical, scientific instruments. Gordon's, 182-BB Madison, Chicago.

MERCURY (Quicksilver) we pay \$1.50 per pound. Western Metal Co., Bloomington, Illinois.

WELDING, SOLDERING

NEW model electric welder 110 volt AC-DC—welds all instruments, easy to use, 10 directions. Complete with power unit, flame and metallic arc attachments, carbons, fluxes, rods, mask all for \$19.95—Used by the Navy, Marine, Navy, Navy Mfg. Co., 195-A Center St., New York City.

BUILD d.c. arc welder without rewinding armature. Plans \$1.00 each, 25 to 600 amperes from 1/2" to 1/4" diameter. Light port generator, 1/2" to 1/4" diameter. Write to Welders Club, WB-3432 M-Mart, Chicago 54.

FORMULAS: White metal rod (Welds die-cast parts). All purpose brazing flux. Arc welding rod coating. All three, \$1.00. Philatelic Exchange, 413 Columbia, Irvington 11, New Jersey.

WELD, Out, Braze with gasoline! New discovery. Make your own touch. Instructions one American dollar. Matthews Mfg. Co., Calgary, Canada.



What goes on under a Nazi pilot's cap?

PUT YOURSELF IN HIS PLACE . . . in his cockpit climbing swiftly away from an Axis airfield into a pitch-black night . . . bomb racks loaded . . . heading for Yank-held territory.

How would your mind work (under a Nazi bonnet), if you knew Radar's sleepless, X-ray "eyes" were waiting up to greet you . . . on warships, airfields, and lookout posts of the United Nations' forces?

What would you be thinking . . . knowing that Radar was robbing you of "surprise", the attacker's one tactical advantage . . . detecting you as much as 130 miles from your target? *Always* watching you . . . in storm, clouds, and fog . . . five miles up or skimming the waves! . . . *marking you for ambush and destruction!*

When the flak whams accurately through the clouds to rip jagged wing holes; when you meet night fighters who need no flame from your exhausts for true aiming, wouldn't you momentarily doubt the infallibility of the "master race"?

Wouldn't you nurse a scowling respect for American ingenuity? For Radar was developed in the United States . . . pretty much the product of Navy and Army research laboratories who weren't as unprepared as you thought.

And shouldn't it occur to you that a fellow can't win when he's fighting against a nation with the inventiveness and resources to produce weapons like this?

Westinghouse Electric & Manufacturing Company, Pittsburgh, Pennsylvania.

Westinghouse was making Radar 18 months before Pearl Harbor. Since then, Westinghouse production of radio communications equipment, including Radar, has increased 41 times!

Westinghouse

PLANTS IN 25 CITIES . . . OFFICES EVERYWHERE

Famous dates in the history of Radar



1922. Naval Laboratory, Anacostia, D. C. Dr. A. Hoyt Taylor and Leo C. Young, observing that radio signals were reflected by passing ships, saw in it a means of detecting enemy vessels in darkness and fog. This was the birth of Radar!




1937. Bloomfield, N. J. Westinghouse developed the key electronic tube for the U. S. Army's first Radar equipment used to detect aircraft. Radar focuses invisible, ultra-high-frequency waves traveling at 186,000 miles per second.



1941. Pearl Harbor, T. H. Approaching Jap bombers were detected by a Westinghouse-made Radar when 132 miles distant. Because a flight of American planes was expected, no warning was sounded. Today, on every front, Radar has revolutionized naval and air battle tactics . . . multiplied a hundredfold the range of human vision.

Can We Crack Hitler's Defenses?



HOW *Fort Busters* BLAST A PATH FOR INVASION

The Axis European fortifications may be a hard nut to crack, but our Army demolition men have the answer in TNT, flame, and courage.

By JACK O'BRINE

Drawings by B. G. SEIELSTAD

AS THE spearhead of invasion rips into the enemy's coastal defense line, the fort busters have their day. For these newest, boldest Army specialists must smash the greatest of all military obstacles—the shell-belching strongholds of cold steel and concrete that guard city approaches and stud countrysides in deadly, defiant patterns of defense. To reach their objectives, these demolition wizards of the combat engineers worm their way under enemy fire, slashing through barbed-wire entanglements, blasting tank traps, and ridding their path of treacherous, concealed land mines. Their chief equipment: TNT, flame throwers, and courage.

When the fort busters begin to move, you can be sure the enemy is in for a bad time. Their "go" sign is a combined assault in which the region is [\(Continued on page 52\)](#)



MOBILE ARTILLERY AT 1,000-YD. RANGE CONCENTRATES FIRE ON EMBRASURE OF PILLBOX TO PROTECT ASSAULT TROOPS

BULLDOZER SCRAPES A ROADWAY ACROSS TANK TRAP—A PATH IS BLASTED THROUGH TANK BARRIER AND WIRE ENTANGLEMENTS FOR MECHANIZED EQUIPMENT

GAP BLASTED IN WIRE ENTANGLEMENTS

SATCHEL CHARGE

RIFLEMEN KEEP UP CONSTANT FIRE ON PILLBOX SO ASSAULT CREW CAN MOVE FORWARD

LIQUID-FIRE MAN WAITS FOR ARTILLERY BARRAGE TO BE LIFTED TO CONTINUE ATTACK

POLE CHARGE

MEN APPROACH ON BLIND SIDE AS FAR AS POSSIBLE



BANGALORE TORPEDO
PUSHED INTO PLACE
TO BLAST OUT WIRE


CONCENTRATED FIRE OF
ARTILLERY AND RIFLEMEN
CAUSES GUNNERS IN
PILLBOX TO KEEP PORTS
CLOSED (BUTTONED UP)
PREVENTING RETURN FIRE

SQUAD LEADER
SIGNALS ARTILLERY
WITH VERY PISTOL
WHEN READY TO
CLOSE IN


and Clear the Way for Mechanized Equipment and the Supporting Infantry



DRAGON'S TEETH are blocks of steel and concrete set in jagged rows to stop attacking tanks



TANK BLOCKADES, with shoofs of steel firmly braced against approach, also ring Nazi defenses



TETRAHEDRONS, pyramidlike skeletons of steel, are scattered freely in the path of attackers



"JACKS" are giant versions of the pieces used in the children's game. They make trouble for tanks

pummeled by heavy artillery and aerial bombardment. This has a triple purpose: to neutralize enemy fire, to strip the fortifications of camouflage, and to open in the terrain places of concealment for the attack-

of several men are the big cylindrical tanks of flame throwers. Others carry six-foot sections of pipe loaded with TNT. Used singly or screwed together to a length of as much as 200 feet, these become the

ers. Experience has proved that well-built bunkers, pillboxes, and blockhouses can withstand a terrific pounding. So actual damage is likely to be small.

Soon this aero-artillery prelude clears the way for use of the direct-fire guns, the 155's, the 105's, the three-inchers, the 75's, and the 37's. As the demolition squad slithers forward, these mobile fieldpieces open up and begin slamming steel and explosives at the embasures. Bunker crews must close steel doors to prevent serious damage. This reduces enemy machine-gun fire to a minimum, and the engineers increase their pace, now and again leaping up from their belly crawl and running a few yards.

It's a strange task force. Uniforms are nowhere in evidence. Camouflaged coveralls speckle the ground. Weapons are chosen for the particular job in hand. On the backs

"LANDSCAPING" by German military engineers removes natural features that would shield attackers. Upper picture shows how a field gun could be sheltered from direct fire by a small hill. Below, how the same terrain would look after landscapers did their work, with all approaches fully covered by the fart's guns





All around Hitler's Europe, frowning guns face seaward in readiness for Allied landings. These Italian defenses, built into the face of a cliff, guard a section of the Mediterranean front. Beyond the coastal area, invaders will encounter deep belts of fortifications such as the famous West Wall of Germany

famous bangalore torpedoes, so devastating to wire entanglements. A few men carry grappling hooks to explode booby traps and antipersonnel mines by the simple expedient of tossing them ahead and pulling them back to catch trip wires. Of utmost importance are the soldiers with charges of TNT slung around their necks in satchels, carried in steel containers, or on long poles for shoving into bunker portholes. Most of the men lug hand grenades and one or two have smoke grenades. Only a handful carry rifles, but close by, protecting the advance, assault infantry bangs away with Garands.

In the vanguard at the outset are soldiers with grappling hooks. They clear the way for safe passage across the fields. When the crew reaches the inevitable ring of wire entanglements, the bangalore boys take over and make short work of that obstacle with a deafening blast. The explosion also destroys antitank mines within three feet of either side.


Thus the first real break-through occurs, and now the attackers are covered even more closely by high-velocity guns, including those mounted on tanks, that roll up to within 1,000 yards of the target. At this juncture, the heavy artillery to the rear raises its lobbing fire to enemy emplacements beyond those under attack.

Direct fire screams over the heads of the advancing fort busters, who now are ap-

proaching their objective. The men with the 70-pound flame-thrower tanks on their backs, copper nozzles in hands, edge into the lead. Their movements are agile, despite their load. They know the tricks of their trade. When they run and fall, they land in a rolling movement that eases the tanks to the ground. Otherwise they might break their backs. They roll over to a crouch before rising.

In the home stretch, all the men crawl forward till the target looms only a stone's throw ahead. Here the leader (a corporal commands each detachment) lets fly with a signal rocket. There's a final burst of direct fire, in the last salvo of which is a smoke shell, indicating the shift of the bombardment to adjoining bunkers. Now is the time for demolition. Into action go the bazookas, those weird tossers of ultrahigh explosives. Their projectiles smash at the embrasures in ear-rending blasts. At 20 yards, the flame throwers begin spouting long, roaring jets of burning oil and gas that blanket the bunker in a mass of fire.

The instant the flame throwers zip off, in rush the blasters with TNT. They explode charges at the bunker doors with a delayed-action fuse that barely gives them time to run back a few paces and throw themselves to the ground. Timing is geared to a split second. No sooner does one charge go off than another *(Continued on page 202)*



When the signal is given, the enslaved peoples of Europe will spring to action everywhere. The compact, fast-firing, easy-to-operate Sten gun will kill many Nazis behind the lines while the Allied armies fight on the newly opened fronts

Sten Gun To Be Forerunner

THOUSANDS WILL BE PARACHUTED TO GUERRILLAS

A HUNK of pipe—with a door spring in it," is the apt description given the new British Sten submachine gun, which soon may be plummeting from the skies over Europe into the eager arms of Frenchmen,

Poles, Czechs, and others who want to fight their way out of slavery.

Faced with the problem of producing in quantities a gun simple enough to be operated by the untrained peasants who will become Europe's new guerrilla fighters, British ordnance experts threw out all previous notions of armament making and came up with this gun (P.S.M., Sept. '42, p. 65; Jan. '43, p. 131) that made orthodox military thinkers gasp. But even the skeptics gave in when they saw the ugly duckling in action. Capable of firing 500 to 550 rounds a minute, this sturdy, six-pound package of dynamite can be operated by a child. It doesn't even require oiling. It has



Sighted from the shoulder or shot freehand from the hip, the gun has a 32-round magazine and fires 500-550 rounds a minute. It is easily dismantled for convenient carrying



British paratroopers also tote the Sten gun. When dropped behind enemy lines, they need a light weapon they can bring into operation fast

Parachutes will drop the cheaply built Stens to the peoples' armies, along with the bullets to fire in them. But enemy munition dumps will also be a handy source of supply as the gun shoots many Axis types of ammunition

Drawings by B. G. SEIELSTAD

of Invasion

BEHIND AXIS LINES


only two machined parts, the bolt and the barrel; every other part is the cheapest kind of stamping. Firing is accurate up to 100 yards.

What's more, engineers thoughtfully designed the Sten to fire all types of 9-mm. Parabellum ammunition and most other shells of the same caliber. Guerrilla fighters will be thankful for this foresight when the "big push" comes and they begin to take over enemy ammunition caches, for they will be able to load Sten magazines with cartridges made for German Schmeisser and Bergmann submachine guns, the Italian Beretta machine carbine, and a wide range of Axis service rifles and carbines.

Because the total cost of the corbinlike weapon is under fifteen dollars, they can be made in huge quantities for generous distribution where they will do the most good



"Invasion guns" are turned out fast on assembly line of this Canadian factory. Some are already waiting for action in secret underground arsenals in Europe





A collapsible stock and detachable barrel make it possible for the gun to be broken down into three parts, none more than a foot long

SUBMACHINE GUN.

Known as the M-3, this handy 45-caliber weapon, designed by the Army for parachute troops, spits out 450 rounds per minute with good accuracy at short range. Almost toy-like in appearance, the gun weighs nine pounds, and when collapsed will fit into a brief case. It is made mostly of stamped parts, and can be mass-produced for only \$20. Amazingly rugged, the gun is said to be comparatively unaffected even by immersion in salt water.



CLEARING A PATH through mine fields is a ticklish job for the combat engineers, even with this hypersensitive mine detector. Powered by batteries, the instrument is an adaptation of the metal finder used by prospectors. As it senses buried metal, a buzz is transmitted to the operator's ear-phones. The louder the buzz, the closer the mine, and the engineer marks the spot with pegs as a guide to sappers who will be sent to remove the mine from the path of advance.

THIS PORTABLE PRESSURE CHAMBER shows which of our airmen can fly high. It is used by a U.S. Air Provisional Medical School in England to test flyers' physical condition and their reaction to high altitudes. The flyer enters the chamber, an airtight door is closed, and the air is slowly pumped out to simulate high-altitude conditions. The men are tested with and without oxygen masks, to ascertain their reactions at various degrees of pressure.



Above, an operator controls the amount of air that is pumped from the chamber to reduce the pressure. Right, a supervising officer peers through a window to observe flyers' reactions




TORPEDOED. Seamen disembarking in a Canadian seaport on the Atlantic coast enjoy having themselves ferried to shore through the gaping hole left in the bow of a freighter by an enemy torpedo. The hardy seamen have a grim name for the trip. They call it the "Scenic Route." Water taxis shuttling back and forth across the harbor find that the novel passageway, which is large enough to accommodate a fair-sized dingy, provides them with a convenient short cut. Attacked by a submarine in the Atlantic, the vessel, as can be seen from the photograph, was solidly hit. Instead of sinking, however, the stout vessel righted itself and the crew brought it to port without aid.



SHIP FENDERS, designed to protect vessels from damage when they refuel or take on cargoes at sea, are now being made of fir from the Pacific Northwest, instead of oriental wicker, which is no longer available. The fir poles are first cut to length, then driven into place in a wooden frame. A woven network of rope holds them fast. Fenders are hung over a ship's side when it goes alongside another vessel to transfer fuel or cargo, to prevent their scraping.

Postwar Locomotives Will Hit New High in Power and Efficiency



By CAPT. W. MACK ANGAS


Civil Engineer Corps, U.S.N.

WHEN the new techniques and materials developed by the war are finally directed toward industrial problems of peacetime, one of the machines most likely to experience radical departures in design and construction is the railroad locomotive.

The familiar steam locomotive will still be with us for a while—but it, too, will undergo revolutionary changes. Air and water-cooled condensers that increase the efficiency of stationary and marine steam engines by permitting them to exhaust at low temperature into a partial vacuum

The opinions expressed in the following article are the author's, and should not be interpreted as those of any department of the Government.

have, as yet, proved impractical for use on a locomotive. But there is no reason why the engine's efficiency cannot be increased by stepping up the pressure and temperature of the steam that drives it. A fire-tube boiler used in conjunction with a water-tube fire box, such as has already been developed, may readily raise current pressures of about 250 pounds per square inch to 400 or even 500 pounds—with a superheater to raise the steam's temperature from 600 to over 750 degrees F. Since steam much over the latter tem. *(Continued on page 210)*



At right are shown three metal airplane parts, with the new plastic dies which have been used to form them. In addition to speeding up production, the dies also save critical metal




THERMO-CAST, a new plastic developed by Prof. James M. Church, of Columbia University, New York City, is expected to speed up production of thin structural airplane parts by 50 percent by replacing the metal tools ordinarily used to form them. Extremely hard, with a high impact strength, the new plastic melts at a much lower temperature than metal and can be cast with considerably greater exactness.

"DUCKS," the Army's new 2½-ton amphibian trucks, are playing an important rôle in landing military supplies on the beachheads of the Pacific. Maneuvering alongside a freighter (left), the big duck takes aboard its load, cargo net and all, and "swims" back to the crane (below). The vehicle can also be used to ferry troops and equipment ashore from transports during the early stages of landing operations.



NONCRITICAL MATERIALS GIVE US HEXAMINE



Hexamethylenetetramine, an important ingredient in the high explosive with which American flyers are smashing German military and industrial targets, can be traced back to plain coal, air, and water.

Secret Chemical Puts More "Bust" in Block Busters

AIR, coal, and water, broken down and recombined by chemists, form the basic ingredient of a new secret explosive that daily blasts Axis war plants, naval bases, and air fields. Known technically as hexamethylenetetramine—or hexamine, for short—this complex organic chemical has long been used as an "accelerator" in the vulcanizing of rubber and the making of phenol-formaldehyde plastics. Under the name of urotropine, it also serves as a vital medicament in the treatment of diseases of the urinary tract. Since Pearl Harbor, however, the Du Pont electrochemical plant, at Perth Amboy, N. J., has been producing, for use in the new explosive, vast quantities of specially treated hexamine whose grain size, moisture content, and other properties are carefully controlled. Resembling sugar in appearance, hexamine is produced by a secret method of combining liquid formaldehyde and liquid ammonia. The resulting solution is passed into an evaporator where it is boiled down into a crystalline state. This substance is then dried and ground into granulated form.

One of the virtues of hexamine is that, unlike TNT, it requires no critical materials.



Hexamine crystals being shoveled from an evaporator at a Du Pont electrochemical plant. They will be granulated for use in preparing the explosive.

Formaldehyde is made from air and synthetic wood alcohol, the latter being made from coal and water. Synthetic ammonia is produced from nitrogen from the air and hydrogen from water, water gas, or coal gas.

Total production of hexamine in the U. S. during 1941 amounted to 4,000,000 pounds. Since then many new plants have sprung up to increase that amount many times over, and to insure an ample supply of the once harmless chemical which now combines with others to produce shattering destruction. Just how this combining is done, of course, must for the present be left for the chemical wizards of the "master race" to figure out.

Can we have rope without dope?



This year America will grow 75,000 tons of hemp fiber whose leaves and flowers (left) will contain marijuana. (Photograph Above from U. S. Department of Agriculture)

Plant Wizards Fight Wartime Drug Peril

We need hemp—lots of it—for cordage, but hemp means marijuana, too. Can scientists take the drug menace out of this useful plant?

By ALDEN P. ARMAGNAC

CO-OPERATING with the U. S. Department of Agriculture, American farmers will produce 75,000 tons of hemp fiber this year, and probably more than twice as much in 1944. The record-shattering crops will replace Manila fiber from the Philippines and sisal from the Dutch East Indies, which are now cut off by the war.

The result will be a boon to users of cordage—and a headache for law-enforcement officers. A Jekyll-and-Hyde plant, hemp provides twine and rope urgently needed for military purposes. But it also yields marijuana, a drug that makes de-

praved creatures of its addicts. What can be done to keep these enormous new supplies, from which there almost inevitably will be "leaks," out of their twitching hands?

"Drugless hemp" is the bold proposal of the Department of Agriculture for solving the problem. In short, it is attempting to breed a strain of hemp of good fiber quality, but containing a negligible amount of the baneful marijuana drug. For aid, it has enlisted the expert services of Dr. H. E. Warmke, at the Cold Springs Harbor, N. Y., experimental station of the Carnegie Institution.

First of Dr. Warmke's problems has been to develop a method of determining reliably the amount of marijuana in individual hemp plants. With undesirables weeded out, he then cross-pollinates and breeds the desirable, or relatively drug-free, plants. Only a little more time will be needed to learn whether he can establish a pure, self-perpetuating race of them.

Fish serve as test animals for determining the potency of marijuana extracts. Previous

This little fish, shown actual size, plays an important role in the fight to breed a drugless hemp.



1 The seedling of one of many plants being bred to reduce the marijuana content of hemp



2 Dried center leaflets from each leaf of mature plant are ground to powder in mortar



3 Measured amount of powder is put in vial, and a chemical is added to extract marijuana



4 To determine the potency of the extract, a pair of killifish are placed in each of four beakers containing solutions of the drug ranging from very strong (left) to weak (right). In this way, the number of fish that are killed gives a graduated measure of the amount of marijuana in the plant tested

experimenters have used dogs, and tried to estimate the extent of their marijuana "jag"—something hard to reduce to cold figures. But when a fish is placed in a strong solution of marijuana extract, it soon is most thoroughly dead, and such an observation cannot be disputed. Therefore, Dr. Warmke puts two killifish, or "Atlantic minnows," into each of four beakers containing precisely measured dilutions of the drug—very strong, strong, medium, and weak. Then he can record the number of fish killed and get a definite measure of the poison in the plant.

First encouraging results show a great range in the amount of marijuana in different hemp plants. Some prove to be one eighth as poisonous as others, an excellent starting point for a plant breeder. And actual breeding has definitely resulted in improvement. With true scientific caution, Dr. Warmke refuses to admit having "Bur-banked" a drugless hemp until a few more plant generations have been tested, but to a layman's eyes he seems close to his goal.




5 In effort to breed a "pure" hemp, plants with low toxicity are cross-pollinated by shaking pollen from male plant (right) on stigmas of female




THREE-IN-ONE COMBAT GLOVES mean the difference between frozen fingers and victory in high-altitude dog fights for flyers of the Royal Canadian Air Force. Successive layers are shown from left to right above. The innermost, made of rayon, has

thumbs and forefingers latex-treated to make paper handling easy. The second pair, worn over the first, is of wool, with easy-grip thumb pads of leather. The outermost gloves, of horsehide, have fingers curved like those of worn gloves.



SCALE MODELS teach Quartermaster personnel their jobs in the Corps school at Camp Lee, Va. Above, future Army cooks and mess sergeants learn how to set up a standard field kitchen. Below, a model of a refrigeration plant uses toy-size models of meat carcasses.




AN AIR-AGE GLOBE manufactured by Rand McNally demonstrates the new routes and distances in an air-minded world. The 12-inch globe can be lifted from its attractive glass base, held in the lap, or passed around like a ball. Free of the old axis rod, meridian, and horizon ring, it gives a true conception of our earth as a free-floating sphere. This globe is an aid in keeping abreast of the war news.



Supplied with this free-moving globe is a plastic tape scaled in nautical and statute miles for measuring both air-line routes and surface distances





FIVE-LENS CAMERA for filming attacking planes is set in same position in bomber as gunner later will occupy. Fred Waller, Trainer's inventor, is shown loading film in camera

TARGET PLANE'S image travels across screen while gunners try to hit it with imaginary bullets. Button on control panel permits instructor to throw light on screen that shows where student is aiming, so he can advise corrections through earphones

Movies Train Air Gunners

FLYERS BLAST PHANTOM PLANES IN BATTLE PRACTICE


By WILLIAM CRIST

Drawings by B. G. SEIELSTAD


TO BRIDGE the jump between shooting at slow-moving sleeve targets towed in a straight line and shooting "live ducks," aerial gunners now are getting their final licks on the Waller Gunnery Trainer. Developed by Fred Waller, who formerly was in charge of special effects for Paramount Pictures and more recently head of their

short-subjects division, the Trainer reproduces, on a mammoth concave movie screen, attacks by dodging, twisting fighter planes, and shows the gunners how to hit them.



The screen is a segment of a sphere, measuring 40 feet from end to end. On this is thrown a picture by five projectors, each covering a separate portion of it. Twenty feet in front of the screen sit the trainees, each in one of four gun positions. They have two gun handles in front of them, just like



GUNNERS sit in 4 positions about a cluster of 5 projectors (A) which throw pictures of attacking planes on a spherical screen (B). Composite of 5 images covers 150° horizontally, 75° vertically. Both free (C) and turret (D) guns are used; ball turrets (E) will be adapted later. The instructor (F) has a score board in front of him that counts the number of hits by each gun. Registers (G) operate score board, and send signal to student's earphones when he hits



HEART OF WALLER TRAINER is hit-recording mechanism. As gun swings in azimuth and zenith, cables move quadrants (right) which move 3 scanner bars (above) across register film. Film has set of light slits for 75° vertical angle, one for each half of horizontal throw. Their location is set by plotting distance to attacking plane against time it takes bullet to reach it. Film is thrown on a screen, a frame at a time, and position of the plane noted. It then is advanced to show position at end of time lapse. (Movie film goes through a projector at 24 frames per second.) This new spot is where gun should be aimed so bullet gets to the second position at same instant plane does. It is marked by a light beam whose location on the screen is transmitted to the 3 masks in a projector loaded with register film, which are moved in the same manner as the scanner bars. These masks pass slits of light to the film in order to expose an image position of the light beam on screen. When gun in Trainer is in correct "point of aim," the scanner bars are moved by the gun's cables into a scoring position, permitting light to pass through slits in them and through the transparent marks in the film. The light strikes a photo-electric cell, which closes a relay, sending signals to both gunner and hit indicator on the central board







DIVIDERS are used to measure wing span of plane so its distance can be calculated. In recording hits, allowance is made for scatter of bullets after firing

PROJECTION EQUIPMENT handles 9 rolls of film at a time; 5 of these are picture film, 4 are the register bands. Synchronous motors run all at same speed

those on a real .50 caliber machine gun. When the image is thrown on the screen, they can see the wing tips of their own bomber, as well as the approaching fighter. They lead it in their standard Mark 9 reflector sights, pulling the trigger when they think they are on the correct "point of aim." If they are in a free-gun position, instead of a turret position, the gun handles start jumping, the vibrations carefully reproduced to simulate those of a real gun. Through earphones they can hear the authentic sound of their own guns. When a hit is scored, it sounds a 1,000-cycle "beep" in their ears and moves a register on the instructor's control panel. The Army Air Forces also use the Waller Trainer.



BURST RECORDER **BULLET RECORDER** **HIT RECORDER**



CONTROL PANEL shows number of bursts and bullets fired and keeps record of hits. The hit indicator also flashes on when a student scores a hit. If light stays out too long, instructor checks student's aim



A 16-WHEEL TRAILER is being used at a large shipyard, engaged in the mass production of Liberty ships, to haul giant prefabricated sections from the assembly shop to the ways. Rolling on rubber-tired wheels

and capable of handling loads weighing as much as 80 tons, the trailer is drawn by a Diesel tractor. Both the trailer and tractor are products of the Caterpillar Tractor Company, of Peoria, Ill.



INNER SOLES made of a new "ventile" wool and designed by the American Felt Co., Glenville, Conn., "exhale" the moisture from perspiration and thus protect troops stationed in Arctic regions from the danger of having ice form in their shoes. Each sole consists of two hinged pieces which "work" under pressure.

THE RUBBER LUNG, a device for administering artificial respiration, has been introduced by the E. D. Bullard Company, of San Francisco. Strapped to the patient's body, the resuscitator is operated by rhythmically depressing and raising the handle. This activates the abdominal muscles and diaphragm, causing the patient to inhale and exhale until his normal breathing has been restored.






ONE-MAN FORTRESSES now command the centers of many of the French and Scandinavian towns occupied by the Nazis. The tiny fort at the left, the size of which can be judged by comparison with the soldier standing beside it, consists of an armored revolving dome set on a heavily armored base. The recent increase in the number of these miniature pillboxes, which are to be found for the most part in coastal villages and towns, gives strong indication that the Germans are now on the receiving end in the war of nerves, and are frantically fortifying themselves against attack by Allied invaders and by enraged natives of the occupied countries.

PORTABLE ELECTRIC MEGAPHONES are now carried by merchant ships for use when bombs or torpedoes knock out the regular communication systems. Powered by a battery carried in a case slung over the shoulder, the instrument amplifies the human voice to permit the giving of commands to gun platforms, engine room, and lifeboats.



BULLET "FOOTPRINTS," left on lacquer-coated targets by the impact of speeding projectiles, are giving Westinghouse scientists new information that may help them to develop tougher armor plate and better armor-piercing shells. When a rifle is fired at a target, as at lower right, stresses set up in the target material are permanently recorded as cracks in the sprayed-on, brittle lacquer coating. On the target below, dye has been added to bring out the circular pattern of lines around the point of impact.



Robot Brain Aims Turret Guns

COMPUTING SIGHT GIVES BOMBERS DEADLY FIRE POWER


AMERICA'S Flying Fortresses and Liberators have enjoyed their signal success at daylight bombing over Europe and in the Pacific because of their terrific fire power, which enables them to fight their way in and out against the best Axis fighter opposition. Behind this deadly bomber defense is a little black box which has, heretofore, been kept on the "secret" list. This is the new Sperry Automatic Computing Sight, a compact and simply operated mechanical brain that does most of the gunner's thinking for him.

Its use has resulted not only in greater accuracy but in increased range. Twin .50 caliber guns fitted with the automatic sight now have an effective range of more than

1,000 yards. Mounted centrally between the guns, the sight swings or raises or lowers as the guns are tracked. The gunner peers into an optical sight, keeping the enemy plane "framed" between two vertical lines. He may alter the distance between these lines by moving a pedal with his left foot, and as long as these lines frame the hostile ship, the guns are "on target."

Upon attack, the gunner moves a small knob on the right side of the little black box to correspond with the known wing span of the enemy plane. Recognizing the attacker as a Messerschmitt 109G-2, for example, the gunner sets the knob so that the scale reads 33, the plane's approximate wing span. As the plane approaches, the gunner keeps it framed by moving the vertical lines in his sight with the foot pedal.

Although he seems to be aiming directly at the enemy ship, the guns are actually pointed ahead of the plane, "leading" it as in skeet or duck shooting. Allowance is also made automatically for vertical ascent or descent and the effect of the wind. Since deflection and windage have been two of the gunner's biggest problems, the new sight will speed training of new gunners.



This little black box does the figuring for the man at the .50 caliber machine guns in a bomber turret


TARGET PLANE
IDENTIFIED AND
WING SPAN SET
ON SIGHT

TRACKING CONTINUES
UNTIL TARGET IS IN RANGE

FIRING BEGINS WHEN
TARGET IS IN RANGE

GUNNER TRACKS
TARGET BY FRAMING
ITS WING TIPS WITH
ILLUMINATED LINES
ON SCREEN

AS TURRET IS MOVED IN
TRACKING TARGET, GUNS
ARE AUTOMATICALLY SET
TO COMPENSATE FOR
FACTORS AFFECTING
BULLET'S FLIGHT



SWIMMING WITH A PACK is not as difficult as it sounds. Far from weighing him down, a soldier's regulation 60-pound load will actually provide enough buoyancy to keep him afloat for a time. When the equipment is properly arranged, air is trapped inside the bag and remains until the fabric is thoroughly soaked. The swimmer is so well supported that he can even aim and fire his rifle while floating in midstream. If he has no pack, a fighting man can apply the same principle by knotting a pillow slip or even a pair of pants so that it will hold enough air to take the place of water wings or a flotation bladder. Such tactics will be handy in landings and other amphibious operations.



Pvt. H. T. Christoffersen demonstrates the knack of floating with a full regulation pack and aiming his rifle at the same time



HOME, SWEET HOME

for glider mechanics at advanced invasion bases will be the seven by 24-foot weatherproofed crates in which their gliders reach them. Student mechanics in training at Sheppard Field, Tex., are taught how to make themselves at home in the boxcarlike crates in preparation for the day when they will use them as huts. At the left, trainees are seen moving cots and bedding into one of the crates, which they christened "Glider Inn."

Looking Ahead

LIFEBOAT REFRIGERATOR. A Toronto manufacturer, working with medical researchers, has perfected a lifeboat refrigerator which makes fresh-water ice out of sea water, then obligingly melts it again for drinking if the temperature is below freezing point.

WOBBIE. A Netherlands Luther Burbank has crossed a carrot with a beet and come up with the hybrid "wobbie," guaranteed to taste better than it sounds. This plant—said to be the first new root vegetable introduced into agriculture in a generation—contains almost four times as much vitamin C as either of its progenitors.

NEWEST TRICK in camouflage is the dark-green paint concocted by Du Pont scientists to make Axis aerial photographers look foolish. The new paint reflects infrared rays and, when photographed, shows up just as light as real vegetation, effectively hiding vital buildings from a prying infrared camera eye.

PLANES OF THE FUTURE may be stuck together, not with rivets and weld spots, but with an adhesive tape said to be stronger than both. Cycleweld, a new plastic cement tape developed by Goodrich, is sandwiched between two sheets of metal with heat and pressure to form a liquidtight and airtight seam.

Strip Germany of Machine Tools!

POPULAR SCIENCE MONTHLY offers a plan for disarmament that would reach down to the roots of the Nazi war menace.

THESE ARE BASIC PROCESSES OF ARMS PRODUCTION

CASTING

Foundries provide heavy parts for war machines.



FORGING

Heated metal is hammered into shape and toughened.



MACHINING

Lathes, shapers, and other machine tools work metal.



GRINDING

Abrasive wheels give precision finish to all work.



WELDING

Arc or flame joins parts in fabrication of weapons.



DE-INDUSTRIALIZE Germany. Strip her of the tools and machines that are the basis of all war production. That is the proposal offered by **POPULAR SCIENCE MONTHLY** as the only way to make sure that 80,000,000 Germans will never again spread the disease of war throughout the world.

Disarmament of Germany is a fundamental of any plan for securing the peace of Europe. But this time we must do the job right. We must not repeat the almost fatal mistake that gave the Nazis their head start on the road to world conquest in 1939.


That mistake was the assumption that rearmament begins with the actual production of guns, tanks, and planes. In modern, mechanized warfare, that is only the final step of a long and complicated process. The groundwork is the building up of a vast supply of machine tools and of the skilled labor to operate them, with the foundries, blast furnaces, mines, and other installations needed to feed them with materials.

To manufacture a 25-pounder field gun requires about 7,000 tools, ranging from a 2,000-ton press to 1½-foot grinders. It calls for thousands of jigs, tools, and gauges, with some 40 traveling cranes and equipment for tempering. Making the 45,000-odd parts of a bomber, or the 40,000 parts of a tank, is likewise a job only for organized industry.

The insidious thing about machine tools is that they can serve as well to make the implements of peace as to forge the weapons of war. Lathes, presses, and milling machines can be turned in a moment from manufacturing vacuum cleaners and washing machines to producing bombers and cannon. Furthermore, they are the only creations of man that are self-regenerative. Machine tools can breed more machine tools, pyramiding productive capacity at an almost unbelievable rate.

These facts served the Nazis well in their carefully planned preparations for the present war. Long before they made the first move in defiance of the Versailles Treaty, they had multiplied their machine-tool production enormously. When M-day came, it was necessary only to switch over these machines to war production with the aid of secretly prepared gauges, jigs, fixtures, and tools. While the British and French were

From German industrial centers, machines and equipment would be moved away to the countries that have been despoiled by the Nazis, to help in the giant task of repairing the ravages of war. German factories would be stripped to bare walls.



THESE FACTORIES MADE THE WAR

trying frantically to create a large-scale armament industry overnight, the Germans poured forth a flood of war materials that nearly gave them world domination.

The same thing will happen again if Germany is allowed to retain her heavy industry and her machine tools. It is too easy to change over from peacetime manufacture to war production. Disarmament must go down to the roots.

How would this be done? To get the answer, **POPULAR SCIENCE MONTHLY** canvassed engineers and manufacturers of machine tools and heavy machinery—men who know how to forge the weapons of war and how to convert plants from peacetime production to the building of guns, tanks, and planes. Many of them had dealings with German industrialists during the period when Hitler was rearming the Reich. One is a former German engineer who witnessed the mockery of the “disarmament” that followed the last war. All know how futile it is to try to win a modern war without

complete leadership in industrial production.

These men say that the only way to disarm Germany effectively is to strip her factories of everything they contain, even to the steel girders. Much of the machinery will be worn out after years of forced war-time use without proper replacements. What is still usable would be divided among the countries the Nazis have despoiled, to help them in the big job of reconstruction. Foundries, blast furnaces, and mines would be dismantled.

The plan would have to be carried out by men who know machines and what they can do for peace and war. An inter-Allied commission of engineers and industrialists would go through Germany's factories and mills, checking all equipment that was fit for salvage. Distribution would be governed by the needs of the various countries to be reconstructed and the amount they have suffered. Equipment for mines and blast furnaces would be shipped to cities like Lille and Kharkov, where they could be used.



...LET THEM REBUILD FOR PEACE

As for the future, strict supervision of German industrial life would make certain that no new start was made toward building up a potential war production. Machine tools and heavy industry would be taboo, until the German people have given proof that they have lost their inveterate urge for conquest.


Is the plan feasible? Yes—if it is administered conscientiously by statesmen and technicians, with full co-operation and support by all the United Nations. It isn't easy to hide the growth of a war machine. Before the present war, it was no secret that Germany was rearming. Even after the preliminary period of planning and experimentation, it took the Nazis six years of intensive work to get ready for the test of battle. It needn't have happened—and it must not happen again!

If this proposal sounds ruthless, it has ample precedent from the Germans themselves. Almost their first act of aggression was aimed at Czechoslovakia, with the pri-

mary object of grabbing her highly developed industries. As the Luftwaffe and the armored divisions swept over Europe, their engineers went through the factories and carted off anything they wanted. When it was not expedient to carry away the equipment, they moved in and exercised control for their own purposes.

What would become of German economy if this plan were put into effect? It is no light matter to turn back the clock 50 years in a highly industrialized country. Germans would have to learn to live under an agrarian and handicraft economy, at least until the virus of war was definitely eliminated from the national mind. Their industrial genius might be employed, under strict control, in the rebuilding of the countries they have ruined. But, at worst, their condition would be no harder than it was during the years of "guns or butter," and civilization would be saved from the catastrophe of another world war. If this is the price of permanent peace, it is a bargain.

Where you'll live after the war



Your Home...Tomorrow

Here's a preview of the house you'll get when peace comes . . . a prefabricated home with built-in conveniences and comforts for modern living.

**By CARL T. SIGMAN
and WILLIAM J. WARD, JR.**

IN YOUR postwar home you will find a fifth freedom—freedom from most of the traditional inconveniences, inadequacies, and high costs of the house of the past. In short, freedom to live in that same postwar future.

Everyone knows that the automobile of tomorrow will be very different from the last prewar models. The same will be true of radios and refrigerators, ranges and furnaces, sanitary and electrical equipment, and even of the roofs, floors, walls, and windows of our new houses. In some of these, improvements have come in the past at widely spaced intervals; others have seen

minor annual changes. But it never seemed to the manufacturer that he could afford to scrap all his dies, tools, and machinery to make a revolutionary change in his product, however far ahead of him his engineers and architects might be. Now, however, all his equipment has been scrapped to meet war demands, and with peacetime conversion he will be free to build the best refrigerator, range, bathroom—or the best house—that his engineers, designers, and architects can conceive, however revolutionary it may be in material, structure, or equipment. Besides being freed from the restriction of existing equipment, these building industries will find themselves aided by recently developed new materials and by astonishing new uses for old ones. The result is bound to be something very like a revolution in house building and equipment.

Your home of tomorrow will be a better and a cheaper house—one designed of modern materials, by the best modern engineering thought and facilities, and geared to modern living. It will be cheaper because it



will be largely or wholly prefabricated. But it will be a far cry from the boxlike "modern" houses that we have known. Prefabrication will at first accommodate styles of design familiar to us, but it will gradually adapt itself more, functionally, to modern living.


The manufacturer will make your house of tomorrow in wall slabs, roof, and floor sections that can be shipped to you in a flatcar. Into the lighter and thinner walls will be built insulation, hot and cold-water pipes, and, in some instances, soil pipes. They will be completely wired with continuous base outlets. The ceilings may come with concealed cove lighting.


Plywood glued in place will make outside and inside walls tighter and stronger than our present ones. Or the interior ones may be made of new plastic materials that can be wiped off clean, will never develop unsightly cracks, need never be papered or painted, but can be, if you wish. Or they may have semiporous surfaces that absorb sound, and into which nails can be driven and withdrawn without leaving holes.

Windows and doors will come in certain of the sections, but, far from determining a standardized design, these sections will fit into houses of innumerable architectural types. Your architect has only to choose the particular section that his design

The walls, partitions, roof, and floors of the house are delivered to the site as prefabricated panels containing all electrical, plumbing, and heating equipment ready for connection. Kitchen unit is set up almost as easily as you plug in your radio. Whole bathroom comes as a unit. Plastic floors are cushioned on warm air space over concrete pad. A compact heating system makes costly cellar excavation unnecessary; chimney needs no heavy foundation. Exterior of house requires no paint

PREFABRICATED PARTS MAKE CONSTRUCTION EASY





YOUR LIVING ROOM ... TOMORROW

The television screen is the focal point in the living room. Radio controls are located strategically in the furniture. Illumination is from an indirect fluorescent cove and specific ceiling sources. Ventilating louvers above and below plate-glass windows leave unbroken vision at all times

calls for. Your new windows will be double-glazed, with dead-air spaces between the panes for insulation against both heat and cold. If you wish, they may be for vision only, with concealed, screened, adjustable louvers at top and bottom for ventilation. For other windows, which may be opened horizontally to their full width, there will be complete weather stripping and screens. With both types will come filters for pollens.

Radiators and registers, you will be glad to know, are to give way to piping within the walls of your house. Installation costs, which will be somewhat higher, will be offset by a fuel saving of one third of present average heating costs. Heating systems will incorporate air-conditioning. In other words, you will have humidified winter heat thermostatically controlled, and summer cooling with proper circulation of dry, filtered air. Windows need never be opened. Your heating will be automatic, of course, whether you use coal, coke, gas, or oil. Where there is cheap hydroelectric power, electricity will not indirectly heat your home by means of hot water or steam, but will work directly through heating elements within the walls and floors, integral with the prefabricated sections.

Since postwar heating systems will be small and compact, space on the ground floor can readily be found for them. So, in planning your house of tomorrow you may write off a large part of the expense of

digging a cellar and building waterproof cellar walls, for with advanced types of floor construction, new chemical ground treatments, and the use of copper shields, the dangers of damp and of termites are eliminated. Only small footings will be required. Many houses will be built on precast concrete slabs which will contain pipes for floor heating.

Your house may also be soundproof. Rooms will be so insulated from each other that your sleeping will be undisturbed by the noise of the late party downstairs. Radio installations and television devices will be in each room.

Even more revolutionary than the changes already mentioned will be your all-metal or all-plastic kitchen built in one unit, and capable, in whole or in part, of removal and trade-in, like an automobile.

Ranges will have lighted, transparent oven fronts. Time and heat control will have been developed so that before the lady of the house goes out for the afternoon, she may put the whole dinner on the stove. Time-controlled to start cooking at a determined time, the dinner will be ready to serve on schedule. If she is late in returning, nothing will burn, for the heat will be automatically reduced to warming temperature at a set time.

The real revelation, however, will be your refrigerator. It is likely to be a plastic cabinet with transparent doors, and a cylin-

drical revolving interior. No hunting in dark recesses for the elusive butter; you switch on a light, turn the shelf levers until the butter dish appears up front, and then open the door to that particular shelf by flipping out a concealed handle, or stepping on a convenient pedal, or by knee action against a button. Ice cubes will be dispensed individually by pressing a button. Cracked ice will be available in the same manner. These ice dispensers will be separate from the main cabinet, so that no cold will be lost in removing the ice. Within the refrigerator, a reservoir connected with the water pipes will furnish cold water uncontaminated by near-by foods.

In your house of the future there will be devices for both the freezing and the dehydration of your surplus garden foods, and


means will be provided for their proper storage. Ultraviolet-ray tubes placed at strategic places in the kitchen will kill harmful bacteria in the refrigerator, prevent mold in the bread box, and sterilize dishes.

The same fine engineering will mark the unit bathrooms and lavatories of your home. In many cases these will come in the same unit with the kitchens, back to back, on one wall, to reduce plumbing lines to a minimum. Or they may come in double bathroom units. Your shower will have sliding non-breakable plastic walls. You will be able to set the temperature for your bath, and the water will mix itself. Condensation units within both the shower and the tub enclosures will eliminate steam, and low-voltage units behind mirrors will prevent condensation on them. *(Continued on page 215)*

YOUR BATHROOM, KITCHEN ... TOMORROW

Gone are the ugly crocks of our tile bathrooms, for the plastic fixtures are integral with the wall and floor. Rounded outlets replace protruding faucets. Pedal buttons control water supply for basin and toilet flush. The floor is a heat chamber; the ventilator fan is humidistat controlled.

Plastic kitchen unit. Left to right: Refrigerator with transparent doors which open by knee pressure on large buttons; ice and water unit. Garbage ejector. Sink, flanked by dish washer and sterilizer; in front center, towel drier; below, floor pedals operating sink outlets. Right, automatic range with transparent oven doors. Floor of indestructible plastic. Note sun visors



new Tools

ADJUSTABLE MIRRORS, looking like large-scale models of a dentist's mirror, aid aircraft workers in examining hard-to-get-at parts. Made by F. P. Kretchmer, of Los Angeles, the plastic-mounted mirrors have a handle sleeve which allows adjustment to any angle.



CHIP-BREAKER GRINDERS, made by the Delta Manufacturing Co., of Milwaukee, are equipped with a universal vise to hold work at any angle. A long spindle with widely spaced bearings permits precise alignment.



TWO-HAND SOLDERING is made possible with this stand, which is fitted with an adjustable, but firmly held, soldering iron. A magnifying lens is located in the hood, which can be raised or lowered, and a 30-inch chimney carries off the fumes. The manufacturer is Photobell Corp., of New York.



MOTORIZED SWEEPERS developed by the Moto-Mower Co., of Detroit, enable a single worker to clean up a fair-sized plant at the rate of 16,000 square feet per hour, thus releasing a crew of broom sweepers for more important work. With minor adjustments, the machine can double as a lawn mower or a snowplow.

**LONG-PLANNED
ATLANTIC SEADROMES
TO BECOME POSTWAR REALITY**

UNCLE SAM ASKED TO BUILD
Floating Ocean Airports

Small inset images showing construction and operation of the floating airports.

At right, a reproduction of the leading page of an article which appeared in P. S. M. over nine years ago, and which described in detail the proposed airports

USS Intrepid (CV-11) at sea, showing the deck and various aircraft.

Deck 11

Deck 10

Deck 9

Deck 8

Deck 7

Deck 6

Deck 5

Deck 4

Deck 3

Deck 2

Deck 1

Deck 0

Deck -1

Deck -2

Deck -3

Deck -4

Deck -5

Deck -6

Deck -7

Deck -8

Deck -9

Deck -10

Deck -11

Deck -12

Deck -13

Deck -14

Deck -15

Deck -16

Deck -17

Deck -18

Deck -19

Deck -20

Deck -21

Deck -22

Deck -23

Deck -24

Deck -25

Deck -26

Deck -27

Deck -28

Deck -29

Deck -30

Deck -31

Deck -32

Deck -33

Deck -34

Deck -35

Deck -36

Deck -37

Deck -38

Deck -39

Deck -40

Deck -41

Deck -42

Deck -43

Deck -44

Deck -45

Deck -46

Deck -47

Deck -48

Deck -49

Deck -50

Deck -51

Deck -52

Deck -53

Deck -54

Deck -55

Deck -56

Deck -57

Deck -58

Deck -59

Deck -60

Deck -61

Deck -62

Deck -63

Deck -64

Deck -65

Deck -66

Deck -67

Deck -68

Deck -69

Deck -70

Deck -71

Deck -72

Deck -73

Deck -74

Deck -75

Deck -76

Deck -77

Deck -78

Deck -79

Deck -80

Deck -81

Deck -82

Deck -83

Deck -84

Deck -85

Deck -86

Deck -87

Deck -88

Deck -89

Deck -90

Deck -91

Deck -92

Deck -93

Deck -94

Deck -95

Deck -96

Deck -97

Deck -98

Deck -99

Deck -100

Deck -101

Deck -102

Deck -103

Deck -104

Deck -105

Deck -106

Deck -107

Deck -108

Deck -109

Deck -110

Deck -111

Deck -112

Deck -113

Deck -114

Deck -115

Deck -116

Deck -117

Deck -118

Deck -119

Deck -120

Deck -121

Deck -122

Deck -123

Deck -124

Deck -125

Deck -126

Deck -127

Deck -128

Deck -129

Deck -130

Deck -131

Deck -132

Deck -133

Deck -134

Deck -135

Deck -136

Deck -137

Deck -138

Deck -139

Deck -140

Deck -141

Deck -142

Deck -143

Deck -144

Deck -145

Deck -146

Deck -147

Deck -148

Deck -149

Deck -150

Deck -151

Deck -152

Deck -153

Deck -154

Deck -155

Deck -156

Deck -157

Deck -158

Deck -159

Deck -160

Deck -161

Deck -162

Deck -163

Deck -164

Deck -165

Deck -166

Deck -167

Deck -168

Deck -169

Deck -170

Deck -171

Deck -172

Deck -173

Deck -174

Deck -175

Deck -176

Deck -177

Deck -178

Deck -179

Deck -180

Deck -181

Deck -182

Deck -183

Deck -184

Deck -185

Deck -186

Deck -187

Deck -188

Deck -189

Deck -190

Deck -191

Deck -192

Deck -193

Deck -194

Deck -195

Deck -196

Deck -197

Deck -198

Deck -199

Deck -200

Deck -201

Deck -202

Deck -203

Deck -204

Deck -205

Deck -206

Deck -207

Deck -208

Deck -209

Deck -210

Deck -211

Deck -212

Deck -213

Deck -214

Deck -215

Deck -216

Deck -217

Deck -218

Deck -219

Deck -220

Deck -221

Deck -222

Deck -223

Deck -224

Deck -225

Deck -226

Deck -227

Deck -228

Deck -229

Deck -230

Deck -231

Deck -232

Deck -233

Deck -234

Deck -235

Deck -236

Deck -237

Deck -238

Deck -239

Deck -240

Deck -241

Deck -242

Deck -243

Deck -244

Deck -245

Deck -246

Deck -247

Deck -248

Deck -249

Deck -250

Deck -251

Deck -252

Deck -253

Deck -254

Deck -255

Deck -256

Deck -257

Deck -258

Deck -259

Deck -260

Deck -261

Deck -262

Deck -263

Deck -264

Deck -265

Deck -266

Deck -267

Deck -268

Deck -269

Deck -270

Deck -271

Deck -272

Deck -273

Deck -274

Deck -275

Deck -276

Deck -277

Deck -278

Deck -279

Deck -280

Deck -281

Deck -282

Deck -283

Deck -284

Deck -285

Deck -286

Deck -287

Deck -288

Deck -289

Deck -290

Deck -291

Deck -292

Deck -293

Deck -294

Deck -295

Deck -296

Deck -297

Deck -298

Deck -299

Deck -300

Deck -301

Deck -302

Deck -303

Deck -304

Deck -305

Deck -306

Deck -307

Deck -308

Deck -309

Deck -310

Deck -311

Deck -312

Deck -313

Deck -314

Deck -315

Deck -316

Deck -317

Deck -318

Deck -319

Deck -320

Deck -321

Deck -322

Deck -323

Deck -324

Deck -325

Deck -326

Deck -327

Deck -328

Deck -329

Deck -330

Deck -331

Deck -332

Deck -333

Deck -334

Deck -335

Deck -336

Deck -337

Deck -338

Deck -339

Deck -340

Deck -341

Deck -342

Deck -343

Deck -344

Deck -345

Deck -346

Deck -347

Deck -348

Deck -349

Deck -350

Deck -351

Deck -352

Deck -353

Deck -354

Deck -355

Deck -356

Deck -357

Deck -358

Deck -359

Deck -360

Deck -361

Deck -362

Deck -363

This illustration shows the design and construction of the latest model of the Armstrong sandstone which the Government recently has accepted ready to try out. Note the arrangement of the test deck.

[illegible]

jack and boom in stormy weather. Armstrong disclosed that the supporting struts from beneath the stern of the ship that is subject to wave motion and the sparwork structure allows waves to pass unobstructed beneath its deck. There is no doubt he has verified by experiments with models up to that of life-size size. Each syndrome would be a single or a combination for the 500 transverse in addition to quarters but its own yaw and heave. Specimen of ship's large transport planes from which the wave syndrome would have a violent first effect around officers, crewmen, and engineers as well as two thirds of the ship's cargo.

Any type of plane—land plane, sea plane or flying boat—could use the straits as refueling stations although Armstrong himself believes that a special

*Putting more punch
in our fighting planes*

By Arthur Grahame

Flying Gun Carriers

**AIRCRAFT ARMAMENT HAS COME A LONG
WAY SINCE WORLD WAR I . . . AND STILL
THE TREND IS TOWARD HEAVIER, MORE
CONCENTRATED FIRE POWER**

TOMORROW'S decisive air battles will be won by toughly armored flying gun carriers packing a weight of fire power far greater than that of the most gun-bristling fighter planes of today.

Aircraft designers and builders of all the major powers are engaged in a breakneck industrial race, trying to satisfy the armed forces' insatiable demands for stronger, better-protected planes, and heavier, more destructive guns to mount in them. Some types of planes already are firing projectiles powerful enough to smash light tanks and motor transport. Bigger guns are being tried out experimentally, and some students of ordnance predict the emergence of an air-cruiser type armed with guns of three-inch caliber or larger, possibly embodying rocket principles or some other means of fire capable of overcoming the serious problem of recoil.

In short, the science of aircraft armament, born in the First World War and more or less stagnant in the 20 years that followed, is now moving ahead again at full speed under the insistent pressure of a bigger and tougher war.

Even in this air-minded day, few Americans realize how greatly airplane fire power has been boosted. The one-place fighter plane offers a good basis of comparison. By 1918, in the closing period of the war, both sides had settled on a main fighter type armed with two rifle-caliber machine guns attached to the fuselage and fitted with synchronizers enabling them to fire through the propeller arc without damaging the blades.

With that armament a pilot who managed to line up an enemy in his sights for a reasonable burst—say five seconds—could pepper the foe with about 166 bullets having a total weight of four pounds. Just before the outbreak of this war the most heavily armed fighter plane in service was the British Hurricane, with eight .303 caliber machine guns firing from the wings. The same five-second burst from these ships delivered around 800 bullets, weigh-

ing 20 pounds—or 400 percent more weight.

One of the most heavily gunned planes on fighter duty in Europe today is the Royal Air Force's Spitfire IX, which goes into action with four .303 caliber machine guns and two 20-mm. automatic cannon spitting lead, steel, high explosive, and destruction. In five seconds the ship can fire 400 machine-gun bullets and 120 20-mm. armor-piercing or high-explosive shells. The total weight of the blast runs around 45 pounds—more than eleven times that of the 1918 plane.

That kind of development in fire power is the logical outcome of a corresponding development in the armor protection of the bombers which are the fighter's natural

FIVE GUNS GIVE THE P-38



HOW FIRE POWER HAS GROWN



1918 Two machine guns mounted on a fighter's fuselage could deliver about 166 bullets in five seconds



1939 Hurricane's eight wing-mounted guns peppered a foe with something like 800 bullets in a five-second burst


ITS STING


Twin-boom design of the Lockheed Lightning simplifies the placing of the guns. Four machine guns are arched over the 20-mm. cannon in the nose, where there is no propeller problem



1943 Four .303 machine guns and two 20-mm. cannon on the Spitfire IX can put 400 bullets and 120 shells in a target within five seconds



CANNON AND MACHINE GUNS ARE THE FLYER'S TOOLS





IMPROVED SIGHTS HAVE given fighter pilots a longer effective range. Since guns of a single-seater are aimed by turning the plane, sights must be fixed to the craft. The optical sight at left and below uses a circle of light that helps a pilot gauge distance of target

SIGHTING FIXED GUNS



Bore-sighting of fixed guns focuses fire power at a definite point, and it's the pilot's job to put the enemy on the spot. If the plane carries a cannon as well as machine guns, it is considered good practice to fire with machine guns until bullets hit target, then cut loose with the bigger stuff

enemy and prey. The rise of air warfare has brought about a repetition in this field of the long-standing race between ordnance and armor plate in naval design. As usual, gun power seems to have the edge, yet the ability of some new bombers, especially the

American heavy types, to absorb punishment and shoot back has proved a painful shock to many an overconfident Axis fighter pilot.


The first military aircraft were not armed at all. The top commanders in 1914 re-

ALLIED PLANES USE 40-MM. AND 20-MM. CANNON

The R.A.F.'s tank buster, the Hurricane II-D, packs a 40-mm. cannon under each wing. Designed for aircraft use, the guns weigh 320 pounds each

For lighter work, a 20-mm. gun is used. Here a ground-crew member is replacing the magazine of a cannon in the wing of a Spitfire at an English fighter station





AERIAL GUN VS. BOMB

For strafing small ground targets such as tanks and communications, airborne cannon have certain advantages over bombs. Perfect timing is essential to accuracy in bombing, but the plane's cannon can pump shells into its target as long as the ship is pointed at the mark. Greater speed and flexibility of maneuver are possible

guarded their planes as observation devices, somewhat more mobile than captive balloons but no more aggressive. Individual pilots took the initiative by carrying carbines, pistols, or shotguns aloft and potting away at enemy ships that ventured within range.

The next step was to mount a light machine gun on the ship, and the simplest arrangement was to have the gun on a swivel to be operated by the gunner in a two-place plane. But single-seater ships had far greater speed and maneuverability, so it was clear that the ideal fighter would be one in which the pilot could do his own shooting, aiming the entire plane at the target and firing the fixed gun by remote control.

A gun bolted to the center of the upper wing could fire above the propeller arc, but it created wind resistance and forced the pilot to stand up if he had to clear a jam or change ammunition pans. This arrangement was superseded by the development of the first practical synchronizer by Anthony Fokker, Dutch aircraft manufacturer.

Fokker's device consisted of a cam mechanism placed between the airplane engine and the machine gun's action. It was a tricky, cranky gadget, but when lined up and adjusted with loving care it worked, by restricting the gun's discharge to the brief instants when the propeller blades were in a horizontal position and out of the line of fire. The Germans had the inside track on Fokker's invention and enjoyed a brief advantage—until British and French engineers duplicated the device.

Both sides continued to experiment with new ideas in aircraft weapons, but the synchronizer was the only development that really


made itself felt in actual combat. All efforts to mount heavier guns, for example, were inconclusive. The British started work on an automatic one-pounder cannon, but the war was over before much progress had been made with the design. In 1917 the French Hispano-Suiza company brought out a short-barreled 37-mm. gun mounted in the notch of a V-type engine and firing through a hollow propeller hub.

This gun was a single-shot type, and thus completely lacking in true air fire power, but its mount was exceedingly well thought out, and variations of it are used today in cannon-firing planes.

The Germans, meanwhile, had worked on

FIXED OR FLEXIBLE GUNS?

Fire power of fixed guns on fighter planes is concentrated into a slash of steel in front, where the pilot controls it by maneuvering. Flexible guns, as on the bomber pictured below, give varying degrees of protection in all quarters. The fixed gun is primarily for offense; the flexible, for defense



A PHOTO HISTORY OF AIR ARMS


a Becker 20-mm. gun with a 12-shot magazine. It never was very successful, and after the war the owner sold out his patents to the Swiss Oerlikon firm. What happened later is an interesting example of how military designs circulate. Oerlikon continued to develop the design, and later sold patent rights to Hispano-Suiza. The French firm, in turn, passed its designs on to the British. Later the United States took it over, modified and improved the design, and is now using a so-called Hispano 20-mm. in some versions of the P-38 Lightning and P-39 Airacobra fighter planes. The Germans also have a short-barreled Oerlikon FF model, but are known to be replacing it with a high-velocity Mauser 20-mm. gun.

Our own ordnance experts carried on numerous experiments during World War I, one of them involving the Davis "no-recoil" gun, an unconventional weapon of about 2¼-inch bore. It was recognized that the element of recoil was one of the biggest limitations to the firing of powerful guns from aircraft. The Davis gun tried to solve this by discharging a dummy slug or a load of shot backwards from its elongated breech at the instant the actual projectile was fired from the muzzle, so that the counteracting forces balanced each other and eliminated recoil at the gun's mount.

Army ordnance even considered using a five-inch gun of this type, but after thorough tests the Davis gun was discarded, mainly because it could not be aimed quickly and because the breech discharge was found to be just about as dangerous to near-by friendly aircraft as its projectile was to the enemy. Later a light 75-mm. mountain howitzer was prepared for plane mounting, but was never test-fired.

America's greatest progress, however, was made in the development of specialized aircraft machine guns, and the pioneer work was carried out by our "gun wizard," the late J. M. Browning, probably the world's greatest designer of automatic weapons.

Browning, the designer of the entire family of machine guns used by the U. S. armed forces, first concentrated on a .30 caliber aircraft machine gun, and produced a 22-pound, air-cooled weapon with a rate of fire of 1,200 shots a minute. It snaps out 150-grain bullets (about 47 to the pound) with a muzzle velocity of 2,750 feet a second. The same Browning design in a .303 caliber ver- *(Continued on page 212)*



FIRST GUN to be fired from a military airplane was a rifle in the hands of Maj. T. E. Fickel, U.S.A., in 1910. Aircraft's rôle seemed to be unarmed scouting



SYNCHRONIZED GUNS to fire through the propeller were a World War development. This is a Vickers aircraft machine gun mounted on a U. S. Navy airplane

WAIST GUNS were not unknown in First World War days, as this well-armed U. S. Navy flying boat testifies. The man on the wing is using an early turret





FIRST MACHINE GUN in the air also was a U. S. achievement. Here Capt. C. DeForest is taking a Browning ground gun aloft in a biplane in 1912




FIRING OVER WING. This fighter plane of World War I has a Lewis machine gun fixed atop its upper wing. It fired above the propeller arc



TURRETS and flexible gunnery were foreshadowed by this World War mounting of a Lewis ground machine gun. Power-driven turrets made their initial appearance about 10 years ago

FLEXIBLE GUNS have taken many forms in the course of their development. Below is a swivel mount that was tested experimentally by the Navy in the search for higher efficiency



WING GUNS came along with post-war experiment. This is a Browning .30 caliber on a U. S. Army plane (1925)


DAVIS CANNON fired a dummy load backward to eliminate recoil. Lewis gun atop this one helped to get the aim






World's Largest Building Cooled by Sun Control

Drawing by B. G. SEIELSTAD



THE sun cools, as it heats, the Army's Pentagon Building in Arlington, Va., (P.S.M., Feb. '43, p. 49). Passing over the vast roof of the world's largest building, its rays fall upon photoelectric cells in five roof-top control stations. Registering the temperature rise, each of these stations in

turn, by means of electronic relays and compression tanks, activates the fans of the cooling system. Designed by the Minneapolis-Honeywell Regulator Company and Charles S. Leopold, consulting engineer of the War Department, the system maintains a temperature of 77 degrees.



Making Lightning Behave

Newly discovered facts about nature's fiery blitz help to guard vital power lines and keep war plants humming.


WHEN your electric lights used to go out, during a thunderstorm, it was just one of those things that couldn't be helped. Nowadays, they stay on. More important, power interruptions that once wrought costly havoc in industrial plants have been virtually ended. Electric motors that turn the wheels of vital war industries keep on humming.

Engineers have learned how to tame lightning. Primarily their aim has been to


safeguard electric service. But their researches have found equally practical application in protecting persons and buildings from nature's pyrotechnics. Weather forecasting and aerial navigation, too, have shared the benefits.

Using a high-speed camera in South Africa, a modern pioneer, B. F. J. Schonland, has literally turned upside down the popular conception of a lightning stroke—and added fascinating embellishments for good measure.

Only tall masts and skyscrapers, he finds, get hit by bolts from the clouds. Between low objects and a cloud, a lightning stroke actually travels upward! But a path has already been made for it by a hitherto unknown kind of downward electric discharge



Just as the rain returns evaporated moisture to earth (left), lightning returns electricity leaking up to the clouds at the rate of 300,000 kilowatts



1. "Pilot streamer" traveling at 500,000 feet a second, starts toward positively charged earth

that he describes as a "pilot streamer."

From a negatively charged center at the base of a thundercloud, the faintly luminous pilot streamer launches itself at the positively charged earth at the comparatively leisurely speed of about 500,000 feet a second. As if to hammer it along, stronger and faster-moving electric discharges, called "step leaders," pulse down to its advancing tip in rapid succession. The combined effect ionizes, or makes electrically conductive, a pencil-thin path through the air.

When the pilot streamer reaches the earth, the fireworks go off. Back along the path it has blazed, to the cloud, crashes the dazzling flash that the man in the street calls lightning. If the pilot streamer has branched on its way to earth—as it is likely to do over uneven terrain—the return bolt follows out and neutralizes the branches as

well as the original charge center in the cloud. The brilliant discharge travels at about 100,000,000 feet a second, or less than one seventh of the speed of light.


Quite likely the performance has not ended. Another charge center in the cloud may "short-circuit" to the path already set up, and launch a nonbranching "dart leader" to earth, evoking a second lightning flash in response. This continues until the cloud is wholly discharged. As many as 22 successive strokes have been observed in a multiple flash. Since the entire exchange takes place within a fraction of a second, and all discharges follow exactly the same path, the series appears to the eye as a single flash.

A tall structure like New York's Empire State Building, in contrast, usually launches a pilot streamer at a thundercloud and receives a bolt of lightning in return. The steel framework carries off the stroke harmlessly to earth.

Tests with man-made lightning in high-voltage laboratories confirm the new discoveries about natural lightning. For most practical purposes, it has



Man-made lightning, directed at this model house, is shown being harmlessly diverted to earth by Dr. McCann's lightning "umbrella." At far left, the same model, when struck without umbrella protection, instantly bursts into flames



2. When streamer hits the earth, lightning flashes back along same path at 100 million feet a second

3. Second negatively charged area, unaffected by the first flash, now "short-circuits" to positive area

4. Following path already set up, second area sends "dart leader" to earth—to evoke a second flash

been found, skyward and groundward thunderbolts differ little in effect. Therefore it remains customary to speak of lightning as striking the earth—a convention that will be followed in this article—even though the opposite may be the fact.

On the whole, thunderbolts do far more good than harm. A stroke of lightning captures nitrogen from the air, "fixing" it in beneficial compounds that raindrops bring to earth. The result is to shower all growing plants with more fertilizer than the combined output of all the factories in the world.

True, there are fifth-column lightning bolts, too—but science is showing how to cope with them and disarm them. A "lightning locator" under recent development reveals the course of an oncoming electric storm as accurately as secret war instruments plot the approach of raiding planes. This enables workers in an ordnance plant to keep up full-speed production until the last moment, when the storm enters a pre-calculated danger zone surrounding the factory. Then the personnel leave the buildings, and return only when the thunderstorm has reached a safe distance.

How far is a safe distance? By measuring electric and magnetic fields around a lightning bolt, experimenters recently have discovered that it need not score a direct hit to start a fire or cause an explosion. A "near miss," as in bombing, may prove as effective. Tests show that a lightning stroke as far as half a mile away may induce a small electric spark between near-by metal objects.

Hitherto unexplained fires in wooden barns are now believed to have been started in this way.

A man driving a modern steel-top car in a thunderstorm is in about the safest place he could be. Its metal body almost completely encloses him in a "Faraday cage," proof against exterior sparks. Any doubt on this score vanished from the minds of spectators who watched Dr. Gilbert D. McCann, Westinghouse lightning expert, seat himself at the driver's wheel of a standard car and submit to a 3,000,000-volt bombardment of man-made lightning from a sphere above. Harmlessly the flash leaped from the metal work over one of the front tires to the ground.

"Lightning umbrellas," recently designed by Dr. McCann, are believed to represent the first radical departure from conventional lightning rods in nearly 200 years. These are intended especially for ordnance plants and oil storage centers, and a number of large-scale installations have already been made.

The simplest plan consists of stringing a single length of steel wire, resembling a radio antenna, above the entire length of the building. From wooden poles that support the horizontal wire, its ends are then brought to earth and grounded. An alternative scheme surrounds the structure with a series of masts bearing projecting and grounded wires. The number of masts varies according to the area to be shielded. How well the systems work has been amply demonstrated by subjecting models to re-

peated strokes of laboratory lightning.

For farmhouses, barns, churches, and other "nonhazardous" buildings, experts agree that the time-honored lightning-rod system still offers first-class protection from lightning, assuming it to be properly installed and grounded. How this should be done is explained and illustrated in Farmers' Bulletin No. 1512, available for five cents from the Superintendent of Documents, Washington, D.C. Copper wire as large as No. 2 A.W.G. (about one quarter inch in diameter) was often used throughout, in prewar days of plenty. Tests now show wire of this size to be needed only where it is likely to be struck directly and burned by lightning. The rest of the system may employ No. 6 A.W.G. wire (about one sixth inch in diameter) to conduct the lightning current safely between these points and the ground. The smaller size saves 60 percent of the copper formerly employed.

Heaviest of all recorded thunderbolts, Westinghouse engineers say, was one that struck a 585-foot smelter stack at Butte, Mont., in the summer of 1940. Its current totaled more than 160,000 amperes of electricity, delivered at a pressure exceeding 15,000,000 volts. Nevertheless, it did no damage, for it streaked to earth along a prearranged channel, writing its life history on the way.

Called a "fulchronograph," the instrument that has measured the power of this and many other lightning strokes applies the principle that hard steel will be permanently magnetized by current passing through adjacent coils. In practice, two coils carry a portion of current diverted from the lightning stroke being measured. Rotating past them, an aluminum wheel bears 408 steel fins on its rim. The particular fin that happens to be passing the coils at a given instant is magnetized in proportion to the punch of the lightning, during 40/1,000,000 of a second. Then the next fin takes over the recording, and so on. Studying the pieces of steel at their leisure, Westinghouse men are able to reconstruct both the duration of the bolt and its variations in

strength from one instant to the next.

Grounded shielding wires, erected parallel to power lines, now intercept lightning strokes and guide them to earth before they do harm. Foot-high models, exposed to 15,000 strokes of artificial lightning, showed the best place to put the shielding cables—above and at an angle of about 30 degrees outside the power lines. Most troublesome are low-flying thunderclouds, about 500 feet from the ground, which have the best chance of flinging a sideward bolt that will "duck" the protective wires. Many lightning bolts, on the other hand, originate in clouds five miles high.

Today, about 6,000,000 lightning arresters stand guard over the nation's power lines, just in case lightning actually does strike them. The smallest, no bigger than cigarette lighters, protect railway signal lines and fire-alarm systems. The largest, 30 feet high, guard huge generators in hydroelectric plants—and are "earthquake-proofed" by being suspended from cables above the earth. These arresters act in the same manner as safety valves.

Automatic circuit breakers, serving like switches to open and close a circuit, provide the final line of defense against a lightning stroke on a transmission line. In your home, a fuse or a small switch will shut off the electricity, because the power passing through the wires is relatively small. But in power stations and substations where the power is high, neither fuses nor even big switches will do. In case of a short circuit or a surge of current caused by lightning, the power would get out of control, and leap through the air in a destructive arc.

A new circuit breaker developed by Westinghouse engineers literally blows out this electric fire with a blast of compressed air exceeding the 750-mile-an-hour velocity of sound, while pistons yank the metal contacts apart. Another type snuffs out the arc with magnetic force. Superseding conventional breakers, immersed in tanks filled with insulating oil, the new designs save steel and oil for war use.—ALDEN P. ARMAGNAC.



Dr. Gilbert D. McCann, one of the developers of the instrument, is shown at right examining a fulchronograph. Porcelain column at left is a lightning arrester, which guards power lines by grounding any lightning that may hit them

Tricks with Figures

By E. J. DINTRUFF

VARIETY is also the spice of figures. If numbers seem dull, very likely you have approached them in the same unvaried way too long. Try these strategic attacks.

In multiplying by five perhaps you subconsciously annex a cipher and then divide by two. But do you know that to multiply by 25 you may add two ciphers and divide by four; or to multiply by 125 you add three ciphers and divide by eight?

To multiply by 11, annex a cipher and add the original to the newly formed. Or put down the last digit of the original number, then to the left place the sum of each digit plus the one to its left, setting down each time only the unit figure, and carrying the figure representing the tens. Multiplying by 111 can be done in a similar manner. (See below.)

To multiply by nine, place a cipher before and after the number. Now subtract each figure from that to the right of it, taking care to borrow when the next figure is too small.

At times, multiplying is an easy way of dividing. Just as to divide by five you may multiply by two and set off the last figure by a decimal point, to divide by 25 you can

$$\begin{array}{l} 137 \div 125 \\ \textcircled{A} \text{ MULTIPLY BY 8} \\ 137 \times 8 = 1096 \\ \textcircled{B} \text{ SET OFF LAST 3 PLACES} \\ = 1.096 \end{array}$$

To divide by 125, multiply by eight and set off three places. To multiply by 111, set down the last digit, then the sum of the last two, that of the last three, then the next three, and so on

18	9	6	3	2	1
18	9	6	3	2	1
19	10	7	4	5	4
20	11	8	5	8	7
21	12	15	12	11	10
22	13	16	13	14	13
23	14	17	14	17	16
24	15	24	21	20	19
25	16	25	22	23	22
26	17	26	23	26	25



Figures are fun, too. Let a friend choose a number and tell you in which of these columns it may be found. Add the numbers at the heads of the columns he designates and you get his number. (From "Mathematical Recreations," by Maurice Kraitchik; W. W. Norton & Co., New York)

multiply by four and set off two figures. Similarly, to divide by 125, multiply by eight and set off three places.

In adding, attack a double column on the left flank instead of the right. Add the figures on the left, put down that representing the tens in your total; to that representing units, annex a cipher and add the figures in the right column. Put the results to the right of the figure already set down.

The same left-flank approach can be made to subtraction. Keep glancing ahead one column to allow for borrowing. Subtracting 72931 from 89068, take 7 from 8; then 2 from 8 (since one must be saved for borrowing); 9 from 10; and so on.

$$\begin{array}{l} 57263 \times 111 = \\ \textcircled{G} \quad \textcircled{F} \quad \textcircled{E} \quad \textcircled{D} \quad \textcircled{C} \quad \textcircled{B} \quad \textcircled{A} \\ (5+7)(5+7+2)(7+2+6)(2+6+3)(6+3) \\ 6 \quad 3 \quad 5 \quad 6 \quad 1 \quad 9 \quad 3 \end{array}$$




Why "DE" Boats Are Death

CLEAN-LINED and businesslike, Uncle Sam's new destroyer escorts (P.S.M., July '43, p. 110) are pounding the high seas in good weather and bad, helping to crush the submarine menace and maintain the vital flow of troops and munitions to the theaters of war.

A comparatively new type of vessel for the U. S. Navy, the 1,300-ton DE is a highly developed cross between the British cor-


vette (which U. S. Navy men rate as too slow and too lightly armed for general use) and the standard destroyer (which is complex, costly, and slow in building). The DE combines a fair amount of the destroyer's speed and hitting power with the corvette's simplicity, low cost, and speed of production; it is an ideal warship for protecting merchant-ship convoys. Each DE has dual-purpose guns and depth charges to fight sub-



to Subs

marines, machine guns and anti-aircraft guns to beat off low-flying planes, and torpedo tubes for use against surface raiders.

Our drawing by Stewart Rouse illustrates construction and equipment. Official U. S. Navy photographs show (upper left) one of the scores of new DE's sliding off the ways of a Texas shipyard and (lower right) dual-purpose and AA guns as seen from the bow of another of the novel craft.



GERMAN PILOTS RENAMED IT:

"Gabelschwanz

(FORK-TAILED)

Our P-38 Lockheed Lightning has taken on the best in the Axis stables . . . and proved it's a lot of plane in any language

By ANDREW R. BOONE

THE U. S. Army prosaically called its new fighter-interceptor "P-38." Lockheed Aircraft engineers and test pilots called it "Lightning," and that name stuck with the combat pilots who flew it. And now the Germans have a word of their own for this twin-engine, twin-boom aerial destroyer. Nazi pilots shot down and captured in recent operations bitterly referred to it as that "*Gabelschwanz-teufel!*"—fork-tailed devil!

But under any name at all, it's a lot of combat airplane—one of the fastest, highest-flying, hardest-hitting ships ever turned out. For all-around versatility and power the P-38 is in a class by itself. It has been used successfully as a fighter, interceptor, bomber escort, bomb carrier, low-level strafing and tank-buster, long-distance reconnaissance ship, and high-altitude photographic plane.

Performance on most of the major battle fronts has shown the Lightning to be equally effective flying from hastily carved-out jungle fields in the far Pacific, from cramped and rocky fields in the Aleutian Islands, from the sandy wastes of North Africa, and from the mist-bound runways of England. One of its most important services was to make possible American daylight bombing raids over Germany. The Lightnings provided fighter escort at high altitude hundreds of miles from the home bases, fending off enemy attacks over the target area for as much as an hour, then accompanying the

bombers on the dangerous return flight and seeing them in to a safe landing.

P-38's didn't swing into action as soon as the United States was plunged into the war. Our enemies unquestionably knew that we had a ship of this unconventional design in the works, but they couldn't know much about its performance and fighting characteristics. Wise military strategy in a case like that dictates that the new weapon be withheld from action until it can be assembled at the proper places in quantities large enough to take maximum advantage of its surprise punch.

Squadrons of Lightnings were organized first in the Pacific area, then others were sent to England, and finally the plane emerged in North Africa as our main fighter type for that theater. The ship has been a thumping success in all three theaters of war.

Probably the first official combat involving P-38's was in the Aleutians, when the fork-tailed ships suddenly popped out of a cloud and shot down two Japanese K-97 four-engined flying boats and two escort fighters. Even more significant than the victory itself was the fact that this combat dispelled a notion that the Lightning was a high-altitude ship, unable to perform at lower levels. There isn't any high altitude to speak of in the fog-shrouded Aleutians.

Even more spectacular in result was the Lightnings' first battle with the Japanese in New Guinea. Twelve of the P-38's ran into a much larger enemy group, including some seven "Val" dive bombers and an escort of 25 or 30 fighter planes—"Zekes,"



Teufel"

DEVIL)

WHAT YOU SHOULD
KNOW ABOUT OUR
FIGHTING PLANES

"Haps," and "Oscars." (Zeke and Hap are the two current versions of the well-publicized Jap Zero fighter; Oscar is another fighter plane, the Nakajima 97.) The Lightning pilots shot down 15 enemy craft and damaged several others which probably didn't get back to their bases. None of our pilots were injured and only one of the planes was damaged.

The P-38 had another brilliant debut in North Africa, one squadron destroying 15

enemy planes in the first day's operations over the Gabés-Sfax area of Tunisia. Later the planes went on important ground-strafting missions and knocked out 11 tanks in two days, along with much enemy transport, including trucks, armored cars, and motorcycles.

The Lightning has fought it out there on even terms with the very hottest enemy fighter planes, among them the German Messerschmitt 109, 110, and 210, and the Focke-

Wulf 190. American pilots swear by their ship, and vow it is the best pursuit job in action there.

This actual battle experience has served to dispel some of the doubts airmen and Army men felt about the P-38 design when it first

FIRE POWER. The P-38 carries its sting in its nose, with four .50-cal. machine guns clustered around a 20-mm. cannon. The result is a concentrated slash of bullets and explosive (lower left)

Here's what the 20-mm. cannon can do. In this test, projectiles have punctured a one-inch steel plate after passing through 20 inches of planking and 12 inches of sand to hit it




Teammate of the Flying Fortress: Long range of the P-38 enables it to escort the big bombers on their sweeping raids

became known. To sum these doubts up: Wasn't it too big—"just too much airplane for one man?" Wouldn't it lack fighter-plane maneuverability? Would that open-work twin-boom construction have the strength to stand up and take the punishment of military operations? And wouldn't that same construction make it impossible for a pilot to get out safely in a parachute if the occasion arose?

The answers have come along fast under war conditions. The P-38 is beyond any doubt a first-class one-man fighter ship. As for its maneuverability, some of the American pilots in North Africa were so enthusiastic they told correspondents they could turn inside a Spitfire. Their testimony naturally must be taken with at least a grain or two of salt; other factors being approximately equal, the smaller and lighter airplane always should have greater maneuverability than the larger and heavier one. And the huskiness, power, and long range built into the Lightning must have required some slight sacrifice of other characteristics. Nevertheless, the battle performance of this P-38 against Germany's best ships is proof that it has maneuverability enough to play in the big league of air warfare.

The question of parachuting from the ship was tricky, but it has turned out that the trick can be done. A pilot can bail out either by flipping the ship over on its back and dropping from the open hatch, or by putting it into a stall and stepping back and down into the space back of the cockpit and between the twin booms. This may sound complicated, but it is not a simple operation to bail out of any hot ship, and the bailer always must follow a prescribed technique to avoid the fast-moving tail and elevator surfaces.

There remained the question of the ship's strength, and a big part of that was whether



the twin-motor arrangement wasn't a real weakness—just two things to get hit or go wrong. The growing list of Lightnings that have come in all right on one engine has set that point at rest; in fact, the climbing powers of the ship with an engine out of action have been a delightful surprise to more than one hard-pressed pilot.

As for the structural strength of the plane, startling proofs of that came in recently from battle areas half the world apart. Over New Guinea Lieut. Kenneth C. Sparks, of Blackwell, Okla., got into a tight dogfight with a Zero, and here is what he reported:

"Our right wing-tips hit, spinning the Zero around so that its propeller struck the trailing edge of my wing. He went down smoking and I kept on going."

Lieutenant Sparks admitted it was a tough jolt, but he was unhurt and his plane showed no damage except for a slight chewing up of that wing.

Around the same time, a group of Lightnings went out on a strafe in Tunisia, and pressed their attack home on one enemy airfield at such a low altitude that one of the ships knocked over a telephone pole. Capt. Mark Morne, of Hinsdale, Ill., in charge of the operation, reported laconically:

"Fortunately the accident only dented a wing of the plane, and he returned safely."

Airplane designers don't advise using their ships for disrupting enemy communications in quite such a direct manner, but it doesn't hurt pilot morale to know that you can get

away with it if the occasion should arise.

Nothing very much like the P-38 had been tried out up until 1937, when the Army called in the nation's plane makers to study specifications for a new fighter aimed primarily to intercept any air raiders that might approach our coasts. Speed, range, and fire power were the prime requisites. The Lockheed company didn't have much military background, but Hall Hibbard, chief engineer, and C. L. Johnson, chief of design, thought they might have the answer in their private notebooks.

From the beginning they planned on a twin-boom, twin-engine ship. Twin engines would give added power and added safety, in case one power plant failed, plus better vision for the pilot and a chance to incorporate heavy gunpower in the nose without getting into the technical problem of synchronizing the guns to fire through a propeller arc.

Twin booms promised excellent control plus improved streamlining—a notion which worked out so well, by the way, that the present model, with its tricycle landing gear retracted, presents no greater drag than a card table 27 inches square.

The first ship began its flight-testing on December 30, 1939, and a few days later made a hop from California to New York in which it loafed along at never better than two-thirds throttle, made two stops for fuel, and completed the run in seven hours, 45 minutes.


(Continued on page 206)

They're fighting for our allies, too. Here another Lightning, wearing the insignie of the R.A.F., flies to meet the best the Nazis can put up against her. The bulges on the tail booms are air scoops for cooling



"Sinking" a Floating Island

A LARGE floating island, 400,000 square feet in area and one to eight feet thick, was removed from a reservoir of the New York Power Corp. near Potsdam, N. Y., by cutting it up into sections and pushing them over the impounding dam. Cut while frozen, the 16 sections were held by cables until spring.



ABDOY
GRIFFIN

ARMY GETS NEW SNAKE-BITE KIT

U. S. soldiers serving in jungle or desert country can give themselves immediate first aid, in case of snake bite, with a compact outfit being supplied to the Army by the Saunders Venom Extractor Co., Tarpon Springs, Fla.

Complete equipment for treatment of snake bite is contained in a water-tight plastic case 4½ inches long: The pump nozzles permit use on both large and small areas

- 1 Plastic container
- 2 Plastic pump
- 3 Suction nozzles
- 4 Tourniquet
- 5 Boric compresses
- 6 Ammonia inhalants
- 7 Lancet and cap
- 8 Iodine applicators



JUNGLE BOOTS, developed by Army officers working in collaboration with designers of the U. S. Rubber Co., are now being issued to our troops in place of regular G. I. leather boots, which have proved impractical in tropical climates because they disintegrate rapidly in damp weather, do not provide sufficiently sure footing, and are inclined to be uncomfortable. Camouflage-green canvas tops, designed to protect the ankles against tropical undergrowth, make it possible for the new boots to withstand repeated soakings and dry out quickly. Heavy, cleated rubber soles guarantee a firm footing even in mountainous regions. Equipped with duck insoles which are easy on overheated feet, the boots can be pulled on or off quickly by means of a special lacing—one lace for the instep and another for the legging, which also permits the boots to be worn partly open, providing ventilation when needed and adding to the soldier's comfort in hot climates.



RANGE-ESTIMATION trainers are teaching our air gunners exactly when to pull the trigger in actual combat. Looking through an iron-ring sight, the gunner, by means of a series of mirrors, is shown a model enemy plane. Mounted on a carriage, two of the mirrors are moved back and forth to make the model appear at distances ranging from 150 to 1,000 yards. Knowing the actual plane's wing span, the gunner, by a quick computation, determines how much of his sight the plane will fill at given distances. Trick is to tell when plane is at 600 yards—the best range for machine guns.



GROUND-TRAINING DEVICES TEACH FLYERS THEIR JOBS


Mechanical devices that save time, materials, and lives are used by the U. S. Army Air Forces Flying Training Command to prepare our air fighters for the test of actual combat.

TRAINING FILMS, prepared by a special Army unit, are speeding up the education of cadet flyers in the techniques of take-offs, landings, night flying, cross-country navigation, and "bailing out." Where it is impractical to "shoot" the actual subject matter, as in enemy-aircraft identification, scale models are carefully "posed" over simulated terrain, as shown in the picture at the right, and photographed.




MARKSMANSHIP training for air gunners is done by means of a lamp (right foreground at left) which throws a moving spot of light on the wall while the student, at upper left, "tracks" it with a photoelectric-cell gun mounted between the turret's two machine guns. Even when off duty, gunners practice on electric-eye guns installed in recreation rooms (below).






PICKABACK GLIDERS that would lend heavily loaded bombers and big transport planes additional wing surface and so help them, during the take-off, to get into the air faster, have been proposed by Vadim S. Makaroff, of New York. As soon as the big plane has reached a safe altitude, the glider detaches itself and returns to the airdrome.

SHAPING BOMB NOSES electrically is said to be improved by the apparatus diagrammed below and developed by Warren F. Heineman, of Milwaukee. A set of dies, made up of three electrodes, is forced against the partly finished nose of a bomb shell, which is made to spin in a revolving chuck. A heating current is then introduced into the bomb nose by the electrodes, and as the metal gradually softens it is formed by the pressure of the electrodes. An automatically controlled current provides graduated heating as the nose advances into the dies.




GRENADE SLINGS that would make it possible for these small bombs to be thrown much farther than when tossed directly from the hand, have been designed by R. A. Dobbelaar, of Plainfield, N. J. The sling, actually a cloth bag in which the grenade is placed, has a drawstring in the loop of which is a large wooden or plastic ball that rolls easily off the hand. This prevents the possibility of the string becoming entangled in the thrower's fingers.

IDEAS




When pilot's hand leaves the stick, hydraulic servomotors actuate the flying surfaces to pull plane out of a dive or dangerous mismaneuver




AN EMERGENCY PILOT that pulls a plane back to level flight if something happens to the human pilot is saving the lives of British airmen. Unlike the ordinary automatic pilot, which is set to keep a plane flying straight and level, the new pilot automati-

cally takes over from whatever position the plane may be in at the moment the human pilot releases the controls. In big bombers, this assumption of control gives other members of the crew enough time to take the stick if their pilot is incapacitated.



HEMISPHERICAL WHEELS are the innovation and the chief principle of the “Roller,” a new amphibian combat vehicle designed by the Greek engineer Elie P. Agnides, of New York City. Two big, ribbed, hemispherical front wheels and a spherical trailer wheel in the rear, all three empty and watertight, make the “Roller” agile on land and buoyant in water. A substitute for the tank, it will carry high-powered armor-piercing guns. Intended for combat, reconnaissance, and sea-borne invasion, it is designed to have automobile speed, to negotiate difficult terrain as well as a tank, to swivel as easily as an office chair, and to right itself automatically if upset. In mud, sand, or snow it offers greater traction surface for less penetration; in water it will both float and propel itself.



How a Violin is Made

Searching Out the Secrets of Old "Strads," American Craftsmen Now Produce the World's Finest Fiddles

TO MOST violinists, how a violin is made is something of a mystery. They know that there was once a golden age of violin making in Italy, when Stradivarius astounded the world with his instruments. And they think that age is gone forever. Actually, however, the skill and ingenuity of American craftsmen, some of them amateurs, have brought about a rebirth of the craft. We're making "Golden Strads" right here—today.

One thing that has helped is a discovery by Christopher E. Mertzanoff, of New York, an American business man and amateur violin designer, of what appears to be the secret of the proportions of Stradivarius violins. It is a geometrical equation well known to Renaissance artists and artisans and simple enough for any high-school freshman to understand. The formula is the "sectio aurea" of Leonardo da Vinci, who had died more than a century before the master violin craftsman was born. Because he found that the formula fits all the features of the Stradivarius top and back, Mertzanoff calls it, and the designs based upon it for

making modern violins, "The Golden Strad."

Stradivarius and his contemporaries probably had no intention of keeping their craftsmanship a secret. Certainly they trained scores of apprentices and taught many pupils all they could. Yet somewhere the way of making these master violins was lost. For two centuries the best violin makers of Europe floundered about with futile searching after illuminating autobiographical details and unworkable formulas, and they produced only inadequate imitations. They could not equal the tonal qualities built into violins by the Italian master craftsmen.


Unhampered by tradition, American designers of the past 20 years have attacked the problem in a scientific manner. Realizing that the beautiful tone of the Stradivarius results not from the aging of wood, but from some wise or fortunate combination of shape, proportion, wood grain, and even varnish, they have focused the eye of science upon each one of these in turn.

The shape of the Stradivarius had been traced and retraced in violin





A VIOLIN'S PARTS

1. Sliced maple for back
2. Sliced spruce for top
3. Neck and scroll
4. Sides or "ribs"
5. Reinforcing blocks
6. Linings for ribs
7. Decorative purfling
8. Bass bar
9. Sound post
10. Maplewood bridge
11. Strings
12. Tuning pegs
13. Top nut
14. Finger board
15. Tailpiece
16. Heavy gut
17. Tailpiece saddle
18. Tail peg
19. Chin rest



Front and rear views of a violin made from C. E. Mertzanoff's "Golden Strad" formula. The instrument is made of "Wesmeraged" wood—produced by a secret process which transforms ordinary green lumber into the equivalent of thoroughly seasoned wood





.. Underside of the top of
244-year-old Stradivarius
shown at a time of repair.
Halk markings indicate
one thickness in millimeters
if the plate at those points

.. This diagrammed formula
if the top or back of a per-
fect Stradivarius, developed
y C. E. Mertznanoff, has
roduced a number of ex-
ceptionally fine instruments

.. Violin making starts with
lluing reinforcing blocks to
orm, and then gluing the
ix preformed ribs to the
locks. Clamps hold the ribs
rmly while the glue dries

pattern making. Not
content with the casual approxima-
tions of tracings, Mertznanoff set himself
the task of ascertaining the mathematical
formula which he felt must have determined the
violins of the great Italian craftsman. His inquiry resulted
in the discovery that the Da Vinci formula of the "golden
section" fits exactly the proportions of the Stradivarius violin.
In this formula the whole is divided into two unequal parts, with
the smaller part having the same mathematical relation to the
larger as the larger has to the whole.

The discovery of the Golden Strad formula is only the beginning
in the vast field of violin acoustics. Mertznanoff is now making a
study of dimensions and positions of the Stradivarius sound holes.
He is also engaged in a scientific investigation into the acoustical
properties of various woods, and with Jack Westall, of Asheville,
N. C., is experimenting with a secret process for transforming
green lumber into the equivalent of long-aged wood which they
call "Wesmeraged" wood.


Indicative of the boom in American violincraft is the exhibition,
recently held at the New York store of the Rudolph Wurlitzer
Company, in which instruments valued at \$100 to \$800 and
carved by some 92 American makers were
played and examined with interest by such
master musicians as Fritz Kreisler and
Mischa Elman.

The violin is still




7. Back is now glued to ribs, which have been
fitted with "lining" to offer more gluing surface

9. Decorative purfling, to keep plates from crack-
ing, is inserted in groove running around edge



8. Ribs and back are removed from form, and
blocks are cut to shape. Lining is made ready for top

10. Calipers are used to check thickness of plates,
whose undersides have been carefully scooped out





the work of craftsmen.

The wood for its making must be chosen with an eye that knows the grain that will produce beauty of tone; the top and back must be cut and scooped out with the craftsman's hand. Every part in the delicate process of making a beautifully toned violin calls for the keen eye, the trained hand, and the comprehensive mind of the expert. It calls for the personality of the artist, too—the patience, the perseverance, and the devotion of the man who works from an inner ideal. No amount of blueprinting has been able to make of the violin an assembly-line job.

Among our best American craftsmen is Carlton F. Stanley, of Newton Center, Mass., whose work is shown on these pages, and who learned his art from his uncle, F. O. Stanley, one of the inventors of the Stanley Steamer automobile. This uncle had learned the art in his boyhood from his grandfather, Liberty Stanley, born in Maine on July 4, 1776, who had taken up violin making as a hobby in his old age. Carlton Stanley's violins are played in many of our leading symphony orchestras.

American violins have not as yet attained the mellow tonal qualities of the best work of the Italian masters, but they display a sweetness and freshness of their own that surpass those of other violins of modern times and even of many of the much-sought-after older instruments. Although the amateur may still cling snobbishly to the old violin merely because it is old, the master violinist of our time, the concertmaster, and the other musicians in the string sections of our best symphony orchestras have discovered the merits of the

American craftsman's violin. These men know that old violins are not all good, that centuries of aging will not make a good violin out of a bad one, and that the virtue of a good violin lies now, as ever, in design and workmanship.



4. Outline of the ribs is now traced on flat-planed, two-piece maple billet, which is then properly trimmed. Note that the neck slot has been cut in block shown at right

5. Rough cutting the arch of the "plate" (which may be either a violin's back or top, as both are made in the same way) is done solely by eye with a small hand plane

6. To achieve precise curvature, however, the carver must use templates. Shown here is one of a set of 13, which duplicates the curves of the Archinto Stradivarius


Photos by I. N. Brennan from Black Star



11. With "F" holes cut, bass bar is glued on a bit off center, and then sandpapered




12. After neck has been fitted exactly, sound post, finger board, nut, tailpiece, and pegs are put in place



13. Tuning up is an exciting moment, for no craftsman knows how a violin will sound until he puts a bow to its strings

HERE is your life stream spread out in a circle. Those disks in the outer ring are red corpuscles and other cells in the blood. The six organs in the center aid the blood cycle.



Saving Lives with Blood

The Pint You Give to the Red Cross Is Packed Full of Curative Agents for Healing the Sick and Wounded

DOCTORS once bled patients to cure them, thinking blood contained "ill humors" that made them sick. Today doctors bleed blood donors to cure others, for science has learned that human blood contains a whole warehouse of curative agents. Plasma for transfusion is only one of a dozen blood products now in use. Blood has become a

major strategic weapon—to help save lives.

A donor who contributes a pint of blood is giving about one fourteenth of the amount in his system. In a person of normal health that pint is replaced within a few days, for the manufacture of blood is a basic function of the body. The red bone marrow, where the red blood cells originate, can make

By HAL BORLAND

10,000,000 cells a second. The average person's blood contains trillions of these red cells; but even that astronomical quantity can be replaced in about 15 days.


Human blood consists of approximately equal portions of corpuscles, or blood cells, and plasma—the river in which the corpuscles float. Plasma is about 92 percent water. In it are dissolved salts of sodium, calcium, potassium, and phosphorus along with albumin, other proteins, and fatty substances. All are important, not only in the blood's normal function, but in the curative products science can now extract from blood itself.

Floating in the plasma are several kinds

of white corpuscles, red corpuscles, and small colorless bodies called "platelets." The white corpuscles can pass through the walls of the capillaries directly into the body tissues; they are the scavengers and defenders of the body, consuming dead cells, waste products, and bacteria, and healing wounds. The red corpuscles, which cannot leave the blood vessels, carry oxygen from the lungs to the tissues. The platelets play an important part in clotting.

The red cells are like barges, simply making the rounds of the blood stream with their cargoes of hemoglobin, which gives them their color, absorbs oxygen in the lungs, takes it to the tissues, releases it, and is ready for another load when the red cells again pass through the lungs.


Nobody knows how red corpuscles are made in the bone marrow, but an excess of dead corpuscles seems to stimulate the production. Each corpuscle lives from 25 to 100 days and may make as many as 50,000 trips




Drawings by
John Gilmore

Man's blood circulatory system, shown above, is vastly complicated. Right, the human heart, from an illustration in "Man in Structure and Function," a two-volume treatise by Dr. Fritz Kahn. Blood flows through the heart in the direction of the numbers from 1 to 10. A magnified section of wall muscle is shown at A, a three-dimensional model at B, and an isolated single fiber at C. Special cardiac vessels (D) from the aorta surround even microscopic fibers with a compact network, as at E

Reprinted from "Man in Structure and Function," by Dr. Fritz Kahn; by permission of and special arrangement with Alfred A. Knopf, Inc. Copyright 1943 by Dr. Fritz Kahn.





Taking blood from a voluntary donor is a process lasting six to eight minutes. Each person gives a pint



Whole blood as it comes from veins



Red cells settle in centrifugation

Much is done with the blood before it can be given in a transfusion. Formerly typed according to its red cells so as not to cause clotting, it is now freed of these red corpuscles by centrifugation. Plasma is pooled, dried, and vacuum-packed. Transported then to the bottlefields, it is made ready for use simply by the addition of sterile water



Plasma from number of donors is pooled, dried

through the blood stream. When it wears out, it is eliminated as the blood passes through the spleen and liver. Most of its hemoglobin is salvaged, and the liver apparently parcels it out to the bone marrow. A reserve supply of new red cells stored in the spleen is picked up by the blood when needed.

Not all red cells are alike. Those in one person may agglutinate, or gather in clots, in the serum of another's blood. So before whole blood can be transfused, it must be typed and matched with the recipient's. If contrary types are mixed, agglutination may be fatal. But when the red cells are removed, plasma can be put in any other person's blood stream without ill effects. This is a reason for preferring plasma for transfusions.

There are several types of white corpuscles. Besides ordinary leucocytes that defend the body against infection, there are lymphocytes that carry the means of making a person immune to disease. When a person has a disease, lymphocytes acquire weapons to fight a recurrence. Though relatively few in number, they are extremely potent. Science is learning more about them every day and is beginning to put them to work.

Among the soluble proteins in plasma are fibrinogen and prothrombin. In the platelets and body tissues is a substance called thrombokinase. When tissues are broken, as in a wound, both tissues and platelets release thrombokinase which, with the calcium in plasma, changes prothrombin to thrombin. The thrombin in turn changes fibrinogen to fibrin, an insoluble mass of woolly fibers in which the red corpuscles are enmeshed like fish in a seine.

If only a vein is ruptured, the clot stops the loss of blood and the white corpuscles

repair the damage. If an artery is severed, however, outside help is needed, for the clot cannot hold against the direct thrust of the heart.

The heart is simply a pump, and, like all pumps, it must have something to pump or it cannot function. There are two ways in which blood pressure may fall to a dangerous level—a reduction of the volume of blood, as in a hemorrhage, and an expansion of the circulatory system making the normal volume inadequate, as in shock. In a hemorrhage, the volume must be restored to normal; in shock, the pressure must be restored. Transfusion may be required in either case.

Early transfusions employed animal blood, particularly that of sheep, and were usually fatal because the two types of blood would not mix. The next step was the use of salt solutions, with somewhat greater success. Then human blood was transfused, with far greater success after procedures were found for typing and matching. Finally came the relatively new use of blood serum, which has been highly successful. Fresh serum, shipped to England under refrigeration, saved thousands of lives during the blitz on London. Dried serum is a further devel-

opment that permits storage and shipment with a minimum of loss—it can be kept for five years, and dilution with sterile water makes it available for use anywhere.

Now an even better transfusion agent is being made from the serum itself—serum albumin. This extract is more concentrated, produces no adverse reactions, and requires a minimum of sterile water—an important factor in battle, particularly in desert or jungle. By its very nature, serum albumin prompts the body to supply the water needed to restore the blood to normal volume. The body can supply that water by drinking it, and potable water is always easier to get than water for injection.


From the serum also can be obtained fibrinogen and thrombin. By using these two substances separately, science has a new means of treating severe burns. The wound is sprayed with fibrinogen, then with thrombin. This forms a clot that normally becomes a scab and protects the area from outside infection, retains the white corpuscles that the body throws into the injured

tissue, and allows the wound to drain naturally.

Another plasma derivative is gamma globulin, which apparently contains the protective antibodies that enable lymphocytes to resist recurrence of a disease. About nine of every 10 persons have had such virus diseases as mumps, measles, and influenza. When donors' blood is pooled, the antibodies are distributed, and when the gamma globulin is extracted, it seems to contain a potent concentration of those antibodies, sufficient to immunize anyone to whom it is administered. On the basis of laboratory work, such injections will enable doctors to halt an epidemic of a virus disease in its tracks.

Until recently, red corpuscles removed in the preparation of plasma were a waste product. Now, however, a means has been found to use some of them in a poultice type of treatment that hastens healing of open wounds. Fresh cells suspended in a saline solution may also be used for treating anemia. There is laboratory evidence that the red cells can eventually provide protein for peptone, a usual constituent of bacterial mediums. Pathogenic bacteria grown on such a medium may serve as an improved starting point for the production of vaccines, toxoids, and antisera.

Both old and new uses of blood to save life have been brought to focus by the war, but work in that field is still essentially in the pioneering stage.




At the front, blood plasma is given to our wounded fighting men as in the photo at right, where the operation is being performed behind the lines in New Guinea. Dehydration of blood plasma, or serum, permits storage for five years or longer and also makes transportation possible, even over difficult terrain, with minimum loss. In New Guinea, Popuon natives carried the plasma to hospitals at the front



INSIDE THREE ALLIED TANKS

Internal arrangements of three leading United Nations tanks are revealed for the first time in these drawings made by G. H. Davis for *The Illustrated London News*. This trio will be right up front in the invasion of Europe.





ONE-ARM ATTACK. If a kick in the shins or instep isn't effective, grasp the mugger's arm above the elbow. Stepping far to the side, get a knee between his legs and throw him over your off shoulder. Then follow up in your own fashion.

How to Beat a Mugger

MUGGING attacks, many made just for the change in the victim's pockets, are becoming more and more common. If the mugger carries a knife or gun, it is foolhardy to resist him, but there are several ways of fighting off the unarmed assailant.

A mugger launches his attack from the rear. He may throw a forearm around the victim's throat and lock it there by grasping his wrist with the other hand, or he may use both forearms and hook his hands around his upper arms. In either case, the simplest countermeasure is to give him a good, hard kick in the shins or instep. The pain may force him to let go. If this doesn't work, you'll have to try something else.

The one-arm attack usually is accompanied by a hip-line push to get you off balance. Where the mugger's right arm is around your throat, move far to the right and work your left leg behind his right. Grasping his right sleeve just above the elbow with your right hand, throw him over your right shoulder. If he is too heavy for that, get down on your right knee and roll over on him.


For the two-arm attack, reach up and grasp both the mugger's shoulders. Step forward with one foot, bend low to throw him off balance, and toss him over your head.

An experienced mugger may forestall such tactics by placing a knee in your back. When this happens, hook one foot behind his and push back hard. Thrown off balance, he will probably release his hold to break his fall.

What you do next is up to you. Remember, the mugger is a desperate character, so don't worry about his feelings.

In all these maneuvers, power and speed are essential. You can practice with a friend—but don't follow through, or you may cause serious injury.

Drawings by
Frank Hubbard



TWO-ARM ATTACK is best countered by reaching up and grasping the assailant's shoulders. By stepping forward with one foot and bending over, you can throw him off balance and send him sprawling.



If a smart mugger puts a knee in the small of your back, hook a foot behind his and push him back. He may let go to break his backward fall.

Scientists Move Ahead




A SKY THERMOMETER for measuring the temperature of the upper air has been developed by Dr. Charles M. Heck of the University of North Carolina. An improvement over a previous model (P.S.M., Dec. '38, p. 99), the current version consists of a thermometer set in the innermost of 12 concentric aluminum cones. This arrangement, Dr. Heck has found, will record the heat in the upper air uninfluenced by temperature on the ground. Since the temperature of the air varies according to the amount of moisture it contains, the sky thermometer makes it possible to determine the moisture content of the atmosphere and its tendency toward cloud formation. Possible uses for the instrument in military forecasting are foreseen.



INDUSTRY

AUTOMATIC X-RAYS of castings or assemblies are made by this new General Electric machine. Parts to be inspected are loaded on a conveyor belt and moved into place under the X-ray unit, where a pretimed exposure is made. A lead-lined shield, surrounding the unit, protects workers from the radiations.



PUBLIC HEALTH

INDOOR SUNSHINE for war workers is provided by this high-powered quartz health lamp which irradiates ultraviolet rays. Accommodating 100 workers an hour, the industrial solarium builds up resistance to colds and fatigue, thereby reducing absenteeism and increasing efficiency on the job.



on Far-Flung Fronts




BACTERIOLOGY

LUMINOUS BACTERIA are being used by Westinghouse laboratories to test the use of the ultra-violet-ray Sterilamp in killing germs. Sprayed into the air under the lamp's rays, the harmless bacteria are caught on Petri plates, incubated, and examined in the dark, where their luminosity distinguishes them from other germs present in the air.



Dr. Harvey C. Rentschler, director of research, prepares one of the Petri plates



Far left, luminous bacteria. Left, same bacteria photographed by their own light




MEDICINE

BODY SOUNDS never before heard can now be picked up with this acoustic stethoscope developed by RCA technicians. With an adjustable range of 40 to 4,000 cycles, the instrument, besides detecting new sounds, amplifies louder ones to aid a physician in making a diagnosis.



"JAPANESE LOVE KNOTS" is the name for this finger-traction apparatus which distributes evenly the pull necessary to set a fractured arm properly. Designed by Navy technicians and made of fiber or straw, the knots grasp the fingers more tightly as tension on them is increased.



Captured Guns Reveal Their Secrets



GERMAN 75-MM. GUNS mounted on eight-wheeled gun carriages capable of traveling 50 m.p.h. were used as tank destroyers during the campaign in North Africa. The gun shown at the left was captured by American troops who later turned it against the enemy


GERMAN ANTITANK RIFLE shown at left below is the standard weapon for this purpose. The 7.92-mm. (.31-in.) Model Pz. B 1939 is a single-shot gun equipped with a folding shoulder extension and a bipod that folds up under the barrel. It fires an armor-piercing tracer that carries a small pellet of tear gas to be set off by the heat of impact

JAPANESE 20-MM. ANTITANK RIFLES are fired from the shoulder off a bipod, just like most similar weapons. The one shown below at right is fed from an eight-round magazine fitted on top, and is gas-operated. The Japs have a wide range of weapons that can be used against tanks, although only one, an .80 caliber air-cooled gun, is used exclusively for this purpose





"SQUEEGEE" is the name given this German antitank gun featuring a barrel with a bore that tapers from 28 mm. at the breech to 20 mm. at the muzzle. The bullet it fires is ringed with two soft iron or copper bands that give it the 28-mm. diameter as it is exploded from the shell. But as it travels through the bore, the rings are compressed to the smaller dimension at the muzzle, where they drop off. Purpose of this construction is to afford a larger area to build up pressure against in a chamber made gastight by the metal skirts. Below, a soldier at Aberdeen demonstrates the use of the telescopic sight



THE ENEMY HOPED TO STOP US WITH THESE WEAPONS, NOW BEING EXAMINED BY ARMY EXPERTS AT THE ABERDEEN PROVING GROUND

GERMAN 88-MM. GUNS, like the one shown at the right, were built for use against aircraft, but during the drive against the Maginot Line it was found that their high muzzle velocity would pierce armor, and this led to their use as antitank guns in Africa. Maximum horizontal range of the 88 is 18,000 yards; effective ceiling (at a 70° elevation) is 25,000 feet. Handled by a crew of six, it can be set up in 3½ minutes. Comparable U. S. weapon is the dual-purpose 90-mm. gun, which fires a heavier projectile farther

ITALIAN ANTITANK GUN. The 20-mm. Solothurn, shown below at right, is a self-loading weapon using the recoil system of operation that fires at the rate of 10-20 rounds a minute. The sights include a blade front sight and a leaf back sight graduated to 1,500 meters, in addition to a telescopic sight mounted on a bracket. Copied after a Swiss gun, the Solothurn is fed by a clip magazine capable of holding 10 rounds, but usually loaded with eight. Overall length, including the recoil reducer, is just over seven feet



WAR HOOKS THE



Photos by HAROLD W. KULICK

Now that his liver is worth nearly \$10 a pound, there's a price on his head and fishermen are going after him in earnest.

SHARK fishing is enjoying a boom. After the German occupation of Norway cut off our main source of cod-liver oil, researchers discovered that oil from the liver of the shark had an even higher vitamin content, with the added advantage of being odorless and tasteless. It is being given to pilots to aid night vision. The oil also has uses in the manufacture of cosmetics and as a cooking fat.

While the liver is the greatest prize, in some cases worth nearly \$10 a pound, other parts of the shark have commercial value. The skin goes into shoes and handbags, the teeth and vertebrae into jewelry. Physicians use

A precious trophy: a shark's liver. Average liver weighs about 80 pounds and yields around 50 pounds of the precious vitamin-packed oil

From shark's liver to pilot's eye . . . Preparing oil for vitamin

Ashore, sharks are cut open from the top to prevent damage to the soft belly hide, most valuable part of the skin



To extract oil, the liver is chopped up in a meat grinder and then bailed in large vats. When the liquid has reached a thick consistency, a centrifugal separator removes all foreign matter



SHARK

serums extracted from the shark's pituitary gland. Chinese restaurants make soup from the fins. The flesh is canned for food, and the rest of the shark goes into fertilizer.

To cash in on this bonanza, shark fishermen have abandoned the slow and dangerous hand-and-line technique. Trawlers drop 1,000-foot chains which are anchored at both ends and marked by buoys. At 25-foot intervals on the line are six-foot chains with large hooks. After a day or more, the trawlers locate the buoys and draw in the lines with special chain winches. From six to 10 sharks may be found on each 1,000-foot line. Most of them are already drowned, but an occasional tiger shark will come aboard with plenty of fight in him and will have to be quieted with a crowbar.

Hauling in a catch. Sharks hooked on chain lines are gaffed and hoisted aboard. Most are already drowned



that gives flyers night vision

Fresh from the centrifuge, refined shark-liver oil is poured off into drums for shipment to pharmaceutical houses. A 50-gallon drum may be worth up to \$7,000



On the trawler, baited hooks are set in holes in the gunwale to make it easy to pay out the 1,000-foot chain line without tangling. Bait is mullet or kingfish, favorite food of sharks. Hooks are on six-foot chains which are attached to the main chain line at 25-foot intervals. An average haul will net six to 10 sharks to the line



What's Your Score on Identifying WOMEN'S WAR BONNETS?



CAN you tell an enlisted WAVE from a SPAR ensign? The service hat is your sure guide. Here are the distinctive headgears of 10 military or volunteer services. If you've been watching war styles, you should be able to identify the wearer's rank as well as service corps. Check answers below. Seven right is a good score.



1. Army Nurse
2. WAFS—pilot
3. Amer. Women's Vol. Ser.
4. Marines—officer
5. Red Cross Spec. Ser.
6. Navy Nurse
7. SPAR—officer
8. WAAC—officer
9. Air-raid warden
10. WAVES—officer






Horse Meat Is Favorite Dish of Circus "Cats"

DON'T worry about what Leo the lion is having for dinner tonight—or lunch tomorrow. Meatless Tuesday and Ration Book Two mean little to the Big Top, for, provided there's a horse market near by, circus animals will dine well without benefit of OPA. Time-honored fare of a circus tiger, puma, leopard, or bear is about 15 pounds of juicy horse meat a day, for which no red

stamps are needed. Gorillas, amiably enough, are as strict as G. B. Shaw in abstaining from meat of any kind, while elephants get those strong, white tusks from buckets of bran. Camels thrive on a gourmet's dish of cod-liver oil in milk. Main headache of the Big Top in feeding its diversified charges under wartime conditions is in procuring hay. The Army wants it, too.



That quartette of expectant looks (top) is there simply because the daily flock of Dobbin hasn't been served up yet. Luckily, most circus animals prefer horseflesh to beef, so that tentmasters don't have to worry about red ration stamps. These apprehensive brethren on the ladder are cannily computing the distance to the sawdust, as this act in Ringling Brothers' Circus reaches a crucial moment. "No more cod-liver oil—I feel fine," roars the tiger of left as he sees his keeper coming to doctor him

No Truce in the War



Fighting flames with an OCD hand pump. This new extinguisher was developed in collaboration with the

Shortages of rubber and brass threatened safety Laboratories found ways to guard priceless military

By HICKMAN POWELL

ONE of the first results of Pearl Harbor was a sudden, vast increase in demand for fire-fighting equipment. Municipalities that had economized on fire hose during the depression immediately poured in orders for new supplies by the millions of feet, while the Army, the Office of Civilian Defense, and war plants added their weight to the demand. Meanwhile householders, acutely conscious of incendiary bombs, wanted fire extinguishers. The OCD with its air-raid precautions whipped up the natural demand to an even higher pitch. But at the same time the War Production Board started clamping down on rubber, brass, and other necessary materials.

All this created something of a crisis in the big Chicago testing station of Underwriters' Laboratories, Inc., which had spent nearly 50 years in building up rigid specifications and standards in all matters related to the prevention and fighting of fire. Underwriters' Laboratories was established under the auspices of fire-insurance companies to provide manufacturers with thorough testing which would give their goods a certified safety factor. But now something more urgent than insurance losses or ordinary safety was at stake. Failure to adjust requirements promptly might have led to a breakdown of fire safety standards at a time when it would have been disastrous, since war supplies are priceless and most civilian equipment is irreplaceable.

Hose is now being produced with malleable iron instead of brass couplings, and

on Fire



Underwriters' Laboratories and fire-equipment makers

standards, but Underwriters' and home-front supplies


it is just as strong as prewar hose, though only seven pounds of crude rubber are allowed where 17 were used before. The dilemma was met by changing the time factor. Standard fire hose is made of a 2½-inch cotton casing, lined with a thin soft-rubber tube that must stretch both in diameter and length. It was found possible to provide this with reclaimed rubber by sacrificing something in length of life. Today's hose is good enough to last at full efficiency probably to the end of the war, certainly until after synthetic rubber is being produced in volume. One length out of every 200 is tested exhaustively to make sure. The aging factor is determined by placing a sample in a bomb of pure oxygen and bathing it in hot water for several hours to speed the process of oxidation. For fire hose must work, not only now,



Plastics are used for pump valves, nozzles, and piston parts, and glass marbles for the valve balls, to save an critical materials

At right, a complete OCD hand pump. The tank is galvanized

Pump tubes are made of enameled steel instead of brass. The hose is made entirely of reclaimed rubber



but for as long as it continues to be in use.

In peacetime, Underwriters' big laboratories are a passing show of new industrial products being put through the most difficult situations imaginable. There are, for instance, long rows of furnaces where oil burners used to go through exhaustive tests; these are cold now. The men who used to test juke boxes, to see that customers would not be knocked over by electric shock, get their chance instead at soft-drink dispensers that are being made for the Army. But for the most part the job is to determine the efficiency of substitutes and of new materials being developed for use in war plants.

One urgent problem was to find a hand fire extinguisher which would not draw on precious supplies of copper and brass. The OCD wanted them by the millions, and is now getting them. In collaboration with manufacturers, the laboratories worked out an extinguisher that will hold four gallons of water and is made almost entirely of

TESTING ELECTRICAL INSULATION



While 100,000 volts are applied, a sheet of insulating material is tested, at left, to determine its protective value. The setup at Underwriters' Laboratories is used to try out insulations for all types of electrical devices

noncritical materials. Its operation is similar to that of the five-gallon pump tank with which fire departments put out a majority of the blazes to which they are called. The pump, instead of being made of critical brass, is steel and kitchenware porcelain, while the valve ball is a glass marble. With a reclaimed-rubber hose and a plastic nozzle, the extinguisher is adequate for most small fires.

Other substitutes of major importance are the new insulations for electric wire, replacing rubber. The war has given great stimulus to the production of wire with synthetic plastic insulation, known as SN wire. The material used is a plasticized polyvinyl chloride, a thermoplastic similar to Vinylite and Koroseal. Pliable unless chilled, this new type of wire is especially useful in airplanes and on other complicated jobs, for the material can be produced in a great variety of contrasting colors.

Also used today in large quantities for war construction is paper-insulated emergency-installation wire, which serves very well and safely as long as it is kept dry. One type of EI wire has the metal wrapped in two strips of cellulose acetate butyrate, which is also used for 16-mm. safety film. A .003-inch thickness of this stuff will resist 1,500 volts. Around this are twisted eight strips of paper and a cotton wrapping impregnated with a flame-resisting and moisture-retarding substance.

Another form of EI wire is simply wrapped in interwoven strips of paper, saturated with pitch. These emergency-installation wires may not be used in the usual metallic cables, where water might condense. Nonmetallic-sheath cable is permitted, but it must be installed where it can be seen, so that it will be replaced after the war.

While many ordinary industrial articles have gone out of circulation, there has been a boom in the testing of articles related to explosions. Incidentally, the Laboratories have discovered, at their explosive proving grounds outside Chicago, that it does no good as bomb protection to paste strips of

MALLEABLE-BRASS HOSE COUPLINGS GET SEVERE TRYOUTS



In a salt-spray chamber, above, a new coupling is tested for corrosion; at left, the coupling stays on a length of fire hose under high water pressure



Above, an expander is used to fasten a malleable-iron coupling on a piece of hose. An old-type brass coupling is on the other end. The only brass in the new coupling is in the swivel ring

tape on window glass—no good, that is, unless the strips are also made fast to the sash which holds the glass. Wired glass is almost three times as resistant to an explosion's suction as plain glass.

Underwriters' Laboratories helped the Army work out lightning protection for ammunition dumps by welding together the steel framework of the reinforced-concrete "igloos" in which the ammunition is stored, and putting points at the top. In this way tremendous quantities of strategic copper were saved.



SWITCH CASES MUST WITHSTAND BLASTS

Wide, matched flanges and a heavy case confine explosions started by sparks. A gas-filled switch case is tested below in a box also containing an explosive vapor




Conductive shoes, required in hospitals and munitions plants to eliminate a static-electricity hazard, receive a thorough test for both wear and loss of conductivity.



Plates on the inner and outer soles of conductive shoes prevent the building up of static electricity in the body by allowing it to escape to the ground.

Overshoes of conductive rubber are furnished to visitors of some plants. They are connected to the bare leg since wool and silk socks are insulators.





TAKING THE KINKS OUT OF *Steering Systems*

By RALPH ROGERS

1 Ross twin-lever gear. To eliminate end play in the worm, loosen the lever-shaft adjusting stud, releasing the pins in the thread, move the upper cover out, and add or remove shims between the gaskets as required; then push the cover back and tighten. In adjusting the mesh of the worm thread and pins, center the steering wheel in the straight-ahead position, tighten the lever-shaft adjusting stud until a slight drag is felt in the middle of the turn as the wheel is rotated slowly from one extreme to the other, tighten the lock nut on the stud, and give the gear a final test

2 Ross roller-bearing mounted-stud gear. To eliminate worm end play, free the stud from the thread by loosening the lever-shaft adjusting stud; then back off the adjusting-plug lock screw and turn down the plug until the drag is barely perceptible when the steering wheel responds to a light grip of the thumb and forefinger. Tighten the lock screw and its lock nut. Backlash in the lever-shaft stud is eliminated in the same way that the worm and pins of a twin-lever gear are meshed (see above). To adjust the roller-bearing stud unit, straighten the bent prong on the lock washer, hold the stud to keep it from turning, and tighten the nut until taps on each end of the stud show the adjustment to be correct; then bend up a locking prong that has not been used before

3 Gemmer external mesh-adjustment gear. To do away with up-and-down motion in the steering column, loosen the worm-cover screws slightly and remove the top shim, separating it from the next with a knife blade run in carefully so as not to mar those remaining; then tighten the cover and test the column. Repeat, if necessary, removing one shim at a time until play is corrected, but if the gear should then bind at any point, one of the shims will have to be replaced. To eliminate end play in the roller shaft, turn the steering wheel to either extreme position and back it one eighth of a turn, loosen the lock nut, and turn the adjusting screw until there is no more end play present; then tighten the lock nut and check for end play and binding through the entire range of the gear. In adjusting the mesh of the worm and roller, remove the roller-shaft lock nut and slip the lock plate down to clear the boss on the cover; then, with the steering wheel centered and the drag link disconnected, tighten the adjusting screw on the roller shaft just enough to get rid of play between the worm and roller-shaft teeth. Check by pulling the pitman arm back and forth. When the adjustment is satisfactory, slide the lock plate back into position, and replace and tighten the lock nut. A cross-sectional view of the roller bearing is shown in the circled inset

4 Saginaw worm-and-roller gear. This external view shows worm and roller-shaft adjusting screws and lash adjuster, all reached from the outside. Detailed instructions and an exploded view of the gear are given on the following page

MANY a fender has been crumpled because of too much play in the steering wheel. Quick-witted though a driver may be, he cannot avoid a crash if it occurs in the fraction of a second required to overcome lost motion before his steering gear begins to function.

What is probably the best insurance is to keep the steering system properly adjusted at all times. This can be done easily by anyone who understands certain fundamentals about steering gears and has a few tools.

Before making any adjustments in the steering gear, however, jack up the front wheels and make sure that the excess play is not caused by some other part of the car mechanism. For example, do not attempt to make adjustments in the steering gear to correct any erratic action of the front wheels evidenced by wheel shimmy or wandering to one or both sides of the road.


If one of these should be your trouble, check the tires for proper inflation and have the wheel alignment looked over by an expert who has the equipment to do a scientific job. Shock absorbers should also be in good working order. Shimmy can sometimes be caused by nothing more than the use of a boot in a front-wheel tire.

If all of these parts measure up satisfactorily, then check on the steering gear. The tie-rod and drag-link sockets and connections should operate freely without end play. Make certain that the pitman arm is tight on the steering-gear cross shaft and that its lock washer and nut also are tight.


The steering gears illustrated are typical of those in use in the majority of cars for the past several years. Compare the gear in your car with those in the illustrations; then choose the one that looks like yours and study its design carefully. This will enable you to proceed intelligently with adjustments and, if necessary, a job of overhauling.

End play in the worm (or cam) shows up as play in the steering tube, indicated by up and down movement of the steering wheel. This adjustment is correct if the steering wheel responds freely when lightly gripped by the thumb and forefinger. Should end play be barely perceptible, no adjustment is necessary.

Misalignment of the steering column is



In eliminating end play in the worm shaft of a Saginaw gear (shown here in an exploded view), loosen the adjusting screw until there is a slight load on the steering wheel when the gear reaches its extreme position. Take care not to back the screw out far enough to let the worm bearings get out of line. To adjust the roller shaft, tighten the four screws holding the side cover, loosen the lock nut, turn the adjusting screw all the way down, back it off slightly, and retighten the lock nut; then turn the gear almost to each extreme and check for binding by moving the pitman arm back and forth. Backlash between the worm and roller may be determined by tightening the screws in the end cover, centering the steering gear, and moving the pitman arm back and forth. To correct it, loosen the lash-adjuster lock screw and, with a soft hammer, tap the adjuster $1/16"$ at a time in the direction of the cutout arrow until the adjustment seems satisfactory; then turn the steering wheel to the right and left to check for tight spots, eliminating any that show up by tapping the adjuster back slightly so the gear will turn without excessive binding; then retighten the lock screw



corrected by loosening the bolts that hold the gear to the frame just enough to allow the gear to shift and to line up as much as it will of its own accord at the angle determined by the setting of the steering-column bracket at the instrument board; when the gear is in this normal position, it is again tightened to the frame. After this has been done, loosen the instrument-board bracket and allow it to shift so that its position and that of the steering column are matched perfectly, and then tighten the bracket. If the bracket is of the single-position type, it must be changed to the position of the steering column. Never try to spring the column to the bracket—this is just the condition that you are trying to correct.

To locate the steering gear in its central position, turn the steering wheel from one extreme to the other, keeping count of the number of turns. Next, turn the wheel back precisely one half the total number of turns, and this will be the central position of the gear. Most wheels have a trade-mark or depression on the underside of the spoke

that should point directly up or down when the gear is in this central position.

Specific directions for the adjustment of the several types of gears pictured are given along with the illustrations. Select the set that fits the steering gear in your car and follow the steps in the order listed, first, however, disconnecting the drag link from the ball end of the pitman arm in order to free the gear of load. When the adjustment is made, the gear should be free from backlash in its straight-ahead driving position and should be free to move through its complete cycle without binding at any point.

Before reconnecting the drag link to the pitman arm, turn the steering wheel to its central point and place the front wheels in their straight-ahead position. It should then be possible to connect the drag link without moving the steering gear appreciably. If this cannot be done, remove the pitman arm from the steering-gear cross shaft and place it on the splines in the correct position, otherwise the front wheels will not swing through equal arcs to the right and left.

USEFUL AUTO HINTS




1 A TOOL COMPARTMENT for cars lacking such a space can be made by welding or bolting an angle bracket in the luggage compartment to the bottom of the back of the rear seat. A board is fitted between the seat and the end of the body and is bolted to the bracket. A cross board keeps tools from damaging the taillight.—P.C.S.

2 AN ORDINARY SHOE BAG temporarily fastened to the rear of the front seat with safety pins provides a handy place for carrying articles with which to entertain small children during an auto trip. The pockets are suitable for small toys, dolls, paper and pencils, flexible books that can be rolled, and boxes of cookies.—C.W.C.

3 PORTABLE-RADIO RECEPTION in an automobile may be improved with a few simple connections. Use a standard whip aerial, connecting it with a shielded lead-in to the plug jack on the dash. A 3' piece of single-conductor shielded cable is attached to a microphone plug, with the shield connected to the shank, and fastened at one end to the grid side of the loop aerial. The shield may be fastened to the radio chassis if this will further improve reception. Be sure to keep all the shielding grounded to eliminate ignition noises.—R.S.

4 EMERGENCY BATTERY CONNECTIONS can be made by taping the cable end and turning an ordinary wood screw through the cable into the battery terminal.—J.K.

DRAWINGS BY STEWART ROUSE





Gus Meets

REPAIRS CAN BE COSTLY IN MORE

By MARTIN BUNN

JOE KENT, a Model Garage old-timer who now lives in New Jersey, snapped his fingers impatiently.

"I can't understand it!" he exclaimed. "When my repair man over home said that this fuel pump had gone haywire, I wouldn't believe him. That's why I took a chance on getting stalled on the road to get my car over here to you, Gus. This is the third fuel pump that's gone bad on me this year. And I've driven only six thousand miles. Why, I used to drive three times that much before the war, and I can't remember ever having fuel-pump trouble. What's the answer?"

Gus Wilson looked up from the fuel pump he had taken off Kent's car and disassembled on his workbench. "I don't know all the answer yet, Joe," he said. "But I do know that your pump won't work right because some of its parts are corroded. Right now there's moisture on them. Feel for yourself—right here."

Kent ran a finger over the place Gus indicated. "It's wet, all right," he agreed. "But where the heck did the water come from?"

"I've checked on that," Gus told him. "The crankcase is the only place it could have come from."

"Huh?" Joe retorted doubtfully. "Be yourself, Gus. How could water get into the crankcase and then out of the crankcase onto the fuel pump?"

"It wasn't water when it came out of the crankcase," Gus said. "It was moisture in the form of vapor, and it condensed into water. . . . Know anything about crankcase ventilation, Joe?"

"Sure I do!" Joe asserted. "It's—it's—Oh, you know—it sort of ventilates the—"

Gus laughed. "Stop stalling," he said. "Crankcase ventilation is just a couple of words to you, same as it is to ninety-nine car owners out of a hundred. It's one of the most important features of modern engine design, but somehow most owners can't appreciate its importance. There are several systems, but they all have the same object—

to force gas vapors out of the crankcase before they have a chance to condense and dilute the engine oil and do other damage. I'm going to do some checking on your car. If you watch, you'll find out why those three fuel pumps went bad after only a couple of thousand miles."

Gus examined the air cleaner on the carburetor of Kent's car and found it in A-1 condition. Then he examined the filter in the crankcase oil-filler cap. It was hopelessly clogged—and to make it even worse, someone had installed the cap with its opening faced toward the back end of the car instead of toward the front end.

"That filter is the cause of all your grief," he told Kent. "When it's clogged up, no air can get through the oil filler pipe. That means that the only ventilation the engine gets is through the outlet pipe. And, of course, putting that cap on wrong-side-to didn't help any. These filters must be kept clean so they'll let the air flow freely through the crankcase and carry off the vapors. That keeps the oil from becoming diluted.

"Keeping them clean is especially important now," Gus went on thoughtfully, "because people don't use their cars so often since gas rationing, and only take short trips when they do. Consequence is, the engine seldom has a chance to get warmed up thoroughly and pass off the vapors in the exhaust. Few owners understand this wartime handicap, and a lot of them are having troubles like yours. And it's a real headache to the service garages. . . . Well, I'll have to clean out that clogged filter. Then I'll install a rebuilt fuel pump for you."

"O. K., Gus," Kent said. "And when I get back home I'm going to give that repair man of mine a good lecture on crankcase ventilation!"

"You do that, Joe," Gus laughed. "Now that you know what it's all about yourself."

Not long after Kent had gone on his way, Vernon Hopkins drove his car into the shop. Most folks in our town think that Vern is a hopeless sourball, but Gus always stands up for him.

"Give me a chance to check a man's car," he says when someone starts panning Vern, "and I'll tell you all you need to know about his character. Vern may be a grouch, but anyone who keeps a five-year-old bus run-

Double Trouble

WAYS THAN ONE—ESPECIALLY IF THEY ARE BUNGLED

ning as smoothly as his, certainly must have some good in him. There's nothing really wrong with Vern Hopkins. His car proves it."

Feeling that way, Gus greeted Hopkins with a friendly, "Hello, there."

Vern had a scowl on his thin face, and he didn't bother to wipe it off when he returned Gus's cheery greeting with a grunt.

"I want you to look at my motor," he grumbled. "Every once in a while it skips three cylinders, and I can't find out why. It's got me worried." He got out, leaving the engine running. "It's doing it now. Hear that?"

Gus nodded. His trained ear told him that there were only three cylinders firing. Knowing how careful and smart Vern is about car upkeep, he felt that he probably had a tough trouble-shooting job ahead of him.

Hopkins hunched his bony frame on the end of the workbench and watched silently and with a scowl as Gus began checking.

While the engine turned over slowly, hitting on only half of its six cylinders, the proprietor of the Model Garage detached a wire

from a spark plug and held its end a quarter of an inch from the plug shell. He got a good spark. The next two plugs he tested also gave good sparks. As he reconnected the wire to the third plug he looked surprised. All the cylinders were firing now. But just to be on the safe side, he checked the three remaining plugs. Like the three checked first, they all gave good sparks.

He grinned at Vern. "As soon as a good man goes to work on your engine," he said, "the trouble vanishes. It's hitting on all six now."

"I can hear that," snapped Vern. "That's the way it's been acting for several days. Sometimes it runs all right, and sometimes it don't. Why?" he demanded, pointing his long thin finger at Gus. "That's what I want to know—why?"

Gus picked up his pipe from the workbench and felt in his overalls pocket for his tin of "Delight"; then remembered that he had left it in the office. He went to get it. When he came back a half minute later, Vern jerked a thumb at his car. "What'd I

Hopkins sat on the workbench as Gus checked. "You're stumped," he jeered



tell you?" he growled. "It's missing again."
"So it is," Gus agreed placidly. "Well, that'll make it a lot easier to locate the trouble."

After switching off the engine, Gus made a quick but careful check that failed to reveal any loose connections. A test of the battery disclosed that it was putting out an adequate amount of current. No cracks showed in the distributor cap. When he pulled the spark-plug cables out of the cap sockets, he found both the terminals and the sockets clean and uncorroded.

Gus's pipe had gone out. As he relighted it, he did a little hard thinking. Vern's tight lips twisted into a sneer. "You're stumped," he gloated.

Gus grinned at him. "Close to it, but not quite," he said. "Any number of things can make an engine miss that haven't got anything to do with the ignition. Carburetor trouble, for example."

But when he checked the carburetor, he found that it was delivering a satisfactory mixture to the cylinders. His tester told him that the compression of each of the cylinders was good. He could find no leaks in the manifold.

"That puts me right back where I started from," he admitted. "It must be ignition-circuit trouble. Can't be anything else. I'll take a look at the coil."

"You needn't," Vern told him. "I put in a new coil as soon as she began to miss, and it didn't do a bit of good." He was looking almost happy. "Now you are stumped!" he jeered.

Gus almost lost his temper, but not quite. "The jinx must be in your distributor," he said. "Let's have a look at it."

"Huh?" Vern grunted. He got red in the face. "There's nothing the matter with that. Why, I—oh, well, go ahead and look at it."

Gus took off the distributor cap. The rotor was in good condition. He lifted it off and looked at the points. "You been doing any monkeying with this?" he demanded of Vern. "These points look new, and so does the breaker lever."

"They're new," Vern admitted. "What of it?"

"If you'd told me that half an hour ago you'd have saved me a lot of time—and what it'll cost you to pay for that time," Gus

told him disgustedly. "You certainly made a bum job of installing that breaker lever. Here. See that grit? That's what's been making your engine miss."

"Grit? Well, all right. So there is a little grit," Vern Hopkins mumbled grudgingly. "But that little bit wouldn't make the whole engine miss," he asserted belligerently.

"Oh, wouldn't it?" Gus retorted. "The bushing on that breaker lever fits tight enough as it is—because it's new. Now you try to wedge it to the pivot post even tighter by getting dirt between them. How do you suppose it can move to make the contact to close the primary circuit? Sure, it'll work sometimes, but when it doesn't, there's no current going to the ignition coil and no spark in the cylinder. Result is, the cylinder misses fire. Catch on?" Gus grinned mischievously.

"No," Vern returned flatly. "Besides I don't believe it anyway."

Gus laughed out loud.

"Well," he said, "maybe you'll believe me when you see your headaches go away with this grit."

He cleaned the grit from the lever bushing and from the pivot post. Then he replaced the distributor cap.

"Try it now," he invited.

Vern got into the car, stepped on the starter, and the motor purred without even the slightest hint of a miss.

"Send me a bill," he grumbled ungraciously. "And see that you don't charge me too much."

"Don't worry about that," replied Gus. "I'll even throw in a bit of free advice. Next time you work on your car, don't be so sloppy. Why, I'd fire a mechanic for being half that careless—even though mechanics are hard to get."

He ambled over to his workbench and picked up a hammer.

"Some people will just never learn . . ." he muttered, but the rest of his words were drowned in the roar of the exhaust from Vern's departing car.

"If you're going to be your own mechanic, be a good one," Gus mused. "Or a clean one, at any rate." Then he chuckled. "At that, I guess Vern Hopkins wasn't as bad as Joe Kent's mechanic over in Jersey. At least he didn't damage someone else's property."

\$175 IN PRIZES


ATTENTION, auto, truck, and jeep experts! For the best letter of not more than 500 words describing a car ailment, its diagnosis, and cure, we will pay \$50. The second-best will win \$25, the next five best \$10 each, and the next ten best \$5 each. In case of a tie, each tying contestant will be awarded the prize tied for. The editor's decision will be final.

Address letters to Gus Wilson, care of POPULAR SCIENCE MONTHLY, 353 Fourth Avenue, New York 10, N. Y. Letters must be postmarked before midnight, September 15, 1943. No entries will be returned, and all will become the property of POPULAR SCIENCE MONTHLY.



EMERGENCY AMBULANCE BODIES have been designed by the OCD for use on converted light four-door sedans as supplemental equipment for its medical division. The bodies, which accommodate four stretchers, are built of wooden frame members and plywood panels. Scrap iron is used for lengthening the chassis of the converted cars. In making the ambulances, the sedan bodies are cut off at the rear of the center door posts, the new bodies are bolted to bent iron pieces welded to the chassis, and two additional leaves taken from junked cars are inserted to strengthen each rear spring. The bodies may be used on 1939, 1940, and 1941 Fords, Chevrolets, and Plymouths. That in the photo above is mounted on a 1939 Ford.

TIRE INSPECTION can be speeded in a busy shop by the addition of one or more auxiliary lightweight spreaders. The one below was designed by Charles E. Harris, of Raton, N. M. Its two arms are steel tubing, and the link consists of two pieces of strap iron. Pipe couplings will serve for the other parts. The fulcrum sleeve is adjustable and can be locked at any place by means of a set-screw. To the sliding sleeve is welded a set of bead jaws. Similar jaws are welded to the fixed fitting at the end of the tool.



HOW TO MOUNT TIRES



Partially inflate the tube before inserting it to prevent buckling



With your hand, guide the valve through the valve hole in the rim



Push the bead under the valve into the well at the center of the rim



Force the rest of this bead over the flange so it rests in the well



Now pry the top bead opposite the valve over the flange and, with a second tool, work around the rim



Seat the valve correctly, pulling it out by hand and centering it




Holding the valve, inflate until both the beads are properly seated



If there is a centering rib, have it show evenly all the way around

From Goodyear Tire & Rubber Company, Inc.

HOME AND WORKSHOP



Cargo vessels converted to plane carriers now do their part in guarding our supply lifelines. These models show a typical motorship before and after conversion


FROM Peacetime Freighter TO Fighting Carrier


TWIN MINIATURE MODELS SHOW
HOW AMERICAN INGENUITY ALTERS
CARGO VESSELS TO ASSIST NAVY
IN GUARDING VITAL WAR CONVOYS

By Theodore Gomme

TWO ship models in miniature—particularly fascinating projects for the home craftsman to tackle at this time—show how the U.S. Merchant Marine has come to the help of the Navy in furnishing craft for guarding other cargo vessels that carry arms and supplies to the A.E.F. and our Allies. Several motor freighters have been converted into efficient aircraft carriers—too slow for regular combat duty with swift-moving warships, but well fitted to accompany convoys and to provide an effective umbrella of fighter planes able to spot and destroy surface and undersea raiders even in the middle of the Atlantic.

The two models shown here are the





LIST OF MATERIALS

No.	Material	T	W	L	For
2	Wood	$\frac{3}{8}$	1	$7\frac{1}{2}$	A (Freighter)
1	"	$\frac{1}{8}$	$\frac{3}{4}$	$1\frac{5}{16}$	B (Carrier)
1	"	$\frac{1}{8}$	$\frac{3}{4}$	$1\frac{7}{16}$	C (Carrier)
1	Paper	$\frac{1}{8}$	1	$1\frac{3}{8}$	D (Freighter)
1	Wood	$\frac{1}{8}$	$\frac{3}{4}$	$1\frac{3}{16}$	D (Carrier)
1	"	$\frac{1}{8}$	$\frac{3}{4}$	$1\frac{7}{16}$	E
1	Paper	$\frac{1}{8}$	1	$1\frac{1}{4}$	F (Freighter)
1	Wood	$\frac{1}{8}$	$\frac{3}{4}$	$1\frac{5}{16}$	F (Carrier)
1	"	$\frac{1}{8}$	$\frac{3}{4}$	$1\frac{1}{8}$	G
1	"	$\frac{1}{8}$	$\frac{1}{2}$	$\frac{5}{16}$	H
1	"	$\frac{1}{8}$	$\frac{1}{2}$	$\frac{9}{16}$	I
1	"	$\frac{1}{8}$	$\frac{1}{2}$	$\frac{7}{16}$	J
1	"	$\frac{3}{16}$	$\frac{1}{2}$	$\frac{7}{16}$	K
1	"	$\frac{1}{8}$	$\frac{5}{16}$	$1\frac{1}{16}$	L
1	"	$\frac{1}{16}$	$\frac{3}{16}$	$1\frac{1}{4}$	M
2	"	$\frac{3}{16}$	$\frac{1}{2}$	$\frac{3}{16}$	N
3	"	$\frac{1}{8}$	$\frac{1}{2}$	$\frac{1}{2}$	Oa
2	"	$\frac{1}{32}$	$\frac{5}{16}$	$\frac{1}{2}$	Ob
2	"	$\frac{1}{32}$	$\frac{7}{16}$	$\frac{5}{16}$	Oc
1	"	$\frac{1}{32}$	$\frac{5}{8}$	$\frac{5}{16}$	P
2	Paper	$\frac{1}{8}$	$\frac{7}{16}$	$2\frac{1}{4}$	Q
1	Wood	$\frac{1}{32}$	1	$\frac{5}{8}$	R
1	"	$\frac{1}{8}$	$1\frac{5}{16}$	$5\frac{1}{4}$	S
4	Paper		Small Scraps		T
1	"		Small Scraps		U (Freighter)
14	Heavy Wire		1		U (Carrier)
28	"		$\frac{1}{2}$		V (Freighter)
26	Light Wire		1		Va (Freighter)
8	"		$\frac{1}{2}$		Vb (Carrier)
1	"		2		W (Freighter)
3	Heavy Wire		$\frac{1}{2}$		X (Freighter)
2	Pins		$\frac{1}{2}$		Y
7	Wood	$\frac{1}{8}$	$\frac{1}{8}$	$\frac{1}{2}$	Z (Carrier)
3	Small Beads				

Small piece of oval tubing for funnel.
White, gray, brown, black, yellow, and green paint.
NOTE: All dimensions are given in inches.

Water-line model of the freighter *Mormacmail* before conversion into an aircraft carrier

"before and after" of the S.S. *Mormacmail*, now an aircraft carrier in the service of the Navy as the U.S.S. *Long Island*, a motorship typical of the C-3 type freighters being furnished by the Maritime Commission for convoy-escort duty as aircraft carriers. In building both these models, it will be possible to see how the conversion was made from a ship of commerce to a ship of war. The scale used is 1" equals 66 2/3'.

After cutting wood, paper, and wire to the dimensions shown in the list of materials, shape the hulls, which are the same for both models. Note, however, that the forecastle *M* is higher in front on the carrier and is not cut back as sharply as it is on the freighter. The

U. S. S. *Long Island*, the converted *Mormacmail*



funnel on the freighter is for looks only since it is a motorship, and it is simply removed on the carrier to make room for the flight deck.

The carrier requires more work, especially in arranging the supports *U* for the flight deck. These must be inserted close to the edge of *A* in an absolutely vertical position. The bridge, *J*, *K*, and *L*, and the elevator housing, *H* and *I*, must reach the same level as the top of *F*. The deck, *Q* and *R*, is then glued to *F*, *I*, and *L*, and the supports *U* are trimmed to touch the underside of *Q*. The sides of the rear hangar *P* are cut from heavy paper or thin cardboard. The edges are glued to the extreme edges of *A* and to

the underside of the flight-deck piece *Q*.

Boats and davits are attached in the positions shown. The AA guns are short bits of wire inserted through small beads.

In finishing the freighter, paint the sides of *A* and *M* gray and the rest white with the exception of the hatch covers, which are brown, and the funnel, which is yellow with green and black stripes.

The carrier is painted battleship gray except for the flight deck. This is medium brown with dark yellow guiding stripes and identification letters. If you prefer, you may glue on brown paper on which the stripes and letters are ruled with thin tempera paint and a ruling pen.

Salt and Pepper Shakers Reminiscent of Crinoline Days




AN EVENING'S work at the lathe will produce these quaint little shakers, which can be made any size desired by drawing the pattern on larger or smaller squares.

Mount a piece of stock for each shaker in the chuck or on a screw center and bore out the inside with a small turning chisel, keeping the sides of the recess straight and square. Turn the bottom slightly concave.

Next, turn a piece of scrap stock to a tight fit in the bored portions. Mount each piece on this mandrel to turn the outer contour and the top. If the stock is long enough, the peglike upper body may be turned from the same piece; otherwise, turn the upper part from dowel with a shoulder to insure its being glued squarely into a hole in the skirt.

Dowel will also serve for the bonnets.

Demure is the word for these salt and pepper shakers. The same design can be altered to make up into powder boxes




Turn a short piece to the bell-like contour shown, with the wider diameter toward the tailstock. Run a 5/16" drill in from this end, flare the mouth, and cut off the piece. Saw off a narrow segment to form the bonnet, which is glued to the turned stem.


A French polish may be applied in the lathe, or the bodies may simply be stained and waxed. The bonnets may be painted white for salt and black for pepper. These condiments are sprinkled through holes drilled through the top of the skirts. Use a 1/16" drill for the salt shaker and a 3/64" drill for the other.—BRUCE MACINTOSH.

KEEPING THE HOME

A pocket made from cardboard, heavy paper, or even fabric, and attached with tape or stitched with thread to the outside of your shopping bag, will hold marketing lists and save you the annoyance of having to dig through your purse for buried memos



An inexpensive household file can be made by stapling together the bottoms of several large-size envelopes. Index tabs are formed by cutting the flaps and gluing them down



A short length of flat curtain rod tacked to the inside of a drawer will form a safe holder for your sewing or household scissors. The sides of the rod can be bent to hold shears of any size



The top of a scouring-powder can placed over a glass makes an ideal holder for starting small plants such as African violets



A note left in the milk bottle can be protected from rain and kept from being blown away by a glass inverted over the neck



An ordinary bottle cap nailed to a short wooden handle makes a good fish scaler. If desired, more than one cap may be used

SHIPSHAPE



**PAINT HANDLES
OF ALL TOOLS A
BRIGHT COLOR**


You can easily distinguish your own garden tools from borrowed ones, and also identify any tools that your neighbors may have borrowed, by painting all the handles of yours the same bright color



**BEND
HANDLE**

**EDGE VIEW SHOWING
COMPLETED
RIVETED LOOP**


To make an easily packed camper's frying pan, bend the handle as shown above, then down, and continue to form a socket. Cut off any excess and rivet the joint. A branch whittled to fit the socket serves as a handle



Keeping the family's umbrellas conveniently in one place is easy if you build shelves inside a closet door as shown above. Holes are bored in the top shelf and the umbrellas inserted in these so that the tips rest in blind holes in the lower shelf. Before rolling umbrellas for storage, be sure they are thoroughly dry



The sharpened tips of a worn-out ruling pen will cut two parallel slits in paper, useful for holding stamps and like enclosures



One spring-type clothespin and one ordinary clothespin nailed together as above will form an adjustable paintbrush holder



Matches can be kept dry on fishing or camping trips if they are inserted in cellulose straws, folded, and made into packages



Wise Planning Helps You to Enjoy the Unrationed Outdoors

By JACK HAZZARD

MANY pleasures, especially long vacation trips, have been curtailed by war, but the great outdoors remains unrationed, and the enjoyment that can be derived from hikes and outings is unlimited, provided such ventures are carefully prepared for and equipment is judiciously selected. The following suggestions, which will help greatly in making life in the outdoors as pleasant as it is healthy, were culled from the writer's own experience and from a pamphlet published by the New York State College of Agriculture, Cornell University, Ithaca, N. Y.

Hiking clothes should be comfortable and sturdy. Wear thick-soled shoes with soft uppers, and be sure they are large enough since you may have to wear an extra pair of woolen socks. Always equip yourself for rainy weather. A waterproof poncho is the best for this purpose, for it can be conveniently folded away when not in use.


An easily made pack is shown in one of the illustrations. The material is 10-oz. duck sewed or riveted together. Web trunk straps make the best carrying straps, with the buckles arranged to permit easy adjustment. The pack when loaded should not weigh over one third of your own weight.

A hatchet or light ax is needed on even a short trip. The ax should have a sturdy handle—one as long as you can carry. Grind the edge to a long cutting bevel and keep it sharp, but

never carry it in your belt without having a leather sheath over the cutting edge to protect yourself against serious injury in case of a fall. An ordinary jackknife will also be needed.

The tarpaulin shown in an accompanying drawing is made of unbleached cotton. The material should be shrunk before being made up, and then waterproofed. It makes a serviceable tent with a front flap that may be left open for sleeping in fine weather or tightly closed to keep out wind and rain.


To waterproof the tent, use two tubs or wash boilers. In one dissolve alum in hot, soft water in the proportion of $\frac{1}{4}$ lb. to the gallon. In the other, using the same amount of hot, soft water, dissolve sugar of lead (lead acetate—a **POISON**) in the same pro-





TO PACK THE OUTFIT

$\frac{1}{8}$ " GALVANIZED WIRE



FOLDING OVEN
MADE FROM
5-GAL. CAN

SHELF
SUPPORT

WIRE COAT
HANGER



WALL
POCKET



PUNCH OUT
RIVETS




REPLACE RIVETS
AND HAMMER TIGHT



PUNCH HOLES FOR
BAIL - LOOP IN BAIL
PREVENTS UPSETTING



PUNCH OUT RIVETS IN HANDLE,
REPLACE TWO, AND HAMMER DOWN.
USE BOLT AND WING NUT
TO HOLD HANDLE ON



PYRAMID TENT
WATERPROOFED
UNBLEACHED COTTON
CANVAS, OR DRILL



MATCH SAFE
FROM JOINT OF
CANE AND CORK



COFFEE-CAN
LIGHT AND
KETTLE

MAKING SHEARS
TO SUPPORT TENT



4 TURNS




DRAW ENDS BETWEEN



TIE WITH SQUARE KNOT



CAMP CRANE
LIFT HERE
AND SWING



HARDWOOD MAGAZINE FIRE
WILL BURN ALL NIGHT AND
KEEP TENT WARM

TREES MOST USEFUL TO CAMPERS





portion. Let the solutions stand until clear; then add the sugar-of-lead solution to the alum. After four hours, pour off the clear liquid and work the tent in it with the hands until every part is thoroughly penetrated. Let the tent soak overnight, and in the morning rinse well, stretch, and hang it up to dry.

Comfortable brush beds can be made of twigs and boughs. Make the first layer of heavy boughs 2' and 3' in length. These are the "springs" of the bed. Smaller pieces are laid on next in overlapping shinglelike layers. The bed when complete should be approximately 2' by 2' by 6'. A lightweight, waterproofed canvas bag will also serve as a good bed. This may be stuffed with any soft material such as leaves, straw, rushes, evergreen twigs, and the like. A rough flooring of dead branches placed under the bag will make sleeping warmer and also provide a store of dry wood for the morning fire. The bag should measure about $2\frac{1}{2}'$ by $6\frac{1}{2}'$ when finished.

A piece of mosquito netting, hemmed and fitted with tie strings, is a seasonal requirement. It can be folded up in the tarpaulin for safe carrying.

Cooking utensils should be cut to a minimum, for they are too heavy and bulky to carry for great distances. Most important of all your cooking equipment is the frying pan. Be sure to choose one that has plenty of depth, for it can also be used to make stew or soup. Pans with detachable handles are good since they are easy to pack.

The folding oven shown in a drawing can be used to make biscuits or pastry, to heat

canned goods, and to keep pancakes and the like warm. It was made from a 5-gal. square kerosene can, and when folded takes up no more room than a school-boy's tablet. The size can be worked out according to the dimensions of the pack used and the material that is available.

Kettles for camp use should have broad bottoms rather than high sides. Two or three should suffice. Pack them with bags of supplies such as flour, corn meal, baking soda, coffee, powdered or canned milk, sugar, and other cooking needs. These, plus the oven and frying pan, are all the cooking utensils needed—but be sure to carry matches. Many a camping trip has been ruined because they were forgotten. The large kitchen matches are best, and they should be carried in a tin or waterproof container along with a piece of sandpaper

that can be kept dry for use in wet weather.

One of the banes of camping is sunburn. Great care should be taken to avoid being burned unless your skin is accustomed to it. If you are mildly burned, treat the affected areas with a solution of cold tea, lemon juice, or vinegar before exposing yourself to the sun again.

Poison ivy and sumac are also sworn enemies of the camper. Learn to recognize both, and never make camp near them. A good preventive measure is washing the hands and other parts of the body that might become exposed to the poison with a strong alkali such as yellow laundry soap. A 5-percent solution of potassium permanganate painted on the skin will cure mild cases.

Nettles, though annoying, are seldom serious, for the sting passes quickly. If the camper moves through a clump of nettles very slowly he will seldom be stung at all.

Take along some simple remedies such as ammonia for insect bites, aspirin, and toothache wax. Sulphur tablets are good in chigger country.

Do not eat roots that have an "edible look"—some of them may be poisonous. And beware of toadstools! The really efficient camper should familiarize himself with various types of roots, herbs, and so on before he makes his trip.

Hiking just for the fun of it is good fun and healthy exercise, but for the best enjoyment of a hike, no matter how long you intend to walk, have an objective in mind, plot out your course beforehand, then "go to it," a modern trail blazer—prepared for the worst—and the best.




All the above paraphernalia will actually fit into the bicycle pack. Included are a pup tent, raincoat, shaving kit, camera, blanket, and change of linen. Left, the completed pack in place on the carrier

Dear Workshop Editor:

Have you plans for a bicycle pack that can be attached to the luggage carrier of any wheel. I am sure many other readers would be interested in such a pack now.

B. W., Salt Lake City, Utah



LIGHTWEIGHT, compact, and waterproof, this pack holds all the essentials for a bicycle trip and can be securely fastened to the seat and luggage carrier of any wheel.

Waterproof artificial leather was used for the pack shown, but canvas, which you can waterproof yourself, may be substituted. A piece of fabric $43\frac{1}{2}$ " by $51\frac{1}{2}$ " is necessary. Lay out the full pattern from the half pattern shown in the drawing. Inserts for pockets should be cut from the waste material after the pattern has been formed. Before shaping the bag, the top front edge is seamed and a cord stiffener is pulled through the seam. The inserts for all the pockets are corded in like manner and stitched into the flaps on the flat material. After the pockets are stitched, the bag is French seamed with strong thread.

A plywood floor $\frac{1}{4}$ " by $8\frac{3}{4}$ " by 15 " is fitted into the bottom of the bag and fastened with four roundheaded upholsterer's spread fasteners. The latter serve as casters when the bag is off the bicycle.

Two $\frac{3}{16}$ " holes are drilled through the plywood floor and fabric for the bolts, which rest on $\frac{3}{8}$ " washers and are lined up with the screw eyes bolted to the luggage carrier. Wing nuts are used to adjust the bag and prevent side sway. The seat straps hold some weight, but the bag rests mainly on the carrier.—ERNEST R. DEWALT.




Enhancing the charms of the smiling miss above is the attractive frame made from show-card stock

LIGHTWEIGHT yet rigid is this picture frame that is made from 14-ply show-card stock. A metal-edged ruler, a compass, and a penknife are the only tools needed to make it.

Using the ruler and compass, lay out the diamond-shaped center on a piece of cardboard and cut. Place this in position on the panel, as shown; then mark the inner lines of the center design and cut out the inside. Next, mark off the trimming strips from

Modernly Styled Picture Frame Made from Show-Card Stock




cardboard and glue in place. Be sure to bevel the edges of the strips and the cutout with fine sandpaper before gluing.

Strips of cardboard $\frac{1}{4}$ " wide are glued at the sides and bottom between the front and back panels. The removable, semicircular bases are slipped on between the strips on the front panel. Smooth all the edges with fine sandpaper. If the picture or snapshot is too small to fit into this frame, it may be attached to thin cardboard.—FRANK SHORE.

Button Place Cards

BUTTONS and a few scraps of colored paper make amusing place cards. Features may be drawn on the buttons with India ink, as below, or the buttons may be sewn on with black thread that will form features. Cut petals from contrasting paper and draw on the stem.—B. N.




Film-Spool Ends Form Useful Grommets

GROMMETS for use on tents, auto covers, and the like may be made from the metal end of wooden film spools and ordinary $\frac{1}{2}$ " washers. Insert the spool end in a hole in the fabric, put on the washer from the other side, and clinch over the collar of the spool end from the washer side. To do this, place the round head of a carriage bolt on it and hammer the bolt, being careful to hold it steady. Such grommets, if carefully made, will hold securely.—B. N.



FISHING PLUGS

YOU CAN WHITTLE WITH A POCKETKNIFE



By ELMA WALTNER

LURES that will attract a fisherman as well as a large-mouth bass or a Northern pike can be made—if you know how to wield a pocketknife—in hardly more time than it takes to buy a new assortment for your kit. And even if you aren't a fishing enthusiast, making plugs can become an interesting and profitable hobby, for commercial lures command a good price.

While some of the newer ones in the sporting-goods shops are of plastic, most are of cedar—a lightweight, buoyant material when properly finished. A common white-cedar post—picked with an eye to as few cracks as possible—will furnish you with material for many lures. Cut 6" lengths and split them into pieces about 1½" thick. Whittle the body—or turn it if you prefer to use a lathe—to the size of the plug you plan to make. In whittling, keep the body as symmetrical as possible by turning the stock often as you work. But don't throw away your first crude efforts. They may prove to be the very plugs to arouse the fighting blood of the big ones when they land with an inviting "pop" beside the lily pads.

Double or triple hooks are the only parts you need to buy, and even these may be salvaged from old plugs. Hook loops and line loops are fashioned from nails. The nickel housing of an old alarm clock, or even a tin can, will furnish metal plates.

Finishing is important, but it need not be artistic. Give the plugs two coats of paint followed by two coats of spar varnish, sanding carefully after each coat has dried. If you wish to try your hand at a scale finish, dip a piece of veiling in dark paint and allow the surplus to drip off. Then, holding the veiling taut, lay it on the plug and immediately lift it off.

Perhaps the easiest plug to make is "Pete Popper," shown in an accompanying drawing. He floats on the surface when at rest,


but "pops" and dives obligingly when retrieved with short, quick jerks. The hook and line loops on "Pete" are used on most of the plugs. Bore a hole of nail diameter on a slant from the top of the body to the tail and counterbore the upper part to take the nail head. Push the nail through as far as it will go, slip a hook over the point, bend the point upward with a pair of pliers until it touches the body, and then drive the nail into the wood. If the counterbore has been deep enough, the head will be perfectly countersunk and can be filled over with plastic composition wood.

The line and the hook on the bottom of the lure are held by loops made with the same nail. Select a longer nail than the one used in the tail and push it through a hole bored from the mouth. This hole need not be counterbored, and the nail head should project for about 1". Slip the hook over the point, bend the nail over, and drive the point deep into the wood; then cut the head off the nail, bend that end over, and drive it a short distance into the wood to form the line loop. Rustproof both nails with a coat of spar varnish.

The V-mouth plug is a versatile fellow. He works equally well for trolling or casting. Two finishes are shown. It is hard to say which the fish prefer.


"Open-Mouth Wiggle Minnow" matches his name. He is streamlined and has a metal plate fastened to his head with four small nails. The two that pass through the top of the head are clinched for safety. A small hole in the horizontal projection of the plate is for fastening the leader snap.

"Willie Wobble-Tail" is perhaps the most complicated of the group. His hook fasteners were bent from heavy wire and fastened with small screws. However, the other type of hook fastener would be equally satisfactory. The line loop is bent from heavy leader wire. It passes under the metal plate and is fastened with the same screw that holds the forward hook loop.






Easy does it! The earnest lad standing up aims for his target as carefully as a bombardier who has just sighted Berlin



CARDBOARD BASE 16" x 16"



In the Groove...

**CAN YOU SCORE
FIVE PERFECT HITS
IN THIS MARBLE GAME
THAT CALLS FOR A KEEN
EYE AND A STEADY HAND?**

By MYRON FLEISHMAN

HERE'S a new game that will not only test your co-ordination of hand and eye, but will also provide good fun for everyone. Made of cardboard and wood, it is played with five marbles. The latter are dropped to the scoring board from a small tablelike disk by pulling a cord attached to a marble holder. This is pulled over the edge of the disk just far enough to release one marble at a time.

The base is cut from heavy cardboard and enclosed with four sides fastened with butt joints. A block bored to a snug fit for a $\frac{3}{4}$ " dowel is glued or nailed to the center, and from each of its sides extends a slot made of two pieces of $\frac{5}{8}$ " by $\frac{3}{4}$ " stock.

Two opposite slots are $\frac{5}{8}$ " wide and are scored for 100 points, while the other two are $\frac{7}{8}$ " wide and score 50 points. These are the widths necessary when marbles $\frac{9}{16}$ " in diameter are used. Short dowel feet raise the base off the floor and keep the marbles from bouncing too high.

A heavy cardboard disk 8" in diameter has a block fastened to it to take the other end of the long $\frac{3}{4}$ " dowel. The guide is sawed to the shape shown in the drawing, and the marble slot is cut out on a jig saw or with a scroll saw. Four nails through the slot form divisions for holding the five marbles, and a small hole is bored through the end for the cord. A circular piece glued to the round end of the guide adds enough weight to keep it on the disk when the end overhangs the edge.

The player stands 3' from the disk and maneuvers the guide in an attempt to drop marbles into the four narrow slots. Only one marble should be dropped into each slot unless the first four all reach their mark, in which case the fifth may be aimed for any slot except the one last scored.



Handle on Wooden Salad Bowl Makes It a Muffin Server

handle will be attached with wooden pegs.

To make a peg, drill a $\frac{1}{4}$ " hole in the end of a piece of $\frac{1}{2}$ " dowel and glue a short piece of $\frac{1}{4}$ " dowel in the hole. Saw the $\frac{1}{2}$ " dowel off $\frac{3}{8}$ " long and the other so it projects $\frac{1}{4}$ ". Round the end of the larger dowel to form a head.

The handle can be made from orange-crane stock, a fruit-basket hoop, or maple or elm ripped $\frac{3}{32}$ " thick and $\frac{7}{8}$ " wide. Cut it a little longer than half the circumference of the bowl, round both ends, and bore $\frac{1}{4}$ " holes about $1\frac{1}{4}$ " from the ends. Soak the strip in tap water for 24 hours, following in boiling water for 30 minutes; then bend it wet on the rounded end of a board, and fasten. When dry, sand and shellac it before removing. It is attached to the flattened sides of the bowl by gluing in the pegs. Clean off surface oil if the bowl is to be decorated, and then shellac.—BERTRAM BROWNOLD.


A QUAINT muffin server can be made of scrap materials and a small salad bowl from a five-and-ten-cent store. Select a slightly oval bowl about $8\frac{3}{4}$ " by 9" and with a pleasing grain. Draw the outline of the top of the bowl on paper; then fold the paper in half to locate the spots where the

In shaping the handle, soak it thoroughly and bend it over a rounded board until it dries. The sides of the bowl are flattened and bored to receive handle pegs made from $\frac{1}{2}$ " and $\frac{1}{4}$ " dowels, as at the right



ADJUSTING LATCH PLATES

[SHIPSHAPE HOME]



Door does not latch freely. Inspect the joint between the lock stile and jamb. If the door is greatly shrunk, the latch may not enter the plate far enough to catch. This can be remedied by placing cardboard shims behind the hinges.

Should rub streaks show that the latch catches the edge of the plate opening, drive the plate toward the streak with a hammer and the point of a screw driver bearing in the corner of the opening. If the plate cannot be driven sufficiently, remove it and file the opening. In extreme cases chisel out the plate gain and screw it back in a new position. Mortises that are too small should be enlarged with a chisel.

Pressure of one corner of a warped door against the stop may prevent entrance of the latch. Adjust the latch plate or drive the stop over with a hammer and block. Too much play will allow the door to rattle.

If the door rebounds when slammed, hammer back the projecting strike to provide better wedging action with the latch.

Three



The two smaller tables slide on guides fastened under the tops to the side aprons. This makes it possible to pick up all three tables at one time

When nested, the tables make a neat appearance and occupy only a 16" by 20" floor area



NESTING TABLES STYLED FOR TODAY ARE PRACTICAL ACCESSORIES FOR ENTERTAINING IN THE SMALL HOME

FOR the moderate-size living room where tables are needed for multiple purposes on occasion, a practical and economical solution is a nest of tables. Three tables ordinarily take little more room than one table, yet when the need arises they may be brought into the open for the use of guests.

As handsome as it is unobtrusive, the set shown here can be made in the home workshop from available materials. Success in building it demands chiefly the ability to glue up perfectly square frameworks.

These frameworks are the side-leg structures, which should be assembled first by doweling together the legs, side aprons, and bottom stretchers. Be sure they are held perfectly square while the glue is drying. Then join the pairs of frames with the back and front aprons. The back aprons are placed with their faces vertical, while the front aprons are placed with their faces in a horizontal plane. This permits the smaller

tables to nest, as shown in the drawing.

The middle table is supported by its overhanging top ends upon two guides screwed to the insides of the aprons of the top table. The smallest table likewise hangs from the middle table. The overhang of all three tops is $\frac{1}{2}$ " on the sides and $\frac{1}{8}$ " on the front and back. When nested, the two smaller tables do not touch the floor. Fasten the tops on, as shown in the sketch, with screws extending upward through holes bored through the aprons. Round off all sharp corners and edges which might impair easy movement of the tables when they are being nested.

The set of tables shown in the photographs was made of scraps of walnut, the tops being glued up of several boards. Almost any wood, however, is suitable for tables of this design. Plywood, either $\frac{1}{2}$ " or $\frac{3}{8}$ " thick, can be used for the tops. Such nests of tables are also attractive in smooth paint finishes.

Tables in One

DESIGNED BY


Joseph Aronson

List of Materials

PIECES	DESCRIPTION	THICKNESS	WIDTH	LENGTH
1	TOP	$\frac{1}{2}$	16	20
1	"	$\frac{1}{2}$	$14\frac{7}{8}$	$17\frac{3}{8}$
1	"	$\frac{1}{2}$	$13\frac{5}{8}$	$14\frac{3}{8}$
4	LEGS	$\frac{3}{4}$	$1\frac{1}{8}$	$20\frac{1}{2}$
4	"	$\frac{3}{4}$	$1\frac{1}{8}$	19
4	"	$\frac{3}{4}$	$1\frac{1}{8}$	$17\frac{5}{8}$
2	SIDE APRONS	$\frac{3}{4}$	$2\frac{1}{2}$	$13\frac{1}{2}$
1	BACK APRON	$\frac{3}{4}$	$2\frac{1}{2}$	$17\frac{1}{2}$
1	FRONT "	$\frac{5}{8}$	2	$17\frac{1}{2}$
2	SIDE APRONS	$\frac{3}{4}$	$1\frac{3}{8}$	$12\frac{3}{8}$

PIECES	DESCRIPTION	THICKNESS	WIDTH	LENGTH
1	BACK APRON	$\frac{3}{4}$	$1\frac{3}{8}$	$14\frac{7}{8}$
1	FRONT "	$\frac{5}{8}$	2	$14\frac{7}{8}$
2	SIDE APRONS	$\frac{3}{4}$	1	$11\frac{1}{8}$
2	FRONT AND BACK APRONS	$\frac{3}{4}$	1	$12\frac{1}{8}$
2	STRETCHERS	$\frac{5}{8}$	$\frac{3}{4}$	$13\frac{1}{2}$
2	"	$\frac{5}{8}$	$\frac{3}{4}$	$12\frac{3}{8}$
2	"	$\frac{5}{8}$	$\frac{3}{4}$	$11\frac{1}{8}$
2	GUIDES	$\frac{1}{2}$	1	$14\frac{3}{8}$
2	"	$\frac{1}{2}$	$\frac{1}{2}$	$13\frac{5}{8}$

NOTE: ALL DIMENSIONS ARE GIVEN IN INCHES.



AIDS TO WARTIME

Housekeeping

ADJUSTABLE SHOPPING BAG. It folds into a 7" by 7½" handbag with a side opening to hold small packages. When fully opened, as at right, the bag measures 18" by 18". It is made of sturdy cotton rep with strong felt handles


THERE'S NO RUBBER in these erasers! Made of vegetable oils processed with chemicals, they will neither smudge nor tear the paper




TASTELESS TABLETS preserve the natural coloring of fruit such as bananas, plums, pears, apples, and peaches that have been cut for use in salads and the like. Simply dissolve one of the tablets in a quart of cold water, immerse the fruit for about 30 seconds, drain, and place in a refrigerator. Fruit so treated will keep its original color several days

A WOODEN JAR SEALER, shown below, fits over the top of any standard jar. Only a small amount of pressure is required for perfect sealing. A metal stud on the inside rim of the sealer molds the flange of the lid into the jar rubber. With this handy device, old lids may safely be used again and again. Save for the stud, no critical materials are used

WOODEN DUSTPANS are on the market as substitutes for hard-to-find metal types. Well built and nonwarping, they last as long as their predecessors. Shaped exactly like the metal ones, the dust catchers come attractively finished in red, black, green, or blue enamel to match or harmonize with other kitchen furnishings. One household size is available





PLASTIC SALT AND PEPPER SHAKERS. Besides adding a decorative touch to a table, these unique shakers are moistureproof and nonbreakable. The opening rests on the table, thus preventing the entrance of air into the salt or pepper chamber. They contain no metal parts for salt to corrode



LIQUID CEDAR. You can cedar-line a closet or a chest with this liquid that is painted, sprayed, or brushed on wood or paper surfaces. It retains its fragrance and does not evaporate, thus repelling moths and other harmful insects. A pint bottle of the liquid will cover approximately 200 sq. ft.





SHOE TREES made of a noncritical cellulose material fit into the toe of the shoe, as shown above, without stretching the sides or straining the stitching. They are scientifically designed to allow free circulation of air inside the shoes

SOAP FOR WOOLENS in the form of a faintly scented, jellylike preparation has appeared on the market. It is added to lukewarm water, and wool washed in it and dried properly, according to the makers, retains its original softness and fluffiness



WITH THIS HOME DEHYDRATOR, you can prepare foods for storage even if you live in a small home or apartment. A table lamp with a 300-watt bulb in it provides adequate heat for dehydration. The fiber-and-hardwood cabinet contains five trays that hold the prepared fruits and vegetables. In it, 25 lb. of tomatoes can be dried to 1½ lb., or 25 lb. of apples to about 4 lb., and stored in a proportionately small space. Such dehydrated food is prepared for use by soaking it in water






ATTENTION TO THE SAILS and running gear of your sailboat will yield dividends in longer life. Turn halyards and sheets end for end to keep them from wearing at the same spots. Mutton tallow applied to ropes where they rub against block sheaves will reduce wear there. If your sail slides aren't swiveled, leave some play in the marlin servings to avoid strain.

Mildewproof your sails with a waterproofing compound made for the purpose. Ease off the main halyard so that shrinkage in wet weather won't stretch the luff of your sail. When using reef points, tie them in such a way as to distribute the strain of the filled sail evenly along its foot. Such precautions, together with those shown in the sketches, will delay replacements and may prevent failures in use.

BOAT HINTS




by J. A. Emmett



CHECKS IN PLANKING AND DECKS


never get better of their own accord, and filling or caulking forces the opening to widen and extend at both ends. Instead, drill a hole at or just beyond each end of a check, its size in proportion to the thickness of the plank— $3/16$ " for the average $5/8$ " or $3/4$ " material. Make cedar or pine plugs a snug fit for the holes, dip them in waterproof resin glue, and tap them in, but not too hard. After 24 hours saw them off and tackle the check itself. If this is small, fill it with thin resin glue, working it well down, but if it is wide, shave off a strip of cedar or soft pine the length of the check, coat this with glue, and press it in. Dress off any excess the next day.

GREASE CUPS in inaccessible places on an outboard or inboard engine will be easier to service if extended by the use of pipe fittings. Screw a short or long pipe nipple in the cup hole, add a coupling or elbow, and screw the cup on the end. Oil holes may be tapped to take a length of small pipe or tubing, straight or bent. As an engine's parts become worn and grease cups require turning down oftener, these extensions will lessen the danger of burning one's fingers.



New SHOP IDEAS


EXTRA DRILL-PRESS SPEEDS are easily obtained by the use of a jackshaft made from an ordinary buffing head. Drill holes in the motor support in order to bolt the buffing head to it, removing the cap of the drill-press column if necessary so that the shaft may extend into the column. If this is impossible, it may be cut short. Mount a step pulley on the shaft and reverse the one on the motor. Both V-belts should be loose enough to shift on the pulleys without undue strain. With this setup, it is possible to obtain very high speeds for shaping and routing, or extremely slow speeds for heavy drilling.—WILLIAM J. PRITCHARD.



A CENTERING GAUGE that will quickly align a shaft under a milling cutter, or level work in the vise of a machine, can be made from a micrometer head and a few pieces of scrap steel. The swivel block at the lower end of the adjusting arm is bored to an accurate fit for the micrometer barrel. Two screws and milled clamping nuts lock all three members rigidly together.



To locate a milling cutter directly above a shaft or a gear blank, for example, the base of the centering tool is placed against the face of the cutter, and the arm and block are locked with the micrometer spindle close to the work and at right angles to the base. The micrometer is then adjusted until the spindle contacts the


side of the work, and the reading is carefully noted. With the gauge against the opposite face of the cutter, the micrometer is again adjusted to contact the shaft on that side, the difference in the readings is noted, and the cross-feed screw is adjusted accordingly in either direction in order to center the work.—H. D. CHAPMAN.



WOMEN WORKERS play an increasingly important part in the nation's war production, and are making their share of suggestions for speeding Victory jobs. Mrs. Helen Bering, an inspector at the Ternstedt plant of the General Motors Fisher Body Division, suggested a three-in-one gauge for checking dimensions of bearing

cups. Formerly three snap gauges were necessary, and it took one hour to check 290 cups. Now one gauge plate makes it possible to check the dimensions of 538 bearing cups an hour. The photos below show both the old and the new gauge setups.





Above, a diamond truing tool in correct position supported close to the point to minimize overhang



A tool-grinding wheel can be dressed by holding an abrasive stick against its rotating surface

TRUING GRINDING WHEELS

MACHINE grinding is the most scientifically accurate method of producing cylindrical, conical, and plane surfaces and of duplicating machine parts. In order to achieve this precision, however, grinding wheels must be perfectly trued. How this may be done is described in an article by E. T. Larson in "Grits and Grinds," a monthly publication of the Norton Company, from which the following pointers and the accompanying illustrations were taken.

All types of abrasive wheels, with the exception of diamond wheels, may be dressed with diamond tools. A dressing tool of this kind consists of one or more stones mounted in a holder, which is traversed across the face of the wheel while the revolving wheel is fed against it.

Mount the tool rigidly and with minimum overhang to avoid chatter, and also be sure that all sources of vibration have been eliminated from the grinding machine itself. The tool should be canted at an angle to the wheel face pointing in the direction of wheel travel. For this "drag angle," a maximum of 10 to 15 deg. and a minimum of 3 deg. are safe margins.

Remember that a diamond dresser is a precision tool. Avoid subjecting it to sudden shocks and blows, turn it frequently in the holder to keep it sharp, and when the diamond has worn badly return it to the manufacturer for resetting.

Before truing is begun, the wheel spindle bearings should be warmed up so that dressing may be done under normal grinding conditions. The dressing operation may be either wet or dry, but it should be the same as that of the grinding. Start truing at

the highest point on the face of the wheel, which will usually be at the center, and take light cuts—never more than .001" for finishing. Let the diamond cool between cuts.

A slow traverse gives a high finish, but if it is too slow, it will cause the wheel to be glazed. A fast traverse produces a free-cutting wheel, but one that is too fast may leave diamond marks that will be transferred to the work. During any one pass, a uniform rate should be maintained.

Cluster-type diamond dressers give better results if traversed faster than the single-point tools. When the diamonds wear down level with the matrix, the dresser can be reconditioned by rolling it up and down and from side to side against the face of a 60- or 80-grit, soft-grade, silicon carbide wheel until the diamonds are again exposed.


In truing for rough grinding, the wheel is fed into the diamond about .001", and the diamond is traversed at medium speed. Truing for finer finishes requires reduction of the traverse to the slowest speed consistent with the finish desired. The feed should also be lessened, and for very fine finishes, it is advisable to make the last two or three passes without any feed.

Because of high wheel speed, diamond wear may be relatively rapid on a thread-grinding job. The diamond, therefore, must be turned and adjusted frequently. Light truing usually results in less diamond wear, and any temptation to employ a heavy feed, even when a wheel has worn excessively, should be scrupulously put aside.

Truing of thread-grinding wheels should be done with a fairly large stream of lubricant. Three types of diamonds are



Occasional use of an abrasive stick on a metal-bonded diamond wheel will keep the surface clean



A good flow of lubricant is necessary in truing a wheel on a cylindrical grinder as shown above

FOR PRECISION WORK


used, one for each sloping side of the V-face and a third for the "flat" at the apex. The width of the wheel at the apex should be slightly narrower than the width of the flat or root of the thread to be ground so as to permit some radial wheel wear.

All shapes of grinding wheels used for tools and cutters can be dressed with an abrasive stick held in the hand, but for truing newly mounted wheels or for reshaping the face, a diamond tool should be employed.

Metal-bonded diamond wheels for offhand sharpening of cemented carbide-tipped tools should be dressed with the abrasive stick that is supplied by the manufacturer. It scours the metal bond without disturbing the diamond particles, and its occasional use will keep the surface clean and sharp.

If this dressing is neglected until the wheel cuts slowly and heats the tool, the wheel should be dismantled and rubbed by hand on a flat iron plate sprinkled with No. 180 abrasive grain. The entire operation takes only a few minutes and will clean out a wheel that has become severely loaded with steel ground from the shanks of carbide-tipped tools. Resinoid-bonded diamond wheels should be cleaned only with a piece of lump pumice such as that sold by paint shops.

Should it become necessary to grind the periphery of a diamond wheel to restore its face, the truing operation can be done by mounting the wheel on an arbor between centers in a cylindrical grinding machine. Use an indicator to see that it runs true. Rotation should be at the slowest available speed, and grinding is done wet with a soft-grade, medium-grain abrasive wheel.



TOP VIEW

Setting Cluster-Type Diamond Dresser

LOCATE DRESSER ON CENTER LINE OF WHEEL, OR $\frac{1}{32}$ BELOW—NEVER ABOVE. TURN FREQUENTLY IN HOLDER


Using Single-Diamond Dresser



NOTE: IF IN DOUBT AS TO LOCATION OF WHEEL CENTER, LOWER TOOL $\frac{1}{8}$ FOR SAFETY

To dress a badly worn metal-bonded diamond wheel, rub it on an iron plate dusted with abrasive grain





Drawings by William Patrick.



ABC's of Blowtorch Use

LIKE many another tool, a blowtorch is safe if used with care—dangerous if misused. How a blowtorch works is shown at the left. Air pressure forces gasoline up into the generating passage, which is kept hot enough by the flame of the torch to vaporize the fuel. A needle valve controls the flow of the vapor through a small orifice into the burner, where it draws in air to form a combustible mixture.

Keep the torch out of drafts while gasoline in the drip cup is burning. Pump up air pressure after the torch is lit to obtain the desired flame volume. It is a good idea to release air pressure after shutting off the torch. Empty and rinse out the fuel tank occasionally. For safety, do this in the open air.—J. MODROCH.




Slotted Guard on Wire Gauge Prevents Errors in Measuring



FOR gauging a number of parts of the same thickness, a slotted disk mounted over a standard wire or sheet-metal gauge will permit only one gauge opening to show at a time, and thus prevent errors. The guard is cut from sheet metal to the same diameter as the gauge and center-punched for a screw. A slot slightly wider than the No. 12 gauge opening will serve for this and all the smaller gauge slots. As shown, both gauge and guard are screwed to a piece of broomstick for ease of handling. A larger slot can be cut opposite the first for gauge openings Nos. 0 to 11.—RONALD EYRICH.

Flaring Tool for Copper Tubes Can Be Made from Heavy Wire

IN REPLACING gasoline lines or installing other small copper tubing, it is necessary to flare the end in order to make a tight fit with the union nut. A simple emergency tool for this purpose can be made from a piece of heavy wire of smaller diameter than the internal diameter of the tubing. Bent as shown and rotated inside the tubing by means of an ordinary brace, this forms a smooth, even flare. Care should be taken not to make the elbow bend too sharp.—R. E.




Ordinary Eraser Holds Small Brads Safely for Easy Starting



A COMMON long eraser, as shown in the photograph at the left, makes a simple device for protecting your fingers when starting small brads. Both ends should be slit back about $\frac{1}{4}$ " without cutting away any of the rubber. This will provide a flexible grip that will pick up the brads and hold them for starting. As the slit wears, shave the eraser back and deepen the slit so that it enters fresh rubber.

New Production Reamer Speeds Work in Restricted Quarters

A NEW production tool developed by Henry Bernadt, of the General Electric works at Schenectady, N. Y., not only reams holes in places difficult to reach with ordinary tools, but also has an adjustment for compensating wear. The reamer is a steel cylinder with multiple cutting edges on its outer surface that ream to specified tolerances at a single turn. Longitudinal slots permit an expansion of .002" when the tapered arbor is tightened against the washer after the reamer is inserted in the hole. These slots also compensate for cutter wear. By decreasing the thickness of the washer .001", the arbor penetrates deeper, expanding the reamer .0001".



Precision Woodworking with

By EDWIN M. LOVE

Small carving motors and flexible shafts are excellent tools for model making, carving, and light grinding. Equipped with special stands developed by

the manufacturers, such motors are capable of accurately reproducing in small scale the work of a lathe, jointer, router, and shaper. Should the home-workshop owner desire to build his own accessories, satisfactory substitutes for the manufacturers' stands




Fig. 1 UNIVERSAL MOTOR STAND




Fig. 2 ROUTING STAND




Fig. 3
VEINING WITH MOTOR TILTED




Fig. 4
SHAPING WITH MOTOR
TILTED UNDERNEATH

Small Carving Motors

Mounted on a stand built as shown on the facing page, a carving motor can be used for many delicate operations in craftwork. Here a border is being veined on a panel with a small ball cutter in the chuck



can readily be made from sound hardwood.

How are these stands built? A universal stand adaptable to any small carving motor or flexible shaft is shown in Fig. 1 and in the photograph above. Slight alterations, such as a change in the size of the motor-mount hole or in the height of the sides, may be required for your particular carving motor. Make the motor mount from a piece of 2" by 3" stock 4" long. Use an expansion bit for boring the motor hole, setting the cutter by first making test cuts in scrap pieces. Saw the mount into halves and counterbore the pivot-bolt holes at the inner ends so that the boltheads may be sunk flush.


The holes in the sides give visibility, and the L-slots, cut to allow easy entrance of the pivot bolts, provide for clamping the

motor mount at various heights and also for lengthwise adjustments of the base. Bore the base to admit the cutter, extending the hole toward one end to allow tilting of the motor. Gouge a trough at the opposite end to clear the chuck when the motor is used in a tilted position. The fence is straight on one edge and notched on the other. Fasten it to the base with two screws passing through washers or a thin yoke and the adjustment slots. The depth gauge is screwed to the top of the fence.

To increase the usefulness of the mount, make a routing column and table as shown in Fig. 2 of the drawings and in the photo at top left on the following page. The column can be held upright in a vise when in use, but a base that can be clamped to the bench may be built for it. A stop on the



Its motor mount bolted to a column, the carving motor routs out the background of a low-relief carving. The push button is held in by a wedge



Mounted on a universal stand, the motor is tilted to plane down the level of the carving. A ball point cuts best when tilted, if the work permits

side of the column makes it possible to replace the table at the proper height if it must be removed for adjustment of the work.

Can a small carving motor be used in making full-sized furniture? One job it does easily is veining, which means cutting a shallow, rounded groove in the face of the work to form a border, to separate a light-stained area from one stained dark, or to make a decorative line design. Mount the motor in the universal stand in a vertical position with the tip of a 3/32" ball cutter projecting below the base by half of the diameter of the cutter. Set the straight edge of the fence to gauge the distance of

the vein from the edge of the work, and mark the starting and stopping points of the lines with a pencil. Start the cut by pressing the fence against the guiding edge and lowering the tool until the base rests on the work. Then push the stand along the edge of the work to the end of the line. A second pass of the cutter without change of setting makes a smoother job.

To cut a border vein on circular work, reverse the fence and use the notched edge as a guide. Veining of intricate designs is best done by using the column and patterns especially cut for the work.

Ball points, in any but small sizes, cut poorly on the ends because of the meeting

Rabbeting a strip with the motor upside down and a cylindrical cutter set in a notch in the fence

Shaping the edge of a disk is done with the motor tilted to bring the side of the cutter into action



of the cutting blades at a dead center. For this reason it is advantageous to tilt the motor in the stand, as in Fig. 3 and in one of the photographs, when the work permits. The cutter, projecting at the end of the base, will be in full view and can be accurately adjusted for depth of cut by varying the tilt of the motor. The fence, fitted with its depth gauge, makes the scoring of lines parallel to the edges easy and rapid. Without the fence, the tilted cutter is efficient for shallow routing when it is not necessary to have vertical sides in the cut.

How is the routing stand used? Bolt the motor stand to the column and set the column upright in the bench vise. Insert the motor mount with the motor shaft parallel to the column. Loosen the column stop and locate the height of the table by resting the work on it and sliding it up until the cutter projects the correct distance below the top of the work. Then clamp the table and set the stop against it.

A small cylindrical cutter with scored teeth works best for routing, but it does not bore well, and therefore a hole should be drilled to depth in the center of each area to be routed. To insert the cutter in the work, loosen the table clamp and swing the front edge of the table down until the work can be placed under the cutter. Raise the table to position against the stop and clamp.


Begin routing by feeding the work lightly

against the rotation of the cutter until the blades graze the outline, steadying your hands against the table and manipulating the work with your fingers. The cutter will tend to slip into the routed area instead of gouging into the outline, thus giving positive control. Work as closely into the corners as possible. When the cavity is routed, lower the table and reset it for another. The corners can be carved out with a chisel.


How is intricate veining done? This is easiest with a jigsawed pattern placed over the work and raised above the cutter blades with shims so that the shank will bear against the edge of the pattern and will be guided by it. The pattern must be accurate, for all irregularities will be transferred to the work. If the pattern is an outside one, cut its edges larger by half the diameter of the shank; if it is an inside one, cut the pattern correspondingly smaller. Soap the edges to reduce friction.

What setup is used for operating the motor as a shaper? Insert the desired cutter and set up the motor as for routing without bolting the stand to the column. Clamp the stand upside down, as in Fig. 4 and in two of the photos. Adjust the straight edge of the fence for straight work and the notched edge for round work. When cutting coves, use a ball cutter with the motor tilted to take advantage of side cutting. Make two or three passes on heavy cuts.

Decorative Clock Case Veined with a Carving Motor



MAKE a dual pattern for the front of the clock case with one end an outside template for the panels and the other an inside guide for the border. Cut stock oversize so that the pattern, laid on shims, can be nailed to it in waste wood, and align with a nail thrust through a hole in the center of the pattern and the work. Run the carving motor around all edges; then pry up and reverse the pattern for completing the front. Assemble with glue and, when it is dry, run the top and side border veins.—E. M. L.





Privateer That Started the U. S. Navy Is Prototype for This

Schooner Weather Vane

HISTORIANS tell us that the first armed vessel to sail under the authority of the Continental Congress was the Marblehead schooner *Hannah* commissioned by George Washington as a privateer. While there are no scale drawings of the *Hannah*, research has given fairly accurate information on her size and general appearance. This weather-vane model follows these specifications, omitting only those details that would be indistinguishable on a mounted vane.

The over-all dimension of the model hull, including the stem, is $12\frac{3}{4}$ ". Use 1" or $1\frac{1}{2}$ " stock, preferably the latter. If light-gauge zinc is not available for the mainsail, any 8" by 8" light sheet metal, or even wood, will be satisfactory. The rigging is 22-gauge copper or galvanized wire fastened to the hull by winding it around partly driven pins that are later driven home.

Make a template for one side of the hull and mark the outline on the stock along with lines for painting and locations of masts, guns, and pivot bearing. Shape the

hull with square edges; then saw a $\frac{1}{4}$ " slot for the stem-keel-rudder part, as shown by the dotted lines *B-C*, *C-D*, and *D-E*. The edges are next rounded on both sides, but only to the top of the green stripe at the stern, which is square from this point to the deck. A rounded bow and square stern are important features of the design.

Drill the two $\frac{1}{4}$ " holes in the hull for the masts at a slight angle from the vertical toward the stern; then bore two $\frac{1}{4}$ " holes through the hull for the guns. The bowsprit is glued into a hole drilled into the bow. Use special care in drilling for good alignment fore and aft. Lay out the entire stem-keel-rudder piece on $\frac{1}{4}$ " material to fit the slot sawed in the hull. Glue this piece in place and sand the hull smooth.

The masts and bowsprit are tapered from $\frac{1}{4}$ " dowels, and the main boom, main gaff, fore boom, and fore gaff are tapered from $\frac{3}{8}$ " dowels. Tapering begins about one third of the way from the base, and can be done with a block plane and then sanded smooth. Give the entire hull a priming coat of flat white and two coats of enamel, coloring the stripes as indicated. The spars and bowsprit are stained brown, and the guns are black. A final coat of spar varnish will provide additional protection from weather.

The mainsail is cut to shape and small holes are punched along three edges for bending it to the mast, boom, and gaff with copper wire. File any burrs caused by punching; then give the sail two coats of flat white and one of glossy white enamel.

Shape the ends of the booms and gaffs to fit the curve of the masts at the angles shown in the drawing. Drill a small hole through the main boom at this end and start the wire around the boom and through the holes at this point, keeping the sail in the center of the boom and the wire pulled taut. Bend the sail to the main gaff in the same manner after most of the rigging has been done, further adjusting the stays if the weight of the sail requires it. Fasten the fore gaff to the fore boom with a brad, lash them together, and tack the end to the deck.

To hold the schooner for rig-



Manned by soldiers of the Continental Army, the schooner *Hannah* sailed out of Beverly, Mass., on September 5, 1775, with a commission from George Washington as a privateer. Her first prize, the British ship *Unity*, fell to her the next day. Above is a copy of a woodcut of the *Hannah* in the book *Origin of the American Navy*, by Henry E. White, which was published in 1890

By

-

CROSS SECTION AT
MIDSHIP LINE "A-A"

Attach all the rigging wires as shown, leaving ends long enough to be adjusted before final fastening. Adjust all wires for tautness and neatness; then make them fast and drive the pins in carefully. Wire ends can be soldered for strength and neatness.

The weather vane on the foremast is made of a piece of celluloid about 1" long. It adds a touch of authenticity.

Gay Designs Add Sparkle to

**BRIGHT NEW THINGS FROM DISCARDED OUT-OF-DATE PIECES
WILL GO FAR TOWARD FRESHENING YOUR HOME SURROUNDINGS**

WHEN you are digging old pieces of furniture from the attic in the hope of salvaging enough to make that spare room livable, try your skill at freehand decoration. It is surprising what it will do toward rejuvenating a hopelessly outdated bureau, chair, or even bed. With a little alteration in addition to the repainting it is highly possible that you will like a done-over piece so much you will promote it to the best rooms in the house.

While the painted decorations on furniture appear—and are—easy to do, they stem from basic principles of technique, as shown on the facing page in the sampler of Peter Hunt, of Provincetown, Mass. This illustrates several fundamental brush strokes that are used singly and in combinations to make any number of motifs. Fruits, flowers, conventional designs, and even vegetables evolve from these simple strokes. It is fun to do, and it is surprising how many attractive original designs will flow from

your palette when you become acquainted with the freehand use of small, pointed, camel's-hair brushes measuring from $\frac{3}{8}$ " to $\frac{1}{4}$ " in length.

Oil paints, available in small tubes and a variety of colors, are used for this fascinating work. The paints can be mixed and blended to make any shade desired, and white can be added to make softer tints. Oil colors are thinned for use with a little turpentine and clear varnish. This makes application easier and drying quicker. Squeeze oil colors first on a palette, which may simply be an old plate or a piece of glass, mix them as desired, and then apply them to the furniture.

Because several colors may be used in combination to make a design, it is necessary to let each dry sufficiently so that it will not mix with the subsequent coat being applied near it or, as in many cases, over it.

Try this new way of decorating old pieces that you have salvaged and rebuilt.



Decorating requires only a few tubes of oil colors, turpentine and clear varnish, and a small palette. Above, a piece of window glass serves as a palette. The gray paper under it provides a neutral background. Keep a glass of turpentine near by for cleaning brushes between colors

Old Furniture



Here is an old oil lamp that was wired, painted white to reflect light, and then decorated in gay colors and hung over a dining-room table. Left, a charming chest decorated with a vegetable motif

Photos and sampler courtesy E. I. du Pont de Nemours & Co.

BASIC DESIGNS TO HELP PERSONALIZE YOUR FURNITURE



Even if you can't draw, study and copy this sampler for decorations that will brighten up your discarded furniture. They require just a few fundamental strokes with a camel's-hair brush and, used singly or in combination, will achieve surprising and fascinating transformations.

Folding

**TAKES THE DRUDGERY OUT
OF WARTIME MARKETING,
SAVES GAS AND TIRES**

THIS sturdy and attractive shopping cart will help take the drudgery out of transporting purchases home from stores. Its tricycle wheel arrangement makes for ease in crossing curbs and allows the cart to stand alone. A shaped bag, 12" square and 21" high, made of waterproofed canvas, will fit the cart and keep a miscellany of small packages safely together. Ties at the back support it upright, and a wire bent to fit inside the seamed top edge holds the bag in shape.

The shopping cart is made almost entirely of dowels. Wheels are of hard yellow pine. Bearings for the large wheels are made of a hardwood such as maple and soaked in oil or hot wax. The maple dowel axle is given the same treatment, which assures squeak-free action for some time.

When not in use, the cart folds to a thickness equal to the diameter of the large wheels and can be tucked away in a closet. Final assembly should be made only after all the parts have been trial-fitted. Use a good grade of waterproof glue for all joints. A first coat of primer paint followed by two coats of enamel will provide a lasting finish.

A hardwood bushing that has been soaked in hot paraffin is driven into each wheel


Two collars are slipped on the front axle and doweled close to the wheel to maintain its central position on the axle



Shopping Cart



Benjamin Nielsen designed and built this folding cart to be the last word in accessories for the home shopper who does her own delivering. The color might be natural or enameled




SEPTEMBER CHECK LIST

[SHIP SHAPE HOME]

1. If basement is wet, dig outside trench and lay tile drain.
2. Dampproof cellar walls before fall wet weather.
3. Reset loose chimney bricks and capping with cement mortar.
4. Repair and paint storm windows and doors.
5. Install weatherstripping on window and door frames.
6. Enlarge fuel bin if necessary. Put in winter supply.
7. Build a cool, ventilated fruit and vegetable room.
8. Replace all loose or cracked glazing putty.
9. Take out broken window panes and install new ones.
10. Inspect sash cords. Replace any that are frayed.

POPULAR SCIENCE MONTHLY SHOP DATA

A black and white photograph of a vintage-style desk lamp. The lamp has a large, round, metallic body with a prominent circular lens in the center. It sits on a small, rounded base. A coiled cord is attached to the side of the lamp. The overall design is reminiscent of mid-20th-century industrial or scientific equipment.




drill a 3/16" hole through the center of the bottom for the wood screw, counterboring for the head. Install the hanger plate with the grain of the bottom. Turn the round-head pins and the washers, and assemble with the washers between the fork and frame. Working time: 6 hours.

PLASTIC BUTTON BOX. The plastic covers, sides, and partitions show at a glance the buttons available. Cut the birch-plywood base, sand smooth, and rout grooves for the sides and partitions. Make two end-pieces of maple, using a generous length for ease in handling when cutting slots. Drill holes for the handle and dowel hinges 1/2" deep, cut the 45-deg. chamfers, shape the tops, and sand. Mortise the base for the end-pieces; then groove the hinges and cut to length.

Clamp the three short plastic partitions between two pieces of wood and pass them across a circular saw for half-lap joints. Drill 3/8" holes through a wood jig, as shown, making semicircular cuts in the plastic to clear the hinges. Cut the long partition and saw out half-lap slots.

Assemble the partitions and cement them into the grooves in the base. Fasten the end-pieces in place, fitting in the hinges and handle. Bend the plastic sides after immersing them in hot water and fit them into the grooves in the endpieces and base. The dimensions of the sides are 1 15/16" by 13 1/4", and the top corners are rounded to clear the hinges. Brads join the sides to the cross partitions. Cut the plastic covers, leaving a lip on each for slotted dowel grips. Cement these in place to complete the assembly. Working time: 6 hours.


ERNEST R. DEWALT ARE PLANNED TO FILL REAL NEEDS



DRAFTSMAN'S SHELF. Scrap pine, three cardboard mailing tubes, and 4 sq. ft. of 1/8" composition board are used for this shelf and tracing holder. Cut three 28" lengths of mailing tube of uniform diameter. Brad the three walls together where the half-lap waste area will occur, and with a circle cutter make holes for the tubes in all three at once. Lap joints are then cut, and the corners are rounded. Drill screw holes in the outside walls and notch the middle wall to fit the saw cuts in the hangers.

Make two shelves, cutting slots as shown, and round the corners. Fit them to the walls, saw out the hangers, and screw the parts together for a trial fit. Remove the hangers to drill and counterbore for the screws.

Stain the wood pieces walnut and varnish them; then paint the tubes black. Between coats, turn the six tube covers, making the inside shoulders a slip fit for the inside of the tubes. Reverse the covers in the chuck, turn the knobs and recesses, and finish with walnut stain and varnish. Working time: 5 hours.



A SEAT AND WASHER combination now on the market not only provides a watertight seal for household faucets, but—as shown in the drawing below—it also eliminates the need for using a separate washer and screw. When installed, it expands and locks tightly in the faucet. Suitable for use in both cold and hot-water taps, the device is available in all of the standard sizes.



WALL PANELS made of a fiber insulation-board core, sealed with a special compound between two layers of asbestos and cement, are being used in homes under construction for war workers. One panel on each side of the framework replaces the sheathing, building paper, and siding or lath and stucco formerly used in wall construction. The product affords ample insulation and can be used with standard sashes and doors.



A DRY WALLPAPER CLEANER, shown in use below, literally "erases" dirt from the walls. Consisting of tiny particles of art-eraser gum enclosed in a porous cotton bag, it requires no special skill, but is merely rubbed gently over soiled surfaces. The cleaner will not cake, dry, or smudge, and is safe to use on all types of wallpaper. It can also be used successfully on window shades, white shoes, lamp shades, felt hats, books, pictures, etchings, paintings, Venetian-blind tapes, and the like. It is available in one handy, easy-to-grip size.

CIRCUIT-BREAKER PLUG. Replacing the conventional receptacle plug usually found on the connecting cord of small electric power tools, office machines, home appliances, heating devices, fluorescent light fixtures, and the like, this device breaks the circuit when a short circuit, motor stall, or accidental ground occurs. Protection is provided not only for each individual piece of equipment on a circuit, but also for the circuit itself—that is, faulty operation of one device need not affect others on the same line. To reset the plug after a circuit break, simply pull it out and lower a lever, which will have sprung from between the two prongs, back into place. This circuit breaker will do much to eliminate dangerous fire hazards and costly repair bills, and is also valuable in shops to prevent breakdowns.



OF INTEREST TO

HOME OWNERS



PLASTIC HINGES are now being used by one aircraft manufacturer on boxes for airplane tools, cases for maps, charts, radios, and the like. Chosen not only because they save essential war metals, but also because they are extremely light in weight and durable, the hinges are said to withstand long, hard wear without denting, chipping, or cracking, and their smooth, lustrous surface is rustproof and dirt resistant. Strips may be cut to any desired length and are easily attached to other materials by means of adhesives, rivets, or screws. They can be made in many colors, and they offer endless possibilities in the designing and manufacturing of light and portable equipment. Such hinges may, in the near future, replace metal ones in a variety of light-duty applications.

THIS SOIL-TESTING KIT, consisting of about 60 strips of chemically treated paper and a color chart for comparing results, comes conveniently packed in a 3" glass tube. The paper, after being inserted in a slit in the ground made with a knife, changes color according to the condition of the soil. Its hue is then compared with the chart to determine whether the acidity or alkalinity of the soil is such that will need correction.



LEAN-TO BASEMENT GREENHOUSE. You can raise flowers and vegetables the year around in this greenhouse, which is easily erected alongside an open basement window. Constructed of red cypress and double-strength glass, it comes semi-assembled and can be put up in less than a day. It is available in three, four, and five-section units measuring from 4' 4" to 7'. Entrance is possible through a door at the end or through a cellar window. In winter, heat from the basement provides the proper temperature, but on extremely cold days a small kerosene stove or electric heater can be used.



HOSE HORSE FOR GARDENS. Simple in construction, the all-wood "horse" shown above holds the hose in such a manner that a spray or stream can be directed on the area desired. By simply adjusting the rear leg, the hose can be placed in any position. The device is covered with a water-repellent wood preservative and comes knocked down, with easy instructions for assembling. It can be set up without the use of screws or nails.



HAVE you ever repeated a scene until, through its very repetition, your audience laughed uproariously? That's what Hollywood calls a "running gag." Have you ever stopped motion, varied your filming speed, or reversed action by filming a scene upside down? Professional productions, including the newsreels, employ all these ruses to get laughs.

There's no reason why home movies, adopting the same simple technique, can't provide merry as well as informative shots of the family and friends. Laughter is an important morale builder, and it doesn't cost a cent. There's no need, either, to make elaborate setups or produce involved continuities, for with a few twists of the wrist the camera will make your scenes funny. Professional movie makers build comedy from situations and dialogue. But you needn't worry about writing funny lines; just produce situations—some with your people, others with your camera.

Take the running gag, for instance. No trickery is involved in it. You need only straight shots to liven up your little document. Suppose you plan to film a summer picnic at the park. Show your friends pitching horseshoes, playing ball, swimming in the pool as usual, but at intervals make a few shots of Dad on the spring board. Have him walk out on it, then change his mind and return to his easy chair. The first sequence should show the entire routine, from chair to board to chair. No one will laugh at this, for this is Dad's regular ritual.

Then shoot successively shorter scenes of each appearance, until you show only his feet as he stands on the board, with his toes wiggling apprehensively. On his last appearance, return to a medium view, and have him walk out to the end, pose, lose his balance, and splash into the water.

Running gags need not be funny in themselves to get a laugh. Repetition alone becomes hilarious. One of the dignified men at your party, for example, repeatedly tries to light his pipe, only to have the match blow out. Or one of the young ladies attempts to powder her nose, without success because the breeze blows the powder from her compact. For the "payoff", the man takes a pipe, already lighted, from his pocket and calmly proceeds to smoke, while the girl gives up and tosses her compact aside.

One way of giving your movies an



Long a specialist in directing children, Charles Lamont makes frequent use of the laugh-getting methods he describes in this article. They add punch to his latest Universal Studios picture, "Oh, Doctor," starring Abbott and Costello. Stop-motion in the sequence below lets a new child, and finally a dog, be put in the barrel after each climbs out. It looks like magic



Putting Laughs INTO YOUR Home Movies

BY CHARLES LAMONT
DIRECTOR, UNIVERSAL STUDIOS

amusing twist is by interrupted action. This is a way of making things happen on the screen that you know can't happen, but which your eyes insist can. It is accomplished by stopping the camera, changing actors or props, and then shooting again.

Using this trick, you can have a lot of film fun with four or five children and a barrel. Set up your camera for a medium shot of an ordinary barrel. Plant the first child inside the barrel and make a shot of him emerging and taking a position alongside it. Stop the camera and put the second child in the barrel. Take him coming out, stop the camera again, and repeat the same procedure until all the children have been taken. You probably will want to title this

one "The Magic Barrel" or some such name, as it will seem that only by some act of legerdemain could so small a barrel hold so many children. It is essential, however, that you set your camera on a tripod or some other steady support, and see that no one disturbs it during the entire time.

The newsreels frequently use stop-motion to emphasize speed. For example, they show people racing out of a subway station to the opening game of the World's Series or scooting across an intersection as a traffic cop waves his arm like a berserk semaphore. This effect is achieved simply by cutting camera speed in half. An occasional flick of the exposure lever makes the scene look like a panic. Even everyday scenes can be made humorous this way.

Set your camera at half speed and make some shots of the youngsters playing about the house. When you project the film on the screen at regular speed, they will seem to be moving at a breakneck rate. Follow this with a normal shot of Mother calling them for their baths; then double the camera speed to slow them down to a snail's crawl as they answer the summons. Many variations of this idea will occur to you.

Don't forget, though, that changes in speed require accommodating changes in exposure. Every change in stop doubles or halves the exposure. If, for instance, you shoot a scene at standard speed at $f/8$, the diaphragm should be set at $f/11$ for half





speed, or $f/6.5$ for double speed. Slow motion heightens interest in many subjects. A calf chases baby across the garden. When the calf is taken at half speed to make its galloping seem faster and the baby in slow motion in order to stress her danger, you have a simple but effective formula for a mirthful sequence.

In the same way, upside-down filming offers many opportunities to provide silly sequences. This is also an old newsreel chestnut. Remember those episodes in which a diver slid feet-first from the water, tumbled upward to land on a high spring board, and walked backward to the platform? All you need do to take such a sequence is to place your camera upside down and make the exposure as the subject

walks out and dives off the board in the usual way.

A simple application of this, to show Junior with extraordinary control over his bike, will make the bike appear to get up off the ground and roll into his hands when he whistles for it. Turn the camera upside down and make a shot of him pushing the bike away. The wheel rolls over and falls on the ground. Now turn the camera over to the normal position and take him standing and whistling as if for the bike. Stop the camera, have someone hand him the bike, and then make a normal shot of him riding away.

When the first shot is cut from the roll and sandwiched top side up between the other two, it will look on the screen as if the bike had come up from the ground at Junior's command.

In trying this stunt with two or more persons, you must have them appear throughout in the correct order from left to right. There's nothing to worry about if you have a 16-mm. camera. When you cut the picture, simply turn the inverted strip end for end with the same side of the film facing you. However, with 8-mm. film it is necessary to reverse the faces of the film when it is turned end for end in order to keep the perforations on the proper side. For this reason, reverse motion cannot be made on 8-mm. film when more than one person ap-



Upside-down shooting will make the tossing away of an armful of bric-a-brac look like a series of humorous catches when the film is projected. Possibilities are limitless



Reverse action, like that above, is taken with the camera upside down. Here the boy really pushes his bicycle away and lets it fall to the ground; but shot upside down, cut from the film, and then turned and spliced, the sequence makes it appear as if the wheel rises at his command. He is photographed normally as he rides off

appears in the scene, since two or more will seem to change places.

All sorts of gags can be brought off by this time-tried stunt of reversed action. For example, dispute your wife's skill as a cook by making egg yolks jump back into their shells, cake batter flow back into the mixing bowl, steaks (if any) leap from the broiler up to her hands. Water soaking Dad's Victory garden can be made to appear to drain back into the hose and leave the earth dry.

Here's another stunt: Have your subject hold an armful of objects such as a vase, a pitcher of water, and one or two other fairly fragile things, and toss them one by one to someone outside the picture. He should use a straight-arm technique, tossing the objects up as well as away from himself and finishing with the palm of his hand open and facing upward. Filmed upside down, this stunt will give every appearance of a series of catches. It will be breath-taking. A similar sequence in which knives are seemingly caught would be especially so.

Did you ever want to stand on the cowcatcher of a train or the front of a street car and film the tracks as the vehicle rolled along? You can do just that, and easily, if you take your position on the rear and shoot at the receding track with the camera upside down. And to "prove" you actually made such a hazardous sequence, have someone grab shots of you climbing on and off the cowcatcher and run these as the introductory and closing scenes. But be sure to reverse the scenic strip!

Jumping offers good reverse-action possibilities. Little Johnny probably can't jump over fences without falling. Stand him on

top of a fence and, with the camera right side up at a 45-deg. angle to the line of jump, make a shot of him leaping forward. Then have him jump backwards from the same spot on the fence and run backwards from where he lands while you shoot him with the camera inverted. Reverse this last scene, splice the two, and you have an excellent sequence showing Johnny clearing an obstacle higher than his head.

These trick shots are intended to get laughs, not to build up feature productions. Nonstandard camera speeds, upside-down filming, repetition, and stop-motion are methods, not materials, and require none but natural props that are available to everybody.

Subjects are too numerous to name. Divers, hurdlers, long-distance runners, golfers, tennis players, soldiers on parade—slow motion will show their form and add interest to their performances.

Simply pick out your subject, apply the technique you desire, and you'll be producing short subjects the like of which have never before been recorded by your camera.



Accurate weighing with this small beam scale will help the amateur photographer get better results in his home developing and printing

DARKROOM SCALE

BUILT FROM WORKSHOP ODDS AND ENDS

By ROGER MOYER

THIS scale, sensitive to 1 grain and suitable for weighing ingredients in photographic and home-laboratory formulas, can be made from bits of scrap. Its 4-oz. capacity is sufficient for most of the amateur's needs.


The main and supplementary beams of the scale shown were made of scraps of aluminum, but another metal or even plastic will serve.

Turn the brass standard first and fasten it to a temporary wood base until the assembling, testing, and calibrating are completed. Notch the bearings in the top for the knife edge with a file and finish with a

scrapping cut with a sharp knife. Strive to get the notches as straight and smooth as possible, for upon this the sensitivity of the scale depends.

The knife edges can be ground from a piece of tool steel, or the tang of a file can be hammered to approximate shape, hardened, ground, and then finished on an oilstone. A 2" tang will make the two knife edges with a piece to spare. Adjust them so that they are parallel to each other and at right angles to the beam.

The poise for the main beam is a piece of brass tubing filled to the slot with molten lead. This leaves some lead to be drilled out to bring the weight to exactly 1 oz. The poise for the small beam should weigh



27 11/32 grains, or 1/16 oz. Make it a little oversize of light metal so that it also can be drilled from the bottom to the exact weight. The counterweight is a piece of brass tubing filled with molten lead after the stirrups have been inserted. A pan 4" in diameter and 1/2" deep can be cut off the bottom of a 10-cent plastic bowl.

In testing and calibrating the scale, it is necessary to have a 1/4-oz. and a 1-oz. weight. Assemble the scale in a level position with the pan in place, and set both poises at zero, marked in pencil on the beams. Drill lead out of the bottom of the counterweight cautiously, testing from time to time, until an exact balance is obtained as shown by the indicator at the end of the beam. Now place a 1-oz. weight in the pan and move the large poise out on the beam until it balances. The distance the poise has been moved should be just 1".

The small beam is tested with a 1/4-oz. weight in the pan, and the distance the poise is moved to balance the scale should

be just 4". The zero marks on the two beams are directly in line. Since the small beam is graduated in 2-grain divisions, and there are 109.375 grains in 1/4-oz. avoirdupois, the 110-grain division will be about 1/64" beyond the 1/4-oz. division.

Check the scale several times; then mark all the divisions in pencil. Permanent marks are made with a small, sharp chisel, and figures are stamped with dies. A little carbon black will make them readable. Minor variations can be adjusted for by turning the balancing nut to right or left.

If it is desired to calibrate the scale in metric units instead of avoirdupois, use a newly minted nickel, which weighs 5 grams. For weight measurements by grains, use a newly minted cent, which weighs 48 grains. Paper clips may be balanced with a cent, for instance, and counted for use in subdividing the 48-grain measurement.

Fasten the finished scale to the bottom of a box as shown, where it will be ready for use when the pan is placed in position.



TWO-PART JARS (above) in which developers are sold form useful containers for photographic solutions that must be used together, such as hypo and ferrocyanide reducer. The upper compartment will hold 2 oz. of potassium ferrocyanide solution, and the lower one 6 oz. of ordinary hypo. The amber glass of the container protects the solutions from harmful light action.—JOHN K. KARLOVIC.

A WINDING FORM for the cord of a home-movie projector, shown below, helps prevent tangling and accidental disconnection of the plug when the machine is in use.


The form is 2 1/4" by 12" and can be cut from a scrap of 1/4" plywood. Saw a notch near one end to receive the toggle switch and connecting plug. Cut a slot along the same side so that the cord may be taped securely to the winding form as shown in the photograph.

When the projector is not in use, the plug is disconnected and the cord wound on the form inside the notches at both ends. Thus coiled, it is easy to carry.—R. WOODBURY.



CARBON DRAWING PENCILS serve well for spotting glossy prints. The point of the pencil is kept just moist with the tongue or, if much spotting is to be done, on a damp cloth. A special advantage is that spotting done with such a pencil is not affected by repeated ferrotyping. Keep the pencil well sharpened.—WILLIAM SWALLOW.

home EXPERIMENTS SHOW HOW GASES BEHAVE



BOYLE'S LAW, which states that the volume of a given quantity of gas is inversely proportional to the pressure upon it, can be demonstrated with a 40" long glass tube bent into a J-shape with the short leg about 6" long. Seal the tip of this leg. Support the tube vertically and pour just enough mercury in it to fill the bottom and rise equally in both legs as at the far left. The air in the short leg is now at normal atmospheric pressure. Pour more mercury into the tube until it stands at a height of about 30", as in the second photo. The air in the short tube is now subjected to the pressure of an extra atmosphere produced by the weight of the mercury. Compare the height of this column of air to that in the first experiment. You will find that it is only half as tall.



CARTESIAN DIVER. Fill a test tube with just enough water so that it will barely float bottom up in a cylinder or vase filled nearly to the top with water. If you seal the top of the cylinder with the palm of your hand and press down strongly, the test tube will sink. Relax your pressure, and the test tube will rise. The explanation is simple. By compressing the air above the water you transmit the pressure through the entire body of water, which in turn compresses the air in the test tube, reducing its buoyancy.

A MODEL GASWORKS TANK will demonstrate how the big ones that supply your kitchen range store gas under pressure. Punch a hole in the top of a tin can having no bottom and seal in a glass tube drawn to a jet. Into the side of a slightly larger can seal another tube bent as shown below. Attach this with a hose to the jet of a stove burner, fit on a pinch clamp, and fill the can with water. Insert the smaller can, which will sink as air escapes through the jet. When it has sunk, turn on the gas, which will lift the can. Turn off the gas and let the can sink again. Repeat until all the air is expelled; then fill the can with gas, shut off the supply, and light the gas issuing from the jet. It will burn at almost undiminished pressure until the can is empty.






ALL GASES shrink evenly when pressure on them is increased, and they expand evenly when, at a given pressure, their temperature is raised. This law is easily demonstrated. Seal one end of a narrow, 6" long glass tube; then drop mercury into the tube so that a plug is formed about halfway down. Stand the tube in a tumbler of cracked ice. When the mercury has descended as far as it will, remove the tube and mark the place with thread. Suspend the tube in the steam of a flask of boiling water. When the mercury stops rising, mark this place with thread. Measure the distance between the threads. The distance the air has expanded from 0 deg. C. to 100 deg. C. is $100/273$ of its original length. For each degree, the expansion is $1/273$ of the volume at 0 deg. C.



WHAT MAKES A SIPHON WORK? Two glasses are half filled with water and connected with rubber tubing full of water as shown below. Raise one glass so that the water in it is above the level in the other glass, and water will start flowing through the siphon and keep on flowing until it is again level in both glasses. The explanation for this is shown in the drawing. The upward pressure on the water in the tube at A is equal to atmospheric pressure (as shown by the arrow) less the weight of the water column AB, while the upward pressure at D is equal to the atmospheric pressure less the weight of the longer column DC. The siphon flows toward the lesser pressure until both columns are the same height.

THE SIPHON AND AIR PRESSURE. Join two small bottles, one of which is partly filled with colored water, with a bent glass tube. The siphon arm which goes into the water-filled bottle is first passed through a cork which seals the bottle. Place the apparatus in a jar which can be tightly closed. If you suck strongly on a glass tube sealed in the cover of the jar, water from the sealed bottle rises in the siphon tube and pours into the open bottle. Let air into the jar, and the water returns to the sealed bottle.





You can make this vital element in your home lab with the gas-collecting apparatus shown above

Oxygen

MAINSTAY OF LIFE

Home Experiments with This Vital Element Help Explain How Fire and Corrosion Act

By **KENNETH M. SWEZEY**

DO YOU know that iron and steel will burn; that the reaction of cold chemicals may produce fire; that the rusting of iron produces as much heat as the actual burning of the metal? Can you explain the mystery of spontaneous combustion? These are just a few of the facts that can be demonstrated by experiments with oxygen, the most widely distributed and abundant of all the elements.

Where can you find oxygen? It might be

easier to list the places and substances where you cannot! Look in the mirror, and behold there a creature made up of 65 percent of this gas by weight! The waters of the sea and the water you drink are nearly 89 percent oxygen. Oxygen makes up about 21 percent of the air you breathe. Oxygen in the earth's crust weighs nearly as much as all the other 91 elements put together—including iron, lead, copper, and all the metallic elements.

Despite its abundance, oxygen was not discovered until a year before the Revolutionary War. Recall that oxygen is a gas without color, taste, or odor, and you can understand how it kept its identity a secret for so long.

Priestley, an English clergyman, made the discovery. He placed some red mercuric oxide on a column of mercury in a glass tube

similar to a barometer tube and heated the oxide by focusing the sun's rays on it. The column of mercury was pushed down, showing that a gas had apparently been produced. Priestley thrust a glowing splinter into the gas and found that the splinter burst into flames. Breathing some of the gas himself, the experimenter felt invigorated. A new gas had been found, which was called oxygen by the famous French chemist Lavoisier, who also showed that the gas could be made to combine with other substances.

Today, huge quantities of oxygen are made by the electrolysis of water, and by the fractional distillation of liquid air. When an electric current is passed through water, its molecules are broken into atoms of oxygen and hydrogen, which may then be collected separately. Since the boiling point of nitrogen is lower than the boiling point of oxygen, nitrogen evaporates first when liquid air is allowed to boil. When the nitrogen has all boiled away, oxygen alone remains.

In the home laboratory, oxygen may be made easily by heating a mixture of potassium chlorate or potassium perchlorate with powdered manganese dioxide. Perchlorate, if obtainable, is preferable to ordinary chlorate, as it is a more stable chemical and its release of oxygen is more easily controlled.

Mix together—without grinding—a few grams of the potassium perchlorate with about a third as much manganese dioxide. Place this in a heat-resistant test tube and clamp the tube almost horizontally on a support, as shown in the photograph on page HW 432.

As oxygen dissolves only slightly in water, the gas may be easily collected in a pneumatic trough. Part of a tin can, with a hole punched in the top and a slot cut in the side, will serve as a support for the inverted bottle in which the gas is to be collected. Bent glass tubing, connected by rubber tubing, leads the oxygen under the water in the trough into the mouth of the collecting bottle. The latter should be filled with water. A square of cardboard or glass is held over the top until the bottle is placed on the support with its mouth under the water. As oxygen is generated, it will slowly bubble up into the bottle, gradually replacing the water in the latter.

Heat the test tube gently with an alcohol lamp or Bunsen burner turned low, moving it along the tube to heat the latter evenly. Then increase the heating until gas commences to bubble from the delivery tube. The first bubbles may be allowed to escape, as these are air being driven from the tube. The following ones should be directed to bubble up into the collecting jar. The flow of oxygen can be regulated by controlling the heat.

When the jar is full, slip the cardboard or glass plate under it again and turn the jar upright. Keep the plate in place to prevent the oxygen from diffusing into the air. Before withdrawing the flame from the test tube, be sure to remove the stopper from the tube; otherwise water will be sucked up from the trough and will crack the hot test tube.

Many substances which burn feebly or not

At left below, a small piece of steel wool which has been ignited glows at red heat in ordinary air. When placed in a jar of pure oxygen, however, as at the right, it at once bursts into bright flame. The presence of oxygen increases the rate of combustion to such an extent that an intense heat results



at all in ordinary air will burn brilliantly in the oxygen you have collected. Thrust a glowing splinter of wood into it, and the splinter will burst into bright white flame with almost explosive suddenness. Twist a short length of iron wire around a small wad of fine steel wool and ignite the steel wool in your Bunsen flame. It will merely glow red. Thrust it quickly into your oxygen tank, however, and it bursts into brilliant flame.

When oxygen combines with other substances so rapidly that the heat of this combination produces flame, we call the reaction combustion. But *all* oxidation produces heat, whether the heat is apparent or not. The rusting of iron or steel, for instance, produces as much heat as the burning of the same metal. This form of oxidation is so slow, however, that the heat is dissipated as fast as it is generated.

A simple experiment will prove that rusting produces a rise in temperature. Wrap the bulb of a thermometer with fine steel wool; then moisten the wad of wool with some dilute acetic acid, which will act as a catalyst to speed up the rusting of the metal. For best results, the acid should be at room temperature, and the moist steel wool should be protected from drafts. Rust will quickly appear, and as it does, the mercury in the thermometer will slowly rise.

Spontaneous combustion is the result of



Steel wool, a few drops of dilute acetic acid, and an ordinary thermometer can be used to prove that oxidation does actually produce heat

the accumulation of heat due to slow oxidation of inflammable materials under conditions where this heat cannot be dissipated. The linseed oil in paints, for example, dries into a tough film because of the combination of the oil with oxygen in the air. Heat is generated, but when the oil is spread over a surface, this heat vanishes as fast as it is produced. Throw rags soaked in linseed oil into a pile, however, and you bottle up the heat of oxidation to such an extent that you produce a dangerous fire hazard.

To demonstrate the heat of oxidation of linseed oil, insulate a jar by placing it in a box stuffed with crumpled paper, and place in the jar a rag or bit of cotton waste wet with this oil. Place a thermometer in the midst of the

rag, and observe it periodically. The temperature climbs steadily. If left long enough, the rag would probably catch fire.

Rapid oxidation resulting in combustion may be produced by the reaction of cold chemicals. Place a few grains of sodium peroxide on some absorbent cotton. Add a drop or two of warm water. Almost instantly the cotton will burst into flames.

Even the familiar hydrogen peroxide may be made to produce oxygen. Heat, alkalies, and even dirt or powdered glass will cause it to decompose. Powdered manganese dioxide dropped into the liquid will cause the gas to come off rapidly.

Place a little sodium peroxide on a wad of cotton and drop some warm water on it as in the first and second photos below. In an instant the cotton flares up as at the right. Reaction between the sodium peroxide and the water oxidizes the cotton so rapidly that it bursts into flame almost immediately






Except for the bed rails, which should be sound, straight stock, scrap can be used to advantage

Collapsible Bed Has No Metal Parts

THIS bed is the perfect answer to your extra bed problem. The scarcity of materials is no hindrance to constructing it because the only metal used is in the casters. The chassis is completely separate from any other part of the bed, and can be used with any type of spring and mattress. A further advantage is that the bed can be taken apart for storage or shipment, and easily reassembled.



The standard height for beds is specified in the drawings, but this can be altered to suit personal needs. Simply measure the spring and mattress and make the legs as high as desired. If made of poplar and oak, with turned feet as shown in the drawings, the rails and legs may be painted bone white, and the caps and turned feet stained a warm brown.—J. I. SOWERS.



This attractive bed base can be built to fit any type of spring regardless of size. Notice end rails have rabbet and dado but side rails dado only

Microscope Specimens Mounted with Cardboard and Tape

AN EASY way to mount dry microscope specimens permanently is to place each in a cardboard cell secured to a slide with ordinary adhesive tape. The cell must be of the same thickness or slightly thicker than the specimen so that the cover glass will not crush it, and it should be of the same area as the cover glass. An opening may be made in it with a paper punch or cut square with a sharp knife. When specimen and cell are in place, cover with the glass and fasten all to the slide with strips of common adhesive tape. A label may be attached at one end for identification. The tape can be varnished for permanence.—H. F. WHITTAKER.



Wire Trusses for Model Yards

TRUSSES to support the lower yards of ship models may be easily made from square copper wire as shown in the drawing above. Hammer the ends of the wire flat, and flatten the middle also so that it can be drilled for an escutcheon pin. The two ends are then bent around the yard as shown and soldered in place. This type of truss will be found entirely suitable for most ship models.—S. P. ROBBINS.



Above is a "before and after" photo in the life of a paintbrush. The bristles were all a hardened mass, but the ones on the left side were given a thorough cleaning until they emerged soft and glossy. Compare them with the caked bristles on the right side


How to

**EVEN THOSE WITH BADLY
CAKED BRISTLES CAN BE
SOFTENED, CLEANED, AND
RESHAPED SO AS TO GIVE
GOOD SERVICE ONCE MORE.**

By ALBERT Q. MAISEL

DON'T throw away that old paintbrush. It may be as hard as a board, bristles may have dried askew, some of them may be missing; but the chances are that there is plenty of life left in the old brush yet. It may need only a cleaning to get out the caked paint and to restore flexibility. If it happens to be a brush made of Chinese hog bristles, which are now scarce, it's worth its weight in gold. Just so long as the bristles are firm in their base, any old brush can be re-claimed.

The first step is to soften the hardened heel in a solvent. Never try to break loose even part of a caked heel while the brush is dry, for you will break valuable bristles in the attempt. Benzine can be used as a solvent, or any good commercial paintbrush cleaner. Use alcohol for old shellac brushes. Put just enough of



Put Your Old Paintbrushes Back to Work

the fluid in a glass container to cover the bristles but not the setting and ferrule.

Soak for 10 minutes; then knead the brush in water to wash out the loosened paint, repeating both steps until the heel is soft. Most of the paint will come out in the water, and the remaining solvent can be strained through a cloth and stored away for future use.

Now spread the bristles with your fingers and sift fine, dry, hardwood sawdust down into the deepest parts of the brush. Then, under a stream of water in a sink, work the brush back and forth over a washboard or a rack made as shown in the drawing. Five to 10 minutes of this, with the addition of more sawdust as required, will clean the worst caked heel. The sawdust picks up particles of paint and carries them away in the water. Any flakes of dried paint remaining can be removed by working the paintbrush across a stiff fiber scrubbing brush held bristles up in a vise or nailed to a bench top. Be sure the paintbrush bristles point backward as you draw them over the fiber brush.

The soaking-wet, soft bristles will stick out in all directions. Comb them straight with a fine comb and remove any loosened ones by grasping them between the blade of a paring knife and the thumb.


Next, wrap the brush in stiff kraft paper to preserve the fine chisel edge while it is being dried. Perforate the paper for better


ventilation and fold it as shown in the drawings. Drying can be done in the hot sun, or over an infrared lamp or an ordinary bulb placed in a box as shown below. A brush of average size will require 45 minutes to one hour to dry, and it should be turned over every 10 minutes during this time. This insures even drying and prevents curling of the bristles.

When thoroughly dry, a brush may need a final combing, and the bristles may be trimmed if they have worn very unevenly. This may be done with a sharp knife or a razor blade. Be careful to cut off no more than absolutely necessary.


Now take a look at the handle, which may be spliced if it is damaged or broken. If the ferrule holding the bristle base to it is loose, it may be tightened. A couple of brads through it into the wood may do the trick, or on some types a wooden wedge may be driven in to make a tight fit.

Take care of the brush once you have it back in shape. Never use force to daub its end into corners, and don't use a brush edgewise. Dip the bristles not more than halfway into the paint. Put the first two coats on rough surfaces with a worn brush, rather than with a new one. Avoid kerosene; it won't evaporate, doesn't mix with paint, and may damage the setting. When left in turpentine, a brush should be suspended so that it won't rest on the bristles. A rack like the one shown below is good.






Laid face down on a glass in the top of this box, a picture may be projected onto a screen. The hinged lid holds it flat



Set at an angle of 45 deg., the mirror reflects the image of the picture above it through the tube (shown above, right, before assembly) to the lens, which in turn throws it onto the screen. Below, a view of the projector with the top off




WITH an opaque-picture projector, or post-card projector, you can throw enlarged images of drawings, photographs, and magazine clippings on a screen in full color. Besides providing entertainment, such a device is useful in instructing groups of people, copying art work, and lettering.

Dimensions of the box can vary, with the possible exception of the height, which is 8" and correct for a lens of about 9" focal length. For a shorter focal length, the height should be reduced. The distance from lens to mirror to picture must be approximately equal to the focal length of the lens.


The mirror is mounted on a piece of $\frac{1}{2}$ " plywood which, in turn, is fastened to a wooden block the upper surface of which is at a 45-deg. angle to the front of the box. A single screw holds the block to the bottom of the box, thus permitting the mirror to be swung slightly to line up the image. Once the mirror is adjusted, the screw is tightened.

The width of the box from front to back may have to be altered, according to the sockets used, to bring the lamp filaments approximately into line with the center of the picture to be projected.

Air space around the lamps protects the wood from heat. An



SINGLE LENS MOUNTING



opening along the bottom of the back and holes in each end provide ventilation. Wire the sockets in parallel, run a cord out through the ventilating slot, and install a through-cord switch a foot or so from the box. The top of the box has a rectangular opening, rabbeted or provided with strips to receive the glass. The glass merely lies in the recess and may be lifted out for cleaning or changing a lamp. Metal hinges or leather strips are used on the hinged lid.

The lens is the most important part of the projector, for upon its performance depends the sharpness of the image. An anastigmat of $f/4.5$ speed or greater and a focal length of 8" or more is best. Such a lens may be taken from a view camera or from another projector. An ordinary reading glass 2" to 4" in diameter and with a focal length of about 8" may be used, but image sharpness will be improved with a multiple lens arrangement.

Mount the lens at the end of the tube near the box, and 3" or so in front of it mount a diaphragm made by cutting a round hole in a cardboard disk. Experiment with hole sizes to determine the best diameter. The smaller the hole, the sharper the image, but illumination decreases as the diameter of the aperture becomes smaller. There is, fortunately, a happy medium. Paint the diaphragm flat black on both surfaces and the edge


of the hole; then cement it to the lens tube.

Two lenses of the reading-glass type, each having a focal length of about 18", can be combined into a two-lens projection objective, as shown in one sketch. Experimenting will reveal the exact spacing of lens elements. To determine focal length, hold a lens so it throws a sharp image of a distant object on a sheet of paper and measure the distance from lens to paper. The lens mount illustrated was made from a cardboard tube and lid. The lid, with its end cut away, became the outside of the lens mount, and a piece of the tube made the movable inside section.

Cut black paper to mask the sharp section of a projected image and paste it on the glass in the top of the box. Cover the underside of the lid with black cloth to keep light from leaking around the edges.

PICTURE PROJECTOR

GIVES BIG, FULL-COLOR IMAGES
FOR ENTERTAINMENT, INSTRUCTION,
OR COPYING OF DESIGNS, ART
WORK, AND LETTERING ALPHABETS



Harnessing Electrons

WHAT HAPPENS IN THE DIODE—SIMPLEST OF FIRST STEPS IN ELECTRONICS

By JOHN W. CAMPBELL, JR.

IT IS a triumph when the electrical engineer produces a device that can break a circuit in 1/100 second, but the electronics engineer can turn a current on and off 500,000,000 times a second. The electrical engineer's control of electricity depends upon relatively crude, slow-acting mechanisms such as rheostats, fuses, circuit breakers, and solenoids; the electronics engineer controls the electronic flow by means of other electrons forced to work in the confines of electron tubes.

These tubes are used for detecting radio waves, amplifying currents, generating alternating currents of practically any frequency, and rectifying alternating current to direct current. Applied in sound motion pictures in the form of highly sensitive photoelectric cells, they convert the varying light density of a film track into sound. Special electron tubes react to the light of a star a billion billion miles away, probe for a bullet, and control big guns with superhuman accuracy.

We know (Fig. 1) that electrons can be repelled by or attracted to a body by putting an electric charge on that body—that is, by crowding other electrons onto it or by robbing it of electrons. By applying this principle inside vacuum tubes, we gain control of these invisible miracle workers. The simplest vacuum tube consists of an electron-emitting electrode, called the *cathode*, and a target for the electrons, called the *plate*. Triodes (three elements), tetrodes (four elements), and so on are only diodes to which additional control elements have been added.

Since the current that will pass through the tube consists of the electrons emitted by the cathode, it will be limited by the number of electrons we can free from the metal of which the cathode is made. The atoms of the metal exchange outer electrons freely;

these electrons may wander at will among the atoms and, if extra electrons are crowded upon one end of a wire by connection to a battery or generator, an equal number of atomic electrons promptly appears at the other end. But unless outside force is applied, the electrons cannot escape from the wire. This is shown in Fig. 2.

Our problem is to supply the electrons with sufficient extra energy to enable them to break loose from the atoms and escape from the metal altogether. This we can do by heating the metal, since heat causes motion of atoms and some of this motion is imparted to the electrons. How much heat is necessary depends upon the nature of the metal or alloy.

Radiant energy such as light, X rays, or cosmic rays will also free electrons by imparting motion to them. Light striking the sensitive element of your photoelectric meter knocks out electrons that flow through a sensitive galvanometer and move a needle to indicate what exposure you must give a scene in photographing it. Cosmic rays, present everywhere on the earth's surface, are always freeing electrons from matter. A single electron striking a metal target at high speed may blast out a number of other electrons before it finally comes to rest. This method is used in Zworykin's electron multiplier, a special multiple diode that can amplify currents more than a billion times.

When a single atom of radium explodes, it shoots out electrons at tremendous speed, as well as high-power X rays called gamma rays. Both of these knock electrons out of any adjacent atoms, and with such violence that these electrons knock out others in turn, until hundreds or even thousands are freed (Fig. 3).

Thermionic emission—the freeing of electrons by heat—is the simplest method and the one most frequently used. Cathodes in modern tubes are coated with certain alkaline-earth oxides that release electrons at moderate temperatures. The

In this X-ray tube, 400,000 volts are required to drive electrons from the filament across a gap to the target



in Glass

ALL VACUUM TUBES

cathode is usually heated by a filament similar to that in a lamp bulb (Fig. 4). In early tubes and some modern types, the filament itself is the electron-emitting body.

If to the plate of the tube in Fig. 4 we apply a positive charge by connecting it to the positive (electron-deficient) side of a battery or generator, electrons emitted from the cathode will be drawn to it and will constitute a current in any outside circuit we may arrange. But if the cathode is positively charged, electrons driven out by the thermionic effect will promptly be drawn back, and no current will flow.


Here the first characteristic of the vacuum tube appears—it will pass current in one direction only. If alternating current is applied to it, the tube will pass current only on that part of each cycle on which the cathode is negative. The diode tube is therefore first of all a *rectifier*.

This is generally useful; a characteristic not so useful is voltage drop. An electronic tube has terrific internal resistance. After electrons have been freed from the cathode by thermionic or other action, they tend to form an invisible cloud in the space surrounding the cathode. This "space charge" acts to repel the electrons driven out by thermionic action, sending them back into the cathode as fast as they emerge.

A space charge normally forms much closer to the cathode than to the plate, and a very much greater voltage is needed on the plate to overcome the space-charge effect because of the inverse-square law effects in electric repulsion. Thus a space charge of only two volts at .01" from the cathode would block electrons attracted by a plate .1" away charged to 150 volts! It would take more than 200 volts on the plate to pull electrons through that two-volt space charge.

In high-vacuum rectifier tubes designed to handle fairly heavy loads, the plate is put extremely close to the cathode—frequently less than .01" separates the two. The un-

Photograph courtesy of General Electric Co.



avoidable gap reduces it but, in spite of this, the space charge resists the passage of electrons from the cathode until they enter its own region. Once they get this far, it pushes them onward with equal force, which now reinforces the pull of the plate charge.

It would seem that a sufficiently high plate charge would drive as much current as we might wish through the tube, but the accelerating action of the space charge just mentioned, plus such a high plate potential, would drive electrons to hit the plate with such violence that their bombardment would heat it. When hot enough, the plate would begin to emit electrons itself, rectification would cease, excessive current would flow, and the tube would be ruined.

There is, however, one type of tube purposely designed as an inefficient rectifier with the plate several inches or, in large tubes, even a foot or so from the cathode. With such a setup, it takes not hundreds of volts, but hundreds of thousands, to drive electrons through the space-charge blockage, and they hit the plate at a speed as high as 175,000 miles per second. Deceleration causes the electrons to radiate extremely short-wave-length electromagnetic energy—called “hard” radiation or X rays.


In a diode having an atmosphere of low-pressure mercury vapor, argon, or neon, electrons flowing from the cathode to the plate are almost certain to bump into a gas atom on the way and knock off a secondary electron. The gas atom, now a positive ion, is attracted toward the cathode, while the dislodged electron heads for the plate. Near the cathode the gas ion picks up another electron and becomes neutral; but it promptly undergoes another collision, and is again a positive ion.

Under such conditions, there will always be many positive ions near the cathode, and their presence will neutralize the negative space charge. The result is that the voltage drop of the gas-filled tube will be very much lower than that of a vacuum tube, actually only a few volts, regardless of the current.

The cathode need supply only a few electrons. Once they start knocking electrons from mercury-vapor atoms, more and more are released until finally a billion or a thousand billion electrons arrive at the plate.

The mercury-vapor rectifier, alone of the electronic devices, is adaptable for heavy duty. It can handle tens of thousands of amperes as readily as it handles milliamperes and can operate at tens of thousands of volts.

Simple Diode Hookup Demonstrates Effect of Space Charge



IF YOU have or can borrow a milliammeter, you can demonstrate with any type of radio tube how electron emission and space charge increase with the temperature of the cathode. Connect the filament or heater to transformer taps of the proper voltage or to the line through a resistor of the correct value, inserting an adjustable rheostat to control the filament temperature and thus the number of electrons emitted.



The milliammeter is connected to the cathode and plate of a heated-cathode tube such as a 117Z6-GT. With a coated-filament tube, connect the meter to the plate and to the center tap of the transformer.

Since no plate-current supply is provided, the cathode, which is losing electrons, will take on a positive charge. The cloud of electrons within the tube gives the plate a negative potential. The more electrons emitted, the greater these opposite charges become. Since the meter is connected across the points of opposite potential, a current of several milliamperes will flow, and this will vary as the number of electrons emitted increases with the temperature of the cathode.

If a high-resistance voltmeter is used instead, the voltage of the space charge can be measured. It is usually one to five volts.

Servicing Your Radio

TONE, volume, and selectivity of midget A.C.-D.C. T.R.F. receivers can be improved by making a few minor changes. Tinny sounds often can be corrected to a certain degree, and a noisy volume control



may be replaced with a more suitable one. Old-style glass-bulb tubes will serve for metal ballast tubes that burn out, while new-type coils will greatly improve range and selectivity.

SQUEAKS AND HOWLS or loss of volume when the volume-control knob is moved indicates a faulty control. About 90 percent of the midget A.C.-D.C. T.R.F. sets use a volume control in the form of a metal-encased variable carbon resistor combined with a switch. Replacing this with a 25,000-ohm control will prove satisfactory in most cases even though the one originally contained in the set may have had a resistance of anywhere from 15,000 to as high as 35,000 ohms.

METAL BALLAST TUBES can easily be replaced when they burn out by those having glass bulbs, and the latter will even be found to have some advantage, especially in the matter of heat dissipation. Be sure that the tubes have the same or equivalent code numbers. In a designation such as K55C, the first letter indicates the type of pilot bulb to use (K—brown bead, No. 40; L—blue bead, No. 46; M—white bead, No. 50 or 51). The number is the voltage drop across the tube, and the last letter gives the key to the tube wiring.

TINNY SOUNDS common in some small A.C.-D.C. receivers may be the result of the high notes being accentuated too much. This annoying condition can be corrected to some extent by connecting a .05-mfd. paper tubular condenser of 400 volts working voltage between the plate of the power tube and the chassis. If the set has a condenser in this position, it probably has a lower capacity than .05 mfd. On a 43 power tube, the plate connection is at pin No. 2; on a 25L6, it is at pin No. 3.

SELECTIVITY AND RANGE can be improved greatly by replacing the old R.F. coils with newer types. The best results will be obtained by substituting iron-core coils, but even air-core, litz-wound coils will make a noticeable difference in the performance. Small T.R.F. sets usually are equipped with coils that are not wound with litz wire, are not so well insulated, and are not sealed against moisture, and therefore do not have as high a Q or amplification factor as the newer coils. Either shielded or unshielded coils may be used in making the replacements.

radio ideas




RADIO AMATEURS, no longer able to indulge in their hobby, may find a place for their energy in the War Emergency Radio Service, a new development in radio communications for civilian defense. Junked radio sets and parts, salvaged from attics and cellars, are being rebuilt by amateurs and professionals into two-way stations and operated for the common good. This means

of communication bids to set our country ahead of all others in having an independent, foolproof auxiliary that will function regardless of the loss or crippling of all other forms of contact across distances. In the photo at left above volunteers are making sets out of junked parts, while in the other operators stand by at a WERS station. These are OCD photos from the Office of War Information.




THIS THROAT MICROPHONE strapped around the neck over the larynx picks up words spoken by the wearer and amplifies them in combination with any standard equipment supplied our armed forces in the air, on land and sea, and under water. The device will be particularly useful in planes and in tanks because there is no need to shout, and the mouth is left free of all restrictions which hamper expression, either by voice or muscular reaction.

FLAPS ON A NEW RECORD ALBUM prevent accidental dropping of records when the album is unintentionally held upside down. Placed at the top of all compartments, they also tend to keep dust from sifting into the envelopes and to guard against slipping records between compartments. Both 10" and 12" albums are available in this style.



COMMUNICATION RECEIVERS are now being built in separate units, each one on its own specially shaped chassis with fixed resistors and condensers conveniently placed on the outside for rapid servicing, as shown in the 12-tube set above.




A PICTURESQUE FENCE that will set off a lawn or flower plot to advantage can be made at low cost from ordinary laths. About 7" at the bottom of the laths should be creosoted by standing the bundle in a bucket of creosote compound. Set the laths about 6" deep in the ground, keeping those that slope in the same direction as parallel as possible. Use single nails where the pieces cross.—HI SIBLEY.



OAR RACK. Where several boats are in constant use, the care of oars is a problem that can be much simplified by the use of a rack, such as the one shown below and in the drawing. It goes far toward reducing the loss of oars and damage caused by warping and breakage, permits the oars to be kept in numbered pairs, tells at a glance how many boats are in use, is easily locked when your camp

is left alone, and provides a winter storage box.

The top of the rack is entirely enclosed. Oars are inserted with the blades uppermost between partitions. The shafts fit between dowels set in the crosspiece, and the handles rest squarely on the bottom. A hinged board across the bottom can be secured with a padlock. When this is closed, none of the oars can be removed.—MILTON KLEIN.



By E. W. LEHMANN

Head of Department, Agricultural Engineering,
University of Illinois

TO GET along with old machines at a time when the farm labor supply is limited makes it particularly important to avoid breakdowns in the field. Since the mower is used during the fall as well as in the early part of the summer, checking and repairing it now will not only insure its readiness for the first cutting of alfalfa next year, but make a better job of the last this fall.


Toward the end of the season is, in fact, always a good time to check machinery because the operator knows then whether there is anything wrong with it. If the mower knife is dull or poorly adjusted, it is hard to pull and takes a lot of unnecessary power, and if parts are loose or badly worn, breakdowns are likely to occur.

Check the alignment of the cutter bar—the heart of the mower. With the machine on level ground, block up the front end of the tongue about $2\frac{1}{2}$ ' and drop the cutter bar so the inner and outer ends rest on the ground. Tie a string to the center of the pitman bearing and hold it tight along the center line of the pitman over the knife head.

Pull the cutter bar back by hand until it is in cutting position; then measure from the line of rivets on the cutter bar to the string. The outer end of a 6' cutter bar should be about $1\frac{1}{2}$ " ahead of the inner end—a lead of about $\frac{1}{4}$ " for each foot of length of the cutter bar. Alignment of the bar may be corrected by adjusting the eccentric behind the yoke as shown in one of the drawings. On some machines, it is necessary to drill out or file the old holes in the yoke casting with a rattail file and fit in oversized pins in order to take up slack caused by wear.

The register of the knife is checked by turning the pitman wheel for a complete stroke of the knife. If the knife sections do not stop in the center of the guards at each end of the stroke, the mower will clog and will not cut properly. Some mowers have a provision for adjusting the entire cutter bar in or out. On older makes it may be necessary to lengthen or shorten the pitman, which is a wooden rod with a box bushing on one end and a ball-and-socket knife-head bearing on the other. The length is changed by removing the rivets and replacing the wooden rod with a new one.

Guard alignment may be checked by moving a straightedge along the top of the guard plates after removing the knife. Note



those that are high and those that are low. Drive unaligned guards back into alignment by a blow with a hammer. The plates have serrated edges and, when badly worn, should be replaced. If the greater thickness of a new plate puts it above the others, it may be necessary to lower the entire guard by placing tin shims between it and the cutter bar.

A sharp knife or sickle is essential, an extra knife is desirable as a spare, and knife sections should be available at all times for replacement of those that may be damaged or broken. Check the knife bar to see that it is straight. In grinding the knife sections, maintain the same cutting angle and bevel as on new sections. To replace an old section that has worn much shorter than the others, remove the knife from the



cutter bar, and then hold the edge of the knife bar on the edge of an anvil or piece of railroad iron. Shear the rivets by striking a sharp blow on the edge of the section above each and remove them with a punch. Special riveting sets are convenient, but a good job can be done with a ball-peen hammer.

For best results, adjust the clips after the knife has been straightened and made to register. Begin with the clip next to the inside shoe and, if it is bent up, tap it lightly until it begins to tighten on the knife bar. Examine and adjust all clips in the same manner; then check to see that the knife can be moved freely by hand.

Check the pitman for end play and twist. Excessive lost motion caused by wear in the ball and socket can best be taken up by renewing the knife head and the pitman bearing. Some mower models are equipped with a knife-head correction self-adjusted to take up wear. If a badly worn crankpin in the pitman wheel causes lost motion, remove the crankshaft, saw partly through the worn crankpin, and break it off with a hammer. The small end of the crankpin can then be

driven from the wheel, and a new one installed. While the crankpin is out is a good time to check the condition of the crankshaft bushings, which may need to be renewed.

For ease in operation, see that the lifting spring is at the proper tension to permit the cutter bar to float over the ground without dragging. Check also the tension of the lifting spring to permit easy raising of the cutter bar.

The chief function of the outer and inner shoes is to support the cutter bar and to keep it level. Replace badly worn parts. The proper angle of the grass board and stick is essential to good operation in cutting high grass. The spring tension on the board should be sufficiently flexible to side pressure and yet stiff enough to force the grass away.

In horse-drawn mowers the power to operate the knife is usually transmitted from the wheels by ratchets and pawls. Check the pawls and the pawl springs, see that the pawl boxes are clean, and renew badly worn parts or surfaces with a file. (CONTINUED)

Provision is made on many machines for adjusting the meshing of drive gears by means of a nut on the end of the countershaft. On some the adjustment is made by means of an adjustable collar or by the use of washers. Replace worn gears and badly worn parts of the clutch mechanism.

To put the mower in the best condition for operation, check all bearings for wear. Flanged bushings can be replaced after driving out the old ones with a piece of shafting slightly smaller than the shaft.

Finally, check the entire machine for loose nuts, worn bolts, broken cotter keys, and

weakened or worn parts. There is always danger of breakage where lost motion is present because of loosely fitting parts, and these also impair operating efficiency.


It is generally understood that, while there may be fewer new machines available, the supply of parts will be adequate for the farmer to make his old machines do their work. Careful cleaning, adjusting, repairing, painting, and lubrication will make these old machines last several years longer. It is wise also to check them early enough to get in your order for parts that you may wish to replace during the winter months.

Handy Blackout Flashlight Made by Reversing the Reflector

ANY ordinary flashlight can be adapted at a moment's notice for blackout use. No additional parts or materials are needed for this handy trick. Remove the flashlight lens entirely. Take out, invert, and replace the reflector; then screw on the lens holder. This

reduces the light aperture to the small hole that formerly accommodated the bulb, so that only a pale circle of light is emitted, which compares favorably with the illumination of elaborate and expensive blackout flashlights.—RAY JUTILA.


Storm Sash Are Stored on Shelf Installed at End of Garage



SPACE in the garage that would otherwise go to waste can be used for easy storage of storm sash in the summer and screens in the winter. Nail 2 by 4's across the garage from stud to stud to form a shelf above the radiator of your car at a height that will be convenient to reach. Nail on either a board floor as shown, or one of slats, which may be nailed a few inches apart to keep dust from collecting. If many sash are to be stored, cleats under the ends of the 2 by 4's will add support.—WILLIAM FREEMAN.

Sealed-Beam Headlight Unit Makes Powerful Searchlight

WHEN one beam of a sealed-beam headlight burns out, the unit can no longer be used legally on a car, but it can be made into a powerful, portable searchlight that will help greatly on a job that must be completed at night. Nail an upright to a wooden box large enough to contain the storage battery that will provide current for the light; then, on the upper end of the standard, fasten a small bracket to which the sealed-beam unit may be bolted by means of its mounting clips. Such a unit may also be mounted on a tractor or other farm machine and connected to the regular starting and ignition battery.—ROBERT MANN.



NOW YOU SEE IT... NOW YOU DON'T

The Story of
Katharine B. Blodgett

CURIOS is the word for Katharine Blodgett. And her eagerness to experiment with new ideas gives an original twist to everything she does. Now one of the outstanding scientists of her day, this twinkling-eyed Bryn Mawr graduate built up 44 *invisible* layers of barium stearate on glass—to make it so non-reflecting that you can't see it!

Though Katharine Blodgett's father had been a General Electric patent lawyer, she didn't "begin with askings" when she came into the Company. Armed with a brand-new M.S. from the University of Chicago, she began her career in the "magic" department of the Research Laboratory. After a few years of experimenting with molecules, she went on to the Mecca of all physicists, the Cavendish Laboratory at Cambridge University, England, where she was the first woman to receive a Ph.D. in physics.

Dr. Blodgett still remembers the cold English winters. The men in the class didn't suffer so much—they had learned to write with either hand, in order to alternate the hands they kept in their pockets. *She* had to sit on one hand and take notes with the other. One day she took a thermometer to class, and it registered only 40 degrees!

Knowing *why* doesn't satisfy a scientist like Dr. Blodgett. She feels deeply that she is not the master of a subject until she knows also *why not*. That's the real reason she makes popovers every Sunday morning—to find out why they aren't consistent in popping. Right now she thinks the answer may lie in the type



of milk used, so she's experimenting with all kinds.

She carries her scientific attitude into the garden, too. She analyzes the soil before she plants the seeds, and this year she has a Victory garden, where she's spending most of her time outside the lab.

So screened is the Research Laboratory with war secrecy that nothing can be told right now of her work there. But it's the seeking, patient minds like Katharine Blodgett's that help to bring the peace nearer, that will make that peace *sure* once it is won. *General Electric Co., Schenectady, N. Y.*

Hear the General Electric radio programs: The "Hour of Charm" Sunday 10 p.m. EWT, NBC—"The World Today" news, weekdays 6:45 p.m. EWT, CBS.

The best investment in the world is in this country's future—BUY WAR BONDS

GENERAL  **ELECTRIC**

968-24E-211

CASITE GUARANTEES

BETTER AND SMOOTHER
MOTOR PERFORMANCE

OR

"Double Your
Money Back"

WHAT CASITE DOES!—Casite restores motor performance, because it cleans out sludge and gum and keeps them out—frees sticking valves and rings, retards formation of engine varnish, and speeds lubrication to high-friction points.

● For better and smoother motor performance, get a Casite tune-up today. It is inexpensive and takes only a few minutes. Sold by most car dealers and service stations everywhere on a double-your-money-back guarantee.

THE CASITE CORPORATION, HASTINGS, MICHIGAN



Guarantee

YOU ARE THE JUDGE —

Add Casite to crankcase and run through carburetor according to instructions, then drive your car 100 miles or for 60 days, whichever is first. If not convinced that Casite gives you better and smoother performance, you get double your money back by filling out guarantee certificate and mailing it to The Casite Corporation, Hastings, Michigan. Maximum refund is \$1.50 per pint, which is twice the nationally advertised price of Casite.

CASITE

CLEANS OUT MOTORS • KEEPS MOTORS CLEAN

Fort Busters

(Continued from page 53)

is slapped in place. The job is incomplete until the walls (sometimes six feet thick) are opened sufficiently to knock out the bunker crew with hand grenades. That done, the leader motions his men on to the next bunker, leaving the mopping up to assault infantry close behind.

German fixed fortifications are known to have as many as nine bunkers connected by bombproof tunnels. Usually each bunker supports at least two others with its fire, and the steel-and-concrete network remains a hazard to attacking forces until the last fort is smashed. That's the task of the demolition engineers. They must keep on smacking as long as there's as much as a pillbox in the vicinity.

The colossal size of the work before them must be understood by Americans at home as well as by our military leaders abroad. It is best shown by intelligence reports that reveal Germany to have fixed fortifications running to a depth of 50 miles, concentrated into jagged belts each several miles deep. Greatest of all Reich fortifications, the West Wall (Siegfried Line) has three such belts, staggered six to 25 miles apart. In the rear are forts with high-velocity guns usable against aircraft or ground forces.

Before the first belt is a landscape sown for 300 yards with mines and gouged with moats. Then come what our engineers call "dragon's teeth," concrete-and-steel tank obstacles five feet high set in jagged rows two to six deep. The approaches are topped with additional mines beneath a tangled morass of barbed wire. Hitler applies 15,000 mines and 100 tons of wire to each division front of 5,000 yards.

Blasting the dragon's teeth with TNT is a relatively simple job once the protecting bunkers and blockhouses have been demolished. But while these are hurling shrapnel at the attackers, it's extremely perilous. Some strategists recommend the use of smoke screens to blot the enemy's vision during assault. Smoke mortars do the trick easily, but the smoke may work to the disadvantage of the attacking force if it becomes necessary to see the objective in order to plaster embrasures with high-velocity shells.

The West Wall, as tough as it may be to crack, holds a secondary place in European fortification lines that must be smashed before invasion forces attain their goal. The Nazis have built an almost incredible number of forts to bolster defense walls and


(Continued on page 204)

SECONDS LATER THE BIG ONE CAME!

A true experience of Mr. and Mrs. James Sproston, of Cheshire, during the big air blitz over England.



1 Night after night they heard the great German Heinkel bombers roaring directly overhead, Liverpool-bound and loaded with bombs. Then one night Jerry was late. Feeling safe, the elderly English couple prepared to retire. Suddenly the sirens began to shriek...



2 Came the rumble of jettisoned bombs. Sproston grabbed up his flashlight. He and his wife hurried downstairs to black out the windows. The next moment an explosion shook the house. Seconds later the big one came...



3 ... Half demolished the house and threw its stunned occupants violently to the floor... Some time after, two passing air warden saw a light shining out of the wreckage. It was the beam from Sproston's faithful flashlight—a beam that directed the rescue of two more victims of the Luftwaffe's ruthlessness.



SPARE YOUR FLASHLIGHT BATTERIES!

For your own emergency protection (witness the Sproston's experience) as well as to conserve critical war materials, use your flashlight normally as little as possible. Make a habit of flashing it *intermittently*, not *continuously*. Also:

If you can't get "Eveready" flashlight batteries, don't blame your dealer. The Army, Navy and Lend-Lease get first call on the supply, and few are left for civilians.

NATIONAL CARBON COMPANY, INC.

30 East 42nd Street, New York

Unit of Union Carbide and Carbon Corporation



The word "Eveready" is a registered trade-mark of National Carbon Company, Inc.

FRESH BATTERIES LAST LONGER...

Look for the **DATE-LINE**



THE "Pals" THEY LEFT BEHIND



are Harley-Davidsons

Letters continue to pour in from men in the armed services telling how they miss the Harley-Davidson Motorcycles they left behind. One outstanding feature of ALL these letters is the way every man speaks of the stamina, power, and rugged dependability of his Harley-Davidson "sweetheart." And they look forward to the day when they can again thrill to the ownership of new Harley-Davidson motorcycles with greater performance than ever, made possible by the severe tests of wartime action.

HARLEY-DAVIDSON
MOTOR COMPANY
Department PS.
Milwaukee, Wis.



Write today for your FREE copy of "Enthusiast" magazine, filled with motorcycle action pictures and stories.

HARLEY-DAVIDSON MOTORCYCLES

Fort Busters

(Continued from page 202)

strongholds on the Channel coast, where the Dieppe raid showed painfully stiff resistance. Farther to the south, German engineers are known to be working feverishly to throw up and gouge out land blockades of ingenious types. And the northern exposure hasn't been neglected. Just how strong the Nazis have built their Northwest Wall along the coast of Norway is not known. But it's believed to match any of the Reich's fortifications, as is the belt of forts erected during the last year or so on Germany's eastern border and the Baltic coast.

Nazi engineers sidestep errors in construction that doomed Belgium's Eben Emael, France's Maginot Line, and the so-called indestructible forts of the Balkans and Greece. For instance, it is known that most of their forts may be evacuated easily, or may disgorge men and guns for mobile counterattacks. In the event of devastating frontal attack, they can shift reinforcements quickly from forts in the rear or to the side.

When the Germans reduced "impregnable" Eben Emael in seven hours with a handful of combat engineers and TNT, they set the pattern of destruction that soon may be used against them. For their enemies have improved the method to a point approaching perfection. For instance, one of the most effective weapons of the fort busters is an improved TNT charge. It's encased in steel, the same as the one which the Germans began using for the first time in 1940. But secret gadgets have greatly increased its blasting power.

The real pay-off, though, is the fact that the idea originally was as American as Brooklyn Bridge. In fact, it was a New Yorker, Prof. Charles E. Munroe, of Columbia University, who conceived it. He wrote about it in *POPULAR SCIENCE MONTHLY* in the year 1900. Eleven years later the Germans tried to tie up the idea with a patent, but somehow failed to do so. As an explosives expert, Professor Munroe discovered that a hollow charge of dynamite was many times more effective than a solid charge of the same weight. He experimented by simply draping a bunch of dynamite sticks around a can with open end out. Using nine pounds of dynamite, he blew a hole three inches in diameter through the five-inch steel walls of a safe. The charge the fort busters use weighs 10 pounds and can blow a hole two inches in diameter through 30 inches of steel-reinforced concrete. It's exploded by pulling a pin like that used in a hand grenade.

CHAMPION SPARK PLUGS

ON ACTIVE DUTY ON EVERY FRONT

In the heat of battle everywhere, on land, water and in the air, Champion-equipped engines add their roar to the thunder of our march to Victory. On the home front too, in a less spectacular way, Champion-equipped engines keep supply lines and transportation rolling with that characteristic dependability which is synonymous with the name Champion.



Spark plugs in today's high-output super-charged aircraft engines take a lot of punishment. The same qualities that made Champion the spark plugs of racing champions have skyrocketed them to favor for our most powerful aircraft engines.



Land battleships, with gas engines of greater size and power than those used by any other land vehicle, are most effective offensive and defensive weapons. Engines must not fail, and tanks with Champion-equipped engines are on every front.



"Handy Andy" of our armed forces everywhere, Champion Spark Plugs keep plugging away through hell and high water in the majority of all jeeps.



Patrolling our coastal waterways is an entire navy of smaller power boats. Champion-equipped gas engines give them extreme speed and maneuverability.



Cars, trucks, and buses, troop transports and commercial transports are all equally vital to the war effort. Champion Spark Plugs are actively in the service here.



Helicopters are destined to become a tremendously valuable defense against submarines. Sikorsky Helicopters are equipped with dependable Champions.


FOR NATIONAL SECURITY—FOR PERSONAL SECURITY—BUY WAR BONDS



It's POP, the foreman. And is he mad! Like any good production head or conscientious mechanic, Pop knows what happens to a file when tossed among other files or tools. Even a few battered teeth can cause skips, throw the filing stroke out of stride—waste time—destroy accuracy—*reduce the efficiency and earning power of the worker.*

In Nicholson and Black Diamond files, Nicholson goes to great pains to provide the toughest, sharpest and most uniform files it is possible to produce. A moment of carelessness in their use can undo much of this great care in their manufacture.

The right file for the job and Twelve perfect files in every dozen are long-standing guarantees in the Nicholson policy of providing mechanics, die makers, model builders and other craftsmen with the very best in filing aids.



SEND FOR THIS FREE BOOK

"FILE PHILOSOPHY" — the foremost book of its kind — contains interesting and valuable information on file use and care; and on many kinds of regular and special-purpose files used by modern industry. 48 illustrated pages.

Nicholson File Co., 19 Acorn St., Providence 1, R. I., U. S. A.
(Also Canadian Plant, Port Hope, Ont.)

NICHOLSON FILES

FOR EVERY
PURPOSE



"Fork-Tailed Devil"

(Continued from page 100)

Minor changes in design were effected, and improvements suggested by actual use incorporated. It was not until September 1940 that the first actual production model rolled off the line. Some airmen, pointing out that the ship was heavier than a 10-passenger commercial transport plane, still thought it was a freak, with no real future as a fighter. The Army knew better, but took the wise decision to keep its husky baby under wraps until it had enough of them to deliver a solid punch.

The combination of power, clean aerodynamic design, and a quick-acting combat flap enables the P-38 to fly great distances and then battle on even terms with enemy interceptors hundreds of miles from its own base. The ship can take off and land at 80 miles per hour, fly faster than 400 m.p.h., climb to 40,000 feet, carry up to two tons of bombs for short distances, and outrun the speediest enemy if that becomes necessary.

That combat flap, developed when the Army called for increased maneuverability, increases the wings' lift substantially while increasing the drag only slightly. Thus the P-38 can roar to its objective at top speed, and in three seconds the pilot can lower the flaps to transform his ship into an acrobatic dogfighter, dive bomber, ground straffer, or precision bomber. After raising the flaps—time, four seconds—he can streak for home, then lower them again to land safely in snow, soft earth, or a rough field.

Although a heavy fighter, the Lightning apparently can be maneuvered in a fairly short radius, and has shown a surprising ability to climb on one engine even in combat with the vaunted lightweight Zero. Its propellers, driven by 1,325-hp. Allison engines, rotate in opposite directions, nullifying the torque and giving it equal maneuverability to either side. Pilots have taken advantage of that to blast many a Jap or Nazi flyer who could pull out of a dive only to the right because of torque.

Its high speed and altitude have made the Lightning invaluable upon occasion as a photographic reconnaissance ship. Stripped of armament, it can snap and run away in broad daylight. Painted dead black for night work, it can get into position for the run, pop flares, snap its pictures, and glide off like a dark cloud before the wind.

In this connection, it is an odd fact that the Lightning's first shooting encounter with the enemy occurred while the ship was unarmed. Capt. Karl Polifka was taking

(Continued on page 208)



You may worry
about the crowd
on the train

but here is one worry you can avoid

TRANSPORTATION, *by any means*, is really a problem these days. Take your car, for instance. Because you drive it *less*, you have a different problem than if you drove it a lot.

For idle batteries run down—idle pistons and bearings can rust from water and sludge in the crankcase—scale and rust can ruin a radiator. And tires lose air just the same.

That's why, *today more than ever*, your car requires regular Marfak 40-Point Chassis Lubrication Service!

Your dealer checks every vital point of your car against his Marfak chart. No guesswork here . . . which means accurate protection for irreplaceable engine and chassis parts.

So insist on genuine Marfak Lubrication today—to keep your car in "top" condition for the important job it does for you and Uncle Sam. At Texaco and other good dealers everywhere.




Tune in the TEXACO STAR THEATRE every Sunday night. See your local newspaper for time and station.

You're Welcome at **TEXACO DEALERS**




Atlas "ARTILLERY"



**MILLING
MACHINE**

SHAPER



As Allied forces move up for the victory campaigns, they'll be staunchly supported by Atlas "artillery" on the home front. Atlas Lathes, Milling Machines, Shapers, and Drill Presses are pouring a steady stream of precision-machined parts into the battle. In shipyards, on airfields, and in key industrial plants throughout the nation, these modern compact tools are favorites for fast, precision production. Remember after victory how Atlas accuracy and rugged strength have been proven in the toughest test of the ages. Atlas Press Company, 955 North Pitcher Street, Kalamazoo 13D, Mich.



**BUY
BONDS
NOW**

-FOR A NEW *Atlas* SHOP
AFTER THE WAR

'Fork-Tailed Devil'

(Continued from page 206)

pictures over Lae and Rabaul, New Guinea, when a flight of Zeros jumped him and knocked out his port engine in the first burst. Unable to fight back, Capt. Polifka climbed to 25,000 feet on the remaining engine, evaded the foe, and got home with photos which were officially credited with helping to win the Battle of the Coral Sea.

As fighters go, the P-38 is a big ship and a strong one. It can take a lot of gunfire punishment without crumpling, for its wings are double-skinned and its strength members double-stressed. If a wing is riddled, the spars can support the ship's weight; if a spar is severed, the skin itself has structural strength to hold together for the homeward flight.

No other fighter surpasses the P-38 in sustained fire power. It has various combinations of armament, a typical arrangement being four .50 caliber machine guns and a 20-millimeter automatic cannon, all concentrated in the nose, whence they can deliver an intense slash of steel and explosive. The pilot also can do a lot of shooting without a reload; the Lightning normally carries some five times the weight of guns and ammunition packed by lighter ships such as the Zero.

Most recent additions to the Lightning's equipment are combinations of extra gas tanks, smoke tanks, and bombs. The streamlined, droppable fuel tank of 150-gallon capacity enables the ship to protect bombers over a combat range of 750 miles and farther. Over shorter ranges, P-38's have carried as much as two tons of extra equipment, including medium-size bombs.

Extra range also has made the P-38 a handy ship for delivery to the war zones. Lightnings flown to the Aleutians gave the Japs a rude surprise early in the war. Hundreds of them have made mass flights across the North and South Atlantic. For such hops, each plane carries two extra 165-gallon fuel tanks, one under each wing. When the gasoline is used, the tanks are jettisoned. Since P-38 pilots have no time or equipment for navigation, a Flying Fortress accompanies each flight as "shepherd."

The P-38 is getting around in this war, and you may see it anywhere. If so, it will be an easy ship to spot from the ground—partly because of the forked tail that impressed the Germans so forcefully, and partly because of the front arrangement of wing, nose, and two engines, which gave it the airmen's poetic description of "three bullets on the edge of a sword."



EVEN THE GENERAL CHANGES HIS HAT

In time of action the leader must lay aside his trim hat, strip off his gold braid and sleek attire. He looks different—but his ability and character remain the same!...PLUMB, too, dons a "service uniform". Because of Government Limitations the appearance of some Plumb Tools has been changed. But the "hidden qualities" remain the same. Plumb Tools have the same hang and balance, design and temper that won them a quality reputation for nearly ninety years. While the fine finish has gone for the duration you will recognize Plumb design and balance by the ease and speed with which it works... Plumb is proud of its service uniform! Fayette R. Plumb, Inc., Dept. M-5, 4957 James Street, Philadelphia, Penna.

Quality Comes First — PLUMB is FIRST in Quality



PLUMB

HAMMERS • HATCHETS • AXES • SLEDGES



HOW TO CUT THREADS WITH WILLIAMS' LATHE TOOLS



FREE! WILLIAMS' TOOL DATA SHEETS

● Data Sheet No. 14 explains how to cut external threads with Williams' Lathe Tools. This, and other Data Sheets listed below, (all punched for 3-ring binder) are free. Circle the subject numbers desired on coupon.

- | | |
|--|--|
| 1. Characteristics of Williams' "Superior" Wrenches. | 8. Data on Williams' "Superior" Wrenches. |
| 2. Data on Williams' Throat Tools. | 9. Saving Time with Williams' "Supersockets" |
| 3. Data on "Vulcan" Chain Pipe Tongs. | 10. Data on "Vulcan" Eye Bolts. |
| 4. Data on Williams' "Supersocket" Wrenches. | 11. Data on Williams' "C" Clamps. |
| 5. Data on "Vulcan" Lathe Dogs. | 12. Use of Williams' Cutting-Off Tool Holders. |
| 6. Data on "Vulcan" Chain Pipe Vises. | 13. Use of Williams' Knurling Tool Holders. |
| 7. Data on Williams' Turning-Tools. | 14. Use of Williams' Threading Tool Holders. |

15. Internal Threading with Williams' Tools.

MAIL THIS COUPON

J. H. Williams & Co., Dept. S-943, Buffalo 7, N.Y.
Please send Data Sheets circled below:

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15

Name _____

Address _____

City _____ State _____

WILLIAMS
SUPERIOR DROP-FORGED TOOLS

Postwar Locomotives

(Continued from page 59)

perature is too hot to be used effectively on anything but a turbine, it is fortunate that the practicability of substituting a non-condensing steam turbine for the reciprocating engine of a coal-burning locomotive has been demonstrated by the "Turbomotive," built by the London, Midland, and Scottish Railway in 1935. This locomotive, known as "Gracie Fields" because "she sings as she goes," uses steam at a 250-pound pressure, superheated to 750 degrees, in a 2,000-hp. turbine geared to the front driving axle.

While the future of the noncondensing turbine-gear locomotive seems bright, it appears that the condensing steam locomotive, if it is to develop at all, will have to do so as a steam-turbo-electric machine. Outstanding example of this type of engine is the one built by General Electric in 1939. It comprises two 2,500-hp. units, with each unit carrying its own generating plant in the form of an oil-burning Babcock and Wilcox water-tube boiler, which furnishes superheated steam at 1,500-pound pressure and 920 degrees F. to a turbine driving a direct-current generator. There is no reason why similar locomotives should not be built to use powdered coal as fuel.

Because of its high thermal efficiency, which reduces fuel cost and permits long nonstop runs, the Diesel-electric locomotive promises to be the standard main-line engine of postwar service. The only rival that may threaten its position is the internal-combustion turbine locomotive with either an electric drive or hydraulic transmission. Chief problem of such an engine is producing metal that will withstand the high temperatures at which the engine must operate. However, an oil-burning gas turbo-electric locomotive is now in operation on the Swiss Federal Railways (P.S.M., May '43, p. 114).

The development of a reliable internal-combustion turbine raises the interesting possibility of combining the gas turbine with some form of gas producer that will give railroads operating in coal-burning districts an engine that will burn coal with an efficiency comparable to that with which Diesel-electric locomotives burn oil. Pioneering efforts have already been made by Brown, Boveri, & Co., builders of the Swiss engine, who have constructed a gas turbine that "burns" powdered coal from which gas is generated. The full development of such an engine, however, is not likely to take place soon enough to make possible its use in the immediate postwar era.

WHAT'S A NUT FOR?

● A nut is for just one purpose.

That is to fasten things together.

A good nut holds tight. It doesn't shake loose even under vibration.

This is the particular virtue of the Elastic Stop Nut.

This nut has an elastic red collar in the top. The collar grips the bolt and keeps the nut and bolt threads pressing tight against each other. There's no play. There's no wobble.


So the nut stays put.

It can be taken off and put back on and still lock. Anywhere on the bolt.

We've made billions of Elastic Stop Nuts.

They're on every airplane made in America. And on all kinds of war material.

And as far as we know, not one has ever failed to do its job surer and better than any other similar fastening.



Elastic Stop Nuts hold tight and make better electrical contact. Connections are safer and more efficient.



Youngsters' toys take a beating. They'll last longer and take less "fixing" when Elastic Stop Nuts are used.

ELASTIC STOP NUTS

Lock fast to make things last



ELASTIC STOP NUT CORPORATION OF AMERICA
UNION, NEW JERSEY AND LINCOLN, NEBRASKA



If you could split a hair into fractions, you'd have a rough measure of tolerances allowed in Stevens' production of military rifles. Each part undergoes many tests with gauges capable of determining accuracy to the ten-thousandth of an inch.



PRECISION . . .

to a fraction of a hair's breadth

Production of military rifles requires technical knowledge and equipment capable of the most precise manufacture. And—these rifles must be turned out in tremendous quantities.

It was not a new experience for Stevens to produce "Quality in Quantity." Before the war Stevens was one of the largest producers of sporting arms. Yet the processes of manufacture followed a routine of painstaking precision that assured a high degree of safety, accuracy and reliability for Stevens products.

When the war is over . . . you can count on Stevens to offer sporting rifles and shotguns that will represent greater values than ever before.

J. STEVENS ARMS COMPANY
Division of Savage Arms Corporation
Chicopee Falls, Mass.

STEVENS



Flying Gun Carriers

(Continued from page 86)

sion is now the standard British aircraft machine gun.

But U. S. airmen now favor the larger Browning .50 caliber air-cooled gun, and say flatly that it is the finest large-caliber aircraft machine gun in the world. Weighing less than three times as much as its little brother, it throws four times as much lead per second, and throws it with a heavier punch. The muzzle velocity of its 800-grain (nine to the pound) bullets is 2,900 feet a second, and after they have traveled 1,800 feet in less than three quarters of a second they still have a striking velocity of 1,950 feet compared with the .30 caliber's 1,500 feet. The .50's rate of fire ranges from 700 to 850 shots a minute, depending on whether it is firing free or is slowed down by synchronization with the propeller.

A synchronized Browning is fired by a mechanical trigger motor attached to its receiver and connected through a solenoid and semiflexible tube with an impulse generator which is part of the airplane engine. This is really a form of high-speed semi-automatic fire, since the trigger motor actuates the trigger for each shot. This device, produced by Army Air Force engineers, is a vast improvement over the often unreliable hydraulic, rocker, and flexible-shaft synchronizers used in 1918.

Nevertheless, modern practice tends increasingly toward the use of wing guns to avoid any synchronizer and to take advantage of the gun's full rate of fire. The wing-mounted gun is fired by a remote-controlled solenoid, and continues to fire as long as the trigger is depressed and the ammunition holds out. Occasional trouble with belt-fed ammunition has been eliminated by the U. S. development of a disintegrating metallic-link belt. Each cartridge, acting as a pin, joins two metal links. When an empty cartridge case is extracted and ejected, the empty links that held it to the rest of the belt fall apart and tumble out with it.

The development of more efficient armor naturally stimulated the demand for harder-hitting guns. The United States was well abreast of the trend and by the time the present war started had an excellent 37-mm. cannon ready for production. This gun, with a bore of about 1½ inches, is recoil-operated and fires 1¾-pound high-explosive shells at a rate of 125 to 150 a minute. The shells have supersensitive nose fuses which will burst the charge on contact with the lightest airplane fabric. Armor-piercing shells of about two pounds also are fired.

The 37 is particularly effective as a tank buster on ground sweeps. It does have a limitation, however, in the amount of this fairly heavy ammunition that a fighter plane can carry on one sortie. For this reason, while some of our Lightnings and Airacobras mount the 37, others are being equipped with our version of the 20-mm. Hispano cannon. In either case, the heavy gun is supplemented with various combinations of .50 caliber guns.

R.A.F. officers long pinned special faith to increased numbers of machine guns, and tried out a fighter carrying 12 rifle-caliber guns, but they have now swung over to the heavier-caliber idea, and are using their own form of the Hispano 20.

The art of aircraft gunnery also has come a long way in recent years, and improved sights have given pilots an effective range of around 1,000 yards with 20 or 37-mm. cannon, and 300 yards with .50 caliber machine guns. For the present, however, the fighter pilot's own skill, reflexes, and "feel" of his plane and guns will count for more than any mechanical device.

For the gunners manning flexible defensive machine guns in a bomber, however, computing sights are invaluable. One of these devices includes an arrangement by which the gunner tracks the enemy plane and fires when it is framed in the sight. The gadget computes the angle at which the gun must lead the target, and corrects the aim automatically.

Since a Flying Fortress or Liberator may carry a dozen or so defensive guns, it is easy to see why these big ships have been so deadly to fighter planes venturing into the area of fire to attack them. Another ingenious device is the fire interrupter, which enables a gunner to fire without worrying about damaging the tail, elevator surfaces, or other parts of his own plane. This works either by guiding the gun's line of fire over or under the exposed part, or by interrupting the firing mechanism just as the gun swings into line with it.

Power-driven gun turrets appeared about 10 years ago, and are now used on many large bombers. The Flying Fortress, for example, has two hydraulic-electric turrets, operated by gunners who ride in them; some British heavy bombers have four.

Developments beyond that point are generally veiled in military secrecy, but it requires no great leap of the imagination to envision future battleships of the air in which multiple power turrets, covering every angle of attack, will be operated possibly from a protected central fire-control position like that of a surface warship, and a new chapter will open in the history of aerial fire power.

FOR MEN WHO REALLY KNOW PIPES



The illustration shows a large, ornate pipe resting on a surface. In the background, there is a small clock, a teapot, and a stack of books. The Royalton logo is prominently displayed at the top.

Royalton

The Pipe that Becomes
Part of a Man's Life . . .

Pipes are like friends. Some are merely casual. Only a rare few can win you completely, become worthy of your constant preference. Knowing smokers say that Royalton is just that kind of pipe. That you could select no better smoking companion to enrich your leisure or busy-at-home hours.



Wherever Better Pipes are Sold

Royalton Silver Crown
\$5
Choice Grains

© 1943, Henry Leonard & Thomas, Inc., Ozone Pk., N. Y.



Will you come along? *you bet you will*

IT'S EARLY on an autumn morning sometime after Victory. A couple of your neighbors stop at your door. Dew shines on their boots. Their guns gleam, and you hear the muffled click of shells in their pockets as they move. They grin. You grin. "Ready?" they ask. "Right with you," you say. You slip into your jacket . . . you pick up your new H&R gun—the gun you've always dreamed of, well-balanced, beautifully finished, a top-notch performer in every way . . . and you're off on the hunt . . .

UNTIL THE WAR IS WON, all of Harrington & Richardson's guncrafting will continue to center on war weapons—principally the famous H&R Reising Submachine Gun.

BUT THEN H&R will return to sporting arms with guns of unprecedented performance, beauty, and "feel." Post-war H&R guns will have the additional benefit of all the new know-how of wartime design and production plus all the suitable new materials—steels and alloys and plastics. No details can be released now—but there'll be shotguns, revolvers, and rifles of great new design proudly bearing the H&R name. We know you'll like them.

HARRINGTON & RICHARDSON

FREE TO GUN FANS

Every man and boy who loves firearms will enjoy the detailed, illustrated H&R Reising Submachine Gun Manual. It's free . . . use the coupon.



HARRINGTON & RICHARDSON ARMS CO.,
Dept. PS-2, Worcester, Mass.

Send my free copy of the H&R Reising Submachine Gun Manual.

Name

Address

YOU CAN EASILY MAKE Telescopes—Magnifiers—Photographic Gadgets and HUNDREDS of EXPERIMENTS with

LOW COST LENSES

Big 10 Page Project and Idea Booklet with all sets—describes successful developments—points the way to new experiments.

ALL LENSES NEW, finely ground and polished, edges very slightly chipped—A **SALVAGE BARGAIN!**

Set No. 301-N "Our Advertising Special" 15 Lenses for \$1.60 Postpaid. For making your own powerful telescopes, strong magnifiers, photo cells, rifle scope, telephoto lens, dummy focusing camera. Kodachrome viewer, stereoscopic viewer, ground glass and enlarging focusing aids. For experimental optics, portraits of babies and small pets, copying, ultra close-up shots, and many, many other uses.

Set No. 305-N "The Gadgeteer's Delight" 35 Lenses for \$5.00 Postpaid. Contains all the lenses in the above set plus twenty more expensive lenses increasing your field of experiment and gadget making. All our lenses are neatly packed and marked.

Set No. 310-N "The Experimenter's Dream" 70 Lenses for \$10.00 Postpaid. Contains all the lenses in the above sets plus 35 others that makes this a sensational buy. The variety of lenses in this set will enable you to conduct countless experiments and build a wide variety of optical equipment. Here is a real worthwhile investment in many hours of pleasure and benefit.

Shoppers! Servicemen! Amateur Photographers! Stamp Collectors! Experimenters Everywhere!

Get in on this Lens Salvage Bargain Now! Order Today!

EDMUND SALVAGE CO.

41 W. Clinton Ave., P.O. Audubon, N. J.

WANTED IDEAS

For New Electrical or Mechanical Toys or Specialties

Half a century of leadership in its special field has earned for a large, highly rated manufacturer an international acceptance and distribution of its electrical products.

At present, this firm's facilities are devoted solely to war work. Plant expansion opens the way to larger and more varied activities when the war is over.

We intend to acquire patents or patentable ideas for new electrical or mechanical toys or specialties marketable under our brand name and through our well established channels of distribution.

Inventors who have an idea or a patent along these lines are invited to write us full particulars. Your ideas will be respected.

ADDRESS

THE PRESIDENT

G.P.O. Box 341 New York 1, N. Y.

Your Home...Tomorrow

(Continued from page 79)

Towel bars will be warmed to dry towels, unless a new and satisfactory substitute is found in paper bath towels. In the bathroom, too, concealed ultraviolet-ray units will go on and off while you are shaving or bathing. Soap dishes will be designed to drain off water, or all our soap for use in the home may come in liquid form. Hand faucets will give way to flush, buttonlike controls, or floor pedals. Clocks and bath scales, as well as properly lighted dressing tables, will be standard equipment.

Your closets will be designed with a particular functional purpose and with care to make the maximum use of every cubic inch. They will, of course, be purchased as complete units. Throughout your house, devices of all kinds will be built into walls to free space for easier movement.

Laundry machines will wash, rinse, dry, and sterilize clothes in one continuous operation; and machine ironing, much improved, will become more common.

Your house of tomorrow will be so flexible that it will be capable of being adapted at short notice and small cost to the changing needs of your family. Extra rooms may be added at a fraction of the cost of such additions today. Within the shell of the house, partitions may be changed to new locations in a few hours.

Tomorrow's house will be able to spread itself horizontally, too, for it will not be limited by the edges of the present 40-foot city lot. Express highways and high-speed transportation will make it possible for people to live in ever-widening circles from urban centers, and will make the narrow city house plot obsolete. You will build your house tomorrow on a larger plot of ground, with lower property tax, at no greater time-distance from your work. With more space to spread out, houses will be built around play areas. You'll get into the sun more, and the sun will get into you more.

Planned as an economical unit, your house of tomorrow will cut down home living costs, decrease housekeeping labors, and reduce the family's doctor bills. Through radio and television it will become more a part of the outside world. But modern engineering will have made it more than ever before a man's castle.

Subscribers in the armed services who notify us of change of address are requested to give us the key symbols appearing on the wrapper in which the magazine is received.



Dear Bud:

You'd get a kick

out of being in this outfit. It's a great gang! Most of 'em never rode a motorcycle before, but they're all fans for life now.

Hill climbs are tame stuff compared to the run over this operations course, but most of the boys are riding Indians and that's a machine built to take it. They all say Indian's dependability and easy handling give them a real feeling of confidence and safety. And by the way, wait till you see the improvements Indian will bring out after the war. Wow!

INDIAN MOTORCYCLE COMPANY, SPRINGFIELD, MASS.



BUY WAR BONDS NOW

★ ★ TO BUY AN INDIAN LATER ★ ★



There's Been a Big Change

● Ever wear one of those old-time bathing suits? They covered the subject well, but they wouldn't do today. There's been a big change.

An important change has taken place in tapered roller bearings, too! Heavier loads—tougher going—longer hours . . . all begged for a bearing with more rollers, to stand up better under sterner work. Tyson developed just that kind of a bearing.

More rollers, yes—Tyson has *thirty per cent* more, on the average. Size for size, Tyson users get greatly increased load capacities. What's more important, they get almost doubled bearing life.


Tyson "All-Rolls" Bearings are in tune with the times. They're tough. They're longer-lived. They carry greater loads. The big name in bearings today is . . . TYSON!

 TYSON BEARING CORPORATION, MASSILLON, OHIO

COUNT THE ROLLS • THE ROLLS COUNT

Tyson
TODAY'S HEAVY-DUTY BEARING





INTAKE SILENCER
FOR NAVY DIESEL
ENGINES—built by
AC since 1924.

AUTOMOTIVE FUEL
PUMP—built by AC
since 1927.



HUSH HUSH for Sea Horsepower

SEA-GOING diesel engines breathe with a constant roar. Transmitted through the intake system, this racket would be hard on engine-room crews. So, many of the diesels of our Navy are hushed by special AC intake silencers.

No adjustments are possible. Silencers must be *right* when they leave the AC production line. So, accurate, painstaking workmanship is demanded.

In spite of all this, Navy thoroughness requires regular checks on silencers—to keep them up to standard.

Your Fuel Pump, too, Needs Attention

The fuel pump on your car, truck, or tractor is blood brother to this silencer in its need for occasional care. Because it is precision built, it, too, gives trouble

very seldom. But, its life can be definitely prolonged—and your transportation protected—if you will have your service man check your pump after thirty thousand miles of use.

Automotive repair shops can give Conservation Service, not only on fuel pumps but on all nine AC products. (The details of this service, and of why you need it, are given briefly below.) To conserve badly needed materials, gasoline, oil, and tires, use this service—faithfully.

When replacement becomes necessary, select AC—for complete satisfaction.



Awarded to the men and women of AC on September 2, 1942, for outstanding achievement in producing for Victory.

AC SPARK PLUG DIVISION
GENERAL MOTORS CORPORATION

SPARK PLUGS—Dirty or worn plugs waste as much gas as one coupon in ten. Oxide coating collects on the plugs and causes them to misfire, especially when the engine is working hard. Dirty plugs also cause hard starting which weakens your battery. Under present slow driving conditions, have your plugs cleaned and adjusted every few months.

AIR CLEANERS—A dirty air cleaner increases gasoline consumption because it chokes down the flow of air into the carburetor. Your air cleaner should be rinsed whenever your car is lubricated.

FUEL PUMPS—Practically trouble-free. But, if yours has been in use thirty or forty thousand miles, it

may be worn to the point where a check-up is due.



DRIVING INSTRUMENTS—Speedometer, gasoline gauge, oil pressure gauge, ammeter, and temperature gauge seldom need service. But, if they give trouble, have them cared for *at once*.

OR, PETERS—Slow driving accelerates formation of soot and carbon in engine oil. If not constantly filtered from the oil, this dirt will clog piston rings, cause increased consumption of oil and gas. So, replace your oil filter element whenever your dealer's AC Oil Test Pad shows that your oil is dirty.

BRING VICTORY QUICKER—BUY U. S. WAR SAVINGS STAMPS AND BONDS

PROTECT THEIR FUTURE—
BUY WAR BONDS



THERE IS NO SUBSTITUTE
FOR EXPERIENCE



Let the Sun Peek Thru

To us, working night and day in the production of war material, this picture has a special meaning. It suggests a possible solution to a serious post-war problem—the return from violence.

We all look forward to peace as a condition that will dissipate bitter hate. But will it—really? Learned men tell us that considerable adjustment is necessary to recover the wholesome attitude, nationally, that makes for balanced living.

In an atmosphere of blue skies and open water, perspectives have a chance to straighten out. Sunshine fills the heart, as in the case of these youngsters. You who have felt the influence of golden hours on the water know what we mean. You who have not, may yet experience this deep satisfaction. We hope, quite unselfishly, that when the right day comes, you will discover the friendliness of sun-swept waters. With—or without—an outboard.

JOHNSON MOTORS, WAUKEGAN, ILLINOIS

JOHNSON SEA HORSES *for Dependability*

Where Tools are Weapons . . .

Everywhere the United Nations are fighting or preparing to fight, *Tools* are essential weapons. Millions of Stanley Tools are used to build, assemble, or repair the bases, barracks, supply, and combat equipment so necessary to our fighting men.

That supplies for our armed forces must come first is understood by all. Consequently, tools for normal uses will be scarce until the war is won.

Tools are vital for Victory. Buy only for essential use. STANLEY TOOLS, Division of The Stanley Works, New Britain, Conn.



1843 **STANLEY** 1943

STANLEY TOOLS

The Tool Box of the World



MASTERPIECE IN METAL

To the skilled metallurgists who have chosen its tough steels and hard alloys, there is beauty in the Allison's metals. ★ To the seasoned engineers whose slide rules and drawing boards have crystallized their dreams, the beauty lies in the design of the compact, smooth-working parts. ★ To the master mechanics whose skill produces mirror-like surfaces and precise fits, it is the superb machining that is beautiful. ★ But beauty is as beauty does. ★ So to the pilot on the fighting front, the sum of all this is the beauty of performance—the dependable, unfailing action so vital to his mission and his safe return. ★ And to General Motors, whose purpose was to produce one of the world's finest aircraft engines, the beauty of the Allison lies in its record of accomplishments on fighting fronts that circle the globe.

POWERED BY ALLISON

P-38—Lightning
P-39—Airacobra
P-40—Warhawk
P-51—Mustang

A comprehensive booklet entitled "Airplane Power"
may be obtained by writing: Room 11-230,
General Motors Bldg., Detroit 2, Mich.

LIQUID-COOLED AIRCRAFT ENGINES

Allison

DIVISION OF





BLOW TORCH COULD DESTROY HARD-TO-KILL ATHLETE'S FOOT FUNGI THAT MAY THRIVE IN SHOES AND RE-INFECT FEET. YOU WOULDN'T USE A BLOW TORCH ON SHOES, BUT YOU CAN FIGHT ATHLETE'S FOOT IN SHOES AND ON FEET, BY USING **QUINSANA POWDER**. AMAZINGLY EFFECTIVE!

BEWARE OF SYMPTOMS
OF ATHLETE'S FOOT :- PEELING AND CRACKS BETWEEN TOES, ITCHING, SOGGY SKIN. EVEN MILD CASES MAY SUDDENLY BECOME SERIOUS!

REMARKABLE RESULTS WITH QUINSANA

74% infected before Quinsana treatment

6% infected after Quinsana treatment

2-WAY TREATMENT
CLEARED UP PRACTICALLY ALL OF THOUSANDS OF TEST CASES OF ATHLETE'S FOOT. USE **QUINSANA** DAILY FOR PREVENTION AND RELIEF. ALSO EXCELLENT FOR EXCESSIVE PERSPIRATION, FOOT ODOR.



Use Quinsana on feet daily to help prevent and relieve infection



Shake Quinsana into shoes to absorb moisture, reducing chances of re-infection

50c **FOR ATHLETE'S FOOT**

*Better model-making-
better arts and crafts-*

**WITH THIS
REVOLUTIONARY KNIFE**

The very knife-design makes you do a better job. The handles make your fingers deft. Super-keenness makes effortless cutting on hard woods, cardboard or plastics. Special blade-shapes make X-ACTOS follow guide lines easily; and surgical sharpness minimizes splitting. NOW, at first sign of dulling, instant change to a new blade renews the surgical keenness. Re-blade to re-sharpen.



No. 1 X-ACTO knife for light, delicate work. 2 styles of blades. Complete with one blade. 50c. With 5 extra assorted blades \$1.00

No. 2 X-ACTO knife for heavy carving - 5 styles of blades. Complete with one blade. 50c. With 5 extra assorted blades \$1.00

No. 42 Double Set 2 handles 12 blades \$2.00.

No. 81 Fixed wooden chest 3 handles, 12 blades \$3.50.

GET FREE BOOK, TELLS "HOW" to build Model Planes prepared by experts. Profusely illustrated, simple, easy to follow instructions. Build solid models for Army and Navy spotter planes. Write for FREE "How to build Model Planes." Send 5c to cover handling and postage. At your local Hobby Shop, Hardware or Department Store or order direct. Extra Blades 50c for pack of 5.

X-ACTO
CRESCENT PRODUCTS CO.
440 Fourth Ave., New York, N.Y.

X-ACTO knife
RE-blade to RE-sharpen



No. 1
No. 2
No. 5 - 1 1/2"
No. 8 - 2 1/4"


ADJUSTABLE INSPECTOR'S MIRROR

Widely used in Aviation, Shipbuilding, etc. for inspecting inside and complicated machinery parts. Light weight - Adjustable - Flexible - Tilts to almost every angle. No. 6 - 1 1/4 x 2 3/4" oblong No. 10 - 2 1/4 x 3 1/2" oblong
F. P. KETCHMER, 3535 Hughes Ave., Los Angeles, Calif.

110-Volts A.C. ANYTIME! with

Katolight Generators and Power Plants

Furnish same kind of current as City power lines permitting emergency hook-ups right out in the field for operating repair equipment such as drills, grinders, saws, etc. for making on the spot repairs; transmitters & receivers; portable X-Ray equipment.



Good deliveries on A.C. generators 300 through 15,000 watts. Available all standard voltages. Good voltage regulation.

Kato's entire production at present must be confined to orders with high priorities.

Also manufacturers of a complete line of rotary converters and complete power plants.

KATO ENGINEERING COMPANY
105 Elm St. Mankato, Minn., U.S.A.

Get DELTA'S Tested HOME SHOP PLANS... $3\frac{1}{4}$ ¢ each!

In The *Delta*gram

A MAGAZINE FOR CRAFTSMEN

Only 50¢ a year

6 BIG ISSUES



WHAT TO MAKE... AND HOW TO MAKE IT Projects • News • Tips • Designs

Experts — beginners — juniors, here's the biggest bargain of all for your home workshop . . . tested, proven IDEAS!

Page after page of projects—tips—designs—news—in every issue of *The Delta*gram, the homecrafters' magazine published by the makers of famous DELTA Power Tools. It's issued all year 'round, so ideas and shop kinks reach you while they're still brand new . . .

Fun... Healthful Recreation!
What can compare with the thrill of making things with your own hands? In your workshop, you forget cares and worries, as you share the fun with friends or family.

The *Delta*gram is your key to exciting avenues of fun. It shows you how to beautify your home . . . operate machines efficiently and safely . . . earn extra money . . . and produce results that win admiration.

Get all this!

every month in the **DELTA**gram

Special Shop Kinks—How to get the most out of your tools. Learn how to overcome shop problems. How to do taper ripping, indexing on the lathe, drawer joints, etc.

One Evening Projects—done in one evening, ready for use or sale. Make Book Ends, Novelty Flower Box Holder—hundreds of others.

Designs and Plans—The latest ideas in wood, metal, or plastic. Furniture, picture frames, novelties, toys, etc.

Shop Ideas—Job set-ups—machine set-ups—new ways of doing work. How to turn turnings on the lathe—French Polishing—and hundreds of others.

Activities—Trade ideas with others—benefit by their experience. Keep in touch with the best in the craft field through *The Delta*gram. Order yours now!

65 Tested Plans — 3/4¢ Each!

Packed with plans, pictures and projects, *The Delta*gram leaves nothing to guesswork. It's detailed—specific. Instructions are step-by-step . . . complete and understandable to both beginners and experts. That's why *The Delta*gram is more popular every year.

Each season *The Delta*gram—only 50¢ for a whole year—contains about 65 different, tested plans . . . so each plan costs you about $\frac{3}{4}$ ¢!

Order Yours NOW!

New subscriptions start with the September-October issue . . . so make sure you get every one. Fill out the coupon . . . enclose 50 cents in check, stamps, or money order . . . and mail today!

HM-2

DELTA
MILWAUKEE
Power Tools

Published by
Delta Mfg.
Co. . . famous power-
tool makers,
now plan-
ning finer
post-war
tools for you.

Fun! Profit!

How Your *Delta*gram Can Pay for Itself!

If you sell just one home-craft item (*The Delta*gram shows you how to produce dozens), this stimulating magazine has paid for itself.

Besides . . . every issue contains a section on "*Making Your Tools Last for the Duration*"—practical, clearly-illustrated helps in protecting your tools. Saves you money—prevents breakdowns and failures. This one feature alone can save you dollars every issue! Mail your order—today!

For a Bargain in Homecraft Help, mail coupon and 50¢ in stamps, check, or money order.

50¢

Mail this coupon NOW!

Editor, *The Delta*gram

THE DELTA MANUFACTURING COMPANY
682K E. Vienna Ave., Milwaukee 1, Wisconsin

I want the practical plans and handy help of *The Delta*gram for one year—six issues, beginning September-October, 1943. Enclosed find 50¢—stamps, check, or money-order.

Name _____

Address _____

City _____

(____) State _____

Zone _____

"One Way to Tell a Good Mechanic
Is by the Tools He Keeps".



John Diggie

Superintendent of Maintenance
WESTERN AIR LINES



Everywhere in AVIATION veterans say, "Snap-on tools"

Western Air Lines... America's pioneer airline... places high importance on every phase of maintenance. With a wealth of experience that spans the entire period of organized air transport... plus a record of operating efficiency which in some years averaged over 99%... Western joins other famed airlines in strong endorsement of Snap-on tools.

Says John Diggie, Superintendent of Maintenance, "It takes good men to hang up records of this kind, and I have always found that one way to tell a good mechanic is by the tools he keeps. Whether it's on delicate instrument repair or heavy engine work, Snap-on tools meet every answer of good design and long life. You'll find plenty of them in daily use around our shops."

Everywhere in aviation Snap-on tools are on the job! Their accuracy, flexibility and ease of application meet today's urgent need for speed, and more speed. In victory-gear industry throughout America you'll find them in the hands of the men who know tools... the choice of better mechanics!

SNAP-ON TOOLS CORPORATION, Kenosha, Wis.



Please mention POPULAR SCIENCE when writing to advertisers.

It's Free

**WARDS
1943
PHOTOGRAPHIC
CATALOG**

Most everything you'll need, you'll find in our big 1943 Catalog... and at Wards moderate prices... either cash or Time Payment Terms. Order now and pay later. Get what you want while our stocks are still complete. Act Now... Get this money-saving 36 Page Free Catalog.

**EQUIPMENT
AND SUPPLIES
★
EXHIBITION
FILM
ACCESSORIES**

Montgomery Ward
PHOTOGRAPHIC DEPT. PB-943A, CHICAGO, ILLINOIS

★ **LEARN RADIO**

RADIO'S FINEST BOOK VALUES

Specially prepared to aid radio training in schools and industry. Full of valuable data. Send for them now!

Radio Formulas and Doto Book No. 37-752...10c
Dictionary of Radio Terms No. 37-751...10c
Radio Circuit Handbook No. 37-753...10c
Radio Builders Handbook No. 37-750...10c
Simplified Radio Servicing No. 37-755...10c
Radio Doto Handbook No. 37-754...25c

ALLIED RADIO CORP.
833 W. Jackson, Dept. 7-J-3, Chicago

★ **ALLIED RADIO**
Everything in Radio and Electronics—War Training Equipment—Replacement Parts



Just Off the Press Free Fall Catalog

Showing Hunting Footwear, Clothing, and forty-three other leather and canvas specialties of our own manufacture for campers and hunters.

L. L. Bean, Inc.
Catalog Dept. 10, Freeport, Me.

QUICK REPAIRS!

Dents and nicks can be filled in quickly with P. W. Handles like putty; hardens into wood. At Paint, Hardware and 10¢ Stores.

PLASTIC WOOD

PLASTIC WOOD

argus in Action



"INSEPARABLE"
CAPT. EDWARD JACQUET
U. S. AIR FORCE
and his Argus C3



"FINE WORK"

Here and there of Argus, Post 2, San Diego, with three and four years of the Army's heavy "E" for the war in the production of the photographs of a typical typical war scene.

"Good Pictures"

Makes the best use of your present camera—makes more about lenses—film, filters and composition. Send 23c today for the 56-page booklet.

"Argus C3 and My 45 Were My Constant Companions"

THIS CAMERA has given very remarkable service. It has gone through twelve bombing and strafing raids by the Japanese but has also been on forty-three bombing raids against the enemy. Most of these raids were run from high altitudes in the Flying Fortress type of airplane at sub-zero temperatures. Naturally, the camera received a few blows here and there but stood up under the strain. The flash bulb equipment was lost and destroyed at Clark Field by fire, bullets, and shell fragments have only come close but never hit it. The camera plus a "forty-five" have been my only and constant companions during these campaigns. They were things I considered valuable during the evacuations of the Philippines and Java.

EDWARD M. JACQUET
Captain, Air Corps
(19th Bombardment Group)

argus

INTERNATIONAL INDUSTRIES, INC.



The accuracy, greater effectiveness and long range of Western Super-X Silvertip cartridges led to their widespread preference among big game hunters. Silvertip cartridges are not used for military purposes.



Now Your Ammunition Is Getting Bigger Game

YOUR favorite Western ammunition helped blast the Japs from Guadalcanal.

The picture above, from a photograph released by the War Department, shows cases of Western military cartridges on Guadalcanal Island. The rifles are the new semi-automatic Garand, the finest infantry arm used by any army in the present war. Western's Winchester division is one of the manufacturers of this ultra-modern weapon.

Here is *part* of your stake in America's great war effort. On many other fronts, too, Western is helping to defeat the enemy. Tomorrow, when the world is again ruled by free peoples, Western Super-X and Xpert cartridges and shot shells will help you enjoy in full measure the great sport of hunting.

Western

CARTRIDGE COMPANY
EAST ALTON, ILL.



Please mention POPULAR SCIENCE when writing to advertisers.

Wood

workers: Here it is! Harold No. 11 wood catalog! Latest UP-TO-DATE IDEAS for experts and amateurs! SPECIAL BARGAINS in rare woods, veneers, and all kinds of supplies. 124 pages—12 of rare woods in color. Get posted! Send only 10c to CRAFTSMAN WOOD SERVICE CO. 2729 S. Mary St., Dept. B-37, Chicago, Ill.

WINN'S NEW IDEA HOME LABORATORY CHEMICAL KITS

For High School & College Students. Send 5c for Literature and Retail Supply Catalog. J. H. WINN MFG. CO., Dept. 109 124 W. 23 St., New York 11, N. Y.

DRILL PRESS OWNERS!

HERE'S 1 TOOL WITH 5 DISTINCT USES

THE BARRON MULTI-PURPOSE ROTARY WOOD PLANER

PLANES & SURFACES • PANELS & BEADS \$750
ROUTS & GROOVES • RABBETS • TENONS COMPLETE

Converts ANY drill press into a time saving, low cost planer, paneler, tenoner, etc. Surface finishes all types of tough grained and knotty surfaces to agree smoothness. Safe! Guaranteed harmless to drill press. Thousands now in use. **SOLD ON MONEY BACK GUARANTEE.** Full refund on 5 day trial. Shipped prepaid on receipt of \$7.50—or C.O.D. YOU RISK NOTHING. Free literature.

BARRON TOOL CO., INC.
370 Architects Bldg., Detroit 1, Mich.

STEEL TOP AUXILIARY DRILL PRESS TABLE

Has 800 sq. in. smooth working surface. Equipped for shaper and many other important workshop uses—a real buy at \$595



TOOLS FOR AIRPLANE WORKERS

Immense industrial facilities throughout America are concentrated on the greatest aircraft building program in all history. In this vitally important work a wide variety of Disston tools are serving long and well at a multitude of tasks.

In many of the huge plants turning out planes you find Disston hand saws, back saws, dovetail saws, compass saws, veneer saws, coping saws, circular saws, band saws, hack saws, hack saw blades, files, mitre squares, try squares, bevels, gauges, levels, cabinet scrapers and many others.

● If you need tools for essential service, see your Hardware Dealer and ask for Disston. An outstanding example of a fine Disston tool for war work is "The Saw Most Carpenters Use," the:

DISSTON D-8



Medium weight Skew-back pattern. Made in 20-inch 10 points cross-cut; 22-inch 8 and 10 points cross-cut; 24-inch 8 and 10 points cross-cut; 26-inch 7, 8, 10 and 11 points cross-cut, 5½ points rip.

GET LONGER LIFE AND BETTER WORK from your tools. Ask your Hardware Dealer for your FREE copy of the valuable Disston Saw, Tool and File Manual. Or write to us direct.



HENRY DISSTON & SONS, INC.
910 Tacony, Philadelphia 35, Pa., U. S. A.

Test-O-Lite the MODERN TROUBLE SHOOTER



← THE NEON GLOW

... LOCATES TROUBLE

INSTANTLY in electric circuits, fuses, cut-outs, motors, radios, appliances. Tests everything electrical from 100 to 550 volts. Indicates hot or grounded wires. Tells AC from DC. Far superior to ordinary clumsy test bulb.

↑ PUTS "FINGER" ON THE TROUBLE SPOT -- QUICKLY

Saves precious time. Indispensable in shop or home. Has patented safety features. Vest pocket size with clip. Lifetime guarantee. List \$1.50

L. S. BRACH MFG. CORP.
55 Dickerson St. Newark, N. J.



FUSES



MOTORS



OUTLETS



ONAN ELECTRIC PLANTS

Electricity for Any Job—Anywhere

ONAN GASOLINE DRIVEN ELECTRIC PLANTS provide electricity in locations where it is not otherwise available, and for emergency and standby service. Thousands doing a winning job in the war.



Sizes from 350 to 35,000 watts. A.C. 50 to 800 cycles, 110 to 660 volts. D.C. 6 to 4000 volts. Also dual A.C. and D.C. output models. Air or water cooled. Details gladly furnished.

D. W. ONAN & SONS
1807 Royalston Ave., Minneapolis, Minn.


BUILD ARC WELDER FROM OLD GENERATOR

For Light or Heavy Work. 30-200 amperes. Complete PLANS 35c. Send today and we'll include FREE our BIG Catalog. LEJAY Mfg. Co., 1323 Lejay Bldg., Minneapolis, Minn.



WITTE DIESELECTRIC PLANTS

A. C.
and
D. C.



For 73 years the WITTE plant has been serving America and the World.

Today WITTE is producing only for the War Effort. After Victory these improved WITTE plants will be available to all.

Remember us then.

WITTE ENGINE WORKS
LARGEST BUILDER OF SMALL DIESELS
KANSAS CITY, MO., U. S. A.

This One



QF5B-QFP-1ND2

BUY
MORE
BONDS



Batteries have gone to war,
In the air, on seas, on shore;
You can't buy them as before:
When it's over there'll be more.



UNFAILING SERVICE
FOR 32 YEARS



FIRST—TO BATTLEFRONTS Later to VACATIONLAND

★After the war you'll be itching to drive again—to the mountains, the great open spaces. Right now the HULL STREAM-LINE COMPASS is doing a grim job helping guide U. S. Army vehicles. Later it can be your guide on pleasure or business motoring trips anywhere.

HULL MANUFACTURING CO.
P.O. Box 246-E9,
WARREN, OHIO



GERSTNER TOOL CHESTS
protect your tools from damage. Choose yours from our Free Catalog for toolmakers and machinists.
GERSTNER TOOL CHESTS
543 Columbia St. Dayton, Ohio

SYNCRON DROPS A BOMB!

SYNCRON Electric Jig Saws are helping to bomb the Axis by furnishing precision-made parts for bombers, tanks, submarines, guns, etc. After war, there'll be even more efficient Synchr Electric Jig Saws ready for your peacetime home workshop projects!


SYNCRON SAFETY SAWS
Synchr Devices, Inc.
3265 Bermuda Ave.
Dept. PS-93 Ferndale 20, Michigan



Sluggish Engine?



TRY THIS AMAZING Tonic Treatment!



BRING YOUR CAR in today for a Mobil Upperlube Tonic Treatment. Most Mobilgas Dealers are prepared to render this service. It should do this for your car:

Free up valve and ring action • Even up piston pressures • Make your gasoline go further • Bring back "new car pep" to a surprising degree.

To keep your car smooth-running and guard against internal rust and corrosion, add Mobil Upperlube to your tank whenever you buy gasoline.



Everywhere—at the Sign
of Friendly Service!

MOBIL UPPERLUBE

MAKE ITS USE A HABIT!

OTHER MOBIL SPECIALTIES:
Mobilgloss • Mobilwax • Mobil Handy Oil
Mobil Radiator Flush • Mobil Stop-Leak • Mobil Window Spray
Mobil Hydrotone • Mobil Spot Remover

BY SOCONY-VACUUM

DESIGNED TO SPEED PRODUCTION



As industry rewards employees who suggest ideas that speed production, so do "Yankee" Fine Mechanics' Tools reward industry by saving time and energy on countless jobs. From Spiral Screw Drivers to Tap Wrenches and from Automatic Drills to Bit Braces, each "Yankee" Tool has been painstakingly designed to get things done. Ingenious and dependable, "Yankee" Tools have contributed to the efficiency of American production for nearly half a century. Today, of course, they've gone to war and are not always available at your dealers.

"YANKEE" SPIRAL SCREW DRIVER No. 130A
A Size For Every Purpose

"YANKEE" TOOLS

make good mechanics better

North Bros. Mfg. Co., Phila., U. S. A.

Established 1880

Makers, also, of "Yankee-Handyman" Tools

SAW-FILING

Pays up to \$2 or \$3 an Hour

A FOLEY Automatic Saw Filer files hand, circular and band saws better than the best hand filer. Cash business, no canvassing, no expense, no strain. No experience needed. "Bought a Foley one year later had all debts paid and \$400 on a new home. Many days I earn as much as \$10."—J. H. Kellorik. Send coupon for FREE PLAN, no obligation.

FOLEY MFG CO., 310-3 Foley Bldg., Minneapolis 12, Minn.
Send Free Plan on Saw Filing business.



Paste coupon on postcard

Name.....
Address.....



WORLD'S LOWEST PRICED ADDING MACHINE

ONLY \$250
IDEAL FOR BUSINESS OR PERSONAL USE. GUARANTEED ACCURATE. Not a toy. Operates with only a finger flick. Adds, subtracts, multiplies, divides. Counts up to ten million. Pays for itself over and over. Ideal Gift for business. Income Tax and School use. **MONEY BACK GUARANTEE.** Send name and address. Pay Postman only \$2.50 plus postage. (Send full cash if outside U.S.) Money Back in 10 days if not delighted. AGENTS WANTED.

CALCULATOR MACHINE COMPANY (Mfrs.)

DEPT. 434, P. O. BOX 1118

CHICAGO, ILLINOIS

BEFORE

AFTER

CONSERVE Valuable Paint Brushes

GOOD paint brushes are expensive and scarce! Keep new brushes soft, flexible and in good painting condition... restore worn, hardened, discarded old brushes to service with **DIC-A-DOO Paint Brush Bath.** Easy to use. Preserves bristles; prolongs brush life by softening up and washing away dried out paint. 5¢ pkg. cleans several brushes. Ask for it by name at paint, hardware and 5 & 10¢ stores. The Patent Cereals Co., Geneva, N.Y., makers of the famous **DIC-A-DOO Paint Cleaners.**

DIC-A-DOO

**PAINT BRUSH
BATH**

IT'S FUN TO MAKE THINGS OF WOOD

CONSTANTINE'S MANUAL TELLS HOW TO DO IT
Beginner or expert will find many helpful hints and tips on veneering, woodfinishing, cabinet making, carpentry, etc. Describes and illustrates over 100 different kinds of wood and 500 different items for you. ALL AT MONEY SAVING PRICES. Includes identification panel and chart of over 60 rare woods in natural color. A source of supply for anything in wood regardless of quantity. Send only 25¢ in stamps or coin. 25¢ refunded or credited on first order so Manual costs you nothing.

ALBERT CONSTANTINE & SON, INC.
793-N East 135th St. New York, N. Y.

ARMSTRONG TOOL HOLDERS

enabled American Industry to change to war production "over night." For they are the permanent, multi-purpose tools used by 96% of the machine shops and tool rooms, on lathes, planers and shapers—the tools used to make dies and jigs, to build production machines. They are the tools you will want for your own shop after the war—ARMSTRONG TOOL HOLDERS for industry, ACE Tool Holders for home work shops.

ARMSTRONG BROS. TOOL CO.
"The Tool Holder People"
320 N. Francisco Ave. Chicago, U. S. A.

LUBRICATES • CLEANS • POLISHES • PREVENTS RUST

3-IN-ONE Heavy Body OIL

**PROTECTS
WASHING
MACHINES**

At Hdwe., Drug, Grocery and 10¢ Stores



SPEED THE FINISH

Mounted firmly on its own steel shank, each Chicago Mounted Wheel is a whirling point of easily controlled power with 100% grinding speed and efficiency.

Famous since their introduction 45 years ago for quality and long life. There is a "just right" Chicago Mounted Wheel for every operation.

PROMPT DELIVERIES—We are working 24 hours a day and due to our central location, can make prompt shipment on all Mounted Points and Grinding Wheels 3" in diameter and under.

With the approval and endorsement of WPB, all our facilities are concentrated on these smaller sizes, enabling us to give faster service to war plants.

Handee Tool of 1001 Uses and Hi-Power Grinders are still available to all who have priorities.

Send for Free Catalog.

CHICAGO WHEEL & MFG. CO.
115 Aberdeen St. Chicago, Ill.



PROTECTION FROM RUST

Tools—Guns—Locks, etc.

For years hunters have used Fiendoil to keep their guns clean and free from rust. . . . equally effective on all metal articles.

At Your Sports or Hardware Store
In Sic, 2 oz. Bottle

FIENDOIL

McCambridge & McCambridge Co.
Baltimore

MICROMETER CALIPERS

heavy duty



Size 0-1 \$14.00, 1-2 \$15.00, 2-3 \$16.25;

other sizes to 11-12

proportionately priced. Money order or check with order. Mailed prepaid, insured. Prompt delivery.

SHERWAY CO.

245 Menadnock Bldg.

San Francisco, Calif.

DIE-LESS DUPLICATING

Many small parts can be formed without dies, to duplicated accuracy of .001" with Di-A-CRO Precision Machines. — Senders Brakes, Shears—saving Man Hours and Critical Materials. Require priority of A-1-A or higher. Write on business letterhead for catalog, or state if employed in War production.

O'NEIL-IRWIN MFG. COMPANY
342 8th Avenue S. Minneapolis 15, Minn.



REPAIR!

YOUR WARTIME DUTY

It is essential to keep your household equipment and auto in good condition and make them last for the "duration".

SMOOTH-ON No. 1 will help you, because this many-purpose iron repair cement seals cracks and stops leaks in plumbing and heating equipment; automobile engines, radiators, gear cases, and other apparatus; and also tightens loose machinery parts, fixtures, handles, hardware, etc.

SMOOTH-ON repairs can be made by any handy man, and do not require dismantling of apparatus, heat, or previous experience. Get **SMOOTH-ON** from your hardware store in 1¾-oz., 7-oz., or larger container, or if necessary, you can get it from us.

The 40-page **Smooth-On Handbook** contains dozens of suggestions, not published elsewhere, for saving time and money on household, auto, and shop repairs. 170 Diagrams. To obtain your copy without charge, fill in and mail the coupon today.

SMOOTH-ON CEMENTS



For the
Motor Car and Boat,
Home, Factory and
Power Plant



Do it with **SMOOTH-ON**



SMOOTH-ON

Seal cracks in boiler, pumps, heaters, etc.



Stop leaks in pipes, radiators, heating, plumbing systems.



Tighten loose handles, knobs, hardware, fixtures.



Stop leaks in utensils, pails, kettles, etc.

FREE HANDBOOK

SMOOTH-ON MFG. CO., Dept. 58
570 Communipaw Ave.,
Jersey City 4, N. J.

Please send Smooth-On Repair Book.

Name

Address

9-43

Please mention POPULAR SCIENCE when writing to advertisers.

HIGH PRECISION

*for High-Speed
War Production*



*Buy
War
Bonds*



High precision is the key to high speed war production — for mass production is based on a degree of accuracy that assures the perfect interchangeability of parts and units.

In hundreds of war production plants, South Bend Lathes are preferred because their high precision makes it easier to maintain exacting tolerances on important tool-room and production operations.

Modern in design, built to the highest standards of workmanship, South Bend Lathes are capable of performing finish turning and boring operations with such accuracy that subsequent grinding, honing, or lapping operations can often be eliminated.

A wide range of spindle speeds permits taking full advantage of carbide or diamond tipped tools.

Convenient controls make for an ease of operation which reduces fatigue and lessens the possibility of error. Requiring a minimum of effort to run, South Bend Lathes are especially desirable where women lathe operators are employed.

"HOW TO RUN A LATHE"

A practical instruction book on the operation and care of metal working lathes. Contains 128 pages, 5½" x 8". Send 25 cents in stamps for your copy.



SOUTH BEND LATHE WORKS
SOUTH BEND, INDIANA • LATHE BUILDERS FOR 36 YEARS